



TECHNICAL REPORT

Fibre optic communication system design guidelines – Part 16: Coherent receivers and transmitters with high-speed digital signal processing

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.01

ISBN 978-2-8322-0094-0

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	6
INTRODUCTION.....	8
1 Scope.....	9
2 Normative references	9
3 Terms, definitions, and abbreviated terms	9
3.1 Terms and definitions.....	9
3.2 Abbreviated terms.....	9
4 Background	12
5 Coherent transmission of vector-modulated signals	13
5.1 Typical receiver architecture	13
5.2 Typical transmitter architecture	14
5.3 Vector-modulated signals.....	15
5.3.1 Mathematical description	15
5.3.2 Binary amplitude and phase modulation.....	16
5.3.3 Quadrature amplitude modulation	17
5.3.4 Polarization multiplexing.....	18
5.3.5 Higher-dimensional coding and constellation shaping	18
6 Coherent receiver architectures and functional capabilities.....	19
6.1 Basic principle of coherent detection.....	19
6.1.1 General	19
6.1.2 Homodyne and heterodyne detection.....	19
6.1.3 Intradyne detection	21
6.1.4 Polarization dependence	21
6.1.5 Frequency dependence	22
6.1.6 Phase and polarization diversity	22
6.2 Single coherent mixer with balanced detection.....	23
6.2.1 Principle of operation.....	23
6.2.2 Common-mode rejection.....	24
6.2.3 Polarization dependence	26
6.2.4 Homodyne detection	27
6.2.5 Heterodyne detection.....	28
6.3 Dual coherent mixer with phase diversity	29
6.3.1 Principle of operation.....	29
6.3.2 Intradyne detection with frequency offset removal.....	31
6.3.3 Compensation of chromatic dispersion.....	33
6.3.4 Compensation of I - Q skew and phase offset	40
6.3.5 Spectral shaping and frequency equalization	42
6.4 Quadruple mixer with phase and polarization diversity	46
6.4.1 Principle of operation.....	46
6.4.2 Polarization demultiplexing.....	48
6.4.3 Compensation of polarization-mode dispersion	51
6.4.4 Compensation of polarization-dependent loss and residual CD	53
6.4.5 Carrier phase recovery	54
6.4.6 Impact of laser phase noise	55
6.5 High-resolution spectral analysis with coherent receivers.....	62
6.5.1 Measurement methods	62

6.5.2	Dual mixer with polarization diversity	63
6.5.3	Examples of high-resolution spectral analysis	64
7	Digital signal processing in coherent receivers	66
7.1	Basic features of digital signal processing	66
7.2	Real-time DSPs for fibre optic communication systems	70
7.2.1	Basic functions	70
7.2.2	Timing recovery	71
7.2.3	Cycle slip detection	71
7.2.4	Compensation of nonlinear transmission effects	71
7.2.5	FEC decoding and performance monitoring	72
7.3	Software-based DSPs for optical modulation analysers	73
8	Transmitters for vector-modulated signals	75
8.1	Generation of vector-modulated signals	75
8.2	Single Mach-Zehnder modulator	77
8.2.1	Principle of operation	77
8.2.2	Modulator extinction ratio	81
8.2.3	Adaptive bias control in Mach-Zehnder modulators	83
8.3	Dual Mach-Zehnder modulators	85
8.3.1	Quadrature-amplitude modulation	85
8.3.2	Compensation of finite extinction ratio	86
8.3.3	Adaptive control of $I-Q$ phase	87
8.4	Quadruple modulators for polarization-multiplexed signals	91
9	Digital signal processing in transmitters for vector-modulated signals	94
9.1	Pre-distortion of optical signals	94
9.1.1	General	94
9.1.2	Pre-compensation of linear transmitter impairments	95
9.1.3	Determination of transmitter frequency response	96
9.1.4	Determination of transmitter skew	101
9.1.5	Pre-compensation of modulator nonlinearity	103
9.2	Symbol mapper, FEC encoding and framing	105
10	Implementation and typical performance specifications	106
10.1	Coherent receiver	106
10.1.1	Implementation	106
10.1.2	Typical performance specifications	107
10.2	Optical transmitter	108
10.2.1	Implementation	108
10.2.2	Typical performance specifications	109
10.3	Integrated coherent receiver and transmitter	111
10.4	Tuneable laser assemblies	111
10.4.1	Implementation	111
10.4.2	Typical performance specifications	111
	Bibliography	113
	Figure 1 – Coherent optical receiver	13
	Figure 2 – Optical transmitter for coherent transmission	14
	Figure 3 – Generation of vector modulated signals	16
	Figure 4 – Examples of modulation formats for coherent communication	17
	Figure 5 – Signal and local oscillator frequencies for homodyne detection	20

Figure 6 – Signal and local oscillator frequencies for heterodyne detection	20
Figure 7 – Electrical spectra of homodyne and heterodyne beat signals.....	21
Figure 8 – Single balanced mixer for coherent reception.....	24
Figure 9 – Balanced heterodyne mixer with electrical down-mixing	28
Figure 10 – Dual coherent mixer with phase diversity.....	30
Figure 11 – Intradyne beat spectrum with 2 GHz frequency offset.....	32
Figure 12 – Differential phase shifts introduced by 3 000 ps/nm GVD	33
Figure 13 – Transfer function for GVD of 3 ns/nm in frequency domain	34
Figure 14 – Inverse transfer functions for GVD of 3 ns/nm and 10 ns/nm in time domain	36
Figure 15 – Fractionally spaced equalizer with a tapped delay line	37
Figure 16 – Processing steps for CD compensation in the frequency domain	38
Figure 17 – Data processing for CD compensation in the frequency domain	39
Figure 18 – Dual coherent mixer with optical phase offset and signal skew	40
Figure 19 – Skew and phase offset removal in a DSP	41
Figure 20 – Example of an I - Q skew and phase error measurement.....	42
Figure 21 – Fifth-order Bessel filter emulated with a 5-tap FSE.....	43
Figure 22 – Shape of inverse Bessel filter generated with a 9-tap FSE	44
Figure 23 – Amplitude and phase of FSE-generated inverse Bessel filter.....	45
Figure 24 – Root-raised-cosine filter emulated with a 33-tap FSE	46
Figure 25 – Quadruple coherent mixer with phase and polarization diversity.....	47
Figure 26 – 2×2 matrix operation for adaptive polarization demultiplexing.....	49
Figure 27 – Constellation points of QPSK signal after polarization demultiplexing.....	50
Figure 28 – 16QAM signal before and after polarization demultiplexing.....	50
Figure 29 – FSE-based compensator for polarization-mode dispersion	52
Figure 30 – QPSK signal constellations for various amounts of PMD	52
Figure 31 – QPSK signal constellations for various amounts of PDL	53
Figure 32 – QPSK signal constellations for various amounts of GVD	53
Figure 33 – Optical phase noise of two narrow-linewidth lasers	56
Figure 34 – Optical frequency noise spectra of two lasers.....	58
Figure 35 – Optical phase noise spectra of two lasers	59
Figure 36 – Laser phase noise measurement with optical bandpass filter.....	60
Figure 37 – Dual coherent mixer with polarization diversity.....	63
Figure 38 – High-resolution optical spectrum of a 32 GBd QPSK signal	65
Figure 39 – QPSK signal measured with coherent OSA and with grating-based OSA	65
Figure 40 – Typical digital signal processing steps in a coherent receiver.....	67
Figure 41 – 100 Gbit/s PM-QPSK signal before and after fibre transmission	68
Figure 42 – De-convolution of a 100 Gbit/s PM-QPSK signal at various DSP stages.....	69
Figure 43 – Block diagram of specially designed integrated circuit with DSP.....	70
Figure 44 – Block diagram of OMA with software-based DSP.....	73
Figure 45 – Typical arrangement for generation of vector-modulated signals	76
Figure 46 – Differentially driven Mach-Zehnder modulator	77
Figure 47 – Mach-Zehnder modulator with adaptive bias control	78
Figure 48 – MZM operation for intensity modulation	79

Figure 49 – Nonlinear MZM operation for binary PSK/ASK.....	80
Figure 50 – Linear MZM operation for quaternary ASK signals.....	81
Figure 51 – Optical power variations in an NRZ-OOK signal with finite extinction ratio.....	82
Figure 52 – Optical and RF output power versus bias voltage for linear operation.....	83
Figure 53 – Dual MZM with adaptive I - Q phase control.....	86
Figure 54 – RF output power of I - Q modulator versus I - Q phase.....	88
Figure 55 – Error signal for I - Q phase control derived from MZM bias dither.....	90
Figure 56 – I - Q phase error resulting from offset in feedback signal.....	91
Figure 57 – Dual I - Q modulators for polarization multiplexing.....	92
Figure 58 – Adaptive bias and phase control in dual-polarization I - Q modulator.....	93
Figure 59 – Typical digital signal processing steps in the transmitter.....	95
Figure 60 – Spectrum and samples of a white test vector.....	96
Figure 61 – Magnitude of transmitter frequency response.....	97
Figure 62 – Phase of transmitter frequency response.....	98
Figure 63 – Example of magnitude and phase of a pre-compensation filter.....	99
Figure 64 – Tap coefficients and effect of a 9-tap pre-compensation filter.....	99
Figure 65 – Impact of pre-compensation on signal waveform in DSP and DAC.....	101
Figure 66 – I - Q skew in a single-sideband modulated signal.....	102
Figure 67 – Non-linear pre-distortion of a Mach-Zehnder modulator.....	103
Figure 68 – Linearized MZM operation for quaternary ASK.....	105
Table 1 – Typical receiver specifications.....	108
Table 2 – Typical modulator specifications.....	110
Table 3 – Additional specifications for integrated driver-modulator.....	110
Table 4 – Typical specifications for tuneable laser assemblies.....	112

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

**Part 16: Coherent receivers and transmitters
with high-speed digital signal processing**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61282-16 has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics. It is a Technical Report.

The text of this Technical Report is based on the following documents:

Draft	Report on voting
86C/1776/DTR	86C/1782/RVDTR

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Report is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/standardsdev/publications.

A list of all parts in the IEC 61282 series, published under the general title *Fibre optic communication system design guidelines*, can be found on the IEC website.

Future documents in this series will carry the new general title as cited above. Titles of existing documents in this series will be updated at the time of the next edition.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

Coherent optical receivers are widely used in long-haul fibre optic communication systems, especially in systems that transmit optical carriers at data rates of 100 Gbit/s and higher. While the principle of coherent detection is very similar to that of super-heterodyne (or homodyne) detection in radio and microwave receivers, its implementation is significantly more challenging. The main reason is that optical frequencies are substantially higher than radio frequencies, so it becomes more difficult to match the local oscillator frequency in the coherent receiver to the frequency of the transmitted optical signal. Furthermore, optical signals tend to be highly polarized, which means that the amplitude of a coherently received signal can be substantially reduced or even vanish if the polarization state of the local oscillator light does not match the polarization state of the received optical signal. This polarization matching is particularly difficult to achieve in fibre optic communications systems, which usually do not preserve the launched state of polarization of the transmitted signal. To overcome these problems, modern coherent receivers typically consist of four parallel coherent optical mixers that provide phase and polarization diversity, and they rely on high-speed digital signal processors to retrieve the transmitted data from the four received electrical signals.

This rather complex coherent receiver architecture is further justified by the fact that it allows the receiver to mitigate various types of signal impairments introduced in the fibre optic link (or in the receiver itself) simply by means of additional electronic signal processing. Most notably, it is possible to substantially reduce the signal distortions caused by polarization-mode dispersion (PMD) or uncompensated chromatic dispersion (CD) in the fibre link, without requiring additional optical PMD or CD compensators. For this reason, coherent optical communication systems generally allow signal transmission at much higher data rates than communication systems using direct-detection receivers. Furthermore, coherent detection with subsequent digital signal processing facilitates the decoding of complex vector-modulated signals, such as quadrature-amplitude modulated signals (QAM) and polarization-multiplexed (PM) signals, and thereby the transmission of higher data rates.

Aside from fibre optic communications systems, coherent optical receivers are also used in various test and measurement instrumentation. Most notable examples are optical modulation analysers (OMAs) and high-resolution optical spectrum analysers (HR-OSAs). Optical modulation analysers are high-performance optical reference receivers and are used to assess the signal quality of complex vector-modulated optical signals. They are typically composed of a carefully calibrated coherent receiver and a high-speed real-time digitizing oscilloscope to record the coherently received signals, which are then analysed with the help of a software-based digital signal processor.

High-resolution optical spectrum analysers are often used to analyse narrowband features of the optical spectrum of a modulated signal, such as a residual optical carrier or other spectral lines. In contrast to OMAs, they typically employ a low-speed coherent receiver, so as to utilize the frequency-selectivity of coherent detection. The key component in these instruments is a continuously tuneable local oscillator, which is scanned over the frequency range of the signal to be analysed while the total power of the coherently received signal is recorded. The spectral resolution of these instruments can be of the order of a few MHz. Other examples of coherent optical test instruments include in-service PMD analysers and in-band optical signal-to-noise ratio analysers for polarization-multiplexed signals.

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 16: Coherent receivers and transmitters with high-speed digital signal processing

1 Scope

This part of IEC 61282 is a technical report on coherent optical receiver and transmitter technologies that are employed in fibre optic communication systems as well as in optical test and measurement equipment. This document describes the principle of operation and functional capabilities of coherent optical receivers as well as the operation of optical transmitters used to generate complex vector-modulated signals. It is intended to serve as a technical foundation for other IEC documents and standards related to coherent optical transmission techniques.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-731, *International Electrotechnical Vocabulary (IEV) – Part 731: Optical fibre communication* (available at www.electropedia.org)

IEC TR 61931, *Fibre optic – Terminology*