

INTERNATIONAL STANDARD

IEC
60909-0

First edition
2001-07

Short-circuit currents in three-phase a.c. systems –

Part 0: Calculation of currents

*This **English-language** version is derived from the original **bilingual** publication by leaving out all French-language pages. Missing page numbers correspond to the French-language pages.*



Reference number
IEC 60909-0:2001(E)

INTERNATIONAL STANDARD

IEC 60909-0

First edition
2001-07

Short-circuit currents in three-phase a.c. systems –

Part 0: Calculation of currents

Withdrawn

© IEC 2001 Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembe, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE **XB**

For price, see current catalogue

CONTENTS

FOREWORD.....	9
1 General.....	13
1.1 Scope.....	13
1.2 Normative references.....	15
1.3 Definitions.....	17
1.4 Symbols, subscripts and superscripts.....	25
1.4.1 Symbols.....	25
1.4.2 Subscripts.....	29
1.4.3 Superscripts.....	31
2 Characteristics of short-circuit currents: calculating method.....	31
2.1 General.....	31
2.2 Calculation assumptions.....	35
2.3 Method of calculation.....	35
2.3.1 Equivalent voltage source at the short-circuit location.....	35
2.3.2 Application of symmetrical components.....	41
2.4 Maximum short-circuit currents.....	45
2.5 Minimum short-circuit currents.....	47
3 Short-circuit impedances of electrical equipment.....	47
3.1 General.....	47
3.2 Network feeders.....	49
3.3 Transformers.....	51
3.3.1 Two-winding transformers.....	51
3.3.2 Three-winding transformers.....	53
3.3.3 Impedance correction factors for two- and three-winding network transformers.....	57
3.4 Overhead lines and cables.....	59
3.5 Short-circuit limiting reactors.....	61
3.6 Synchronous machines.....	61
3.6.1 Synchronous generators.....	61
3.6.2 Synchronous compensators and motors.....	65
3.7 Power station unit.....	65
3.7.1 Power station units with on-load tap-changer.....	65
3.7.2 Power station units without on-load tap-changer.....	69
3.8 Asynchronous motors.....	71
3.8.1 General.....	71
3.8.2 Contribution to short-circuit currents by asynchronous motors.....	73
3.9 Static converters.....	77
3.10 Capacitors and non-rotating loads.....	77
4 Calculation of short-circuit currents.....	79
4.1 General.....	79
4.2 Initial symmetrical short-circuit current I_k''	83

4.2.1	Three-phase short circuit.....	83
4.2.2	Line-to-line short circuit	95
4.2.3	Line-to-line short circuit with earth connection.....	99
4.2.4	Line-to-earth short circuit	101
4.3	Peak short-circuit current i_p	101
4.3.1	Three-phase short circuit.....	101
4.3.2	Line-to-line short circuit	105
4.3.3	Line-to-line short circuit with earth connection.....	105
4.3.4	Line-to-earth short circuit	107
4.4	DC component of the short-circuit current	107
4.5	Symmetrical short-circuit breaking current I_b	107
4.5.1	Far-from-generator short circuit.....	107
4.5.2	Near-to-generator short circuit	109
4.6	Steady-state short-circuit current I_k	117
4.6.1	Three-phase short circuit of one generator or one power station unit	117
4.6.2	Three-phase short circuit in non-meshed networks.....	121
4.6.3	Three-phase short circuit in meshed networks.....	123
4.6.4	Unbalanced short circuits.....	123
4.6.5	Short circuits at the low-voltage side of transformers, if one line conductor is interrupted at the high-voltage side.....	125
4.7	Terminal short circuit of asynchronous motors.....	127
4.8	Joule integral and thermal equivalent short-circuit current.....	129
Annex A (normative) Equations for the calculation of the factors m and n		137
Figure 1 – Short-circuit current of a far-from-generator short circuit with constant a.c. component (schematic diagram).....		31
Figure 2 – Short-circuit current of a near-to-generator short circuit with decaying a.c. component (schematic diagram).....		33
Figure 3 – Characterization of short circuits and their currents.....		37
Figure 4 – Illustration for calculating the initial symmetrical short-circuit current I_k'' in compliance with the procedure for the equivalent voltage source		39
Figure 5 – Short-circuit impedances of a three-phase a.c. system at the short-circuit location F.....		43
Figure 6 – System diagram and equivalent circuit diagram for network feeders		49
Figure 7 – Three-winding transformer (example)		55
Figure 8 – Phasor diagram of a synchronous generator at rated conditions		63
Figure 9 – Example for the estimation of the contribution from the asynchronous motors in relation to the total short-circuit current.....		75
Figure 10 – Diagram to determine the short-circuit type (figure 3) for the highest short-circuit current referred to the symmetrical three-phase short-circuit current at the short-circuit location when the impedance angles of the sequence impedances $Z_{(1)}$, $Z_{(2)}$, $Z_{(0)}$ are identical.....		81
Figure 11 – Examples of single-fed short circuits.....		85
Figure 12 – Example of a non-meshed network		89

Figure 13 – Short-circuit currents and partial short-circuit currents for three-phase short circuits between generator and unit transformer with or without on-load tap-changer, or at the connection to the auxiliary transformer of a power station unit and at the auxiliary busbar A	89
Figure 14 – Example of a meshed network fed from several sources.....	97
Figure 15 – Factor κ for series circuit as a function of ratio R/X or X/R	101
Figure 16 – Factor μ for calculation of short-circuit breaking current I_b	111
Figure 17 – Factor q for the calculation of the symmetrical short-circuit breaking current of asynchronous motors	113
Figure 18 – λ_{\min} and λ_{\max} factors for cylindrical rotor generators.....	119
Figure 19 – Factors λ_{\min} and λ_{\max} for salient-pole generators	119
Figure 20 – Transformer secondary short circuits, if one line (fuse) is opened on the high-voltage side of a transformer Dyn5	125
Figure 21 – Factor m for the heat effect of the d.c. component of the short-circuit current (for programming, the equation for m is given in annex A).....	131
Figure 22 – Factor n for the heat effect of the a.c. component of the short-circuit current (for programming, the equation for n is given in annex A).....	133
Table 1 – Voltage factor c	41
Table 2 – Factors α and β for the calculation of short-circuit currents with equation (90) Rated transformation ratio $t_r = U_{rTHV}/U_{rTLV}$	127
Table 3 – Calculation of short-circuit currents of asynchronous motors in the case of a short circuit at the terminals (see 4.7).....	129

WITHDRAWN

INTERNATIONAL ELECTROTECHNICAL COMMISSION

SHORT-CIRCUIT CURRENTS IN THREE-PHASE AC SYSTEMS –

Part 0: Calculation of currents

FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.
- 3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical specifications, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.
- 5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.
- 6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60909-0 has been prepared by IEC technical committee 73: Short-circuit currents.

This first edition cancels and replaces IEC 60909 published in 1988 and constitutes a technical revision.

The text of this standard is based on the following documents:

FDIS	Report on voting
73/119/FDIS	73/121/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

Annex A forms an integral part of this standard.

This part of IEC 60909 shall be read in conjunction with the International Standards, Technical Reports and Technical Specifications mentioned below:

- IEC TR 60909-1,— *Short-circuit current calculation in three-phase a.c. systems – Part 1: Factors for the calculation of short-circuit currents in three-phase a.c. systems according to IEC 60909-0*¹⁾
- IEC TR3 60909-2:1992, *Electrical equipment – Data for short-circuit current calculations in accordance with IEC 60909*
- IEC 60909-3:1995, *Short-circuit current calculation in three-phase a.c. systems – Part 3: Currents during two separate simultaneous single-phase line-to-earth short circuits and partial short-circuit currents following through earth*
- IEC TR 60909-4:2000, *Short-circuit current calculation in three-phase a.c. systems – Part 4: Examples for the calculation of short-circuit currents*

The committee has decided that the contents of this publication will remain unchanged until 2007. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

The contents of the corrigendum of February 2002 have been included in this copy.

¹⁾ To be published.

SHORT-CIRCUIT CURRENTS IN THREE-PHASE AC SYSTEMS –

Part 0: Calculation of currents

1 General

1.1 Scope

This part of IEC 60909 is applicable to the calculation of short-circuit currents:

- in low-voltage three-phase a.c. systems
- in high-voltage three-phase a.c. systems

operating at a nominal frequency of 50 Hz or 60 Hz.

Systems at highest voltages of 550 kV and above with long transmission lines need special consideration.

This part of IEC 60909 establishes a general, practicable and concise procedure leading to results, which are generally of acceptable accuracy. For this calculation method, an equivalent voltage source at the short-circuit location is introduced. This does not exclude the use of special methods, for example the superposition method, adjusted to particular circumstances, if they give at least the same precision. The superposition method gives the short-circuit current related to the one load flow presupposed. This method, therefore, does not necessarily lead to the maximum short-circuit current.

This part of IEC 60909 deals with the calculation of short-circuit currents in the case of balanced or unbalanced short circuits.

In case of an accidental or intentional conductive path between one line conductor and local earth, the following two cases must be clearly distinguished with regard to their different physical properties and effects (resulting in different requirements for their calculation):

- line-to-earth short circuit, occurring in a solidly earthed neutral system or an impedance earthed neutral system;
- a single line-to-earth fault, occurring in an isolated neutral earthed system or a resonance earthed neutral system. This fault is beyond the scope of, and is therefore not dealt with in, this standard.

For currents during two separate simultaneous single-phase line-to-earth short circuits in an isolated neutral system or a resonance earthed neutral system, see IEC 60909-3.

Short-circuit currents and short-circuit impedances may also be determined by system tests, by measurement on a network analyzer, or with a digital computer. In existing low-voltage systems it is possible to determine the short-circuit impedance on the basis of measurements at the location of the prospective short circuit considered.

The calculation of the short-circuit impedance is in general based on the rated data of the electrical equipment and the topological arrangement of the system and has the advantage of being possible both for existing systems and for systems at the planning stage.

In general, two short-circuit currents, which differ in their magnitude, are to be calculated:

- the maximum short-circuit current which determines the capacity or rating of electrical equipment; and
- the minimum short-circuit current which can be a basis, for example, for the selection of fuses, for the setting of protective devices, and for checking the run-up of motors.

NOTE The current in a three-phase short circuit is assumed to be made simultaneously in all poles. Investigations of non-simultaneous short circuits, which may lead to higher aperiodic components of short-circuit current, are beyond the scope of this standard.

This standard does not cover short-circuit currents deliberately created under controlled conditions (short-circuit testing stations).

This part of IEC 60909 does not deal with the calculation of short-circuit currents in installations on board ships and aeroplanes.

1.2 Normative references

The following normative documents contain provisions which, through reference in this text, constitute provisions of this part of IEC 60909. For dated references, subsequent amendments to, or revisions of, any of these publications do not apply. However, parties to agreements based on this part of IEC 60909 are encouraged to investigate the possibility of applying the most recent editions of the normative documents indicated below. For undated references, the latest edition of the normative document referred to applies. Members of IEC and ISO maintain registers of currently valid International Standards.

IEC 60038:1983, *IEC standard voltages*

IEC 60050(131):1978, *International Electrotechnical Vocabulary – Chapter 131: Electric and magnetic circuits*

IEC 60050(151):1978, *International Electrotechnical Vocabulary – Chapter 151: Electric and magnetic devices*

IEC 60050-195:1998, *International Electrotechnical Vocabulary – Part 195: Earthing and protection against electric shock*

IEC 60056:1987, *High-voltage alternating-current circuit-breakers*

IEC 60071-1:1993, *Insulation coordination – Part 1: Definitions, principles and rules*

IEC 60781:1989, *Application guide for calculation of short-circuit currents in low-voltage radial systems*

IEC 60865-1:1993, *Short-circuit currents – Calculation of effects – Part 1: Definitions and calculation methods*

IEC TR 60909-1,— *Short-circuit currents calculation in three-phase a.c. systems – Part 1: Factors for the calculation of short-circuit currents in three-phase a.c. systems according to IEC 60909-0*¹⁾

IEC TR3 60909-2:1992, *Electrical equipment – Data for short-circuit current calculations in accordance with IEC 60909*

IEC 60909-3:1995, *Short-circuit current calculation in three-phase a.c. systems – Part 3: Currents during two separate simultaneous single phase line-to-earth short circuits and partial short-circuit currents flowing through earth*

IEC TR 60909-4:2000, *Short-circuit current calculation in three-phase a.c. systems – Part 4: Examples for the calculation of short-circuit currents*

IEC 60949:1988, *Calculation of thermally permissible short-circuit currents, taking into account non-adiabatic heating effects*

IEC 60986:1989, *Guide to the short-circuit temperature limits of electrical cables with a rated voltage from 1,8/3 (3,6) kV to 18/30 (36) kV*

¹⁾ To be published.