



INTERNATIONAL STANDARD



This extended version of IEC 61439-4:2023 includes the content of the references made to IEC 61439-1:2020

Low-voltage switchgear and controlgear assemblies – Part 4: Particular requirements for assemblies for construction sites (ACS)

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 29.130.20

ISBN 978-2-8322-7709-6

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	8
INTRODUCTION.....	11
1 Scope.....	12
2 Normative references	12
3 Terms and definitions	15
3.1 General terms	16
3.2 Constructional units of assemblies.....	18
3.3 External design of assemblies.....	19
3.4 Structural parts of assemblies.....	20
3.5 Conditions of installation of assemblies	22
3.6 Insulation characteristics	22
3.7 Protection against electric shock.....	25
3.8 Characteristics.....	29
3.9 Verification	33
3.10 Manufacturer	33
3.10.1 Function of the ACS.....	34
4 Symbols and abbreviations.....	34
5 Interface characteristics	35
5.1 General.....	35
5.2 Voltage ratings.....	35
5.2.1 Rated voltage (U_n) (of the assembly).....	35
5.2.2 Rated operational voltage (U_e) (of a circuit of an assembly)	36
5.2.3 Rated insulation voltage (U_i) (of a circuit of an assembly).....	36
5.2.4 Rated impulse withstand voltage (U_{imp}) (of the assembly)	36
5.3 Current ratings.....	36
5.3.1 Rated current of an ACS (I_{nA}).....	36
5.3.2 Rated current of a main outgoing circuit (I_{nC})	36
5.3.3 Group rated current of a main circuit (I_{ng}).....	37
5.3.4 Rated peak withstand current (I_{pk})	37
5.3.5 Rated short-time withstand current (I_{cW}) (of a main circuit of an assembly).....	37
5.3.6 Rated conditional short-circuit current (I_{CC}) (of an assembly or a circuit of an assembly)	38
5.4 Rated diversity factor (RDF).....	38
5.5 Rated frequency (f_n).....	38
5.6 Other characteristics.....	38
6 Information	39
6.1 ACS designation marking.....	39
6.2 Documentation.....	39
6.2.1 Information relating to the ACS.....	39
6.2.2 Instructions for handling, installation, operation and maintenance.....	40
6.3 Device and/or component identification.....	41
7 Service conditions	41
7.1 Normal service conditions	41
7.1.1 Climatic conditions	41
7.1.2 Pollution degree	41

7.2	Special service conditions.....	42
7.3	Conditions during transport, storage and installation	42
8	Constructional requirements	42
8.1	Strength of materials and parts	42
8.1.1	General	42
8.1.2	Protection against corrosion	43
8.1.3	Properties of insulating materials.....	43
8.1.4	Resistance to ultra-violet (UV) radiation.....	44
8.1.5	Mechanical strength	44
8.1.6	Lifting provision	44
8.2	Degree of protection provided by an assembly enclosure.....	44
8.2.1	Protection against mechanical impact (IK code).....	44
8.2.2	Protection against contact with live parts, ingress of solid foreign bodies and water (IP code)	45
8.2.3	Assembly with removable parts.....	45
8.3	Clearances and creepage distances.....	45
8.3.1	General	45
8.3.2	Clearances	46
8.3.3	Creepage distances.....	46
8.4	Protection against electric shock.....	47
8.4.1	General	47
8.4.2	Basic protection.....	47
8.4.3	Fault protection	48
8.4.4	Additional requirements for class II assemblies	51
8.4.5	Limitation of steady-state touch currents and charge	51
8.4.6	Operating and servicing conditions	52
8.5	Incorporation of switching devices and components	52
8.5.1	Fixed parts	52
8.5.2	Removable parts	52
8.5.3	Selection of switching devices and components.....	52
8.5.4	Installation of switching devices and components	53
8.5.5	Accessibility	53
8.5.6	Barriers	53
8.5.7	Direction of operation and indication of switching positions.....	54
8.5.8	Indicator lights and push-buttons	54
8.5.9	Power factor correction banks	54
8.5.101	Accessible parts of ACS	54
8.6	Internal electrical circuits and connections	54
8.6.1	Main circuits	54
8.6.2	Auxiliary circuits	55
8.6.3	Bare and insulated conductors.....	55
8.6.4	Selection and installation of non-protected live conductors to reduce the possibility of short-circuits	56
8.6.5	Identification of the conductors of main and auxiliary circuits.....	56
8.6.6	Identification of the protective conductor (PE, PEL, PEM, PEN) and of the neutral conductor (N) and the mid-point conductor (M) of the main circuits.....	56
8.6.7	Conductors in AC circuits passing through ferromagnetic enclosures or plates	57
8.7	Cooling	57

8.8	Terminals for external cables	57
8.101	Supports and securing devices of ACS	58
8.102	Cable outlet	59
9	Performance requirements	59
9.1	Dielectric properties	59
9.1.1	General	59
9.1.2	Power-frequency withstand voltage	59
9.1.3	Impulse withstand voltage	59
9.1.4	Protection of surge protective devices	60
9.2	Temperature-rise limits	60
9.2.1	General	60
9.2.2	Adjustment of rated currents for alternative ambient air temperatures.....	60
9.3	Short-circuit protection and short-circuit withstand strength	61
9.3.1	General	61
9.3.2	Information concerning short-circuit withstand strength.....	61
9.3.3	Relationship between peak current and short-time current.....	61
9.3.4	Coordination of protective devices	62
9.4	Electromagnetic compatibility (EMC).....	62
10	Design verification	62
10.1	General.....	62
10.2	Strength of materials and parts	64
10.2.1	General	64
10.2.2	Resistance to corrosion	64
10.2.3	Properties of insulating materials.....	66
10.2.4	Resistance to ultraviolet (UV) radiation.....	67
10.2.5	Lifting	68
10.2.6	Verification of mechanical strength	69
10.2.7	Marking	70
10.2.8	Mechanical operation.....	71
10.3	Degree of protection of assemblies (IP Code)	71
10.4	Clearances and creepage distances.....	72
10.5	Protection against electric shock and integrity of protective circuits	72
10.5.1	General	72
10.5.2	Effective earth continuity between the exposed-conductive-parts of the class I assembly and the protective circuit.....	72
10.5.3	Short-circuit withstand strength of the protective circuit	73
10.6	Incorporation of switching devices and components	73
10.6.1	General	73
10.6.2	Electromagnetic compatibility	74
10.7	Internal electrical circuits and connections	74
10.8	Terminals for external conductors	74
10.9	Dielectric properties	74
10.9.1	General	74
10.9.2	Power-frequency withstand voltage	74
10.9.3	Impulse withstand voltage	75
10.9.4	Testing of enclosures made of insulating material.....	77
10.9.5	External door or cover mounted operating handles of insulating material.....	77
10.9.6	Testing of conductors and hazardous live parts covered by insulating material to provide protection against electric shock.....	78

10.10	Temperature-rise	78
10.10.1	General	78
10.10.2	Verification by testing	78
10.10.3	Verification by comparison.....	85
10.10.4	Verification assessment.....	87
10.11	Short-circuit withstand strength.....	87
10.11.1	General	87
10.11.2	Circuits of assemblies which are exempted from the verification of the short-circuit withstand strength.....	87
10.11.3	Verification by comparison with a reference design – Using a checklist	88
10.11.4	Verification by comparison with a reference design(s) – Using calculation	88
10.11.5	Verification by test.....	88
10.12	Electromagnetic compatibility (EMC).....	94
11	Routine verification.....	94
11.1	General.....	94
11.2	Degree of protection against contact with hazardous live parts, ingress of solid foreign bodies and water of enclosures.....	95
11.3	Clearances and creepage distances.....	95
11.4	Protection against electric shock and integrity of protective circuits	95
11.5	Incorporation of built-in components	96
11.6	Internal electrical circuits and connections	96
11.7	Terminals for external conductors	96
11.8	Mechanical operation.....	96
11.9	Dielectric properties.....	96
11.10	Wiring, operational performance and function	96
101	Particular features of ACS	97
101.1	General requirements and functions.....	97
101.2	Incoming unit	97
101.3	Metering unit.....	97
101.4	Transformer unit	97
101.4.1	General	97
101.4.2	LV/ELV unit	97
101.4.3	LV/LV units.....	98
101.5	Outgoing units	98
Annex A (normative)	Minimum and maximum cross-section of copper cables suitable for connection to terminals for external cables (see 8.8)	109
Annex B (normative)	Method of calculating the cross-sectional area of protective conductors with regard to thermal stresses due to currents of short duration	110
Annex C (informative)	User information template	111
Annex D (informative)	Design verification	115
Annex E (informative)	Rated diversity factor	116
E.1	General.....	116
E.2	Rated diversity factor for outgoing circuits within an assembly	116
E.2.1	General	116
E.2.2	Example of an assembly with an RDF of 0,68	119
E.2.3	Example of an assembly with RDF declared for each section.....	120
Annex F (normative)	Measurement of clearances and creepage distances	121
F.1	Basic principles.....	121

F.2	Use of ribs	121
Annex G (normative)	Correlation between the nominal voltage of the supply system and the rated impulse withstand voltage of the equipment	126
Annex H (informative)	Operating current and power loss of copper cables	128
Annex I (informative)	Thermal equivalent of an intermittent current	130
Annex J (normative)	Electromagnetic compatibility (EMC)	131
J.1	General	131
Annex K (normative)	Operating current and power loss of bare copper bars	138
Annex L (informative)	Guidance on verification of temperature-rise	141
L.1	General	141
L.1.1	Principles	141
L.1.2	Current ratings of assemblies	141
L.2	Temperature-rise limits	142
L.3	Test	143
L.3.1	General	143
L.3.2	Method a) – Verification of the complete assembly (10.10.2.3.5)	143
L.3.3	Method b) – Verification considering individual functional units separately and the complete assembly (10.10.2.3.6)	143
L.3.4	Method c) – Verification considering individual functional units and the main and distribution busbars separately as well as the complete assembly (10.10.2.3.7)	144
L.4	Verification assessment	144
L.5	Verification by comparison with a reference design	144
Annex M (normative)	Verification of the short-circuit withstand strength of busbar structures by comparison with a reference design by calculation	145
Annex N (informative)	List of notes concerning certain countries	146
Bibliography	147
Figure 101	– Impact test using striking element	70
Figure E.1	– Typical assembly	117
Figure E.2	– Example 1: Table E.1 – Functional unit loading for an assembly with a rated diversity factor of 0,68	119
Figure E.3	– Example 2: Table E.1 – Functional unit loading for an assembly with a rated diversity factor of 0,6 in Section B and 0,68 in Section C	120
Figure F.1	– Measurement of clearance and creepage distances	125
Figure I.1	– Example of average heating effect calculation	130
Figure J.1	– Examples of ports	131
Figure L.1	– Not applicable	144
Table 1	– Minimum clearances in air (8.3.2)	99
Table 2	– Minimum creepage distances (8.3.3)	100
Table 3	– Cross-sectional area of a copper protective conductor (8.4.3.2.2)	101
Table 4	– Conductor selection and installation requirements (8.6.4)	101
Table 5	– Minimum terminal capacity for copper protective conductors (PE) (8.8)	101
Table 6	– Temperature-rise limits (9.2)	102
Table 7	– Values for the factor n^a (9.3.3)	103
Table 8	– Power-frequency withstand voltage for main circuits (10.9.2)	103

Table 9 – Power-frequency withstand voltage for auxiliary circuits (10.9.2)	103
Table 10 – Impulse withstand test voltages (10.9.3).....	103
Table 11 – Copper test conductors for rated currents up to 400 A inclusive (10.10.2.3.2).....	104
Table 12 – Copper test conductors for rated currents from 400 A to 7 000 A (10.10.2.3.2).....	105
Table 13 – Short-circuit verification by comparison with reference designs: checklist (10.5.3.3, 10.11.3 and 10.11.4).....	106
Table 14 – Relationship between prospective fault current and diameter of copper wire ...	107
Table 15 – Climatic conditions	107
Table 101 – Values of assumed loading.....	108
Table A.1 – Cross-section of copper cables suitable for connection to terminals for external cables	109
Table B.1 – Values of k for insulated protective conductors not incorporated in cables or bare protective conductors in contact with cable covering.....	110
Table C.1 – Items subject to agreement between the assembly manufacturer and the user	111
Table D.1 – List of design verifications to be performed	115
Table E.1 – Examples of loading for an assembly	118
Table F.1 – Minimum width of grooves.....	121
Table G.1 – Correspondence between the nominal voltage of the supply system and the equipment rated impulse withstand voltage	127
Table H.1 – Operating current and power loss of single-core copper cables with a permissible conductor temperature of 70 °C (ambient temperature inside the assembly: 55 °C).....	128
Table H.2 – Reduction factor k_1 for cables with a permissible conductor temperature of 70 °C (extract from IEC 60364-5-52:2009, Table B.52.14).....	129
Table J.1 – Tests for EMC immunity for environment A (see J.10.12.2).....	135
Table J.2 – Tests for EMC immunity for environment B (see J.10.12.2).....	136
Table J.3 – Acceptance criteria when electromagnetic disturbances are present.....	137
Table K.1 – Operating current and power loss of bare copper bars with rectangular cross-section, run horizontally and arranged with their largest face vertical, frequency 50 Hz to 60 Hz (ambient air temperature inside the assembly: 55 °C, temperature of the conductor 70 °C).....	138
Table K.2 – Factor k_4 for different temperatures of the air inside the assembly and/or for the conductors.....	139

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR ASSEMBLIES –

Part 1: General rules

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

This extended version (EXV) of the official IEC Standard provides the user with the comprehensive content of the Standard.

IEC 61439-4:2023 EXV includes the content of IEC 61439-4:2023, and the references made to IEC 61439-1:2020.

The specific content of IEC 61439-4:2023 is displayed on a [blue background](#).

IEC 61439-4 has been prepared by subcommittee 121B: Low-voltage switchgear and controlgear assemblies, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low voltage. It is an International Standard.

This second edition of IEC 61439-4 cancels and replaces the first edition published in 2012. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) alignment with IEC 61439-1:2020 regarding the structure and technical content, as applicable.

The text of this document is based on the following documents:

Draft	Report on voting
121B/183/FDIS	121B/188/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

This document is to be read in conjunction with IEC 61439-1:2020. The provisions of the general rules dealt with in IEC 61439-1:2020 are only applicable to this document insofar as they are specifically cited. When this document states “addition”, “modification” or “replacement”, the relevant text in IEC 61439-1:2020 is to be adapted accordingly.

Subclauses that are numbered with a 101 (102, 103, etc.) suffix are additional to the same subclause in IEC 61439-1:2020.

Tables and figures in this document that are new are numbered starting with 101.

New annexes in this document are lettered AA, BB, etc.

In this document, terms written in small capitals are defined in Clause 3.

The reader’s attention is drawn to the fact that Annex N lists all of the “in-some-country” clauses on differing practices of a less permanent nature relating to the subject of this document.

A list of all parts of the IEC 61439 series, under the general title *Low-voltage switchgear and controlgear assemblies*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be:

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

IMPORTANT – The "colour inside" logo on the cover page of this document indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The purpose of this document is to harmonize as far as practicable all rules and requirements of a general nature applicable to low-voltage switchgear and controlgear assemblies, in order to obtain uniformity of requirements and verification for assemblies and to avoid the need for verification in other standards. All those requirements for the various assembly standards which can be considered as general have therefore been gathered in this document together with specific subjects of wide interest and application, e.g. temperature-rise, dielectric properties, etc.

For each type of low-voltage switchgear and controlgear assembly, only two main standards are necessary to determine all requirements and the corresponding methods of verification:

- the basic standard, (this document) referred to as “IEC 61439-1” in the specific standards, covering the various types of low-voltage switchgear and controlgear assemblies;
- the specific assembly standard hereinafter also referred to as the relevant assembly standard.

For a general rule to apply to a specific assembly standard, it should be explicitly referred to by quoting this document followed by the relevant clause or subclause number e.g. “IEC 61439-1:2020, 9.1.3”.

A specific assembly standard may not require, and hence need not call up, a general rule where it is not applicable, or it can add requirements if the general rule is deemed inadequate in the particular case, but it may not deviate from it unless there is substantial technical justification detailed in the specific assembly standard.

Where, in this document, a cross-reference is made to another clause, the reference is to be taken to apply to that clause as amended by the specific assembly standard, where applicable.

Requirements in this document that are subject to agreement between the assembly manufacturer and the user are summarized in Annex C (informative). This schedule also facilitates the supply of information on basic conditions and additional user specifications to enable proper design, application and utilization of the assembly.

For the IEC 61439 series, the following parts are published:

- a) IEC 61439-1: General rules
- b) IEC 61439-2: Power switchgear and controlgear assemblies (PSC-assemblies)¹
- c) IEC 61439-3: Distribution boards intended to be operated by ordinary persons (DBO)
- d) IEC 61439-4: Particular requirements for assemblies for construction sites (ACS)
- e) IEC 61439-5: Assemblies for power distribution in public networks
- f) IEC 61439-6: Busbar trunking systems (busways)
- g) IEC 61439-7: Assemblies for specific applications such as marinas, camping sites, market squares, electric vehicle charging stations
- h) IEC TR 61439-0: Guidance to specifying assemblies.

This list is not exhaustive; additional parts can be developed as the need arises.

¹ IEC 61439-2 includes requirements for assemblies for use in photovoltaic installations.

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR ASSEMBLIES –

Part 1: General rules

1 Scope

NOTE Throughout this document, the abbreviation ACS (assembly for construction site, see 3.1.101) is used for a low-voltage switchgear and controlgear assembly intended for use on construction and similar sites.

This document defines the specific requirements of ACS as follows:

- assemblies for which the rated voltage does not exceed 1 000 V in case of AC or 1 500 V in case of DC;
- assemblies where the nominal primary voltage and the nominal secondary voltage of transformers incorporated in ACS are within the limits specified above;
- assemblies intended for use on construction sites, both indoors and outdoors, i.e. temporary places of work to which the public do not generally have access and where building construction, installation, repairs, alteration or demolition of property (buildings) or civil engineering (public works) or excavation or any other similar operations are carried out;
- transportable (semi-fixed) or MOBILE assemblies with enclosure.

The manufacture and/or assembly can be carried out by an entity other than by the original manufacturer (see 3.10.1 of IEC 61439-1:2020).

This document does not apply to individual devices and self-contained components, such as motor starters, fuse switches, electronic equipment, etc. which will comply with the relevant product standards.

This document does not apply to assemblies for use in the administrative centres of construction sites (offices, cloakrooms, meeting rooms, canteens, restaurants, dormitories, toilets, etc.).

Requirements for electrical protection provided by equipment manufactured according to this document are given in IEC 60364-7-704.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60068-2-2:2007, *Environmental testing – Part 2-2: Tests – Test B: Dry heat*

IEC 60068-2-11:1981, *Basic environmental testing procedures – Part 2-11: Tests – Test Ka: Salt mist*

IEC 60068-2-27, *Environmental testing – Part 2-27: Tests – Test Ea and guidance: Shock*

IEC 60068-2-30:2005, *Environmental testing – Part 2-30: Tests – Test Db: Damp heat, cyclic (12 h + 12 h cycle)*

IEC 60068-2-42, *Environmental testing – Part 2-42: Tests – Test Kc: Sulphur dioxide test for contacts and connections*

IEC 60073:2002, *Basic and safety principles for man-machine interface, marking and identification – Coding principles for indicators and actuators*

IEC 60085:2007, *Electrical insulation – Thermal evaluation and designation*

IEC 60364 (all parts), *Low-voltage electrical installations*

IEC 60364-4-41:2005, *Low-voltage electrical installations – Part 4-41: Protection for safety – Protection against electric shock*

IEC 60364-4-41:2005/AMD1:2017

IEC 60364-5-51:2005, *Electrical installations of buildings – Part 5-51: Selection and erection of electrical equipment – Common rules*

IEC 60364-5-52:2009, *Low-voltage electrical installations – Part 5-52: Selection and erection of electrical equipment – Wiring systems*

IEC 60364-7-704:2017, *Low-voltage electrical installations – Part 7-704: Requirements for special installations or locations – Construction and demolition site installations*

IEC 60439 (all parts), *Low-voltage switchgear and controlgear assemblies*²

IEC 60445:2017, *Basic and safety principles for man-machine interface, marking and identification – Identification of equipment terminals, conductor terminations and conductors*

IEC 60447:2004, *Basic and safety principles for man-machine interface, marking and identification – Actuating principles*

IEC 60529:1989, *Degrees of protection provided by enclosures (IP Code)*³

IEC 60529:1989/AMD1:1999

IEC 60529:1989/AMD2:2013

IEC 60695-2-10:2013, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60695-2-11:2014, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products (GWEPT)*

IEC 60695-2-12, *Fire hazard testing – Part 2-12: Glowing/hot-wire based test methods – Glow-wire flammability index (GWFI) test method for materials*

IEC 60865-1:2011, *Short-circuit currents – Calculation of effects – Part 1: Definitions and calculation methods*

IEC TR 60890:2014, *A method of temperature-rise verification of low-voltage switchgear and controlgear assemblies by calculation*

² Withdrawn. The IEC 60439 series has been cancelled and replaced by the IEC 61439 series.

³ There is a consolidated document edition 2.2 (2013) that includes IEC 60529 (1989) and its Amendment 1 (1999) and Amendment 2 (2013).

IEC 60947-4-1:2018, *Low-voltage switchgear and controlgear – Part 4-1: Contactors and motor-starters – Electromechanical contactors and motor-starters*

IEC 61000-4-2:2008, *Electromagnetic compatibility (EMC) – Part 4-2: Testing and measurement techniques – Electrostatic discharge immunity test*

IEC 61000-4-3:2006, *Electromagnetic compatibility (EMC) – Part 4-3: Testing and measurement techniques – Radiated, radio frequency, electromagnetic field immunity test*⁴
IEC 61000-4-3:2006/AMD1:2007
IEC 61000-4-3:2006/AMD2:2010

IEC 61000-4-4:2012, *Electromagnetic compatibility (EMC) – Part 4-4: Testing and measurement techniques – Electrical fast transient/burst immunity test*

IEC 61000-4-5:2014, *Electromagnetic compatibility (EMC) – Part 4-5: Testing and measurement techniques – Surge immunity test*⁵
IEC 61000-4-5:2014/AMD1:2017

IEC 61000-4-6:2013, *Electromagnetic compatibility (EMC) – Part 4-6: Testing and measurement techniques – Immunity to conducted disturbances, induced by radio-frequency fields*

IEC 61000-4-8:2009, *Electromagnetic compatibility (EMC) – Part 4-8: Testing and measurement techniques – Power frequency magnetic field immunity test*

IEC 61000-4-11:2004, *Electromagnetic compatibility (EMC) – Part 4-11: Testing and measurement techniques – Voltage dips, short interruptions and voltage variations immunity tests*
IEC 61000-4-11:2004/AMD1:2017

IEC 61000-6-3:2006, *Electromagnetic compatibility (EMC) – Part 6-3: Generic standards – Emission standard for residential, commercial and light-industrial environments*
IEC 61000-6-3:2006/AMD1:2010

IEC 61000-6-4:2018, *Electromagnetic compatibility (EMC) – Part 6-4: Generic standards – Emission standard for industrial environments*

IEC 61082-1:2014, *Preparation of documents used in electrotechnology – Part 1: Rules*

IEC 61180:2016, *High-voltage test techniques for low-voltage equipment – Definitions, test and procedure requirements, test equipment*

IEC 61439 (all parts), *Low-voltage switchgear and controlgear assemblies*

IEC 61439-1:2020, *Low-voltage switchgear and controlgear assemblies – Part 1: General rules*

IEC 61558-2-23, *Safety of transformers, reactors, power supply units and combinations thereof – Part 2-23: Particular requirements and tests for transformers and power supply units for construction sites*

⁴ There is a consolidated edition 3.2 (2010) that includes IEC 61000-4-3 (2006) and Amendment 1 (2007) and Amendment 2 (2010).

⁵ There is consolidated edition 3.1 (2017) that includes IEC 61000-4-5 (2014) and its Amendment 1 (2017).

IEC 61921:2017, *Power capacitors – Low-voltage power factor correction banks*

IEC 62208:2011, *Empty enclosures for low-voltage switchgear and controlgear assemblies – General requirements*

IEC 81346-1:2009, *Industrial systems, installations and equipment and industrial products – Structuring principles and reference designations – Part 1: Basic rules*

IEC 81346-2:2019, *Industrial systems, installations and equipment and industrial products – Structuring principles and reference designations – Part 2: Classification of objects and codes for classes*

CISPR 11:2015, *Industrial, scientific and medical equipment – Radio-frequency disturbance characteristics – Limits and methods of measurement*

CISPR 11:2015/AMD1:2016

CISPR 11:2015/AMD2:2019

CISPR 32:2015, *Electromagnetic compatibility of multimedia equipment – Emission requirements*

CISPR 32:2015/AMD1:2019

ISO 178:2010, *Plastics – Determination of flexural properties*

ISO 178:2010/AMD1:2013

ISO 179-1:2010, *Plastics – Determination of Charpy impact properties – Part 1: Non-instrumented impact test*

ISO 179-2:1997, *Plastics – Determination of Charpy impact properties – Part 2: Instrumented impact test*

ISO 179-2:1997/AMD1:2011

ISO 2409:2013, *Paints and varnishes – Cross-cut test*

ISO 4628-3:2016, *Paints and varnishes – Evaluation of degradation of coatings – Designation of quantity and size of defects, and of intensity of uniform changes in appearance – Part 3: Assessment of degree of rusting*

ISO 4892-2:2013, *Plastics – Methods of exposure to laboratory light sources – Part 2: Xenon-arc lamps*

ISO 7010, *Graphical symbols – Safety colours and safety signs – Registered safety signs*

INTERNATIONAL STANDARD

NORME INTERNATIONALE

**Low-voltage switchgear and controlgear assemblies –
Part 4: Particular requirements for assemblies for construction sites (ACS)**

**Ensembles d'appareillage à basse tension –
Partie 4: Exigences particulières pour ensembles de chantiers (EC)**



CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	6
4 Symbols and abbreviations	8
5 Interface characteristics.....	8
6 Information	9
7 Service conditions	10
8 Constructional requirements	10
9 Performance requirements.....	13
10 Design verification	13
11 Routine verification.....	16
Annexes	19
Annex C (informative) User information template	20
Annex D (informative) Design verification	24
Annex L (informative) Guidance on verification of temperature-rise.....	25
Annex M (normative) Verification of the short-circuit withstand strength of BUSBAR structures by comparison with a reference design by calculation.....	26
Annex N (informative) List of notes concerning certain countries	27
Bibliography.....	28
Figure 101 – Impact test using striking element	15
Table 101 – Values of assumed loading.....	18
Table C.1 – Items subject to agreement between the assembly manufacturer and the user	20
Table D.1 – List of design verifications to be performed	24

INTERNATIONAL ELECTROTECHNICAL COMMISSION

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR ASSEMBLIES –

Part 4: Particular requirements for assemblies for construction sites (ACS)

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) IEC draws attention to the possibility that the implementation of this document may involve the use of (a) patent(s). IEC takes no position concerning the evidence, validity or applicability of any claimed patent rights in respect thereof. As of the date of publication of this document, IEC had not received notice of (a) patent(s), which may be required to implement this document. However, implementers are cautioned that this may not represent the latest information, which may be obtained from the patent database available at <https://patents.iec.ch>. IEC shall not be held responsible for identifying any or all such patent rights.

IEC 61439-4 has been prepared by subcommittee 121B: Low-voltage switchgear and controlgear assemblies, of IEC technical committee 121: Switchgear and controlgear and their assemblies for low voltage. It is an International Standard.

This second edition of IEC 61439-4 cancels and replaces the first edition published in 2012. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) alignment with IEC 61439-1:2020 regarding the structure and technical content, as applicable.

The text of this document is based on the following documents:

Draft	Report on voting
121B/183/FDIS	121B/188/RVD

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this International Standard is English.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

This document is to be read in conjunction with IEC 61439-1:2020. The provisions of the general rules dealt with in IEC 61439-1:2020 are only applicable to this document insofar as they are specifically cited. When this document states “addition”, “modification” or “replacement”, the relevant text in IEC 61439-1:2020 is to be adapted accordingly.

Subclauses that are numbered with a 101 (102, 103, etc.) suffix are additional to the same subclause in IEC 61439-1:2020.

Tables and figures in this document that are new are numbered starting with 101.

New annexes in this document are lettered AA, BB, etc.

In this document, terms written in small capitals are defined in Clause 3.

The reader’s attention is drawn to the fact that Annex N lists all of the “in-some-country” clauses on differing practices of a less permanent nature relating to the subject of this document.

A list of all parts of the IEC 61439 series, under the general title *Low-voltage switchgear and controlgear assemblies*, can be found on the IEC website.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be:

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

LOW-VOLTAGE SWITCHGEAR AND CONTROLGEAR ASSEMBLIES –

Part 4: Particular requirements for assemblies for construction sites (ACS)

1 Scope

NOTE Throughout this document, the abbreviation ACS (assembly for construction site, see 3.1.101) is used for a low-voltage switchgear and controlgear assembly intended for use on construction and similar sites.

This document defines the specific requirements of ACS as follows:

- assemblies for which the rated voltage does not exceed 1 000 V in case of AC or 1 500 V in case of DC;
- assemblies where the nominal primary voltage and the nominal secondary voltage of transformers incorporated in ACS are within the limits specified above;
- assemblies intended for use on construction sites, both indoors and outdoors, i.e. temporary places of work to which the public do not generally have access and where building construction, installation, repairs, alteration or demolition of property (buildings) or civil engineering (public works) or excavation or any other similar operations are carried out;
- transportable (semi-fixed) or MOBILE assemblies with enclosure.

The manufacture and/or assembly can be carried out by an entity other than by the original manufacturer (see 3.10.1 of IEC 61439-1:2020).

This document does not apply to individual devices and self-contained components, such as motor starters, fuse switches, electronic equipment, etc. which will comply with the relevant product standards.

This document does not apply to assemblies for use in the administrative centres of construction sites (offices, cloakrooms, meeting rooms, canteens, restaurants, dormitories, toilets, etc.).

Requirements for electrical protection provided by equipment manufactured according to this document are given in IEC 60364-7-704.

2 Normative references

This clause of IEC 61439-1:2020 is applicable except as follows:

Addition:

IEC 60068-2-27, *Environmental testing – Part 2-27: Tests – Test Ea and guidance: Shock*

IEC 60068-2-42, *Environmental testing – Part 2-42: Tests – Test Kc: Sulphur dioxide test for contacts and connections*

IEC 60364-7-704:2017, *Low-voltage electrical installations – Part 7-704: Requirements for special installations or locations – Construction and demolition site installations*

IEC 61439-1:2020, *Low-voltage switchgear and controlgear assemblies – Part 1: General rules*

IEC 61558-2-23, *Safety of transformers, reactors, power supply units and combinations thereof*
– Part 2-23: *Particular requirements and tests for transformers and power supply units for construction sites*

SOMMAIRE

AVANT-PROPOS	31
1 Domaine d'application	33
2 Références normatives	33
3 Termes et définitions	34
4 Symboles et abréviations	36
5 Caractéristiques d'interface	36
6 Informations	37
7 Conditions d'emploi	38
8 Exigences de construction	39
9 Exigences de performance	41
10 Vérification de la conception	42
11 Vérification individuelle de série	44
Annexes	48
Annexe C (informative) Modèle d'information de l'utilisateur	49
Annexe D (informative) Vérification de la conception	53
Annexe L (informative) Recommandations concernant la vérification de l'échauffement	54
Annexe M (normative) Vérification de la tenue aux courts-circuits des structures de JEUX DE BARRES par comparaison avec une conception de référence par calcul	55
Annexe N (informative) Liste des notes concernant certains pays	56
Bibliographie	57
Figure 101 – Essai d'impact à l'aide d'une pièce de frappe	43
Tableau 101 – Valeurs de charge présumée	47
Tableau C.1 – Éléments soumis à un accord entre le constructeur de l'ensemble et l'utilisateur	49
Tableau D.1 – Liste des vérifications de conception à effectuer	53

COMMISSION ÉLECTROTECHNIQUE INTERNATIONALE

ENSEMBLES D'APPAREILLAGE À BASSE TENSION –

Partie 4: Exigences particulières pour ensembles de chantiers (EC)

AVANT-PROPOS

- 1) La Commission Électrotechnique Internationale (IEC) est une organisation mondiale de normalisation composée de l'ensemble des comités électrotechniques nationaux (Comités nationaux de l'IEC). L'IEC a pour objet de favoriser la coopération internationale pour toutes les questions de normalisation dans les domaines de l'électricité et de l'électronique. À cet effet, l'IEC – entre autres activités – publie des Normes internationales, des Spécifications techniques, des Rapports techniques, des Spécifications accessibles au public (PAS) et des Guides (ci-après dénommés "Publication(s) de l'IEC"). Leur élaboration est confiée à des comités d'études, aux travaux desquels tout Comité national intéressé par le sujet traité peut participer. Les organisations internationales, gouvernementales et non gouvernementales, en liaison avec l'IEC, participent également aux travaux. L'IEC collabore étroitement avec l'Organisation Internationale de Normalisation (ISO), selon des conditions fixées par accord entre les deux organisations.
- 2) Les décisions ou accords officiels de l'IEC concernant les questions techniques représentent, dans la mesure du possible, un accord international sur les sujets étudiés, étant donné que les Comités nationaux de l'IEC intéressés sont représentés dans chaque comité d'études.
- 3) Les Publications de l'IEC se présentent sous la forme de recommandations internationales et sont agréées comme telles par les Comités nationaux de l'IEC. Tous les efforts raisonnables sont entrepris afin que l'IEC s'assure de l'exactitude du contenu technique de ses publications; l'IEC ne peut pas être tenue responsable de l'éventuelle mauvaise utilisation ou interprétation qui en est faite par un quelconque utilisateur final.
- 4) Dans le but d'encourager l'uniformité internationale, les Comités nationaux de l'IEC s'engagent, dans toute la mesure possible, à appliquer de façon transparente les Publications de l'IEC dans leurs publications nationales et régionales. Toutes divergences entre toutes Publications de l'IEC et toutes publications nationales ou régionales correspondantes doivent être indiquées en termes clairs dans ces dernières.
- 5) L'IEC elle-même ne fournit aucune attestation de conformité. Des organismes de certification indépendants fournissent des services d'évaluation de conformité et, dans certains secteurs, accèdent aux marques de conformité de l'IEC. L'IEC n'est responsable d'aucun des services effectués par les organismes de certification indépendants.
- 6) Tous les utilisateurs doivent s'assurer qu'ils sont en possession de la dernière édition de cette publication.
- 7) Aucune responsabilité ne doit être imputée à l'IEC, à ses administrateurs, employés, auxiliaires ou mandataires, y compris ses experts particuliers et les membres de ses comités d'études et des Comités nationaux de l'IEC, pour tout préjudice causé en cas de dommages corporels et matériels, ou de tout autre dommage de quelque nature que ce soit, directe ou indirecte, ou pour supporter les coûts (y compris les frais de justice) et les dépenses découlant de la publication ou de l'utilisation de cette Publication de l'IEC ou de toute autre Publication de l'IEC, ou au crédit qui lui est accordé.
- 8) L'attention est attirée sur les références normatives citées dans cette publication. L'utilisation de publications référencées est obligatoire pour une application correcte de la présente publication.
- 9) L'IEC attire l'attention sur le fait que la mise en application du présent document peut entraîner l'utilisation d'un ou de plusieurs brevets. L'IEC ne prend pas position quant à la preuve, à la validité et à l'applicabilité de tout droit de brevet revendiqué à cet égard. À la date de publication du présent document, l'IEC n'avait pas reçu notification qu'un ou plusieurs brevets pouvaient être nécessaires à sa mise en application. Toutefois, il y a lieu d'avertir les responsables de la mise en application du présent document que des informations plus récentes sont susceptibles de figurer dans la base de données de brevets, disponible à l'adresse <https://patents.iec.ch>. L'IEC ne saurait être tenue pour responsable de ne pas avoir identifié de tels droits de brevets.

L'IEC 61439-4 a été établie par le sous-comité 121B: Ensembles d'appareillages à basse tension, du comité d'études 121 de l'IEC: Appareillages et ensembles d'appareillages basse tension. Il s'agit d'une Norme internationale.

Cette deuxième édition de l'IEC 61439-4 annule et remplace la première édition parue en 2012. Cette édition constitue une révision technique.

Cette édition inclut les modifications techniques majeures suivantes par rapport à l'édition précédente:

- a) alignement sur l'IEC 61439-1:2020 en ce qui concerne la structure et le contenu technique, selon le cas.

Le texte de ce document est issu des documents suivants:

Projet	Rapport de vote
121B/183/FDIS	121B/188/RVD

Le rapport de vote indiqué dans le tableau ci-dessus donne toute information sur le vote ayant abouti à son approbation.

La langue employée pour l'élaboration de cette Norme internationale est l'anglais.

Ce document a été rédigé selon les Directives ISO/IEC, Partie 2, il a été développé selon les Directives ISO/IEC, Partie 1 et les Directives ISO/IEC, Supplément IEC, disponibles sous www.iec.ch/members_experts/refdocs. Les principaux types de documents développés par l'IEC sont décrits plus en détail sous www.iec.ch/publications.

Le présent document doit être lu conjointement avec l'IEC 61439-1:2020. Les dispositions des règles générales traitées dans l'IEC 61439-1:2020 s'appliquent uniquement au présent document dans la mesure où elles sont spécifiquement citées. Lorsque le présent document mentionne "addition", "modification" ou "remplacement", le texte correspondant de l'IEC 61439-1:2020 doit être adapté en conséquence.

Les paragraphes qui sont numérotés avec un suffixe 101 (102, 103, etc.) sont ajoutés au même paragraphe de l'IEC 61439-1:2020.

Les nouveaux tableaux et figures du présent document sont numérotés à partir de 101.

Les nouvelles annexes du présent document sont désignées AA, BB, etc.

Dans le présent document, les termes écrits en petites majuscules sont définis à l'Article 3.

L'attention du lecteur est attirée sur le fait que l'Annexe N énumère tous les articles qui traitent des différences à caractère moins permanent inhérentes à certains pays, concernant le sujet du présent document.

Une liste de toutes les parties de la série IEC 61439, publiées sous le titre général *Ensembles d'appareillage à basse tension*, se trouve sur le site web de l'IEC.

Le comité a décidé que le contenu de ce document ne sera pas modifié avant la date de stabilité indiquée sur le site web de l'IEC sous webstore.iec.ch dans les données relatives au document recherché. À cette date, le document sera

- reconduit,
- supprimé,
- remplacé par une édition révisée, ou
- amendé.

ENSEMBLES D'APPAREILLAGE À BASSE TENSION –

Partie 4: Exigences particulières pour ensembles de chantiers (EC)

1 Domaine d'application

NOTE Dans le présent document, l'abréviation EC (ensemble de chantier, voir 3.1.101) désigne un ensemble d'appareillage à basse tension destiné à être utilisé sur des chantiers ou sites similaires.

Le présent document définit les exigences particulières des EC comme suit:

- ensembles dont la tension assignée ne dépasse pas 1 000 V en courant alternatif ou 1 500 V en courant continu;
- ensembles dont les valeurs nominales des tensions primaire et secondaire des transformateurs incorporés dans les EC se situent dans les limites spécifiées ci-dessus;
- ensembles destinés à être utilisés sur des chantiers, à l'intérieur comme à l'extérieur, c'est-à-dire des lieux de travail temporaires qui ne sont généralement pas accessibles au public et où sont exécutés des travaux de construction, d'installation, de réparation, de modification ou de démolition d'immeubles (bâtiments) ou d'ouvrage de génie civil (travaux publics) ou encore des travaux de terrassement ou tout autre travail analogue;
- ensembles de type transportable (semi-fixe) ou MOBILE avec enveloppe.

La fabrication et/ou l'assemblage peuvent être réalisés par une entité qui n'est pas le constructeur d'origine (voir 3.10.1 de l'IEC 61439-1:2020).

Le présent document ne s'applique pas aux appareils individuels et aux composants indépendants, tels que les démarreurs de moteurs, fusibles-interrupteurs, matériels électroniques, etc. qui sont conformes aux normes de produit applicables.

Le présent document ne s'applique pas aux ensembles destinés à être utilisés dans les locaux de service des chantiers (bureaux, vestiaires, salles de réunion, cantines, restaurants, dortoirs, locaux sanitaires, etc.).

Les exigences de protection électrique fournies par l'équipement fabriqué selon le présent document sont données dans l'IEC 60364-7-704.

2 Références normatives

L'article de l'IEC 61439-1:2020 s'applique, avec les exceptions suivantes:

Addition:

IEC 60068-2-27, *Essais d'environnement – Partie 2-27: Essais – Essai Ea et guide: Chocs*

IEC 60068-2-42, *Essais d'environnement – Partie 2-42: Essais – Essai Kc: Essai à l'anhydride sulfureux pour contacts et connexions*

IEC 60364-7-704:2017, *Installations électriques à basse tension – Partie 7-704: Exigences pour les installations ou emplacements spéciaux – Installations de chantiers de construction et de démolition*

IEC 61439-1:2020, *Ensembles d'appareillage à basse tension – Partie 1: Règles générales*

IEC 61558-2-23, *Sécurité des transformateurs, bobines d'inductance, blocs d'alimentation et des combinaisons de ces éléments – Partie 2-23: Règles particulières et essais pour les transformateurs et les blocs d'alimentation pour chantiers*