



TECHNICAL REPORT



Fibre optic communication system design guidelines – Part 14: Determination of the uncertainties of attenuation measurements in fibre plants

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 33.180.01

ISBN 978-2-8322-7069-1

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	7
1 Scope.....	8
2 Normative references	8
3 Terms, definitions and abbreviated terms	8
3.1 Terms and definitions.....	8
3.2 Abbreviated terms.....	10
4 Overview of uncertainty	10
4.1 What is uncertainty?	10
4.2 Origin of uncertainties.....	11
4.3 What may not be considered as uncertainty?	11
5 Fibre cabling attenuation measurement	11
5.1 Test methods	11
5.2 Sources of uncertainty to be considered	11
5.2.1 Analysis.....	11
5.2.2 Uncertainties due to the environment.....	14
5.2.3 Uncertainties due to operator skills	14
5.2.4 Uncertainties due to test methods.....	14
5.2.5 Uncertainties due to measuring instruments	14
5.2.6 Uncertainties due to the setup	16
5.2.7 Uncertainties due to cabling.....	16
6 Uncertainties estimation	17
6.1 Measurement model.....	17
6.2 Accumulation of uncertainties	19
7 General representation of the equation using sensitivity coefficients.....	19
8 Calculation	23
8.1 Combined standard uncertainty.....	23
8.2 Expanded uncertainty	23
8.3 Determination of the coverage factor k	23
8.3.1 General approach	23
8.3.2 Discussion.....	23
8.3.3 Typical values of degree of freedom	24
Annex A (informative) Mathematical basis.....	25
A.1 General.....	25
A.2 Type A evaluation of uncertainty	25
A.3 Type B evaluation of uncertainty	25
A.4 Determining the combined standard uncertainty.....	26
A.5 Reporting	27
Annex B (informative) Test methods	28
B.1 Test methods as per IEC 61280-4-1 and 61280-4-2	28
B.1.1 General	28
B.1.2 Measurement configuration.....	28
B.1.3 One-cord reference configuration	28
B.1.4 Two-cord reference configuration	29
B.1.5 Three-cord reference configuration	29

B.2	Test methods defined in ISO/IEC 14763-3:2014	29
B.2.1	General	29
B.2.2	Channels	30
B.2.3	Links.....	31
Annex C	(informative) Uncertainties evaluation	32
C.1	Type A uncertainties	32
C.1.1	General	32
C.1.2	Evaluation of optical source instability and associated uncertainties	32
C.2	Type B uncertainties	32
C.2.1	General	32
C.2.2	Evaluation of the power meter noise	32
C.2.3	Elements to be considered for power meter stability analysis.....	33
C.2.4	Evaluation of the centre wavelength dependence	33
C.2.5	Spectral width dependence.....	35
C.2.6	Evaluation of the uncertainties due to MM launch conditions	35
C.2.7	Evaluation of the PDL	36
C.2.8	Uncertainty of absolute power measurement	37
Annex D	(informative) Typical values of uncertainties	38
Annex E	(informative) Linear to dB scale conversion of uncertainties.....	40
E.1	Definition of decibel	40
E.2	Conversion of relative uncertainties	40
Bibliography	41
Figure 1	– Fishbone analysis	13
Figure 2	– Measurement model.....	17
Figure B.1	– Measurement configuration.....	28
Figure B.2	– One-cord reference measurement.....	28
Figure B.3	– Two-cord reference measurement.....	29
Figure B.4	– Three-cord reference measurement	29
Figure B.5	– Measurement on channel.....	30
Figure B.6	– Channel reference measurement	30
Figure B.7	– Link measurement configuration	31
Figure B.8	– Link reference measurement.....	31
Figure C.1	– Typical spectral response of a fibre	34
Figure C.2	– Uncertainties due to the launch conditions for a given loss	36
Table 1	– Source of uncertainty (raw list).....	12
Table 2	– Uncertainties due to measuring instruments	15
Table 3	– Uncertainties due to the setup	16
Table 4	– Uncertainties due to cabling	16
Table 5	– Sensitivity coefficients for IEC 61280-4-1 and IEC 61280-4-2 methods.....	21
Table 6	– Sensitivity coefficients for ISO/IEC 14763-3:2014 methods.....	22
Table 7	– Values of k_{95} for different values of ν	24
Table 8	– Typical values of ν_i	24
Table C.1	– Spectral attenuation coefficients	34

Table C.2 – Sensitivity coefficients	35
Table D.1 – Typical values of uncertainties	39

INTERNATIONAL ELECTROTECHNICAL COMMISSION

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 14: Determination of the uncertainties of attenuation measurements in fibre plants

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

The main task of IEC technical committees is to prepare International Standards. However, a technical committee may propose the publication of a technical report when it has collected data of a different kind from that which is normally published as an International Standard, for example "state of the art".

IEC 61282-14, which is a Technical Report, has been prepared by subcommittee 86C: Fibre optic systems and active devices, of IEC technical committee 86: Fibre optics.

This publication contains an attached file titled "Supplemental Data for Section 8" in the form of an Excel spreadsheet. This file is intended to be used as a complement and does not form an integral part of the standard.

This second edition cancels and replaces the first edition published in 2016. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) in the title: replacement of "guide" by "guidelines";
- b) text adaptation to allow both standard grade B and reference grade connectors for termination of test cords;
- c) addition of values needed for calculation of uncertainties, when standard grade connectors are used, to Annex D;
- d) correction of minor inconsistencies in Equation (18) and after.

The text of this Technical Report is based on the following documents:

Enquiry draft	Report on voting
86C/1572/DTR	86C/1584/RVDTR

Full information on the voting for the approval of this Technical Report can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 61282 series, published under the general title *Fibre optic communication system design guides*, can be found on the IEC website.

Future standards in this series will carry the new general title as cited above. Titles of existing standards in this series will be updated at the time of the next edition.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

A bilingual version of this publication may be issued at a later date.

IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.

INTRODUCTION

The determination of the uncertainty of every measurement is a key activity, which should be performed by applying dedicated methods as extensively presented in reference documents such as ISO/IEC Guide 98-3:2008, *Guide to the uncertainty of measurement (GUM)*.

This document shows a practical application of these methods for the determination of the measurement uncertainty of the attenuation of fibre optic cabling using optical light sources and power meters as defined in IEC 61280-4-1 and IEC 61280-4-2.

It includes the review of all contributing factors to uncertainty (such as launch conditions, spectral width, stability of source, power meter polarization, resolution, linearity, quality of test cord connectors) to determine the overall measurement uncertainty. This part of IEC 61282 applies to the measurement of single mode or multimode fibres without restrictions to the fibre parameters, including mode field diameter, core diameter and numerical aperture. However, numerical values given in Clause C.2 and typical values given in Annex D are not valid for multimode fibres types A2, A3 and A4.

The list of uncertainties presented in this document is related to this particular application and should be reconsidered if measurement conditions are not compliant to measurement requirements defined by IEC 61280-4-1 and IEC 61280-4-2.

The reference document for general uncertainty calculations is ISO/IEC Guide 98-3:2008, and this document does not intend to replace it; it only represents an example and should be used in conjunction with ISO/IEC Guide 98-3:2008. A brief introduction to the determination of measurement uncertainty according to ISO/IEC Guide 98-3:2008 is given in Annex A.

This document is associated with a calculation spreadsheet (Excel) containing practical calculations.

FIBRE OPTIC COMMUNICATION SYSTEM DESIGN GUIDELINES –

Part 14: Determination of the uncertainties of attenuation measurements in fibre plants

1 Scope

This part of IEC 61282, which is a Technical Report, establishes the detailed analysis and calculation of the uncertainties related to the measurement of the attenuation of both multimode and single mode optical fibre cabling using optical light sources and power meters.

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 61280-4-1:2009, *Fibre-optic communication subsystem test procedures – Part 4-1: Installed cable plant – Multimode attenuation measurement*

IEC 61280-4-2:2014, *Fibre-optic communication subsystem test procedures – Part 4-2: Installed cable plant – Single-mode attenuation and optical return loss measurement*

ISO/IEC Guide 98-3:2008, *Uncertainty of measurement – Part 3: Guide to the expression of uncertainty in measurement* (GUM:1995)