This is a preview - click here to buy the full publication

INTERNATIONAL STANDARD

ISO/ IEC/IEEE 8802-11

Third edition
2022-07

Telecommunications and information exchange between systems — Specific requirements for local and metropolitan area networks —

Part 11: Wireless LAN medium access control (MAC) and physical layer (PHY) specifications

Télécommunications et échange entre systèmes informatiques — Exigences pour les réseaux locaux et métropolitains —

Partie 11: Spécifications du contrôle d'accès du milieu sans fil (MAC) et de la couche physique (PHY)

Reference number
ISO/IEC/IEEE 8802-11:2022(E)

© IEEE 2022

This is a preview - click here to buy the full publication

COPYRIGHT PROTECTED DOCUMENT

© IEEE 2022

All rights reserved. Unless otherwise specified, or required in the context of its implementation, no part of this publication may be reproduced or utilized otherwise in any form or by any means, electronic or mechanical, including photocopying, or posting on the internet or an intranet, without prior written permission. Permission can be requested from IEEE at the address below.

Institute of Electrical and Electronics Engineers, Inc
3 Park Avenue, New York
NY 10016-5997, USA

Email: stds.ipr@ieee.org
Website: www.ieee.org

Published in Switzerland

© IEEE 2022 – All rights reserved

This is a preview - click here to buy the full publication

Foreword

ISO (the International Organization for Standardization) and IEC (the International Electrotechnical Commission) form the specialized system for worldwide standardization. National bodies that are members of ISO or IEC participate in the development of International Standards through technical committees established by the respective organization to deal with particular fields of technical activity. ISO and IEC technical committees collaborate in fields of mutual interest. Other international organizations, governmental and non-governmental, in liaison with ISO and IEC, also take part in the work.

The procedures used to develop this document and those intended for its further maintenance are described in the ISO/IEC Directives, Part 1. In particular, the different approval criteria needed for the different types of ISO/IEC documents should be noted. This document was drafted in accordance with the editorial rules of the ISO/IEC Directives, Part 2 (see www.iso.org/directives or www.iec.ch/members_experts/refdocs).

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO and IEC shall not be held responsible for identifying any or all such patent rights. Details of any patent rights identified during the development of the document will be in the Introduction and/or on the ISO list of patent declarations received (see www.iso.org/patents) or the IEC list of patent declarations received (see https://patents.iec.ch).

Any trade name used in this document is information given for the convenience of users and does not constitute an endorsement.

For an explanation of the voluntary nature of standards, the meaning of ISO specific terms and expressions related to conformity assessment, as well as information about ISO's adherence to the World Trade Organization (WTO) principles in the Technical Barriers to Trade (TBT), see www.iso.org/iso/foreword.html. In the IEC, see www.iec.ch/understanding-standards.

ISO/IEC/IEEE 8802-11 was prepared by the LAN/MAN of the IEEE Computer Society (as IEEE 802.11-2020) and drafted in accordance with its editorial rules. It was adopted, under the “fast-track procedure” defined in the Partner Standards Development Organization cooperation agreement between ISO and IEEE, by Joint Technical Committee ISO/IEC JTC 1, *Information technology*, Subcommittee SC 6, *Telecommunications and information exchange between systems*.

This third edition cancels and replaces the second edition (ISO/IEC/IEEE 8802-11:2018), which has been technically revised. It also incorporates the Amendments ISO/IEC/IEEE 8802-11:2018/Amd 1:2019, ISO/IEC/IEEE 8802-11:2018/Amd 2:2019, ISO/IEC/IEEE 8802-11:2018/Amd 3:2020, ISO/IEC/IEEE 8802-11:2018/Amd 4:2020, ISO/IEC/IEEE 8802-11:2018/Amd 5:2020.

A list of all parts in the ISO/IEC/IEEE 8802 series can be found on the ISO and IEC websites.

© IEEE 2021 – All rights reserved

This is a preview - click here to buy the full publication

Any feedback or questions on this document should be directed to the user's national standards body. A complete listing of these bodies can be found at www.iso.org/members.html and www.iec.ch/national-committees.

© IEEE 2021 – All rights reserved

This is a preview - click here to buy the full publication

IEEE Std 802.11™-2020
(Revision of IEEE Std 802.11-2016)

**IEEE Standard for Information Technology—
Telecommunications and Information Exchange between Systems
Local and Metropolitan Area Networks—
Specific Requirements**

Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications

Developed by the

LAN/MAN Standards Committee
of the
IEEE Computer Society

Approved 3 December 2020

IEEE SA Standards Board

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Abstract: Technical corrections and clarifications to IEEE Std 802.11 for wireless local area networks (WLANs) as well as enhancements to the existing medium access control (MAC) and physical layer (PHY) functions are specified in this revision. Amendments 1 to 5 published in 2016 and 2018 have also been incorporated into this revision.

Keywords: 2.4 GHz, 256-QAM, 3650 MHz, 4.9 GHz, 5 GHz, 5.9 GHz, 60 GHz, advanced encryption standard, AES, audio, beamforming, carrier sense multiple access/collision avoidance, CCMP, channel switching, clustering, contention based access period, Counter mode with Cipher-block chaining Message authentication code Protocol, confidentiality, CSMA/CA, DFS, direct link, directional multi-gigabit, dynamic allocation of service period, dynamic extension of service period, dynamic frequency selection, dynamic truncation of service period, E911, EDCA, emergency alert system, emergency services, fast session transfer, forwarding, GCMP, generic advertisement service, high throughput, IEEE 802.11™, international roaming, interworking, interworking with external networks, LAN, local area network, MAC, management, measurement, medium access control, media-independent handover, medium access controller, mesh, MIS, millimeter-wave, MIMO, MIMO-OFDM, multi-band operation, multi-hop, multi-user MIMO, multiple input multiple output, network advertisement, network discovery, network management, network selection, noncontiguous frequency segments, OCB, path-selection, personal basic service set, PHY, physical layer, power saving, QoS, quality of service, quality-of-service management frame, radio, radio frequency, RF, radio resource, radio management, relay operation, spatial sharing, SSPN, subscriber service provider, television white spaces, TPC, transmit power control, video, wireless access in vehicular environments, wireless LAN, wireless local area network, WLAN, wireless network management, zero-knowledge proof

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2021 by The Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 26 February 2021. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by The Institute of Electrical and Electronics Engineers, Incorporated.

Print: ISBN 978-1-5044-7283-8 STD24548
PDF: ISBN 978-1-5044-7284-5 STD24548

IEEE prohibits discrimination, harassment and bullying.
For more information, visit http://www.ieee.org/web/aboutus/whatis/policies/p9-26.html.
No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Important Notices and Disclaimers Concerning IEEE Standards Documents

IEEE Standards documents are made available for use subject to important notices and legal disclaimers. These notices and disclaimers, or a reference to this page (https://standards.ieee.org/ipr/disclaimers.html), appear in all standards and may be found under the heading "Important Notices and Disclaimers Concerning IEEE Standards Documents."

Notice and Disclaimer of Liability Concerning the Use of IEEE Standards Documents

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE SA) Standards Board. IEEE develops its standards through an accredited consensus development process, which brings together volunteers representing varied viewpoints and interests to achieve the final product. IEEE Standards are documents developed by volunteers with scientific, academic, and industry-based expertise in technical working groups. Volunteers are not necessarily members of IEEE or IEEE SA, and participate without compensation from IEEE. While IEEE administers the process and establishes rules to promote fairness in the consensus development process, IEEE does not independently evaluate, test, or verify the accuracy of any of the information or the soundness of any judgments contained in its standards.

IEEE makes no warranties or representations concerning its standards, and expressly disclaims all warranties, express or implied, concerning this standard, including but not limited to the warranties of merchantability, fitness for a particular purpose and non-infringement. In addition, IEEE does not warrant or represent that the use of the material contained in its standards is free from patent infringement. IEEE Standards documents are supplied "AS IS" and "WITH ALL FAULTS."

Use of an IEEE standard is wholly voluntary. The existence of an IEEE Standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard.

In publishing and making its standards available, IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity, nor is IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing any IEEE Standards document, should rely upon his or her own independent judgment in the exercise of reasonable care in any given circumstances or, as appropriate, seek the advice of a competent professional in determining the appropriateness of a given IEEE standard.

IN NO EVENT SHALL IEEE BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO: THE NEED TO PROCURE SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE PUBLICATION, USE OF, OR RELIANCE UPON ANY STANDARD, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE AND REGARDLESS OF WHETHER SUCH DAMAGE WAS FORESEEABLE.

Translations

The IEEE consensus development process involves the review of documents in English only. In the event that an IEEE standard is translated, only the English version published by IEEE is the approved IEEE standard.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Official statements

A statement, written or oral, that is not processed in accordance with the IEEE SA Standards Board Operations Manual shall not be considered or inferred to be the official position of IEEE or any of its committees and shall not be considered to be, nor be relied upon as, a formal position of IEEE. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that the presenter's views should be considered the personal views of that individual rather than the formal position of IEEE, IEEE SA, the Standards Committee, or the Working Group.

Comments on standards

Comments for revision of IEEE Standards documents are welcome from any interested party, regardless of membership affiliation with IEEE or IEEE SA. However, **IEEE does not provide interpretations, consulting information, or advice pertaining to IEEE Standards documents**.

Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Since IEEE standards represent a consensus of concerned interests, it is important that any responses to comments and questions also receive the concurrence of a balance of interests. For this reason, IEEE and the members of its Societies and Standards Coordinating Committees are not able to provide an instant response to comments, or questions except in those cases where the matter has previously been addressed. For the same reason, IEEE does not respond to interpretation requests. Any person who would like to participate in evaluating comments or in revisions to an IEEE standard is welcome to join the relevant IEEE working group. You can indicate interest in a working group using the Interests tab in the Manage Profile & Interests area of the IEEE SA myProject system. An IEEE Account is needed to access the application.

Comments on standards should be submitted using the Contact Us form.

Laws and regulations

Users of IEEE Standards documents should consult all applicable laws and regulations. Compliance with the provisions of any IEEE Standards document does not constitute compliance to any applicable regulatory requirements. Implementers of the standard are responsible for observing or referring to the applicable regulatory requirements. IEEE does not, by the publication of its standards, intend to urge action that is not in compliance with applicable laws, and these documents may not be construed as doing so.

Data privacy

Users of IEEE Standards documents should evaluate the standards for considerations of data privacy and data ownership in the context of assessing and using the standards in compliance with applicable laws and regulations.

Copyrights

IEEE draft and approved standards are copyrighted by IEEE under US and international copyright laws. They are made available by IEEE and are adopted for a wide variety of both public and private uses. These include both use, by reference, in laws and regulations, and use in private self-regulation, standardization, and the promotion of engineering practices and methods. By making these documents available for use and adoption by public authorities and private users, IEEE does not waive any rights in copyright to the documents.

Photocopies

Subject to payment of the appropriate licensing fees, IEEE will grant users a limited, non-exclusive license to photocopy portions of any individual standard for company or organizational internal use or individual, non-commercial use only. To arrange for payment of licensing fees, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400; https://www.copyright.com/. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Updating of IEEE Standards documents

Users of IEEE Standards documents should be aware that these documents may be superseded at any time by the issuance of new editions or may be amended from time to time through the issuance of amendments, corrigenda, or errata. An official IEEE document at any point in time consists of the current edition of the document together with any amendments, corrigenda, or errata then in effect.

Every IEEE standard is subjected to review at least every 10 years. When a document is more than 10 years old and has not undergone a revision process, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE standard.

In order to determine whether a given document is the current edition and whether it has been amended through the issuance of amendments, corrigenda, or errata, visit IEEE Xplore or contact IEEE. For more information about the IEEE SA or IEEE's standards development process, visit the IEEE SA Website.

Errata

Errata, if any, for all IEEE standards can be accessed on the IEEE SA Website. Search for standard number and year of approval to access the web page of the published standard. Errata links are located under the Additional Resources Details section. Errata are also available in IEEE Xplore. Users are encouraged to periodically check for errata.

Patents

IEEE Standards are developed in compliance with the IEEE SA Patent Policy.

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken by the IEEE with respect to the existence or validity of any patent rights in connection therewith. If a patent holder or patent applicant has filed a statement of assurance via an Accepted Letter of Assurance, then the statement is listed on the IEEE SA Website at https://standards.ieee.org/about/sasb/patcom/patents.html. Letters of Assurance may indicate whether the Submitter is willing or unwilling to grant licenses under patent rights without compensation or under reasonable rates, with reasonable terms and conditions that are demonstrably free of any unfair discrimination to applicants desiring to obtain such licenses.

Essential Patent Claims may exist for which a Letter of Assurance has not been received. The IEEE is not responsible for identifying Essential Patent Claims for which a license may be required, for conducting inquiries into the legal validity or scope of Patents Claims, or determining whether any licensing terms or conditions provided in connection with submission of a Letter of Assurance, if any, or in any licensing agreements are reasonable or non-discriminatory. Users of this standard are expressly advised that determination of the validity of any patent rights, and the risk of infringement of such rights, is entirely their own responsibility. Further information may be obtained from the IEEE Standards Association.

IMPORTANT NOTICE

IEEE Standards do not guarantee or ensure safety, security, health, or environmental protection, or ensure against interference with or from other devices or networks. IEEE Standards development activities consider research and information presented to the standards development group in developing any safety recommendations. Other information about safety practices, changes in technology or technology implementation, or impact by peripheral systems also may be pertinent to safety considerations during implementation of the standard. Implementers and users of IEEE Standards documents are responsible for determining and complying with all appropriate safety, security, environmental, health, and interference protection practices and all applicable laws and regulations.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Participants

At the time this revision was sent to sponsor ballot, the IEEE 802.11 Working Group (WG) had the following officers:

Dorothy V. Stanley, *Chair*
Jon W. Rosdahl, *1st Vice Chair*
Robert Stacey, *2nd Vice Chair*
Stephen McCann, *Secretary*

The officers of the WG Task Group md and the members of the WG ballot group for this revision are as follows:

Dorothy V. Stanley, *Chair*
Mark Hamilton, *Vice Chair*
Michael Montemurro, *Vice Chair*
Jon W. Rosdahl, *Secretary*
Emily H. Qi, *Technical Editor*
Edward Au, *Technical Sub-editor*

Osama S. Aboulmagd
Tomoko Adachi
Jinsoo Ahn
Woojin Ahn
Kosuke Aio
Carlos H. Aldana
Yaron Alpert
Song-Haur An
Carol Ansley
Lee R. Armstrong
Yusuke Asai
Alfred Asterjadhi
Kwok Shum S. Au
Vijay Auluck
Geert A. Awater
Shahrnaz Azizi
Robert Baeten
Eugene Baik
Stephane Baron
Anuj Batra
Friedbert Berens
Christian Berger
Nehru Bhandaru
John Buffington
George Calcev
Rui Cao
Laurent Cariou
William Carney
Ricky Chair
Clint F. Chaplin
Jiamin Chen
Xiaogang Chen
George Cherian
Dmitry Cherniavsky
Rojan Chitrakar
Hangyu Cho
Jinsoo Choi
Liwen Chu
Jinyoung Chun
Dana Ciochina
Sean Coffey
Carlos Cordeiro
Claudio da Silva
Subir Das
Rolf J. de Vegt
Pierre Debergh
Donald E. Eastlake
Peter Ecclesine
Richard Edgar
Marc Emmelmann
Vinko Erceg
Andrew Estrada
Ping Fang
Yonggang Fang
Xiang Feng
Norman Finn
Matthew J. Fischer
Michael Fischer
Shunsuke Fujio
Sho Furuichi
Ming Gan
Eduard Garcia Villegas
Chittabrata Ghosh
James P. Gilb
Tim Godfrey
Niranjan Grandhe
Michael Grigat
Qiang Guo
Yuchen Guo
Robert Hall
Xiao Han
Thomas Handte
Christopher J. Hansen
Chris Hartman
Victor Hayes
Allen D. Heberling
Ahmadreza Hedayat
Robert F. Heile
Guido R. Hiertz
Duncan Ho
Hanseul Hong
Koji Horisaki
Chunyu Hu
Lei Huang
Po-Kai Huang
Zhiyong Huang
Sung Hyun H. Hwang
Yasuhiko Inoue
Timothy Jeffries
Jia Jia
Jinjing Jiang
Liang Jin
Allan Jones
Vincent Knowles Jones
Volker Jungnickel
Christophe Jurczak
Carl W. Kain
Naveen K. Kakani
Dzevdan Kapetanovic
Assaf Y. Kasher
Oren Kedem
Richard H. Kennedy
Stuart J. Kerry
Evgeny Khorov
Jeongki Kim
Jin Min Kim
Sang Gook Kim
Suhwook Kim
Yongho Kim
Youhan Kim
Jarkko Kneckt
Geonjung Ko
Fumihide Kojima
Bruce P. Kraemer
Manish Kumar
Rajesh Kumar
Massinissa Lalam
Zhou Lan
Leonardo Lanante
James Lansford

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Jae Seung S. Lee
Sungeun Lee
Suzanne Leicht
James Lepp
Joseph Levy
Dejian Li
Guoqing Li
Huan-Bang Li
Qiang Li
Yanchun Li
Yunbo Li
Dong Guk Lim
Yingpei Lin
Erik Lindskog
Der-Zheng Liu
Jianhan Liu
Yong Liu
Peter Loc
Artyom Lomayev
Hui-Ling Lou
Kaiying Lv
Lily Lv
Jing Ma
Narendar Madhavan
Jouni K. Malinen
Alexander Maltsev
Hiroshi Mano
Roger Marks
Stephen McCann
Simone Merlin
Apurva Mody
Bibhu Mohanty
Hitoshi Morioka
Yuichi Morioka
Hiroyuki Motozuka
Robert Mueller
Yutaka Murakami
Andrew Myles
Patrice Nezou
Paul Nikolich
Yujin Noh
John Notor
Minseok Oh
Oghenekome Oteri
Kazuyuki Ozaki
Stephen Palm
Eunsung Park
Minyoung Park
Sung-jin Park
Glenn Parsons
Abhishek Patil
Hakan Persson
James E. Petranovich
Albert Petrick
Ron Porat
Rethnakaran Pulikkoonattu
Dengyu Qiao
Demir Rakanovic
Enrico-Henrik Rantala
Maximilian Riegel
Mark Rison
Zhigang Rong
Kiseon Ryu
Bahareh Sadeghi
Takenori Sakamoto
Kazuyuki Sakoda
Sam Sambasivan
Hemanth Sampath
Naotaka Sato
Sigurd Schelstraete
Andy Scott
Yongho Seok
Stephen J. Shellhammer
Ian Sherlock
Shimi Shilo
Graham K. Smith
Ju-Hyung Son
Sudhir Srinivasa
Robert Stacey
Adrian P. Stephens
Noel Stott
Jung Hoon H. Suh
Takenori Sumi
Bo Sun
Chen Sun
Li-Hsiang Sun
Sheng Sun
Yanjun Sun
Dennis Sundman
Mineo Takai
Sagar Tamhane
Yusuke Tanaka
Kentaro Taniguchi
Wu Tao
Bin Tian
Fei Tong
Solomon B. Trainin
Yoshio Urabe
Richard D. Van Nee
Allert Van Zelst
Lorenzo Vangelista
Jerome Vanthournout
Prabodh Varshney
Ganesh Venkatesan
Lochan Verma
Sameer Vermani
Pascal Viger
George A. Vlantis
Chao Chun Wang
Haiming Wang
Huizhao Wang
James June J. Wang
Lei Wang
Xiaofei Wang
Xuehuan Wang
Lisa Ward
Julian Webber
Menzo M. Wentink
Leif Wilhelmsson
Eric Wong
Tianyu Wu
Yan Xin
Qi Xue
Rui Yang
Xun Yang
Yunsong Yang
Kazuto Yano
James Yee
Peter Yee
Su Khiong K. Yong
Christopher Young
Heejung Yu
Jian Yu
Mao Yu
SunWoong Yun
Alan Zeleznikar
Hongyuan Zhang
Xingxin Zhang
Yan Zhang
Xiayu Zheng
Lan Zhuo

Major contributions were received from the following individuals:

Tomo Adachi
Edward Au
Gabr Bajko
Nehru Bhandaru
Jiamin Chen
Sean Coffey
Thomas Derham
Peter Ecclesine
Marc Emmelmann
Matthew J. Fischer
David Goodall
Mark Hamilton
Christopher J. Hansen
Daniel N. Harkins
Jerome Henry
Guido R. Hiertz
Srinivas Kandala
Assaf Y. Kasher
Youhan Kim
Jouni K. Malinen
Stephen McCann
Michael Montemurro
Yujin Noh
Abhishek Patil
Emily H. Qi
Mark Rison
Jon W. Rosdahl
Kazuyuki Sakoda
Sigurd Schelstraete
Graham K. Smith
Robert Stacey
Dorothy V. Stanley
Bo Sun
Payam Torab
Solomon B. Trainin
Ganesh Venkatesan
Haiming Wang
Menzo M. Wentink

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

The following members of the individual balloting committee voted on this revision. Balloters may have voted for approval, disapproval, or abstention.

Osama Aboulmagd
Tomoko Adachi
Robert Aiello
Thomas Alexander
Nobumitsu Amachi
Carol Ansley
Butch Anton
Alfred Asterjadhi
Kwok Shum S. Au
Harry Bims
Nancy Bravin
Jason Brent
Vern Brethour
Demetrio Bucaneg
William Byrd
Paul Cardinal
William Carney
Juan Carreon
Pin Chang
Cheng Chen
Evelyn Chen
George Cherian
Rojan Chitrakar
Paul Chiuchiolo
John Coffey
Charles Cook
D. Nelson Costa
Claudio da Silva
Antonio de la Oliva Delgado
Peter Ecclesine
Richard Edgar
Alecsander Eitan
Marc Emmelmann
Xiang Feng
Matthew J. Fischer
Michael Fischer
Avraham Freedman
Sho Furuichi
Devon Gayle
Mariana Goldhamer
David Goodall
Michael Gundlach
Mark Hamilton
Christopher J. Hansen
Jerome Henry
Marco Hernandez
Lili Hervieu
Guido R. Hiertz
Werner Hoelzl
Oliver Holland
Glenn Hu
Yasuhiko Inoue
Atsushi Ito
Raj Jain
SangKwon Jeong
Pranav Jha
Jeffrum Jones
Joe Natharoj Juisai
Lokesh Kabra
Srinivas Kandala
Piotr Karocki
Assaf Y. Kasher
Stuart J. Kerry
Evgeny Khorov
Yongbum Kim
Youhan Kim
Patrick Kinney
Shoichi Kitazawa
Jan Kruys
Yasushi Kudoh
Thomas Kurihara
Hyeong Ho Lee
Kang Lee
Wookbong Lee
Frank Leong
James Lepp
Joseph Levy
Yong Liu
Javier Luiso
Valerie Maguire
Jouni K. Malinen
Jeffery Masters
Stephen McCann
Brett McClellan
Michael Montemurro
Hiroyuki Motozuka
Ronald Murias
Rick Murphy
Andrew Myles
Paul Neveux
Nick S. A. Nikjoo
Paul Nikolich
Robert O'Hara
Satoshi Obara
Bansi Patel
Abhishek Patil
Arumugam Paventhan
Albert Petrick
Brian Petry
David Piehler
Walter Pienciak
Clinton Powell
Venkatesha Prasad
Emily H. Qi
Demir Rakanovic
R. K. Rannow
Ranga Reddy
Alon Regev
Maximilian Riegel
Mark Rison
Robert Robinson
Benjamin Rolfe
Jon W. Rosdahl
Kazuyuki Sakoda
Stephan Sand
Chester Sandberg
Shigenobu Sasaki
Naotaka Sato
Sigurd Schelstraete
Andy Scott
Yongho Seok
Kunal Shah
Ian Sherlock
Di Dieter Smely
Graham K. Smith
Robert Stacey
Dorothy V. Stanley
Thomas Starai
Noel Stott
Walter Struppler
Mark Sturza
Mitsutoshi Sugawara
Bo Sun
Li-Hsiang Sun
Jasja Tijink
Payam Torab Jahromi
Solomon B. Trainin
Mark-Rene Uchida
Allert Van Zelst
Prabodh Varshney
John Vergis
Lochan Verma
George A. Vlantis
Lei Wang
Lisa Ward
Hung-Yu Wei
Matthias Wendt
Menzo M. Wentink
Scott Willy
Andreas Wolf
Chun Yu Charles Wong
Forrest Wright
Peter Wu
Yunsong Yang
Yu Yuan
Oren Yuen
Janusz Zalewski

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

When the IEEE SA Standards Board approved this recommended practice on 3 December 2020, it had the following membership:

Gary Hoffman, *Chair*
Jon Walter Rosdahl, *Vice Chair*
John D. Kulick, *Past Chair*
Konstantinos Karachalios, *Secretary*

Ted Burse
Doug Edwards
J. Travis Griffith
Grace Gu
Guido R. Hiertz
Joseph L. Koepfinger*
David J. Law
Howard Li
Dong Liu
Kevin Lu
Paul Nikolich
Damir Novosel
Dorothy V. Stanley
Mehmet Ulema
Lei Wang
Sha Wei
Philip B. Winston
Daidi Zhong
Jingyi Zhou

*Member Emeritus

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Introduction

This introduction is not part of IEEE Std 802.11-2020, IEEE Standard for Information Technology—Telecommunications and Information Exchange between Systems—Local and Metropolitan Area Networks—Specific Requirements—Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications.

This revision gives users, in one document, the IEEE 802.11 standard for wireless local area networks (WLANs) with all of the amendments that have been published to date.

Incorporating published amendments

The original standard was published in 1997, revised in 1999 with MIB changes, and reaffirmed in 2003.

A revision was published in 2007, which incorporated into the 1999 edition the following amendments:

- IEEE Std 802.11a™-1999: High-speed Physical Layer in the 5 GHz Band (Amendment 1)
- IEEE Std 802.11b™-1999: Higher-Speed Physical Layer Extension in the 2.4 GHz Band (Amendment 2)
- IEEE Std 802.11b-1999/Corrigendum 1-2001: Higher-speed Physical Layer (PHY) extension in the 2.4 GHz band (Corrigendum 1 to Amendment 2)
- IEEE Std 802.11d™-2001: Specification for operation in additional regulatory domains (Amendment 3)
- IEEE Std 802.11g™-2003: Further Higher Data Rate Extension in the 2.4 GHz Band (Amendment 4)
- IEEE Std 802.11h™-2003: Spectrum and Transmit Power Management Extensions in the 5 GHz band in Europe (Amendment 5)
- IEEE Std 802.11i™-2004: Medium Access Control (MAC) Security Enhancements (Amendment 6)
- IEEE Std 802.11j™-2004: 4.9 GHz–5 GHz Operation in Japan (Amendment 7)
- IEEE Std 802.11e™-2005: Medium Access Control (MAC) Quality of Service Enhancements (Amendment 8)

A revision was published in 2012, which incorporated into the 2007 revision the following amendments:

- IEEE Std 802.11k™-2008: Radio Resource Measurement of Wireless LANs (Amendment 1)
- IEEE Std 802.11r™-2008: Fast Basic Service Set (BSS) Transition (Amendment 2)
- IEEE Std 802.11y™-2008: 3650–3700 MHz Operation in USA (Amendment 3)
- IEEE Std 802.11w™-2009: Protected Management Frames (Amendment 4)
- IEEE Std 802.11n™-2009: Enhancements for Higher Throughput (Amendment 5)
- IEEE Std 802.11p™-2010: Wireless Access in Vehicular Environments (Amendment 6)
- IEEE Std 802.11z™-2010: Extensions to Direct-Link Setup (DLS) (Amendment 7)
- IEEE Std 802.11v™-2011: Wireless Network Management (Amendment 8)
- IEEE Std 802.11u™-2011: Interworking with External Networks (Amendment 9)
- IEEE Std 802.11s™-2011: Mesh Networking (Amendment 10)

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

A revision was published in 2016, which incorporated into the 2012 revision the following amendments:

- IEEE Std 802.11ae™-2012: Prioritization of Management Frames (Amendment 1)
- IEEE Std 802.11aa™-2012: MAC Enhancements for Robust Audio Video Streaming (Amendment 2)
- IEEE Std 802.11ad™-2012: Enhancements for Very High Throughput in the 60 GHz Band (Amendment 3)
- IEEE Std 802.11ac™-2013: Enhancements for Very High Throughput for Operation in Bands below 6 GHz (Amendment 4)
- IEEE Std 802.11af™-2013: Television White Spaces (TVWS) Operation (Amendment 5)

This revision is based on IEEE Std 802.11-2016, into which the following amendments have been incorporated:

- IEEE Std 802.11ai™-2016 (second printing): Fast Initial Link Setup (Amendment 1)
- IEEE Std 802.11ah™-2016: Sub 1 GHz License Exempt Operation (Amendment 2)
- IEEE Std 802.11aj™-2018: Enhancements for Very High Throughput to Support Chinese Millimeter Wave Frequency Bands (60 GHz and 45 GHz) (Amendment 3)
- IEEE Std 802.11ak™-2018: Enhancements for Transit Links Within Bridged Networks (Amendment 4)
- IEEE Std 802.11aq™-2018: Preassociation Discovery (Amendment 5)

Technical corrections, clarifications, and enhancements

In addition, this revision specifies technical corrections and clarifications to IEEE Std 802.11 as well as enhancements to the existing medium access control (MAC) and physical layer (PHY) functions. In addition, this revision removes some features previously marked as obsolete and adds new indications of other obsolete features.

Generally, features that are marked deprecated or obsolete are not maintained; there might be technical errors in the material describing these features.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Renumbering of clauses and annexes

The numbering of certain clauses and annexes has been modified since IEEE Std 802.11-2007.

The evolution of this numbering is shown in Figure 1.



Figure 1—The evolution of numbering in IEEE Std 802.11

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Contents

1. Overview ... 149

1.1 Scope ... 149
1.2 Purpose ... 149
1.3 Supplementary information on purpose ... 149
1.4 Word usage ... 150
1.5 Terminology for mathematical, logical, and bit operations ... 151

2. Normative references ... 154

3. Definitions, acronyms, and abbreviations ... 158

3.1 Definitions ... 158
3.2 Definitions specific to IEEE Std 802.11 ... 173
3.3 Definitions specific to IEEE 802.11 operation in some regulatory domains ... 205
3.4 Acronyms and abbreviations ... 205
3.5 Abbreviations and acronyms in some regulatory domains ... 218

4. General description ... 219

4.1 General description of the architecture ... 219
4.2 How wireless local area networks (WLANs) are different ... 219
4.2.1 Introduction ... 219
4.2.2 Wireless station (STA) ... 219
4.2.3 Media impact on design and performance ... 219
4.2.4 The impact of handling mobile STAs ... 220
4.2.5 Interaction with other IEEE 802® layers ... 220
4.2.6 Interaction with non-IEEE-802 protocols ... 220
4.3 Components of the IEEE 802.11 architecture ... 220
4.3.1 General ... 220
4.3.2 Independent BSS (IBSS) ... 221
4.3.3 Personal BSS (PBSS) ... 221
4.3.4 STA membership in a BSS is dynamic ... 221
4.3.5 Distribution system (DS) concepts ... 222
4.3.5.1 Overview ... 222
4.3.5.2 Extended service set (ESS): the large coverage network ... 223
4.3.6 Area concepts ... 224
4.3.7 Integration with non-IEEE-802.11 LANs ... 225
4.3.8 Robust security network association (RSNA) ... 226
4.3.9 Centralized coordination service set (CCSS) and extended centralized AP or PCP clustering (ECAPC) ... 226
4.3.10 QoS BSS ... 228
4.3.11 Wireless LAN radio measurements ... 229
4.3.11.1 General ... 229
4.3.11.2 Beacon ... 230
4.3.11.3 Measurement pilot ... 230
4.3.11.4 Frame ... 230
4.3.11.5 Channel load ... 230
4.3.11.6 Noise histogram ... 231
4.3.11.7 STA statistics ... 231
4.3.11.8 Location ... 231
4.3.11.9 Measurement pause ... 231

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

4.3.11.10 Neighbor report 231
4.3.11.11 Link measurement 231
4.3.11.12 Transmit stream/category measurement 231
4.3.12 Operation in licensed frequency bands 232
4.3.12.1 General 232
4.3.12.2 Dynamic STA enablement (DSE) in licensed bands 232
4.3.12.3 Contention based protocol (CBP) in nonexclusively licensed bands . 232
4.3.12.4 Using DSE STA identification to resolve interference 232
4.3.12.5 Further coexistence enhancements in nonexclusively licensed bands 232
4.3.13 High-throughput (HT) STA 232
4.3.14 Sub 1 GHz (S1G) STA 233
4.3.14.1 Overview 233
4.3.14.2 S1G relay 234
4.3.15 Very high throughput (VHT) STA 234
4.3.16 Television very high throughput (TVHT) STA 235
4.3.17 STA transmission of Data frames outside the context of a BSS 237
4.3.18 Tunneled direct-link setup 237
4.3.19 Wireless network management 237
4.3.19.1 Overview 237
4.3.19.2 BSS max idle period management 238
4.3.19.3 BSS transition management 238
4.3.19.4 Channel usage 238
4.3.19.5 Collocated interference reporting 239
4.3.19.6 Diagnostic reporting 239
4.3.19.7 Directed multicast service (DMS) 239
4.3.19.8 Event reporting 239
4.3.19.9 Flexible multicast service (FMS) 239
4.3.19.10 Location services 239
4.3.19.11 Multicast Diagnostic report 239
4.3.19.12 Multiple BSSID capability 240
4.3.19.13 Proxy ARP 240
4.3.19.14 QoS traffic capability 240
4.3.19.15 SSID list 240
4.3.19.16 Triggered STA statistics 240
4.3.19.17 TIM broadcast 240
4.3.19.18 Timing measurement 240
4.3.19.19 Fine timing measurement 240
4.3.19.20 Traffic filtering service 241
4.3.19.21 U-APSD coexistence 241
4.3.19.22 WNM notification 241
4.3.19.23 WNM sleep mode 241
4.3.20 Subscription service provider network (SSPN) interface 241
4.3.21 Mesh BSS 242
4.3.21.1 General 242
4.3.21.2 Overview of the mesh BSS 242
4.3.21.3 Mesh STA 243
4.3.21.4 IEEE 802.11 components and mesh BSS 243
4.3.21.5 Introduction to mesh functions 245
4.3.22 DMG STA 248
4.3.23 DMG relay 249
4.3.24 Robust audio video (AV) streaming 249
4.3.24.1 Introduction 249
4.3.24.2 Groupcast with retries (GCR) 249
4.3.24.3 Stream classification service (SCS) 250

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

4.3.24.4 Mirrored stream classification service (MSCS) 250
4.3.24.5 Overlapping BSS (OBSS) management 250
4.3.24.6 Interworking with IEEE 802.1Q Stream Reservation Protocol (SRP) 250
4.3.24.7 Intra-access category prioritization 250
4.3.25 Operation under geolocation database (GDB) control 251
4.3.26 CDMG STA 252
4.3.27 CMMG STA 253
4.3.28 General link (GLK) 254
4.3.28.1 General 254
4.3.28.2 Selective reception of group addressed frames 254
4.3.28.3 GLK Service Sets 255
4.3.29 Ethertype protocol discrimination (EPD) 259
4.4 Logical service interfaces 260
4.4.1 General 260
4.4.2 SS 260
4.4.3 PBSS control point service (PCPS) 261
4.4.4 DSS 261
4.5 Overview of the services 262
4.5.1 General 262
4.5.2 Distribution of MSDUs within a DS 263
4.5.2.1 Distribution 263
4.5.2.2 Integration 264
4.5.2.3 QoS traffic scheduling 264
4.5.3 Connectivity-related services 264
4.5.3.1 General 264
4.5.3.2 Mobility types 265
4.5.3.3 Association 265
4.5.3.4 Reassociation 266
4.5.3.5 Disassociation 266
4.5.4 Access control and data confidentiality services 267
4.5.4.1 General 267
4.5.4.2 Authentication 267
4.5.4.3 Deauthentication 268
4.5.4.4 Data confidentiality 269
4.5.4.5 Key management 270
4.5.4.6 Data origin authenticity 270
4.5.4.7 Replay detection 270
4.5.4.8 Fast BSS transition 270
4.5.4.9 Management frame protection 270
4.5.4.10 MAC privacy enhancements 271
4.5.5 Spectrum management services 271
4.5.5.1 General 271
4.5.5.2 TPC 271
4.5.5.3 DFS 271
4.5.6 Traffic differentiation and QoS support 272
4.5.6.1 General 272
4.5.6.2 Quality-of-service management frame support 272
4.5.7 Support for higher layer timer synchronization 272
4.5.8 Radio measurement service 273
4.5.9 Interworking with external networks 273
4.5.9.1 General 273
4.5.9.2 Preassociation discovery (PAD) 274
4.5.10 Generic advertisement service (GAS) 275
4.6 Multiple logical address spaces 276

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

4.7 Differences among ESS, PBSS, and IBSS LANs 276
4.8 Differences between ESS and MBSS LANs 278
4.9 Reference model 279
4.9.1 General 279
4.9.2 Interworking reference model 279
4.9.3 Reference model for supporting multiple MAC sublayers 281
4.9.4 Reference model for multi-band operation 282
4.10 IEEE Std 802.11 and IEEE Std 802.1X-2010 284
4.10.1 General 284
4.10.2 IEEE 802.11 usage of IEEE Std 802.1X-2010 284
4.10.3 Infrastructure functional model overview 284
4.10.3.1 General 284
4.10.3.2 AKM operations with AS 284
4.10.3.3 AKM operations with a password or PSK 287
4.10.3.4 Alternate operations with PSK 288
4.10.3.5 Disassociation 288
4.10.3.6 AKM operations using FILS authentication 288
4.10.4 IBSS functional model description 289
4.10.4.1 General 289
4.10.4.2 Key usage 289
4.10.4.3 Sample IBSS 4-way handshakes 290
4.10.4.4 IBSS IEEE 802.1X example 291
4.10.5 PBSS functional model description 292
4.10.6 Authenticator-to-AS protocol 293
4.10.7 PMKSA caching 293
4.10.8 Protection of group addressed robust Management frames 294

5. MAC service definition 295

5.1 Overview of MAC services 295
5.1.1 Data service 295
5.1.1.1 General 295
5.1.1.2 Determination of UP 295
5.1.1.3 Interpretation of priority parameter in MAC service primitives 295
5.1.1.4 Interpretation of service class parameter in MAC service primitives in a STA 296
5.1.2 Security services 297
5.1.3 MSDU ordering 297
5.1.4 MSDU format 298
5.1.5 MAC data service architecture 299
5.1.5.1 General 299
5.1.5.2 Non-GLK non-AP STA role 302
5.1.5.3 Non-GLK AP role 302
5.1.5.4 Non-GLK mesh STA role 303
5.1.5.5 Mesh gate role 303
5.1.5.6 S1G relay 303
5.1.5.7 GLK STA role 305
5.1.5.8 GLK AP role 305
5.1.5.9 GLK mesh STA role 305
5.2 MAC data service specification 307
5.2.1 General 307
5.2.2 GLK MAC data service specification 307
5.2.3 MA-UNITDATA.request 307
5.2.3.1 Function 307

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

5.2.3.2 Semantics of the service primitive 307
5.2.3.3 When generated 308
5.2.3.4 Effect of receipt 308
5.2.4 MA-UNITDATA.indication 310
5.2.4.1 Function 310
5.2.4.2 Semantics of the service primitive 310
5.2.4.3 When generated 311
5.2.4.4 Effect of receipt 311
5.2.5 MA-UNITDATA-STATUS.indication 313
5.2.5.1 Function 313
5.2.5.2 Semantics of the service primitive 313
5.2.5.3 When generated 314
5.2.5.4 Effect of receipt 314

6. Layer management 315

6.1 Overview of management model 315
6.2 Generic management primitives 316
6.3 MLME SAP interface 316
6.3.1 Introduction 316
6.3.2 Power management 317
6.3.2.1 Introduction 317
6.3.2.2 MLME-POWERMGT.request 317
6.3.2.3 MLME-POWERMGT.confirm 318
6.3.3 Scan 318
6.3.3.1 Introduction 318
6.3.3.2 MLME-SCAN.request 318
6.3.3.3 MLME-SCAN.confirm 322
6.3.3.4 MLME-SCAN-STOP.request 337
6.3.4 Synchronization 337
6.3.4.1 Introduction 337
6.3.4.2 MLME-JOIN.request 337
6.3.4.3 MLME-JOIN.confirm 340
6.3.5 Authenticate 341
6.3.5.1 Introduction 341
6.3.5.2 MLME-AUTHENTICATE.request 341
6.3.5.3 MLME-AUTHENTICATE.confirm 342
6.3.5.4 MLME-AUTHENTICATE.indication 344
6.3.5.5 MLME-AUTHENTICATE.response 345
6.3.6 Deauthenticate 347
6.3.6.1 Introduction 347
6.3.6.2 MLME-DEAUTHENTICATE.request 347
6.3.6.3 MLME-DEAUTHENTICATE.confirm 347
6.3.6.4 MLME-DEAUTHENTICATE.indication 348
6.3.7 Associate 348
6.3.7.1 Introduction 348
6.3.7.2 MLME-ASSOCIATE.request 349
6.3.7.3 MLME-ASSOCIATE.confirm 352
6.3.7.4 MLME-ASSOCIATE.indication 358
6.3.7.5 MLME-ASSOCIATE.response 363
6.3.8 Reassociate 367
6.3.8.1 Introduction 367
6.3.8.2 MLME-REASSOCIATE.request 367
6.3.8.3 MLME-REASSOCIATE.confirm 371

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.8.4 MLME-REASSOCIATE.indication 377
6.3.8.5 MLME-REASSOCIATE.response 383
6.3.9 Disassociate 388
6.3.9.1 MLME-DISASSOCIATE.request 388
6.3.9.2 MLME-DISASSOCIATE.confirm 388
6.3.9.3 MLME-DISASSOCIATE.indication 389
6.3.10 Reset 389
6.3.10.1 Introduction 389
6.3.10.2 MLME-RESET.request 389
6.3.11 Start 390
6.3.11.1 Introduction 390
6.3.11.2 MLME-START.request 390
6.3.11.3 MLME-START.confirm 396
6.3.12 Stop 397
6.3.12.1 General 397
6.3.12.2 MLME-STOP.request 397
6.3.13 Protocol layer model for spectrum management and radio measurement 398
6.3.14 Measurement request 401
6.3.14.1 Introduction 401
6.3.14.2 MLME-MREQUEST.request 401
6.3.14.3 MLME-MREQUEST.indication 402
6.3.15 Channel measurement 403
6.3.15.1 Introduction 403
6.3.15.2 MLME-MEASURE.request 403
6.3.15.3 MLME-MEASURE.confirm 403
6.3.16 Measurement report 404
6.3.16.1 Introduction 404
6.3.16.2 MLME-MREPORT.request 404
6.3.16.3 MLME-MREPORT.indication 405
6.3.17 Channel switch 406
6.3.17.1 MLME-CHANNELSWITCH.request 406
6.3.17.2 MLME-CHANNELSWITCH.confirm 407
6.3.17.3 MLME-CHANNELSWITCH.indication 408
6.3.17.4 MLME-CHANNELSWITCH.response 409
6.3.18 TPC request 410
6.3.18.1 Introduction 410
6.3.18.2 MLME-TPCADAPT.request 410
6.3.18.3 MLME-TPCADAPT.confirm 411
6.3.19 SetKeys 412
6.3.19.1 MLME-SETKEYS.request 412
6.3.20 DeleteKeys 413
6.3.20.1 MLME-DELETEKEYS.request 413
6.3.21 MIC (michael) failure event 414
6.3.21.1 MLME-MICHAELMICFAILURE.indication 414
6.3.22 EAPOL 415
6.3.22.1 MLME-EAPOL.request 415
6.3.22.2 MLME-EAPOL.confirm 416
6.3.23 SetProtection 416
6.3.23.1 MLME-SETPROTECTION.request 416
6.3.24 MLME-PROTECTEDFRAMEDROPPED 417
6.3.24.1 MLME-PROTECTEDFRAMEDROPPED.indication 417
6.3.25 TS management interface 418
6.3.25.1 General 418
6.3.25.2 MLME-ADDTS.request 419

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.25.3 MLME-ADDTS.confirm 421
6.3.25.4 MLME-ADDTS.indication 424
6.3.25.5 MLME-ADDTS.response 426
6.3.25.6 MLME-DELTS.request 429
6.3.25.7 MLME-DELTS.indication 430
6.3.25.8 MLME-ADDTSRESERVE.request 431
6.3.25.9 MLME-ADDTSRESERVE.confirm 432
6.3.25.10 MLME-ADDTSRESERVE.indication 433
6.3.25.11 MLME-ADDTSRESERVE.response 434
6.3.26 Higher layer synchronization support 434
6.3.26.1 Introduction 434
6.3.26.2 MLME-HL-SYNC.request 435
6.3.26.3 MLME-HL-SYNC.indication 435
6.3.27 Block Ack 436
6.3.27.1 General 436
6.3.27.2 MLME-ADDBA.request 436
6.3.27.3 MLME-ADDBA.confirm 437
6.3.27.4 MLME-ADDBA.indication 439
6.3.27.5 MLME-ADDBA.response 440
6.3.27.6 MLME-DELBA.request 441
6.3.27.7 MLME-DELBA.indication 442
6.3.28 Schedule element management 443
6.3.28.1 Introduction 443
6.3.28.2 MLME-SCHEDULE.request 443
6.3.28.3 MLME-SCHEDULE.indication 444
6.3.29 Vendor-specific action 445
6.3.29.1 Introduction 445
6.3.29.2 MLME-VSPECIFIC.request 445
6.3.29.3 MLME-VSPECIFIC.indication 446
6.3.30 Neighbor report request 447
6.3.30.1 General 447
6.3.30.2 MLME-NEIGHBORREPREQ.request 447
6.3.30.3 MLME-NEIGHBORREPREQ.indication 448
6.3.31 Neighbor report response 449
6.3.31.1 General 449
6.3.31.2 MLME-NEIGHBORREPRESP.request 449
6.3.31.3 MLME-NEIGHBORREPRESP.indication 450
6.3.32 Link Measure Request 451
6.3.32.1 General 451
6.3.32.2 MLME-LINKMEASURE.request 451
6.3.32.3 MLME-LINKMEASURE.confirm 452
6.3.33 MLME SAP interface for resource request 453
6.3.33.1 MLME-RESOURCE-REQUEST.request 453
6.3.33.2 MLME-RESOURCE-REQUEST.indication 454
6.3.33.3 MLME-RESOURCE-REQUEST.response 455
6.3.33.4 MLME-RESOURCE-REQUEST.confirm 455
6.3.33.5 MLME-RESOURCE-REQUEST-LOCAL.request 456
6.3.33.6 MLME-RESOURCE-REQUEST-LOCAL.confirm 457
6.3.34 MLME SAP interface for remote requests 457
6.3.34.1 MLME-REMOTE-REQUEST.request 457
6.3.34.2 MLME-REMOTE-REQUEST.indication 458
6.3.35 Extended channel switch announcement 458
6.3.35.1 General 458
6.3.35.2 MLME-EXTCHANNELSWITCH.request 459

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.35.3 MLME-EXTCHANNELSWITCH.confirm 460
6.3.35.4 MLME-EXTCHANNELSWITCH.indication 460
6.3.35.5 MLME-EXTCHANNELSWITCH.response 462
6.3.36 DSE power constraint announcement 463
6.3.36.1 General 463
6.3.36.2 MLME-DSETPC.request 463
6.3.36.3 MLME-DSETPC.confirm 464
6.3.36.4 MLME-DSETPC.indication 465
6.3.36.5 MLME-DSETPC.response 465
6.3.37 Enablement 466
6.3.37.1 General 466
6.3.37.2 MLME-ENABLEMENT.request 466
6.3.37.3 MLME-ENABLEMENT.confirm 467
6.3.37.4 MLME-ENABLEMENT.indication 468
6.3.37.5 MLME-ENABLEMENT.response 469
6.3.38 Deenablement 470
6.3.38.1 MLME-DEENABLEMENT.request 470
6.3.38.2 MLME-DEENABLEMENT.indication 471
6.3.39 SA Query support 472
6.3.39.1 MLME-SA-QUERY.request 472
6.3.39.2 MLME-SA-QUERY.confirm 473
6.3.39.3 MLME-SA-QUERY.indication 473
6.3.39.4 MLME-SA-QUERY.response 474
6.3.40 Get TSF timer 475
6.3.40.1 General 475
6.3.40.2 MLME-GETTSFTIME.request 475
6.3.40.3 MLME-GETTSFTIME.confirm 475
6.3.41 Timing Advertisement 476
6.3.41.1 General 476
6.3.41.2 MLME-TIMING-ADVERTISEMENT.request 476
6.3.41.3 MLME-TIMING-ADVERTISEMENT.indication 477
6.3.42 TDLS Discovery 478
6.3.42.1 General 478
6.3.42.2 MLME-TDLSDISCOVERY.request 478
6.3.42.3 MLME-TDLSDISCOVERY.confirm 479
6.3.42.4 MLME-TDLSDISCOVERY.indication 480
6.3.42.5 MLME-TDLSDISCOVERY.response 480
6.3.43 TDLS direct-link establishment 481
6.3.43.1 General 481
6.3.43.2 MLME-TDLSSETUPREQUEST.request 481
6.3.43.3 MLME-TDLSSETUPREQUEST.indication 482
6.3.43.4 MLME-TDLSSETUPRESPONSE.request 483
6.3.43.5 MLME-TDLSSETUPRESPONSE.indication 484
6.3.43.6 MLME-TDLSSETUPCONFIRM.request 484
6.3.43.7 MLME-TDLSSETUPCONFIRM.indication 485
6.3.43.8 MLME-TDLSPOTENTIALPEERSTA.request 485
6.3.43.9 MLME-TDLSPOTENTIALPEERSTA.confirm 486
6.3.44 TDLS direct-link teardown 487
6.3.44.1 General 487
6.3.44.2 MLME-TDLSTEARDOWN.request 487
6.3.44.3 MLME-TDLSTEARDOWN.indication 488
6.3.45 TDLS peer U-APSD (TPU) 488
6.3.45.1 General 488
6.3.45.2 MLME-TDLSPTI.request 489

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.45.3 MLME-TDLSPTI.confirm ... 490
6.3.45.4 MLME-TDLSPTI.indication ... 490
6.3.45.5 MLME-TDLSPTI.response ... 491
6.3.46 TDLS channel switching ... 492
6.3.46.1 General ... 492
6.3.46.2 MLME-TDLSCHANNELSWITCH.request ... 492
6.3.46.3 MLME-TDLSCHANNELSWITCH.confirm ... 493
6.3.46.4 MLME-TDLSCHANNELSWITCH.indication ... 494
6.3.46.5 MLME-TDLSCHANNELSWITCH.response ... 494
6.3.47 TDLS peer PSM ... 495
6.3.47.1 General ... 495
6.3.47.2 MLME-TDLSPEERPSM.request ... 495
6.3.47.3 MLME-TDLSPEERPSM.confirm ... 496
6.3.47.4 MLME-TDLSPEERPSM.indication ... 497
6.3.47.5 MLME-TDLSPEERPSM.response ... 497
6.3.48 Event request ... 498
6.3.48.1 General ... 498
6.3.48.2 MLME-EVLREQUEST.request ... 499
6.3.48.3 MLME-EVLREQUEST.indication ... 499
6.3.49 Event report ... 500
6.3.49.1 General ... 500
6.3.49.2 MLME-EVLREPORT.request ... 500
6.3.49.3 MLME-EVLREPORT.indication ... 501
6.3.50 Event ... 502
6.3.50.1 General ... 502
6.3.50.2 MLME-EVLOG.request ... 502
6.3.50.3 MLME-EVLOG.confirm ... 502
6.3.51 Diagnostic request ... 503
6.3.51.1 General ... 503
6.3.51.2 MLME-DIAGREQUEST.request ... 503
6.3.51.3 MLME-DIAGREQUEST.indication ... 504
6.3.52 Diagnostic report ... 505
6.3.52.1 MLME-DIAGREPORT.request ... 505
6.3.52.2 MLME-DIAGREPORT.indication ... 506
6.3.53 Location configuration request ... 506
6.3.53.1 General ... 506
6.3.53.2 MLME-LOCATIONCFG.request ... 507
6.3.53.3 MLME-LOCATIONCFG.confirm ... 508
6.3.53.4 MLME-LOCATIONCFG.indication ... 508
6.3.53.5 MLME-LOCATIONCFG.response ... 509
6.3.54 Location track notification ... 510
6.3.54.1 General ... 510
6.3.54.2 MLME-LOCATIONTRACKNOTIF.request ... 510
6.3.54.3 MLME-LOCATIONTRACKNOTIF.indication ... 511
6.3.55 Timing measurement ... 512
6.3.55.1 General ... 512
6.3.55.2 MLME-TIMINGMSMTRQ.request ... 512
6.3.55.3 MLME-TIMINGMSMTRQ.indication ... 513
6.3.55.4 MLME-TIMINGMSMT.request ... 514
6.3.55.5 MLME-TIMINGMSMT.confirm ... 515
6.3.55.6 MLME-TIMINGMSMT.indication ... 516
6.3.56 Fine timing measurement (FTM) ... 517
6.3.56.1 General ... 517
6.3.56.2 MLME-FINETIMINGMSMTRQ.request ... 518

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.56.3 MLME-FINETIMINGMSMTRQ.indication 519
6.3.56.4 MLME-FINETIMINGMSMT.request 520
6.3.56.5 MLME-FINETIMINGMSMT.confirm 522
6.3.56.6 MLME-FINETIMINGMSMT.indication 523
6.3.57 BSS transition management 524
6.3.57.1 BSS transition management procedure 524
6.3.57.2 MLME-BTMQUERY.request 525
6.3.57.3 MLME-BTMQUERY.indication 526
6.3.57.4 MLME-BTM.request 527
6.3.57.5 MLME-BTM.indication 528
6.3.57.6 MLME-BTM.response 529
6.3.57.7 MLME-BTM.confirm 530
6.3.58 FMS setup 532
6.3.58.1 General 532
6.3.58.2 MLME-FMS.request 532
6.3.58.3 MLME-FMS.confirm 533
6.3.58.4 MLME-FMS.indication 534
6.3.58.5 MLME-FMS.response 535
6.3.59 Collocated Interference request 535
6.3.59.1 General 535
6.3.59.2 MLME-CLINTERFERENCEREQUEST.request 536
6.3.59.3 MLME-CLINTERFERENCEREQUEST.indication 537
6.3.60 Collocated Interference report 538
6.3.60.1 General 538
6.3.60.2 MLME-CLINTERFERENCEREPORT.request 538
6.3.60.3 MLME-CLINTERFERENCEREPORT.indication 539
6.3.61 TFS setup 540
6.3.61.1 General 540
6.3.61.2 MLME-TFS.request 540
6.3.61.3 MLME-TFS.confirm 541
6.3.61.4 MLME-TFS.indication 542
6.3.61.5 MLME-TFS.response 542
6.3.62 WNM sleep mode request 543
6.3.62.1 General 543
6.3.62.2 MLME-SLEEPMODE.request 544
6.3.62.3 MLME-SLEEPMODE.indication 544
6.3.62.4 MLME-SLEEPMODE.response 545
6.3.62.5 MLME-SLEEPMODE.confirm 546
6.3.63 TIM broadcast setup 547
6.3.63.1 General 547
6.3.63.2 MLME-TIMBROADCAST.request 548
6.3.63.3 MLME-TIMBROADCAST.confirm 548
6.3.63.4 MLME-TIMBROADCAST.indication 549
6.3.63.5 MLME-TIMBROADCAST.response 550
6.3.64 QoS traffic capability update 551
6.3.64.1 General 551
6.3.64.2 MLME-QOSTRAFFICCAPUPDATE.request 551
6.3.64.3 MLME-QOSTRAFFICCAPUPDATE.indication 552
6.3.65 Channel Usage request 553
6.3.65.1 General 553
6.3.65.2 MLME-CHANNELUSAGE.request 553
6.3.65.3 MLME-CHANNELUSAGE.confirm 554
6.3.65.4 MLME-CHANNELUSAGE.indication 555
6.3.65.5 MLME-CHANNELUSAGE.response 556

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.66 DMS or GCR request and response procedure 557
6.3.66.1 General 557
6.3.66.2 MLME-GATS.request 558
6.3.66.3 MLME-GATS.confirm 558
6.3.66.4 MLME-GATS.indication 559
6.3.66.5 MLME-GATS.response 560
6.3.66.6 MLME-GATS-TERM.request 560
6.3.66.7 MLME-GATS-TERM.indication 561
6.3.67 WNM notification request 562
6.3.67.1 General 562
6.3.67.2 MLME-WNMNOTIFICATIONREQUEST.request 562
6.3.67.3 MLME-WNMNOTIFICATIONREQUEST.indication 563
6.3.68 WNM notification response 564
6.3.68.1 MLME-WNMNOTIFICATIONRESPONSE.request 564
6.3.68.2 MLME-WNMNOTIFICATIONRESPONSE.indication 564
6.3.69 Network discovery and selection support 565
6.3.69.1 General 565
6.3.69.2 MLME-GAS.request 565
6.3.69.3 MLME-GAS.confirm 567
6.3.69.4 MLME-GAS.indication 568
6.3.69.5 MLME-GAS.response 569
6.3.70 QoS Map element management 571
6.3.70.1 General 571
6.3.70.2 MLME-QOS-MAP.request 571
6.3.70.3 MLME-QOS-MAP.indication 572
6.3.71 Mesh peering management 573
6.3.71.1 Introduction 573
6.3.71.2 MLME-MESHPEERINGMANAGEMENT.request 573
6.3.71.3 MLME-MESHPEERINGMANAGEMENT.confirm 574
6.3.71.4 MLME-MESHPEERINGMANAGEMENT.indication 575
6.3.71.5 MLME-MESHPEERINGMANAGEMENT.response 575
6.3.72 Mesh power management 576
6.3.72.1 Introduction 576
6.3.72.2 MLME-MESHPOWERMGT.request 576
6.3.72.3 MLME-MESHPOWERMGT.confirm 577
6.3.73 Mesh neighbor offset synchronization 577
6.3.73.1 Introduction 577
6.3.73.2 MLME-MESHNEIGHBOROFFSETSYNCSTART.request 578
6.3.73.3 MLME-MESHNEIGHBOROFFSETSYNCSTART.confirm 578
6.3.73.4 MLME-MESHNEIGHBOROFFSETCALCULATE.request 579
6.3.73.5 MLME-MESHNEIGHBOROFFSETCALCULATE.confirm 579
6.3.73.6 MLME-MESHNEIGHBOROFFSETSYNCSTOP.request 580
6.3.73.7 MLME-MESHNEIGHBOROFFSETSYNCSTOP.confirm 580
6.3.74 Mesh TBTT adjustment 581
6.3.74.1 Introduction 581
6.3.74.2 MLME-MESHTBTTADJUSTMENT.request 581
6.3.74.3 MLME-MESHTBTTADJUSTMENT.confirm 582
6.3.74.4 MLME-MESHTBTTADJUSTMENT.indication 583
6.3.74.5 MLME-MESHTBTTADJUSTMENT.response 583
6.3.75 MCCA management interface 584
6.3.75.1 Introduction 584
6.3.75.2 MLME-ACTIVATEMCCA.request 584
6.3.75.3 MLME-MCCASETUP.request 585
6.3.75.4 MLME-MCCASETUP.confirm 586

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.75.5 MLME-MCCASETUP.indication 587
6.3.75.6 MLME-MCCASETUP.response 588
6.3.75.7 MLME-MCCAADVERTISEMENT.request 589
6.3.75.8 MLME-MCCAADVERTISEMENT.confirm 589
6.3.75.9 MLME-MCCAADVERTISEMENT.indication 590
6.3.75.10 MLME-MCCAADVERTISEMENT.response 591
6.3.75.11 MLME-MCCATEARDOWN.request 591
6.3.75.12 MLME-MCCATEARDOWN.indication 592
6.3.76 MBSS congestion control 593
6.3.76.1 Introduction 593
6.3.76.2 MLME-MBSSCONGESTIONCONTROL.request 593
6.3.76.3 MLME-MBSSCONGESTIONCONTROL.indication 593
6.3.77 MBSS proxy update 594
6.3.77.1 Introduction 594
6.3.77.2 MLME-MBSSPROXYUPDATE.request 594
6.3.77.3 MLME-MBSSPROXYUPDATE.confirm 595
6.3.77.4 MLME-MBSSPROXYUPDATE.indication 596
6.3.77.5 MLME-MBSSPROXYUPDATE.response 596
6.3.78 MBSS mesh gate announcement 597
6.3.78.1 Introduction 597
6.3.78.2 MLME-MBSSGATEANNOUNCEMENT.request 597
6.3.78.3 MLME-MBSSGATEANNOUNCEMENT.indication 598
6.3.79 Mesh link metric 599
6.3.79.1 Introduction 599
6.3.79.2 MLME-MESHLINKMETRICREAD.request 599
6.3.79.3 MLME-MESHLINKMETRICREAD.confirm 599
6.3.79.4 MLME-MESHLINKMETRICREPORT.request 600
6.3.79.5 MLME-MESHLINKMETRICREPORT.indication 601
6.3.80 HWMP mesh path selection 602
6.3.80.1 Introduction 602
6.3.80.2 MLME-HWMPMESHPATHSELECTION.request 602
6.3.80.3 MLME-HWMPMESHPATHSELECTION.indication 603
6.3.81 QMF policy 604
6.3.81.1 Introduction 604
6.3.81.2 MLME-QMFPOLICY.request 604
6.3.81.3 MLME-QMFPOLICY.indication 605
6.3.81.4 MLME-QMFPOLICYCHANGE.request 605
6.3.81.5 MLME-QMFPOLICYCHANGE.confirm 606
6.3.81.6 MLME-QMFPOLICYCHANGE.indication 607
6.3.81.7 MLME-QMFPOLICYCHANGE.response 608
6.3.81.8 MLME-QMFPOLICYSET.request 609
6.3.82 SCS request and response procedure 609
6.3.82.1 General 609
6.3.82.2 MLME-SCS.request 610
6.3.82.3 MLME-SCS.confirm 611
6.3.82.4 MLME-SCS.indication 612
6.3.82.5 MLME-SCS.response 612
6.3.82.6 MLME-SCS-TERM.request 613
6.3.82.7 MLME-SCS-TERM.indication 614
6.3.83 QLoad report management 615
6.3.83.1 General 615
6.3.83.2 MLME-QLOAD.request 615
6.3.83.3 MLME-QLOAD.confirm 615
6.3.83.4 MLME-QLOAD.indication 616

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.83.5 MLME-QLOAD.response 617
6.3.84 HCCA TXOP advertisement management 618
6.3.84.1 General 618
6.3.84.2 MLME-TXOPADVERTISEMENT.request 618
6.3.84.3 MLME-TXOPADVERTISEMENT.confirm 619
6.3.84.4 MLME-TXOPADVERTISEMENT.indication 620
6.3.84.5 MLME-TXOPADVERTISEMENT.response 621
6.3.85 GCR group membership management 622
6.3.85.1 General 622
6.3.85.2 MLME-GROUP-MEMBERSHIP.request 622
6.3.85.3 MLME-GROUP-MEMBERSHIP.confirm 623
6.3.85.4 MLME-GROUP-MEMBERSHIP.indication 624
6.3.85.5 MLME-GROUP-MEMBERSHIP.response 624
6.3.86 AP PeerKey management 625
6.3.86.1 General 625
6.3.86.2 MLME-APPEERKEY.request 625
6.3.86.3 MLME-APPEERKEY.indication 626
6.3.87 On-channel Tunneling operation 627
6.3.87.1 General 627
6.3.87.2 MLME-OCTunnel.request 628
6.3.87.3 MLME-OCTunnel.indication 628
6.3.87.4 MLME-OCTunnel.confirm 629
6.3.88 Multi-band operation 630
6.3.88.1 General 630
6.3.88.2 MLME-FST-SETUP.request 630
6.3.88.3 MLME-FST-SETUP.indication 630
6.3.88.4 MLME-FST-SETUP.response 631
6.3.88.5 MLME-FST-SETUP.confirm 632
6.3.88.6 MLME-FST-ACK.request 632
6.3.88.7 MLME-FST-ACK.indication 633
6.3.88.8 MLME-FST-ACK.response 633
6.3.88.9 MLME-FST-ACK.confirm 634
6.3.88.10 MLME-FST-TEARDOWN.request 634
6.3.88.11 MLME-FST-TEARDOWN.indication 635
6.3.88.12 MLME-FST-INCOMING.request 636
6.3.89 DMG relay operation 636
6.3.89.1 General 636
6.3.89.2 MLME-RELAY-SEARCH.request 637
6.3.89.3 MLME-RELAY-SEARCH.confirm 637
6.3.89.4 MLME-RELAY-SEARCH.indication 638
6.3.89.5 MLME-RELAY-SEARCH.response 638
6.3.89.6 MLME-RLS.request 639
6.3.89.7 MLME-RLS.confirm 640
6.3.89.8 MLME-RLS.indication 640
6.3.89.9 MLME-RLS.response 641
6.3.89.10 MLME-RLS-TEARDOWN.request 642
6.3.89.11 MLME-RLS-TEARDOWN.indication 642
6.3.90 Quieting adjacent BSS operation 643
6.3.90.1 General 643
6.3.90.2 MLME-QAB.request 643
6.3.90.3 MLME-QAB.confirm 644
6.3.90.4 MLME-QAB.indication 645
6.3.90.5 MLME-QAB.response 646
6.3.91 DMG beamforming 646

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.91.1 General ... 646
6.3.91.2 MLME-BF-TRAINING.request ... 647
6.3.91.3 MLME-BF-TRAINING.confirm ... 647
6.3.91.4 MLME-BF-TRAINING.indication ... 648
6.3.92 PN event report ... 648
6.3.92.1 General ... 648
6.3.92.2 MLME-PN-EXHAUSTION.indication ... 648
6.3.92.3 MLME-PN-WARNING.indication ... 649
6.3.93 Channel Availability Query ... 650
6.3.93.1 Introduction ... 650
6.3.93.2 MLME-CHANNELAVAILABILITYQUERY.request ... 650
6.3.93.3 MLME-CHANNELAVAILABILITYQUERY.confirm ... 651
6.3.93.4 MLME-CHANNELAVAILABILITYQUERY.indication ... 652
6.3.93.5 MLME-CHANNELAVAILABILITYQUERY.response ... 653
6.3.94 Channel schedule management ... 654
6.3.94.1 Introduction ... 654
6.3.94.2 MLME-CHANNELSCHEDULEMANAGEMENT.request ... 654
6.3.94.3 MLME-CHANNELSCHEDULEMANAGEMENT.confirm ... 655
6.3.94.4 MLME-CHANNELSCHEDULEMANAGEMENT.indication ... 656
6.3.94.5 MLME-CHANNELSCHEDULEMANAGEMENT.response ... 657
6.3.95 Contact verification signal ... 658
6.3.95.1 Introduction ... 658
6.3.95.2 MLME-CVS.request ... 658
6.3.95.3 MLME-CVS.indication ... 659
6.3.96 GDD Enablement ... 660
6.3.96.1 Introduction ... 660
6.3.96.2 MLME-GDDENABLEMENT.request ... 660
6.3.96.3 MLME-GDDENABLEMENT.confirm ... 661
6.3.96.4 MLME-GDDENABLEMENT.indication ... 662
6.3.96.5 MLME-GDDENABLEMENT.response ... 662
6.3.97 Network channel control management ... 663
6.3.97.1 Introduction ... 663
6.3.97.2 MLME-NETWORKCHANNELCONTROL.request ... 664
6.3.97.3 MLME-NETWORKCHANNELCONTROL.confirm ... 664
6.3.97.4 MLME-NETWORKCHANNELCONTROL.indication ... 665
6.3.97.5 MLME-NETWORKCHANNELCONTROL.response ... 666
6.3.98 White space map (WSM) ... 667
6.3.98.1 Introduction ... 667
6.3.98.2 MLME-WSM.request ... 667
6.3.98.3 MLME-WSM.indication ... 668
6.3.99 Estimated Throughput ... 668
6.3.99.1 General ... 668
6.3.99.2 MLME-ESTIMATED-THROUGHPUT.request ... 668
6.3.99.3 MLME-ESTIMATED-THROUGHPUT.confirm ... 670
6.3.100 Get authentication and association state ... 670
6.3.100.1 General ... 670
6.3.100.2 MLME-GETAUTHASSOCSTATE.request ... 671
6.3.100.3 MLME-GETAUTHASSOCSTATE.confirm ... 671
6.3.101 FILS Container ... 672
6.3.101.1 General ... 672
6.3.101.2 MLME-FILSContainer.request ... 672
6.3.101.3 MLME-FILSContainer.confirm ... 672
6.3.101.4 MLME-FILSContainer.indication ... 673
6.3.101.5 MLME-FILSContainer.response ... 674

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.102 Dynamic AID assignment operation 674
6.3.102.1 General 674
6.3.102.2 MLME-AIDSWITCH.request 674
6.3.102.3 MLME-AIDSWITCH.confirm 675
6.3.102.4 MLME-AIDSWITCH.indication 676
6.3.102.5 MLME-AIDSWITCH.response 677
6.3.103 Sync Control 678
6.3.103.1 General 678
6.3.103.2 MLME-SYNCCONTROL.request 678
6.3.103.3 MLME-SYNCCONTROL.indication 678
6.3.104 STA Information Announcement 679
6.3.104.1 General 679
6.3.104.2 MLME-STAINFORMATION.request 679
6.3.104.3 MLME-STAINFORMATION.indication 680
6.3.105 EDCA Parameter Set update 680
6.3.105.1 General 680
6.3.105.2 MLME-EDCAPARAMETERSET.request 680
6.3.105.3 MLME-EDCAPARAMETERSET.indication 681
6.3.106 EL Operation 682
6.3.106.1 General 682
6.3.106.2 MLME-ELOPERATION.request 682
6.3.106.3 MLME-ELOPERATION.indication 683
6.3.107 TWT Setup 683
6.3.107.1 General 683
6.3.107.2 MLME-TWTSETUP.request 683
6.3.107.3 MLME-TWTSETUP.confirm 684
6.3.107.4 MLME-TWTSETUP.indication 685
6.3.107.5 MLME-TWTSETUP.response 685
6.3.108 TWT Teardown 686
6.3.108.1 General 686
6.3.108.2 MLME-TWTTEARDOWN.request 686
6.3.108.3 MLME-TWTTEARDOWN.indication 687
6.3.109 Sectorized Group ID List management 688
6.3.109.1 General 688
6.3.109.2 MLME-SECTORIZEDGROUPID.request 688
6.3.109.3 LME-SECTORIZEDGROUPID.indication 688
6.3.110 Header Compression procedure 689
6.3.110.1 General 689
6.3.110.2 MLME-HEADERCOMPRESSION.request 689
6.3.110.3 MLME-HEADERCOMPRESSION.confirm 690
6.3.110.4 MLME-HEADERCOMPRESSION.indication 691
6.3.110.5 MLME-HEADERCOMPRESSION.response 691
6.3.111 Reachable Address Update 692
6.3.111.1 General 692
6.3.111.2 MLME-REACHABLEADDRESSUPDATE.request 692
6.3.111.3 MLME-REACHABLEADDRESSUPDATE.indication 693
6.3.112 Control response MCS negotiation operation 694
6.3.112.1 General 694
6.3.112.2 MLME-CONTROLRESPONSEMCS.request 694
6.3.112.3 MLME-CONTROLRESPONSEMCS.confirm 695
6.3.112.4 MLME-CONTROLRESPONSEMCS.indication 695
6.3.112.5 MLME-CONTROLRESPONSEMCS.response 696
6.3.113 S1G relay (de)activation 697
6.3.113.1 General 697

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.3.113.2 MLME-S1GRELAYACTIVATE.request 697
6.3.113.3 MLME-S1GRELAYACTIVATE.confirm 697
6.3.113.4 MLME-S1GRELAYACTIVATE.indication 698
6.3.113.5 MLME-S1GRELAYACTIVATE.response 699
6.3.114 DCS procedure 699
6.3.114.1 General 699
6.3.114.2 MLME-DCSMEASUREMENT.request 699
6.3.114.3 MLME-DCSMEASUREMENT.indication 700
6.3.114.4 MLME-DCSMEASUREMENT.response 701
6.3.114.5 MLME-DCSMEASUREMENT.confirm 701
6.3.114.6 MLME-DCS.request 702
6.3.114.7 MLME-DCS.indication 703
6.3.114.8 MLME-DCS.response 703
6.3.114.9 MLME-DCS.confirm 704
6.3.115 Update 705
6.3.115.1 Introduction 705
6.3.115.2 MLME-UPDATE.request 705
6.3.115.3 MLME-UPDATE.confirm 706
6.3.116 MSCS request and response procedure 706
6.3.116.1 General 706
6.3.116.2 MLME-MSCS.request 706
6.3.116.3 MLME-MSCS.confirm 707
6.3.116.4 MLME-MSCS.indication 708
6.3.116.5 MLME-MSCS.response 709
6.3.116.6 MLME-MSCS-TERM.request 710
6.3.116.7 MLME-MSCS-TERM.indication 710
6.3.117 MAC Address Update 711
6.3.117.1 MLME-UPDATEMACADDRESS.request 711
6.3.117.2 MLME-UPDATEMACADDRESS.confirm 712
6.4 MAC state generic convergence function (MSGCF) 712
6.4.1 Overview of the convergence function 712
6.4.2 Overview of convergence function state machine 712
6.4.3 Convergence function state list 713
6.4.3.1 ESS_CONNECTED 713
6.4.3.2 ESS_DISCONNECTED 713
6.4.3.3 ESS_DISENGAGING 713
6.4.3.4 STANDBY 714
6.4.4 Convergence function state transitions 714
6.4.4.1 Transitions to ESS_CONNECTED 714
6.4.4.2 Transitions to ESS_ DISCONNECTED 714
6.4.4.3 Transitions to ESS_DISENGAGING 714
6.4.4.4 Transitions to STANDBY 715
6.4.5 Convergence function informational events 715
6.4.6 MAC state generic convergence SAP 715
6.4.7 ESS status reporting 715
6.4.7.1 MSGCF-ESS-LINK-UP.indication 715
6.4.7.2 MSGCF-ESS-LINK-DOWN.indication 716
6.4.7.3 MSGCF-ESS-LINK-GOING-DOWN.indication 717
6.4.7.4 MSGCF-ESS-LINK-EVENT-ROLLBACK.indication 718
6.4.7.5 MSGCF-ESS-LINK-DETECTED.indication 719
6.4.7.6 MSGCF-ESS-LINK-SCAN.request 720
6.4.7.7 MSGCF-ESS-LINK-SCAN.confirm 721
6.4.8 Network configuration 722
6.4.8.1 MSGCF-ESS-LINK-CAPABILITY.request 722

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

6.4.8.2 MSGCF-ESS-LINK-CAPABILITY.confirm 722
6.4.8.3 MSGCF-ESS-LINK-PARAMETERS.request 724
6.4.8.4 MSGCF-ESS-LINK-PARAMETERS.confirm 725
6.4.8.5 MSGCF-GET-ESS-LINK-PARAMETERS.request 726
6.4.8.6 MSGCF-GET-ESS-LINK-PARAMETERS.confirm 726
6.4.9 Network events 727
6.4.9.1 MSGCF-ESS-LINK-THRESHOLD-REPORT.indication 727
6.4.10 Network command interface 728
6.4.10.1 MSGCF-ESS-LINK-COMMAND.request 728
6.4.11 MAC state SME SAP—mobility management 729
6.4.11.1 MSSME-ESS-LINK-GOING-DOWN.indication 729
6.5 PLME SAP interface 729
6.5.1 General 729
6.5.2 PLME-RESET.request 730
6.5.2.1 Function 730
6.5.2.2 Semantics of the service primitive 730
6.5.2.3 When generated 730
6.5.2.4 Effect of receipt 730
6.5.3 PLME-CHARACTERISTICS.request 730
6.5.3.1 Function 730
6.5.3.2 Semantics of the service primitive 730
6.5.3.3 When generated 730
6.5.3.4 Effect of receipt 730
6.5.4 PLME-CHARACTERISTICS.confirm 730
6.5.4.1 Function 730
6.5.4.2 Semantics of the service primitive 730
6.5.4.3 When generated 733
6.5.4.4 Effect of receipt 733
6.5.5 PLME-TXTIME.request 733
6.5.5.1 Function 733
6.5.5.2 Semantics of the service primitive 733
6.5.5.3 When generated 733
6.5.5.4 Effect of receipt 734
6.5.6 PLME-TXTIME.confirm 734
6.5.6.1 Function 734
6.5.6.2 Semantics of the service primitive 734
6.5.6.3 When generated 734
6.5.6.4 Effect of receipt 734

7. DS SAP specification 735

7.1 Introduction 735
7.2 SAP primitives 735
7.2.1 General 735
7.2.2 MSDU transfer 736
7.2.2.1 General 736
7.2.2.2 DS-UNITDATA.request 736
7.2.2.3 DS-UNITDATA.indication 736
7.2.3 Mapping updates 737
7.2.3.1 General 737
7.2.3.2 DS-STA-NOTIFY.request 737

8. PHY service specification 739

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

8.1 Scope of PHY services 739
8.2 PHY functions 739
8.3 Detailed PHY service specifications 739
8.3.1 Scope and field of application 739
8.3.2 Overview of the service 739
8.3.3 Overview of interactions 739
8.3.4 Basic service and options 739
8.3.4.1 PHY SAP peer-to-peer service primitives 739
8.3.4.2 PHY SAP inter-(sub)layer service primitives 740
8.3.4.3 PHY SAP service primitives parameters 740
8.3.4.4 Vector descriptions 741
8.3.5 PHY SAP detailed service specification 742
8.3.5.1 Introduction 742
8.3.5.2 PHY-DATA.request 742
8.3.5.3 PHY-DATA.indication 743
8.3.5.4 PHY-DATA.confirm 744
8.3.5.5 PHY-TXSTART.request 744
8.3.5.6 PHY-TXSTART.confirm 745
8.3.5.7 PHY-TXEND.request 745
8.3.5.8 PHY-TXEND.confirm 746
8.3.5.9 PHY-TXHEADEREND.indication 746
8.3.5.10 PHY-CCARESET.request 747
8.3.5.11 PHY-CCARESET.confirm 748
8.3.5.12 PHY-CCA.indication 748
8.3.5.13 PHY-RXSTART.indication 752
8.3.5.14 PHY-RXEND.indication 753
8.3.5.15 PHY-CONFIG.request 754
8.4 PHY management 754

9. Frame formats 755

9.1 General requirements 755
9.2 MAC frame formats 755
9.2.1 Basic components 755
9.2.2 Conventions 755
9.2.3 General frame format 757
9.2.4 Frame fields 758
9.2.4.1 Frame Control field 758
9.2.4.2 Duration/ID field 767
9.2.4.3 Address fields 768
9.2.4.4 Sequence Control field 770
9.2.4.5 QoS Control field 771
9.2.4.6 HT Control field 777
9.2.4.7 Frame Body field 787
9.2.4.8 FCS field 790
9.2.5 Duration/ID field (QoS STA) 791
9.2.5.1 General 791
9.2.5.2 Setting for single and multiple protection under enhanced distributed channel access (EDCA) 791
9.2.5.3 Setting for QoS CF-Poll frames 794
9.2.5.4 Setting for frames sent by a TXOP holder under HCCA 794
9.2.5.5 Settings within a PSMP sequence 794
9.2.5.6 Settings within a dual CTS sequence 795
9.2.5.7 Setting for control response frames 795

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.2.5.8 Setting for other response frames ... 796
9.3 Format of individual frame types ... 796
9.3.1 Control frames ... 796
9.3.1.1 Format of Control frames ... 796
9.3.1.2 RTS frame format ... 797
9.3.1.3 CTS frame format ... 798
9.3.1.4 Ack frame format ... 798
9.3.1.5 PS-Poll frame format ... 799
9.3.1.6 CF-End frame format ... 799
9.3.1.7 BlockAckReq frame format ... 800
9.3.1.8 BlockAck frame format ... 803
9.3.1.9 Control Wrapper frame format ... 807
9.3.1.10 Poll frame format ... 808
9.3.1.11 Service period request (SPR) frame format ... 808
9.3.1.12 Grant frame format ... 809
9.3.1.13 DMG CTS frame format ... 809
9.3.1.14 DMG DTS frame format ... 810
9.3.1.15 Sector sweep (SSW) frame format ... 810
9.3.1.16 Sector sweep feedback (SSW-Feedback) frame format ... 811
9.3.1.17 Sector sweep Ack (SSW-Ack) frame format ... 811
9.3.1.18 Grant Ack frame format ... 812
9.3.1.19 VHT NDP Announcement frame format ... 812
9.3.1.20 Beamforming Report Poll frame format ... 814
9.3.1.21 TACK frame format ... 814
9.3.2 Data frames ... 815
9.3.2.1 Format of Data frames ... 815
9.3.2.2 Aggregate MSDU (A-MSDU) format ... 819
9.3.3 (PV0) Management frames ... 822
9.3.3.1 Format of (PV0) Management frames ... 822
9.3.3.2 Beacon frame format ... 825
9.3.3.3 ATIM frame format ... 829
9.3.3.4 Disassociation frame format ... 829
9.3.3.5 Association Request frame format ... 830
9.3.3.6 Association Response frame format ... 832
9.3.3.7 Reassociation Request frame format ... 835
9.3.3.8 Reassociation Response frame format ... 839
9.3.3.9 Probe Request frame format ... 843
9.3.3.10 Probe Response frame format ... 845
9.3.3.11 Authentication frame format ... 850
9.3.3.12 Deauthentication ... 856
9.3.3.13 Action frame format ... 856
9.3.3.14 Action No Ack frame format ... 856
9.3.3.15 Timing Advertisement frame format ... 857
9.3.4 Extension frames ... 857
9.3.4.1 Format of Extension frames ... 857
9.3.4.2 DMG Beacon ... 857
9.3.4.3 S1G Beacon frame format ... 863
9.3.5 Frame addressing in an MBSS ... 865
9.4 Management and Extension frame body components ... 867
9.4.1 Fields that are not elements ... 867
9.4.1.1 Authentication Algorithm Number field ... 867
9.4.1.2 Authentication Transaction Sequence Number field ... 867
9.4.1.3 Beacon Interval field ... 868
9.4.1.4 Capability Information field ... 868

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.1.5 Current AP Address field 870
9.4.1.6 Listen Interval field 870
9.4.1.7 Reason Code field 871
9.4.1.8 AID field 874
9.4.1.9 Status Code field 875
9.4.1.10 Timestamp field 880
9.4.1.11 Action field 880
9.4.1.12 Dialog Token field 882
9.4.1.13 Block Ack Parameter Set field 882
9.4.1.14 Block Ack Timeout Value field 883
9.4.1.15 Originator Preferred MCS field 883
9.4.1.16 DELBA Parameter Set field 884
9.4.1.17 QoS Info field 884
9.4.1.18 Measurement Pilot Interval field 885
9.4.1.19 Max Transmit Power field 886
9.4.1.20 Transmit Power Used field 886
9.4.1.21 Channel Width field 886
9.4.1.22 Operating Class and Channel field 887
9.4.1.23 SM Power Control field 887
9.4.1.24 PSMP Parameter Set field 888
9.4.1.25 PSMP STA Info field 888
9.4.1.26 MIMO Control field 889
9.4.1.27 CSI Report field 891
9.4.1.28 Noncompressed Beamforming Report field 893
9.4.1.29 Compressed Beamforming Report field 895
9.4.1.30 Antenna Selection Indices field 898
9.4.1.31 Organization Identifier field 898
9.4.1.32 Rate Identification field 899
9.4.1.33 GAS Query Response Fragment ID field 900
9.4.1.34 Venue Info field 901
9.4.1.35 Target Channel 904
9.4.1.36 Operating Class 904
9.4.1.37 Send-Confirm field 904
9.4.1.38 Anti-Clogging Token field 905
9.4.1.39 Scalar field 905
9.4.1.40 FFE field 905
9.4.1.41 Confirm field 905
9.4.1.42 Finite Cyclic Group field 905
9.4.1.43 TXOP Reservation field 906
9.4.1.44 Relay Capable STA Info field 906
9.4.1.45 Band ID field 907
9.4.1.46 DMG Parameters field 907
9.4.1.47 CMMG Parameters field 908
9.4.1.48 VHT MIMO Control field 908
9.4.1.49 VHT Compressed Beamforming Report field 910
9.4.1.50 TVHT Compressed Beamforming Report field 921
9.4.1.51 MU Exclusive Beamforming Report field 922
9.4.1.52 TVHT MU Exclusive Beamforming Report field 926
9.4.1.53 Operating Mode field 926
9.4.1.54 Membership Status Array field 930
9.4.1.55 User Position Array field 930
9.4.1.56 Device Location Information Body field 931
9.4.1.57 WSM Type field and WSM Information field 931
9.4.1.58 Sync Control field 932

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.1.59 Suspend Duration field ... 932
9.4.1.60 TWT Information field ... 933
9.4.1.61 CMMG MIMO Control field ... 934
9.4.1.62 CMMG Compressed Beamforming Report field ... 935
9.4.1.63 CMMG Operating Mode field ... 939
9.4.2 Elements ... 940
9.4.2.1 General ... 940
9.4.2.2 SSID element ... 949
9.4.2.3 Supported Rates and BSS Membership Selectors element ... 950
9.4.2.4 DSSS Parameter Set element ... 951
9.4.2.5 TIM element ... 951
9.4.2.6 IBSS Parameter Set element ... 959
9.4.2.7 Challenge Text element ... 959
9.4.2.8 Country element ... 959
9.4.2.9 Request element ... 962
9.4.2.10 Extended Request element ... 962
9.4.2.11 ERP element ... 963
9.4.2.12 Extended Supported Rates and BSS Membership Selectors element ... 964
9.4.2.13 Power Constraint element ... 964
9.4.2.14 Power Capability element ... 965
9.4.2.15 TPC Request element ... 965
9.4.2.16 TPC Report element ... 966
9.4.2.17 Supported Channels element ... 966
9.4.2.18 Channel Switch Announcement element ... 967
9.4.2.19 Secondary Channel Offset element ... 967
9.4.2.20 Measurement Request element ... 968
9.4.2.21 Measurement Report element ... 1000
9.4.2.22 Quiet element ... 1049
9.4.2.23 IBSS DFS element ... 1050
9.4.2.24 RSNE ... 1051
9.4.2.25 Vendor Specific element ... 1060
9.4.2.26 Extended Capabilities element ... 1061
9.4.2.27 BSS Load element ... 1067
9.4.2.28 EDCA Parameter Set element ... 1068
9.4.2.29 TSPEC element ... 1071
9.4.2.30 TCLAS element ... 1078
9.4.2.31 TS Delay element ... 1092
9.4.2.32 TCLAS Processing element ... 1092
9.4.2.33 Schedule element ... 1093
9.4.2.34 QoS Capability element ... 1094
9.4.2.35 AP Channel Report element ... 1094
9.4.2.36 Neighbor Report element ... 1094
9.4.2.37 RCPI element ... 1101
9.4.2.38 BSS Average Access Delay element ... 1101
9.4.2.39 Antenna element ... 1102
9.4.2.40 RSNI element ... 1103
9.4.2.41 Measurement Pilot Transmission element ... 1103
9.4.2.42 BSS Available Admission Capacity element ... 1104
9.4.2.43 BSS AC Access Delay element ... 1105
9.4.2.44 RM Enabled Capabilities element ... 1107
9.4.2.45 Multiple BSSID element ... 1110
9.4.2.46 Mobility Domain element (MDE) ... 1112
9.4.2.47 Fast BSS Transition element (FTE) ... 1112
9.4.2.48 Timeout Interval element (TIE) ... 1116

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.2.49 RIC Data element (RDE) 1116
9.4.2.50 RIC Descriptor element 1117
9.4.2.51 DSE Registered Location element 1117
9.4.2.52 Extended Channel Switch Announcement element 1119
9.4.2.53 Supported Operating Classes element 1119
9.4.2.54 Management MIC element 1121
9.4.2.55 HT Capabilities element 1121
9.4.2.56 HT Operation element 1129
9.4.2.57 20/40 BSS Intolerant Channel Report element 1133
9.4.2.58 Overlapping BSS Scan Parameters element 1134
9.4.2.59 20/40 BSS Coexistence element 1134
9.4.2.60 Time Advertisement element 1135
9.4.2.61 Link Identifier element 1137
9.4.2.62 Wakeup Schedule element 1137
9.4.2.63 Channel Switch Timing element 1138
9.4.2.64 PTI Control element 1138
9.4.2.65 TPU Buffer Status element 1138
9.4.2.66 Event Request element 1139
9.4.2.67 Event Report element 1146
9.4.2.68 Diagnostic Request element 1151
9.4.2.69 Diagnostic Report element 1162
9.4.2.70 Location Parameters element 1164
9.4.2.71 Nontransmitted BSSID Capability element 1172
9.4.2.72 SSID List element 1173
9.4.2.73 Multiple BSSID-Index element 1173
9.4.2.74 FMS Descriptor element 1174
9.4.2.75 FMS Request element 1175
9.4.2.76 FMS Response element 1176
9.4.2.77 QoS Traffic Capability element 1179
9.4.2.78 BSS Max Idle Period element 1180
9.4.2.79 TFS Request element 1181
9.4.2.80 TFS Response element 1183
9.4.2.81 WNM Sleep Mode element 1184
9.4.2.82 TIM Broadcast Request element 1185
9.4.2.83 TIM Broadcast Response element 1186
9.4.2.84 Collocated Interference Report element 1187
9.4.2.85 Channel Usage element 1189
9.4.2.86 Time Zone element 1189
9.4.2.87 DMS Request element 1190
9.4.2.88 DMS Response element 1193
9.4.2.89 Destination URI element 1195
9.4.2.90 U-APSD Coexistence element 1196
9.4.2.91 Interworking element 1197
9.4.2.92 Advertisement Protocol element 1199
9.4.2.93 Expedited Bandwidth Request element 1200
9.4.2.94 QoS Map element 1201
9.4.2.95 Roaming Consortium element 1202
9.4.2.96 Emergency Alert Identifier element 1203
9.4.2.97 Mesh Configuration element 1204
9.4.2.98 Mesh ID element 1208
9.4.2.99 Mesh Link Metric Report element 1208
9.4.2.100 Congestion Notification element 1209
9.4.2.101 Mesh Peering Management element 1209
9.4.2.102 Mesh Channel Switch Parameters element 1211

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.2.103 Mesh Awake Window element 1212
9.4.2.104 Beacon Timing element 1212
9.4.2.105 MCCAOP Setup Request element 1213
9.4.2.106 MCCAOP Setup Reply element 1214
9.4.2.107 MCCAOP Advertisement Overview element 1215
9.4.2.108 MCCAOP Advertisement element 1216
9.4.2.109 MCCAOP Teardown element 1218
9.4.2.110 GANN element 1218
9.4.2.111 RANN element 1219
9.4.2.112 PREQ element 1220
9.4.2.113 PREP element 1222
9.4.2.114 PERR element 1223
9.4.2.115 PXU element 1225
9.4.2.116 PXUC element 1226
9.4.2.117 Authenticated Mesh Peering Exchange element 1227
9.4.2.118 MIC element 1227
9.4.2.119 Quality-of-Service Management Frame Policy element 1228
9.4.2.120 Intra-Access Category Priority element 1229
9.4.2.121 SCS Descriptor element 1230
9.4.2.122 QLoad Report element 1231
9.4.2.123 HCCA TXOP Update Count element 1233
9.4.2.124 Higher Layer Stream ID element 1234
9.4.2.125 GCR Group Address element 1234
9.4.2.126 DMG BSS Parameter Change element 1235
9.4.2.127 DMG Capabilities element 1235
9.4.2.128 DMG Operation element 1242
9.4.2.129 DMG Beam Refinement element 1244
9.4.2.130 DMG Wakeup Schedule element 1246
9.4.2.131 Extended Schedule element 1246
9.4.2.132 STA Availability element 1250
9.4.2.133 DMG TSPEC element 1251
9.4.2.134 CMMG TSPEC element 1254
9.4.2.135 Next DMG ATI element 1255
9.4.2.136 Channel Measurement Feedback element 1255
9.4.2.137 Awake Window element 1258
9.4.2.138 Multi-band element 1258
9.4.2.139 ADDBA Extension element 1260
9.4.2.140 Next PCP List element 1261
9.4.2.141 PCP Handover element 1261
9.4.2.142 DMG Link Margin element 1262
9.4.2.143 DMG Link Adaptation Acknowledgment element 1263
9.4.2.144 Switching Stream element 1263
9.4.2.145 Session Transition element 1265
9.4.2.146 Cluster Report element 1266
9.4.2.147 Relay Capabilities element 1268
9.4.2.148 Relay Transfer Parameter Set element 1269
9.4.2.149 Quiet Period Request element 1270
9.4.2.150 Quiet Period Response element 1271
9.4.2.151 BeamLink Maintenance element 1271
9.4.2.152 Multiple MAC Sublayers (MMS) element 1271
9.4.2.153 U-PID element 1273
9.4.2.154 ECAPC Policy element 1274
9.4.2.155 Cluster Time Offset element 1275
9.4.2.156 Antenna Sector ID Pattern element 1275

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.2.157 VHT Capabilities element ... 1277
9.4.2.158 VHT Operation element ... 1284
9.4.2.159 Extended BSS Load element ... 1286
9.4.2.160 Wide Bandwidth Channel Switch element ... 1287
9.4.2.161 Transmit Power Envelope element ... 1288
9.4.2.162 Channel Switch Wrapper element ... 1290
9.4.2.163 AID element ... 1291
9.4.2.164 Quiet Channel element ... 1291
9.4.2.165 Operating Mode Notification element ... 1292
9.4.2.166 UPSIM element ... 1292
9.4.2.167 Fine Timing Measurement Parameters element ... 1293
9.4.2.168 Device Location element ... 1297
9.4.2.169 White Space Map element ... 1297
9.4.2.170 Reduced Neighbor Report element ... 1298
9.4.2.171 TVHT Operation element ... 1300
9.4.2.172 FTM Synchronization Information element ... 1301
9.4.2.173 Estimated Service Parameters Inbound element ... 1302
9.4.2.174 Future Channel Guidance element ... 1304
9.4.2.175 Association Delay Info element ... 1304
9.4.2.176 CAG Number element ... 1305
9.4.2.177 FILS Request Parameters element(... 1306
9.4.2.178 FILS Key Confirmation element ... 1308
9.4.2.179 FILS Session element ... 1309
9.4.2.180 FILS Public Key element ... 1309
9.4.2.181 AP Configuration Sequence Number (AP-CSN) element ... 1309
9.4.2.182 FILS Indication element ... 1310
9.4.2.183 FILS HLP Container element ... 1311
9.4.2.184 FILS IP Address Assignment element ... 1312
9.4.2.185 Key Delivery element ... 1316
9.4.2.186 DILS element ... 1316
9.4.2.187 FILS Wrapped Data element ... 1318
9.4.2.188 Fragment element ... 1318
9.4.2.189 FILS Nonce element ... 1319
9.4.2.190 S1G Open-Loop Link Margin Index element ... 1319
9.4.2.191 RPS element ... 1320
9.4.2.192 Page Slice element ... 1325
9.4.2.193 AID Request element ... 1327
9.4.2.194 AID Response element ... 1329
9.4.2.195 S1G Sector Operation element ... 1330
9.4.2.196 S1G Beacon Compatibility element ... 1332
9.4.2.197 Short Beacon Interval element(... 1333
9.4.2.198 Change Sequence element ... 1333
9.4.2.199 TWT element ... 1333
9.4.2.200 S1G Capabilities element ... 1339
9.4.2.201 Subchannel Selective Transmission (SST) element ... 1349
9.4.2.202 Authentication Control element ... 1351
9.4.2.203 TSF Timer Accuracy element ... 1353
9.4.2.204 S1G Relay element ... 1353
9.4.2.205 Reachable Address element ... 1354
9.4.2.206 S1G Relay Activation element ... 1355
9.4.2.207 S1G Relay Discovery element ... 1356
9.4.2.208 AID Announcement element ... 1358
9.4.2.209 PV1 Probe Response Option element ... 1358
9.4.2.210 EL Operation element ... 1362

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.2.211 Sectorized Group ID List element 1362
9.4.2.212 S1G Operation element 1363
9.4.2.213 Header Compression element 1365
9.4.2.214 SST Operation element 1366
9.4.2.215 MAD element 1367
9.4.2.216 Password Identifier element 1367
9.4.2.217 Max Channel Switch Time element 1367
9.4.2.218 Vendor Specific Request element 1368
9.4.2.219 CDMG Capabilities element 1369
9.4.2.220 Dynamic Bandwidth Control element 1371
9.4.2.221 CDMG Extended Schedule element 1372
9.4.2.222 SSW Report element 1374
9.4.2.223 Cluster Probe element 1375
9.4.2.224 Extended Cluster Report element 1375
9.4.2.225 Cluster Switch Announcement element 1376
9.4.2.226 Enhanced Beam Tracking element 1377
9.4.2.227 SPSH Report element 1378
9.4.2.228 Clustering Interference Assessment element 1379
9.4.2.229 CMMG Capabilities element 1380
9.4.2.230 CMMG Operation element 1389
9.4.2.231 CMMG Operating Mode Notification element 1390
9.4.2.232 CMMG Link Margin element 1391
9.4.2.233 CMMG Link Adaptation Acknowledgment element 1392
9.4.2.234 GLK-GCR Parameter Set element 1392
9.4.2.235 Estimated Service Parameters Outbound element 1393
9.4.2.236 OCI element 1395
9.4.2.237 Service Hint element 1395
9.4.2.238 Service Hash element 1397
9.4.2.239 GAS Extension element 1397
9.4.2.240 Non-Inheritance element 1398
9.4.2.241 RSN Extension element (RSNXE) 1399
9.4.2.242 TCLAS Mask element 1400
9.4.2.243 MSCS Descriptor element 1400
9.4.2.244 Supplemental Class 2 Capabilities element 1402
9.4.2.245 OCT Source element 1402
9.4.2.246 Rejected Groups element 1403
9.4.2.247 Anti-Clogging Token Container element 1403
9.4.3 Subelements 1404
9.4.4 TLV encodings 1404
9.4.4.1 General 1404
9.4.4.2 Common TLVs 1405
9.4.5 Access network query protocol (ANQP) elements 1409
9.4.5.1 General 1409
9.4.5.2 Query List ANQP-element 1410
9.4.5.3 Capability List ANQP-element 1411
9.4.5.4 Venue Name ANQP-element 1411
9.4.5.5 Emergency Call Number ANQP-element 1412
9.4.5.6 Network Authentication Type ANQP-element 1413
9.4.5.7 Roaming Consortium ANQP-element 1414
9.4.5.8 Vendor Specific ANQP-element 1415
9.4.5.9 IP Address Type Availability ANQP-element 1415
9.4.5.10 NAI Realm ANQP-element 1416
9.4.5.11 3GPP Cellular Network ANQP-element 1420
9.4.5.12 AP Geospatial Location ANQP-element 1420

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.4.5.13 AP Civic Location ANQP-element 1421
9.4.5.14 AP Location Public Identifier URI/FQDN ANQP-element 1421
9.4.5.15 Domain Name ANQP-element 1421
9.4.5.16 Emergency Alert URI ANQP-element 1422
9.4.5.17 Emergency NAI ANQP-element 1422
9.4.5.18 TDLS Capability ANQP-element 1423
9.4.5.19 Neighbor Report ANQP-element 1423
9.4.5.20 Venue URL ANQP-element 1423
9.4.5.21 Advice of Charge ANQP-element 1424
9.4.5.22 Local Content ANQP-element 1425
9.4.5.23 Network Authentication Type with Timestamp ANQP-element 1426
9.4.5.24 Query AP List ANQP-element 1427
9.4.5.25 AP List Response ANQP-element 1428
9.4.5.26 CAG ANQP-element 1429
9.4.5.27 Service Information Request ANQP-element 1429
9.4.5.28 Service Information Response ANQP-element 1430
9.4.5.29 Local MAC Address Policy ANQP-element 1430
9.4.6 Registered location query protocol (RLQP) elements 1433
9.4.6.1 General 1433
9.4.6.2 Channel Availability Query RLQP-element 1433
9.4.6.3 Channel Schedule Management RLQP-element 1435
9.4.6.4 Network Channel Control RLQP-element 1436
9.4.6.5 Vendor Specific RLQP-element 1437
9.5 Fields used in Management and Extension frame bodies and Control frames 1437
9.5.1 Sector Sweep field 1437
9.5.2 Dynamic Allocation Info field 1438
9.5.3 Sector Sweep Feedback field 1439
9.5.4 BRP Request field 1440
9.5.5 Beamforming Control field 1441
9.5.6 Beamformed Link Maintenance field 1442
9.6 Action frame format details 1443
9.6.1 Introduction 1443
9.6.2 Spectrum Management Action frames 1443
9.6.2.1 General 1443
9.6.2.2 Spectrum Measurement Request frame format 1444
9.6.2.3 Spectrum Measurement Report frame format 1444
9.6.2.4 TPC Request frame format 1445
9.6.2.5 TPC Report frame format 1445
9.6.2.6 Channel Switch Announcement frame format 1446
9.6.3 QoS Action frame details 1447
9.6.3.1 General 1447
9.6.3.2 Basic and DMG ADDTS Request frame format 1448
9.6.3.3 Basic and DMG ADDTS Response frame format 1450
9.6.3.4 DELTS frame format 1452
9.6.3.5 Schedule frame format 1453
9.6.3.6 QoS Map Configure frame format 1453
9.6.3.7 ADDTS Reserve Request frame format 1454
9.6.3.8 ADDTS Reserve Response frame format 1454
9.6.4 Block Ack Action frame details 1455
9.6.4.1 General 1455
9.6.4.2 ADDBA Request frame format 1456
9.6.4.3 ADDBA Response frame format 1457
9.6.4.4 DELBA frame format 1458
9.6.5 Vendor-specific action details 1458

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.6.6 Radio Measurement action details 1459
9.6.6.1 General 1459
9.6.6.2 Radio Measurement Request frame format 1459
9.6.6.3 Radio Measurement Report frame format 1460
9.6.6.4 Link Measurement Request frame format 1460
9.6.6.5 Link Measurement Report frame format 1461
9.6.6.6 Neighbor Report Request frame format 1462
9.6.6.7 Neighbor Report Response frame format 1463
9.6.7 Public Action details 1463
9.6.7.1 Public Action frames 1463
9.6.7.2 20/40 BSS Coexistence Management frame format 1465
9.6.7.3 Measurement Pilot frame format 1465
9.6.7.4 DSE Enablement frame format 1467
9.6.7.5 DSE Deenablement frame format 1468
9.6.7.6 DSE Registered Location Announcement frame format 1468
9.6.7.7 Extended Channel Switch Announcement frame format 1469
9.6.7.8 DSE Measurement Request frame format 1470
9.6.7.9 DSE Measurement Report frame format 1470
9.6.7.10 DSE Power Constraint frame format 1471
9.6.7.11 Vendor Specific Public Action frame format 1472
9.6.7.12 GAS Initial Request frame format 1473
9.6.7.13 GAS Initial Response frame format 1474
9.6.7.14 GAS Comeback Request frame format 1475
9.6.7.15 GAS Comeback Response frame format 1476
9.6.7.16 TDLS Discovery Response frame format 1477
9.6.7.17 Location Track Notification frame format 1479
9.6.7.18 QMF Policy frame format 1480
9.6.7.19 QMF Policy Change frame format 1480
9.6.7.20 QLoad Request frame format 1481
9.6.7.21 QLoad Report frame format 1481
9.6.7.22 HCCA TXOP Advertisement frame 1482
9.6.7.23 HCCA TXOP Response frame 1482
9.6.7.24 Public Key frame 1483
9.6.7.25 Channel Availability Query frame format 1484
9.6.7.26 Channel Schedule Management frame format 1485
9.6.7.27 Contact Verification Signal frame format 1486
9.6.7.28 GDD Enablement Request frame format 1487
9.6.7.29 GDD Enablement Response frame format 1487
9.6.7.30 Network Channel Control frame format 1488
9.6.7.31 White Space Map Announcement frame format 1489
9.6.7.32 Fine Timing Measurement Request frame format 1489
9.6.7.33 Fine Timing Measurement frame format 1490
9.6.7.34 QAB Request frame format 1492
9.6.7.35 QAB Response frame format 1493
9.6.7.36 FILS Discovery frame format 1494
9.6.7.37 DCS Measurement Request frame format 1500
9.6.7.38 DCS Measurement Response frame format 1501
9.6.7.39 DCS Request frame format 1503
9.6.7.40 DCS Response frame format 1503
9.6.7.41 Extended Notification Period Request frame format 1504
9.6.7.42 Extended Notification Period Response frame format 1505
9.6.7.43 Extended Channel Splitting Request frame format 1505
9.6.7.44 Extended Channel Splitting Response frame format 1506
9.6.7.45 Group Addressed GAS Request frame format 1506

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.6.7.46 Group Addressed GAS Response frame format 1507
9.6.7.47 On-channel Tunnel Request frame format 1508
9.6.8 FT Action frame details 1509
9.6.8.1 General 1509
9.6.8.2 FT Request frame 1509
9.6.8.3 FT Response frame 1510
9.6.8.4 FT Confirm frame 1511
9.6.8.5 FT Ack frame 1511
9.6.9 SA Query Action frame details 1512
9.6.9.1 General 1512
9.6.9.2 SA Query Request frame 1513
9.6.9.3 SA Query Response frame 1513
9.6.10 Protected Dual of Public Action frames 1513
9.6.11 HT Action frame details 1515
9.6.11.1 HT Action field 1515
9.6.11.2 Notify Channel Width frame format 1515
9.6.11.3 SM Power Save frame format 1516
9.6.11.4 PSMP frame format 1516
9.6.11.5 CSI frame format 1517
9.6.11.6 Noncompressed Beamforming frame format 1517
9.6.11.7 Compressed Beamforming frame format 1518
9.6.11.8 Antenna Selection Indices Feedback frame format 1518
9.6.12 TDLS Action field formats 1518
9.6.12.1 General 1518
9.6.12.2 TDLS Setup Request Action field format 1519
9.6.12.3 TDLS Setup Response Action field format 1521
9.6.12.4 TDLS Setup Confirm Action field format 1522
9.6.12.5 TDLS Teardown Action field format 1524
9.6.12.6 TDLS Peer Traffic Indication Action field format 1524
9.6.12.7 TDLS Channel Switch Request Action field format 1525
9.6.12.8 TDLS Channel Switch Response Action field format 1525
9.6.12.9 TDLS Peer PSM Request Action field format 1526
9.6.12.10 TDLS Peer PSM Response Action field format 1526
9.6.12.11 TDLS Peer Traffic Response Action field format 1527
9.6.12.12 TDLS Discovery Request Action field format 1527
9.6.13 WNM Action details 1528
9.6.13.1 WNM Action fields 1528
9.6.13.2 Event Request frame format 1529
9.6.13.3 Event Report frame format 1530
9.6.13.4 Diagnostic Request frame format 1530
9.6.13.5 Diagnostic Report frame format 1531
9.6.13.6 Location Configuration Request frame format 1531
9.6.13.7 Location Configuration Response frame format 1532
9.6.13.8 BSS Transition Management Query frame format 1533
9.6.13.9 BSS Transition Management Request frame format 1534
9.6.13.10 BSS Transition Management Response frame format 1536
9.6.13.11 FMS Request frame format 1537
9.6.13.12 FMS Response frame format 1537
9.6.13.13 Collocated Interference Request frame format 1538
9.6.13.14 Collocated Interference Report frame format 1539
9.6.13.15 TFS Request frame format 1539
9.6.13.16 TFS Response frame format 1540
9.6.13.17 TFS Notify frame format 1540
9.6.13.18 TFS Notify Response frame format 1540

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.6.13.19 WNM Sleep Mode Request frame format 1541
9.6.13.20 WNM Sleep Mode Response frame format 1541
9.6.13.21 TIM Broadcast Request frame format 1544
9.6.13.22 TIM Broadcast Response frame format 1544
9.6.13.23 QoS Traffic Capability Update frame format 1545
9.6.13.24 Channel Usage Request frame format 1545
9.6.13.25 Channel Usage Response frame format 1546
9.6.13.26 DMS Request frame format 1547
9.6.13.27 DMS Response frame format 1547
9.6.13.28 Timing Measurement Request frame format 1548
9.6.13.29 WNM Notification Request frame format 1548
9.6.13.30 WNM Notification Response frame format 1549
9.6.14 Unprotected WNM Action details 1550
9.6.14.1 Unprotected WNM Action fields 1550
9.6.14.2 TIM frame format 1550
9.6.14.3 Timing Measurement frame format 1551
9.6.15 Self-protected Action frame details 1552
9.6.15.1 Self-protected Action fields 1552
9.6.15.2 Mesh Peering Open frame format 1552
9.6.15.3 Mesh Peering Confirm frame format 1554
9.6.15.4 Mesh Peering Close frame format 1555
9.6.15.5 Mesh Group Key Inform frame format 1556
9.6.15.6 Mesh Group Key Acknowledge frame format 1557
9.6.16 Mesh Action frame details 1557
9.6.16.1 Mesh Action fields 1557
9.6.16.2 Mesh Link Metric Report frame format 1558
9.6.16.3 HWMP Mesh Path Selection frame format 1558
9.6.16.4 Gate Announcement frame format 1559
9.6.16.5 Congestion Control Notification frame format 1560
9.6.16.6 MCCA Setup Request frame format 1560
9.6.16.7 MCCA Setup Reply frame format 1561
9.6.16.8 MCCA Advertisement Request frame format 1561
9.6.16.9 MCCA Advertisement frame format 1562
9.6.16.10 MCCA Teardown frame format 1562
9.6.16.11 TBTT Adjustment Request frame format 1563
9.6.16.12 TBTT Adjustment Response frame format 1563
9.6.17 Multihop Action frame details 1564
9.6.17.1 Multihop Action fields 1564
9.6.17.2 Proxy Update frame format 1564
9.6.17.3 Proxy Update Confirmation frame format 1565
9.6.18 Robust AV Streaming Action frame details 1565
9.6.18.1 General 1565
9.6.18.2 SCS Request frame format 1566
9.6.18.3 SCS Response frame format 1566
9.6.18.4 Group Membership Request frame format 1567
9.6.18.5 Group Membership Response frame format 1567
9.6.18.6 MSCS Request frame format 1568
9.6.18.7 MSCS Response frame format 1568
9.6.19 DMG Action frame details 1569
9.6.19.1 DMG Action field 1569
9.6.19.2 Power Save Configuration Request frame format 1570
9.6.19.3 Power Save Configuration Response frame format 1570
9.6.19.4 Information Request frame format 1571
9.6.19.5 Information Response frame format 1572

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.6.19.6 Handover Request frame format ... 1573
9.6.19.7 Handover Response frame format ... 1573
9.6.19.8 Relay Search Request frame format ... 1574
9.6.19.9 Relay Search Response frame format ... 1574
9.6.19.10 Multi-relay Channel Measurement Request frame format ... 1575
9.6.19.11 Multi-relay Channel Measurement Report frame format ... 1575
9.6.19.12 RLS Request frame format ... 1577
9.6.19.13 RLS Response frame format ... 1578
9.6.19.14 RLS Announcement frame format ... 1578
9.6.19.15 RLS Teardown frame format ... 1579
9.6.19.16 Relay Ack Request frame format ... 1579
9.6.19.17 Relay Ack Response frame format ... 1580
9.6.19.18 TPA Request frame format ... 1580
9.6.19.19 TPA Response frame format ... 1581
9.6.19.20 TPA Report frame format ... 1582
9.6.19.21 ROC Request frame format ... 1582
9.6.19.22 ROC Response frame format ... 1583
9.6.20 FST Action frame details ... 1583
9.6.20.1 FST Action field ... 1583
9.6.20.2 FST Setup Request frame format ... 1584
9.6.20.3 FST Setup Response frame format ... 1585
9.6.20.4 FST Teardown frame format ... 1586
9.6.20.5 FST Ack Request frame format ... 1586
9.6.20.6 FST Ack Response frame format ... 1587
9.6.20.7 On-channel Tunnel Request frame format ... 1587
9.6.21 Unprotected DMG Action frame details ... 1588
9.6.21.1 Unprotected DMG Action field ... 1588
9.6.21.2 Announce frame format ... 1588
9.6.21.3 BRP frame format ... 1590
9.6.22 VHT Action frame details ... 1591
9.6.22.1 VHT Action field ... 1591
9.6.22.2 VHT Compressed Beamforming frame format ... 1592
9.6.22.3 Group ID Management frame format ... 1592
9.6.22.4 Operating Mode Notification frame format ... 1593
9.6.23 FILS Action frame details ... 1593
9.6.23.1 General ... 1593
9.6.23.2 FILS Container frame ... 1593
9.6.24 Unprotected S1G Action frame details ... 1594
9.6.24.1 Unprotected S1G Action field ... 1594
9.6.24.2 AID Switch Request frame format ... 1594
9.6.24.3 AID Switch Response frame format ... 1595
9.6.24.4 Sync Control frame format ... 1596
9.6.24.5 STA Information Announcement frame format ... 1596
9.6.24.6 EDCA Parameter Set frame format ... 1597
9.6.24.7 EL Operation frame format ... 1597
9.6.24.8 TWT Setup frame format ... 1597
9.6.24.9 TWT Teardown frame format ... 1598
9.6.24.10 Sectorized Group ID List frame format ... 1599
9.6.24.11 Sector ID Feedback frame format ... 1599
9.6.24.12 TWT Information frame format ... 1600
9.6.25 S1G Action frame details ... 1601
9.6.25.1 S1G Action field ... 1601
9.6.25.2 Reachable Address Update frame format ... 1601
9.6.25.3 Relay Activation Request frame format ... 1602

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

9.6.25.4 Relay Activation Response frame format 1602
9.6.25.5 Header Compression frame format 1603
9.6.25.6 Protected TWT Setup frame format 1603
9.6.25.7 Protected TWT Teardown frame format 1603
9.6.25.8 Protected TWT Information frame format 1603
9.6.26 Flow Control Action frame details 1604
9.6.26.1 Flow Control Action field 1604
9.6.26.2 Flow Suspension frame format 1604
9.6.26.3 Flow Resumption frame format 1604
9.6.27 Control Response MCS Negotiation frame details 1605
9.6.27.1 Control Response MCS Negotiation Action field 1605
9.6.27.2 Control Response MCS Negotiation Request frame format 1605
9.6.27.3 Control Response MCS Negotiation Response frame format 1606
9.6.28 CDMG Action frame details 1606
9.6.28.1 CDMG Action field 1606
9.6.28.2 Notification Period Request frame format 1607
9.6.28.3 Notification Period Response frame format 1607
9.6.28.4 Channel Splitting Request frame format 1608
9.6.28.5 Channel Splitting Response frame format 1608
9.6.28.6 CDMG Allocation Request frame format 1609
9.6.28.7 CDMG Allocation Response frame format 1609
9.6.29 CMMG Action frame details 1610
9.6.29.1 CMMG Action field 1610
9.6.29.2 CMMG Compressed Beamforming frame format 1610
9.6.29.3 CMMG Operating Mode Notification frame format 1611
9.6.30 GLK Action frame details 1611
9.6.30.1 GLK Action field 1611
9.6.30.2 GLK Groupcast Mode Change Notification 1612
9.7 Aggregate MPDU (A-MPDU) 1612
9.7.1 A-MPDU format 1612
9.7.2 MPDU delimiter CRC field 1615
9.7.3 A-MPDU contents 1615
9.8 MAC frame format for PV1 frames 1619
9.8.1 Basic components 1619
9.8.2 General PV1 frame format 1619
9.8.3 PV1 frame fields 1619
9.8.3.1 Frame Control field 1619
9.8.3.2 Address fields 1621
9.8.3.3 Sequence Control field 1622
9.8.3.4 Frame Body field 1622
9.8.3.5 Overhead for encryption 1622
9.8.3.6 FCS field 1622
9.8.4 PV1 Control frames 1623
9.8.4.1 General 1623
9.8.4.2 STACK frame format 1623
9.8.4.3 BAT frame format 1624
9.8.5 PV1 Management frames 1625
9.8.5.1 Format of PV1 Management frames 1625
9.8.5.2 Action and Action No Ack frames 1626
9.8.5.3 PV1 Probe Response frame format 1627
9.8.5.4 Resource Allocation frame format 1628

10. MAC sublayer functional description 1631

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.1 Introduction ... 1631
10.2 MAC architecture ... 1631
10.2.1 General ... 1631
10.2.2 DCF ... 1633
10.2.3 Hybrid coordination function (HCF) ... 1633
10.2.3.1 General ... 1633
10.2.3.2 HCF contention based channel access (EDCA) ... 1634
10.2.3.3 HCF controlled channel access (HCCA) ... 1637
10.2.4 Mesh coordination function (MCF) ... 1638
10.2.5 Combined use of DCF and HCF ... 1638
10.2.6 Fragmentation/defragmentation overview ... 1638
10.2.7 MAC data service ... 1639
10.3 DCF ... 1640
10.3.1 General ... 1640
10.3.2 Procedures common to the DCF and EDCAF ... 1642
10.3.2.1 CS mechanism ... 1642
10.3.2.2 MAC-level acknowledgments ... 1643
10.3.2.3 IFS ... 1643
10.3.2.4 Setting and resetting the NAV ... 1648
10.3.2.5 Setting and resetting the RID ... 1650
10.3.2.6 RTS/CTS with fragmentation ... 1653
10.3.2.7 VHT and S1G RTS procedure ... 1654
10.3.2.8 CMMG RTS procedure ... 1655
10.3.2.9 CTS and DMG CTS procedure ... 1655
10.3.2.10 Dual CTS protection ... 1657
10.3.2.11 Acknowledgment procedure ... 1660
10.3.2.12 Fragment BA procedure ... 1663
10.3.2.13 MU acknowledgment procedure ... 1664
10.3.2.14 Duplicate detection and recovery ... 1665
10.3.2.15 NAV distribution ... 1669
10.3.2.16 Operation of aSlotTime ... 1670
10.3.2.17 Response Indication procedure ... 1670
10.3.3 Random backoff procedure ... 1672
10.3.4 DCF access procedure ... 1673
10.3.4.1 Introduction ... 1673
10.3.4.2 Basic access ... 1673
10.3.4.3 Backoff procedure for DCF ... 1674
10.3.4.4 Recovery procedures and retransmit limits ... 1677
10.3.4.5 Control of the channel ... 1678
10.3.5 Individually addressed MPDU transfer procedure ... 1679
10.3.6 Group addressed MPDU transfer procedure ... 1679
10.3.7 DCF timing relations ... 1680
10.3.8 Signal extension ... 1683
10.3.9 Determination of PLME aCWmin characteristics ... 1684
10.4 MSDU and MMPDU fragmentation ... 1684
10.5 MSDU and MMPDU defragmentation ... 1685
10.6 Multirate support ... 1686
10.6.1 Overview ... 1686
10.6.2 Basic HT-MCS Set field ... 1687
10.6.3 Basic STBC MCS ... 1687
10.6.4 Basic rate set, basic HT-MCS set, and basic VHT-MCS and NSS set for mesh STA ... 1687
10.6.5 Rate selection for Data and Management frames ... 1688
10.6.5.1 Rate selection for non-STBC Beacon and non-STBC PSMP frames 1688

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.6.5.2 Rate selection for STBC group addressed Data and Management frames ... 1688
10.6.5.3 Rate selection for other group addressed Data and Management frames ... 1688
10.6.5.4 Rate selection for polling frames ... 1689
10.6.5.5 Rate selection for +CF-Ack frames ... 1689
10.6.5.6 Rate selection for Data frames sent within an FMS stream ... 1689
10.6.5.7 Rate selection for other individually addressed Data and Management frames ... 1689
10.6.6 Rate selection for Control frames ... 1691
10.6.6.1 General rules for rate selection for Control frames ... 1691
10.6.6.2 Rate selection for Control frames that initiate a TXOP ... 1692
10.6.6.3 Rate selection for CF-End frames ... 1692
10.6.6.4 Rate selection for Control frames that are not control response frames ... 1693
10.6.6.5 Rate selection for control response frames ... 1694
10.6.6.6 Channel Width selection for Control frames ... 1699
10.6.6.7 Control frame TXVECTOR parameter restrictions ... 1701
10.6.7 Multirate support for DMG STAs ... 1701
10.6.7.1 Usage of DMG Control modulation class ... 1701
10.6.7.2 Rate selection rules for Control frames transmitted by DMG STAs 1702
10.6.7.3 Rate selection for group addressed Data and Management frames transmitted by DMG STAs ... 1702
10.6.7.4 Rate selection for individually addressed Data and Management frames transmitted by DMG STAs ... 1703
10.6.7.5 Rate selection for BRP PPDUs ... 1703
10.6.8 Multirate support for CMMG STAs ... 1704
10.6.8.1 Usage of CMMG Control modulation class ... 1704
10.6.8.2 Rate selection rules for Control frames transmitted by CMMG STAs ... 1704
10.6.8.3 Rate selection for group addressed Data and Management frames transmitted by CMMG STAs ... 1705
10.6.8.4 Rate selection for individually addressed Data and Management frames transmitted by CMMG STAs ... 1705
10.6.8.5 Rate selection for BRP PPDUs for CMMG STAs ... 1706
10.6.9 Multiple BSSID Rate Selection ... 1706
10.6.10 Modulation classes ... 1706
10.6.11 Non-HT basic rate calculation ... 1708
10.6.12 Channel Width in non-HT and non-HT duplicate PPDUs ... 1708
10.6.13 Rate selection constraints for VHT STAs ... 1709
10.6.13.1 Rx Supported VHT-MCS and NSS Set ... 1709
10.6.13.2 Tx Supported VHT-MCS and NSS Set ... 1710
10.6.13.3 Additional rate selection constraints for VHT PPDUs ... 1711
10.6.14 Rate selection constraints for S1G STAs ... 1711
10.6.14.1 RX Supported S1G-MCS and NSS Set ... 1711
10.6.14.2 TX Supported S1G-MCS and NSS Set ... 1712
10.6.14.3 Additional rate selection constraints for S1G PPDUs ... 1712
10.6.15 Rate selection constraints for CMMG STAs ... 1713
10.6.15.1 Rx supported CMMG-MCS and NSS set ... 1713
10.6.15.2 Tx supported CMMG-MCS and NSS set ... 1713
10.7 MSDU transmission restrictions ... 1713
10.8 HT Control field operation ... 1714
10.9 Control Wrapper operation ... 1715
10.10 MSDU processing ... 1715

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.11 A-MSDU operation ... 1715
10.12 A-MPDU operation ... 1719
10.12.1 A-MPDU contents ... 1719
10.12.2 A-MPDU length limit rules ... 1719
10.12.3 Minimum MPDU Start Spacing field ... 1720
10.12.4 A-MPDU aggregation of group addressed Data frames ... 1721
10.12.5 Transport of A-MPDU by the PHY data service ... 1722
10.12.6 A-MPDU padding for VHT PPDU or S1G PPDU ... 1722
10.12.7 Setting the EOF field of the MPDU delimiter ... 1723
10.12.8 Transport of S-MPDUs ... 1724
10.13 PPDU duration constraint ... 1724
10.14 DMG A-PPDU operation ... 1724
10.15 Low-density parity check code (LDPC) operation ... 1725
10.16 STBC operation ... 1725
10.17 Short GI operation ... 1726
10.18 Greenfield operation ... 1729
10.19 Group ID and partial AID in VHT and CMMG PPDUs ... 1729
10.20 S1G dynamic AID assignment operation ... 1731
10.21 Group ID, partial AID, Uplink Indication, and COLOR in S1G PPDUs ... 1733
10.22 Operation across regulatory domains ... 1735
10.22.1 General ... 1735
10.22.2 Operation upon entering a regulatory domain ... 1735
10.22.3 Operation with operating classes ... 1736
10.22.4 Operation with the Transmit Power Envelope element ... 1736
10.22.5 Operation with coverage classes ... 1737
10.23 HCF ... 1737
10.23.1 General ... 1737
10.23.2 HCF contention based channel access (EDCA) ... 1738
10.23.2.1 Reference model ... 1738
10.23.2.2 EDCA backoff procedure ... 1739
10.23.2.3 EDCA TXOPs ... 1741
10.23.2.4 Obtaining an EDCA TXOP ... 1741
10.23.2.5 EDCA channel access in a VHT or TVHT BSS ... 1743
10.23.2.6 EDCA channel access in an S1G BSS ... 1745
10.23.2.7 Sharing an EDCA TXOP ... 1746
10.23.2.8 Multiple frame transmission in an EDCA TXOP ... 1747
10.23.2.9 TXOP limits ... 1750
10.23.2.10 Truncation of TXOP ... 1751
10.23.2.11 Termination of TXOP ... 1753
10.23.2.12 Retransmit procedures ... 1754
10.23.2.13 EDCA channel access in a CMMG BSS ... 1756
10.23.3 HCF controlled channel access (HCCA) ... 1756
10.23.3.1 General ... 1756
10.23.3.2 HCCA procedure ... 1757
10.23.3.3 HCCA TXOP structure and timing ... 1759
10.23.3.4 NAV operation of a TXOP under HCCA ... 1760
10.23.3.5 HCCA transfer rules ... 1761
10.23.4 Admission control at the HC ... 1763
10.23.4.1 General ... 1763
10.23.4.2 Contention based admission control procedures ... 1763
10.23.4.3 Controlled-access admission control ... 1765
10.23.5 Restricted access window (RAW) operation ... 1767
10.23.5.1 General ... 1767
10.23.5.2 RAW structure and timing ... 1769

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.23.5.3 Slot assignment procedure in RAW 1770
10.23.5.4 Slotted channel access procedure in RAW 1771
10.23.5.5 EDCA backoff procedure in generic RAW or triggering frame RAW 1772
10.23.5.6 EDCA backoff procedure in RAWs other than generic or triggering frame RAW 1772
10.23.5.7 RAW Operation with Resource Allocation frame 1773
10.23.5.8 Periodic RAW (PRAW) operation 1773
10.24 Mesh coordination function (MCF) 1774
10.24.1 General 1774
10.24.2 MCF contention based channel access 1775
10.24.3 MCF controlled channel access (MCCA) 1775
10.24.3.1 General 1775
10.24.3.2 MCCA activation 1775
10.24.3.3 MCCAOP reservations 1776
10.24.3.4 Neighborhood MCCAOP periods at a mesh STA 1777
10.24.3.5 MCCA access fraction (MAF) 1777
10.24.3.6 MCCAOP setup procedure 1778
10.24.3.7 MCCAOP advertisement 1779
10.24.3.8 MCCAOP teardown 1783
10.24.3.9 Access during MCCAOPs 1784
10.24.3.10 Interaction with time synchronization 1786
10.25 Block acknowledgment (block ack) 1786
10.25.1 Introduction 1786
10.25.2 Setup and modification of the block ack parameters 1787
10.25.3 Data and acknowledgment transfer using immediate block ack policy 1789
10.25.4 Teardown of the block ack mechanism 1789
10.25.5 Selection of BlockAck and BlockAckReq variants 1789
10.25.6 HT-immediate block ack extensions 1791
10.25.6.1 Introduction to HT-immediate block ack extensions 1791
10.25.6.2 HT-immediate block ack architecture 1791
10.25.6.3 Scoreboard context control during full-state operation 1792
10.25.6.4 Scoreboard context control during partial-state operation 1793
10.25.6.5 Generation and transmission of BlockAck frames by an HT STA, DMG STA, or S1G STA 1794
10.25.6.6 Receive reordering buffer control operation 1795
10.25.6.7 Originator's behavior 1797
10.25.6.8 Maintaining block ack state at the originator 1798
10.25.6.9 Originator's support of recipient's partial state 1799
10.25.7 Protected block ack agreement 1799
10.25.8 GCR and GLK-GCR block ack 1800
10.25.8.1 Introduction 1800
10.25.8.2 Scoreboard context control during GCR block ack 1800
10.25.8.3 Scoreboard context control during GLK-GCR block ack 1801
10.25.8.4 GCR block ack BlockAckReq and BlockAck frame exchanges 1802
10.25.9 DMG block ack with flow control 1804
10.25.9.1 General 1804
10.25.9.2 DMG block ack architecture with flow control 1804
10.25.9.3 Scoreboard context control with flow control 1805
10.25.9.4 Receive Reordering Buffer with flow control operation 1805
10.25.9.5 Generation and transmission of BlockAck frame by a STA with flow control 1807
10.25.9.6 Originator's behavior with flow control support 1808
10.26 No Acknowledgment (No Ack) 1808

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.27 Protection mechanisms 1808
10.27.1 Introduction 1808
10.27.2 Protection mechanism for non-ERP receivers 1808
10.27.3 Protection mechanisms for transmissions of HT PPDUs 1810
10.27.3.1 General 1810
10.27.3.2 Protection rules for HT STA operating a direct link 1812
10.27.3.3 RIFS protection 1813
10.27.3.4 Use of OBSS Non-HT STAs Present field 1813
10.27.3.5 Protection rules for an HT mesh STA 1814
10.27.4 L_LENGTH and L_DATARATE parameter values for HT-mixed format PPDUs 1815
10.27.5 Protection rules for VHT STAs 1815
10.28 MAC frame processing 1816
10.28.1 Introduction 1816
10.28.2 Revision level field processing 1816
10.28.3 Duration/ID field processing 1816
10.28.4 Response to an invalid Action and Action No Ack frame 1816
10.28.5 Operation of the Dialog Token field 1816
10.28.6 Element parsing 1816
10.28.7 Vendor specific element parsing 1816
10.28.8 Extensible element parsing 1817
10.28.9 Extensible subelement parsing 1817
10.28.10 Extensible TLV parsing 1817
10.28.11 Element fragmentation 1817
10.28.12 Element defragmentation 1819
10.29 Reverse direction protocol 1819
10.29.1 General 1819
10.29.2 Reverse direction (RD) exchange sequence 1819
10.29.3 Rules for RD initiator 1820
10.29.4 Rules for RD responder 1821
10.30 PSMP operation 1823
10.30.1 General 1823
10.30.2 Frame transmission mechanism during PSMP 1823
10.30.2.1 PSMP frame transmission (PSMP-DTT and PSMP-UTT) 1823
10.30.2.2 PSMP downlink transmission (PSMP-DTT) 1824
10.30.2.3 PSMP uplink transmission (PSMP-UTT) 1824
10.30.2.4 PSMP burst 1825
10.30.2.5 Resource allocation within a PSMP burst 1826
10.30.2.6 PSMP-UTT retransmission 1828
10.30.2.7 PSMP acknowledgment rules 1828
10.30.2.8 PSMP group addressed transmission rules 1829
10.30.3 Scheduled PSMP 1830
10.30.4 Unscheduled PSMP 1830
10.31 Sounding PPDUs 1831
10.32 Link adaptation 1832
10.32.1 Introduction 1832
10.32.2 Link adaptation using the HT variant HT Control field 1832
10.32.3 Link adaptation using the VHT variant HT Control field 1834
10.32.4 Link adaptation using the CMMG variant HT Control field 1837
10.33 CMMG beamforming 1840
10.34 Transmit beamforming 1840
10.34.1 HT steering matrix calculations 1840
10.34.2 HT transmit beamforming with implicit feedback 1841
10.34.2.1 General 1841

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.34.2.2 Unidirectional implicit transmit beamforming 1843
10.34.2.3 Bidirectional implicit transmit beamforming..... 1843
10.34.2.4 Calibration..... 1845
10.34.3 Explicit feedback beamforming..... 1849
10.34.4 VHT MU beamforming 1853
10.34.5 Explicit feedback beamforming for CMMG STAs 1853
10.35 Antenna selection (ASEL) 1856
10.35.1 Introduction..... 1856
10.35.2 ASEL frame exchange procedure 1857
10.36 Null data PPDU (NDP) sounding 1860
10.36.1 HT NDP sounding protocol 1860
10.36.2 Transmission of an HT NDP 1862
10.36.3 Determination of HT NDP destination 1862
10.36.4 Determination of HT NDP source 1862
10.36.5 VHT sounding protocol 1863
10.36.5.1 General..... 1863
10.36.5.2 Rules for VHT sounding protocol sequences 1863
10.36.5.3 Rules for fragmented feedback in VHT sounding protocol sequences 1867
10.36.6 Transmission of a VHT NDP..... 1868
10.36.7 Transmission of an S1G NDP..... 1869
10.37 Null data PPDU (NDP) sounding for CMMG STAs..... 1869
10.37.1 NDP rules..... 1869
10.37.2 Transmission of a CMMG NDP 1870
10.37.3 Determination of CMMG NDP destination..... 1870
10.37.4 Determination of CMMG NDP source 1871
10.38 Mesh forwarding framework 1871
10.38.1 General..... 1871
10.38.2 Forwarding information..... 1871
10.38.3 Addressing and forwarding of individually addressed mesh Data frames 1872
10.38.3.1 At source mesh STAs (individually addressed)..... 1872
10.38.3.2 At intermediate and destination mesh STAs (individually addressed)..... 1872
10.38.4 Addressing and forwarding of group addressed mesh Data frames 1874
10.38.4.1 At source mesh STAs (group addressed)..... 1874
10.38.4.2 At recipient mesh STAs (group addressed) 1874
10.38.5 Addressing of Management frames and MMPDU forwarding 1875
10.38.5.1 General..... 1875
10.38.5.2 MMPDU forwarding using individually addressed Multihop Action frames..... 1875
10.38.5.3 MMPDU forwarding using group addressed Multihop Action frames..... 1876
10.38.6 Detection of duplicate MSDUs/MMPDUs..... 1876
10.38.7 Mesh STAs that do not forward..... 1877
10.38.8 MSDU forwarding and unknown destination..... 1877
10.39 DMG and CMMG channel access 1878
10.39.1 General..... 1878
10.39.2 Access periods within a beacon interval..... 1878
10.39.3 ATI transmission rules..... 1879
10.39.4 DTI transmission rules..... 1882
10.39.5 Contention based access period (CBAP) transmission rules..... 1882
10.39.6 Channel access in scheduled DTI 1884
10.39.6.1 General..... 1884
10.39.6.2 Service period (SP) allocation..... 1885

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.39.6.3 Contention based access period (CBAP) allocation 1886
10.39.6.4 Pseudo-static allocations 1887
10.39.6.5 Guard time 1888
10.39.6.6 DMG and CMMG protected period 1888
10.39.6.7 Service period recovery 1895
10.39.7 Dynamic allocation of service period 1896
10.39.7.1 General 1896
10.39.7.2 Polling period (PP) 1897
10.39.7.3 Grant period (GP) 1898
10.39.8 Dynamic truncation of service period 1900
10.39.8.1 DMG dynamic truncation of service period 1900
10.39.8.2 CDMG dynamic truncation of service period 1901
10.39.9 Dynamic extension of service period 1901
10.39.10 Updating multiple NAVs 1902
10.39.11 Opportunistic transmission in alternative channel for CDMG STAs 1906
10.40 DMG and CMMG AP or PCP clustering 1908
10.40.1 General 1908
10.40.2 Cluster formation 1909
10.40.2.1 Decentralized AP or PCP cluster formation 1909
10.40.2.2 Centralized AP or PCP cluster formation 1910
10.40.3 Cluster maintenance 1914
10.40.3.1 General cluster maintenance 1914
10.40.3.2 Decentralized AP or PCP cluster maintenance 1914
10.40.3.3 Centralized AP or PCP cluster maintenance 1915
10.40.3.4 Centralized AP or PCP cluster MAC requirements 1916
10.40.4 Cluster report and rescheduling 1917
10.40.5 Decentralized AP or PCP cluster request 1919
10.41 CDMG AP or PCP clustering 1919
10.41.1 General 1919
10.41.2 Cluster formation 1920
10.41.2.1 Decentralized CDMG AP or PCP cluster formation 1920
10.41.2.2 Centralized CDMG AP or PCP cluster formation 1924
10.41.3 Cluster maintenance 1925
10.41.3.1 General cluster maintenance 1925
10.41.3.2 Decentralized CDMG AP or PCP cluster maintenance 1925
10.41.3.3 Cluster coordination 1927
10.41.3.4 Centralized CDMG AP or PCP cluster maintenance 1927
10.41.3.5 Centralized CDMG AP or PCP cluster MAC requirements 1928
10.41.4 Cluster report and rescheduling 1928
10.41.5 Decentralized AP or PCP cluster request 1929
10.41.6 Spatial sharing in a CDMG AP or PCP cluster 1929
10.42 DMG beamforming 1931
10.42.1 General 1931
10.42.2 Sector-level sweep (SLS) phase 1933
10.42.2.1 General 1933
10.42.2.2 Initiator sector sweep (ISS) 1935
10.42.2.3 Responder sector sweep (RSS) 1937
10.42.2.4 Sector sweep (SSW) feedback 1940
10.42.2.5 SSW ack 1941
10.42.3 Beam Refinement Protocol (BRP) phase 1941
10.42.3.1 General 1941
10.42.3.2 BRP setup subphase 1943
10.42.4 Beamforming in BTI 1946
10.42.5 Beamforming in A-BFT 1946

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.42.5.1 Allocation of A-BFT 1946
10.42.5.2 Operation during the A-BFT 1946
10.42.5.3 STA Beamforming after A-BFT 1950
10.42.5.4 Beamforming in A-BFT with multiple DMG antennas 1951
10.42.6 Beamforming in DTI 1952
10.42.6.1 General 1952
10.42.6.2 SLS phase execution 1952
10.42.6.3 Multiple sector ID capture (MIDC) subphase 1953
10.42.6.4 BRP phase execution 1961
10.42.7 Beam tracking 1964
10.42.8 State machines 1966
10.42.9 CDMG enhanced beam tracking 1967
10.43 DMG link adaptation 1970
10.43.1 General 1970
10.43.2 DMG TPC 1971
10.43.3 Fast link adaptation 1971
10.44 Link adaptation using the CMMG link measurement 1972
10.44.1 General 1972
10.44.2 CMMG TPC 1973
10.44.3 CMMG fast link adaptation 1974
10.45 DMG relay operation 1975
10.45.1 General 1975
10.45.2 Link switching 1975
10.45.2.1 General 1975
10.45.2.2 SP request and allocation 1975
10.45.2.3 Usage of RDS 1975
10.45.2.4 Relay frame exchange rules 1976
10.45.2.5 Link monitoring 1979
10.45.3 Link cooperation 1979
10.45.3.1 TPA procedure 1979
10.45.3.2 Link cooperation data transmission procedure 1980
10.45.4 Relay link adaptation 1981
10.46 S1G BSS operation 1981
10.46.1 Basic S1G BSS functionality 1981
10.46.2 System information update procedure 1983
10.46.3 S1G BSS channel selection methods 1984
10.46.4 S1G BSS channel switching methods 1984
10.46.5 Scanning requirements for S1G STA 1985
10.46.6 NAV and RID assertion in an S1G BSS 1985
10.46.7 BSS Basic S1G-MCS and NSS set operation 1985
10.46.8 S1G coexistence with non-IEEE-802.11 systems 1986
10.47 Target wake time (TWT) 1986
10.47.1 TWT overview 1986
10.47.2 TWT acknowledgment procedure 1989
10.47.3 Explicit TWT operation 1990
10.47.4 Implicit TWT operation 1991
10.47.5 TWT grouping 1992
10.47.6 NDP Paging setup 1992
10.47.7 TWT Sleep setup 1995
10.47.8 TWT teardown 1995
10.48 Non-TIM operation 1995
10.48.1 Resource protection for S1G STAs in non-TIM mode 1995
10.48.1.1 General 1995

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

10.48.1.2 Resource protection for S1G STAs in non-TIM mode using periodic RAW (PRAW) operation ... 1996
10.48.2 Rescheduling of awake/doze cycle ... 1997
10.49 Sync frame operation ... 1998
10.50 Bidirectional TXOP ... 2000
10.50.1 Overview ... 2000
10.50.2 Rules for BDT ... 2000
10.51 Page slicing ... 2002
10.52 Subchannel selective transmission (SST) ... 2005
10.52.1 SST overview ... 2005
10.52.2 Aperiodic SST operation ... 2005
10.52.3 Periodic SST operation ... 2009
10.53 Sectorized beam operation ... 2009
10.53.1 Introduction ... 2009
10.53.2 Sector Capabilities Exchange ... 2009
10.53.3 Group sectorization operation ... 2010
10.53.4 TXOP-based sectorization operation ... 2012
10.53.5 Sector training operation ... 2017
10.53.5.1 Introduction ... 2017
10.53.5.2 Procedure ... 2017
10.53.5.3 Sector ID feedback ... 2019
10.53.5.4 Fast Sector Discovery ... 2019
10.54 S1G relay operation ... 2019
10.54.1 General ... 2019
10.54.2 S1G relay operation ... 2020
10.54.3 Addressing and forwarding of individually addressed relay frames ... 2023
10.54.4 Addressing and forwarding of group addressed relay frames ... 2024
10.54.5 Procedures of TXOP sharing for S1G relay operation ... 2025
10.54.5.1 General ... 2025
10.54.5.2 Explicit Ack procedure ... 2026
10.54.5.3 Implicit Ack procedure ... 2026
10.54.5.4 Relay-shared TXOP protection mechanisms ... 2027
10.54.6 S1G relay discovery procedure ... 2028
10.55 Group AID ... 2029
10.56 Traveling pilot operation ... 2030
10.57 Bitmap protection for NDP BlockAck frames ... 2030
10.58 Generation of PV1 MPDUs and header compression procedure ... 2030
10.59 Transmission of an NDP CMAC PPDU ... 2032
10.60 S1G_Long operation ... 2033
10.61 S1G flow control ... 2033
10.62 Energy limited STAs operation ... 2034
10.63 S1G BSS type and STA type ... 2036
10.64 DBC mechanism for CDMG STAs ... 2036
10.64.1 General ... 2036
10.64.2 CDMG channel access ... 2037
10.64.2.1 CDMG BSS operating on a 2.16 GHz channel ... 2037
10.64.2.2 CDMG BSS operating on a 1.08 GHz channel ... 2037
10.64.2.3 Synchronization of CDMG infrastructure BSS or PBSSs on the adjacent 1.08 GHz channels within a 2.16 GHz channel ... 2039
10.64.3 Channel splitting of a 2.16 GHz channel ... 2042
10.64.4 Channel expansion of a 1.08 GHz channel ... 2043
10.64.5 Backward compatibility and interoperation ... 2044
10.65 Addressing of GLK Data frame transmission ... 2047
10.66 SYNRA filtering operation ... 2048

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11. MLME 2049

11.1 Synchronization 2049
11.1.1 General 2049
11.1.2 Basic approach 2049
11.1.2.1 TSF for an infrastructure BSS or a PBSS 2049
11.1.2.2 TSF for an IBSS 2050
11.1.2.3 TSF for an MBSS 2050
11.1.3 Maintaining synchronization 2050
11.1.3.1 General 2050
11.1.3.2 Beacon generation in non-DMG infrastructure networks 2051
11.1.3.3 Beacon generation in a DMG infrastructure BSS and in a PBSS 2052
11.1.3.4 DMG beacon generation before establishment of a BSS 2053
11.1.3.5 Beacon generation in an IBSS 2054
11.1.3.6 Beacon generation in an MBSS 2055
11.1.3.7 Beacon reception 2055
11.1.3.8 Multiple BSSID procedure 2056
11.1.3.9 TSF timer accuracy 2057
11.1.3.10 Maintaining synchronization using S1G Beacon frames 2058
11.1.4 Acquiring synchronization, scanning 2059
11.1.4.1 General 2059
11.1.4.2 Passive scanning 2061
11.1.4.3 Active scanning and probing procedures 2061
11.1.4.4 Initializing a BSS 2075
11.1.4.5 Synchronizing with a BSS 2075
11.1.4.6 Operation of Supported Rates and BSS Membership Selectors element and Extended Supported Rates and BSS Membership Selectors element 2076
11.1.5 Adjusting STA timers 2077
11.1.6 Terminating a BSS 2078
11.2 Power management 2078
11.2.1 General 2078
11.2.2 Bufferable MMPDUs 2078
11.2.3 Power management in a non-DMG infrastructure network 2079
11.2.3.1 General 2079
11.2.3.2 Non-AP STA power management modes 2081
11.2.3.3 AP TIM transmissions 2082
11.2.3.4 TIM types 2083
11.2.3.5 Power management with APSD 2084
11.2.3.6 AP operation 2087
11.2.3.7 Receive operation for STAs in PS mode 2091
11.2.3.8 Receive operation using APSD 2092
11.2.3.9 STAs operating in the active mode 2093
11.2.3.10 AP aging function 2093
11.2.3.11 PSMP power management 2093
11.2.3.12 TDLS peer power save mode 2093
11.2.3.13 TDLS peer U-APSD (TPU) 2096
11.2.3.14 FMS power management 2098
11.2.3.15 TIM Broadcast 2101
11.2.3.16 WNM sleep mode 2103
11.2.3.17 VHT TXOP power save 2105
11.2.3.18 AP power management 2106
11.2.3.19 CMMG TXOP power save 2108
11.2.4 Power management in an IBSS 2109

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.2.4.1 Introduction 2109
11.2.4.2 Basic approach 2109
11.2.4.3 Initialization of power management within an IBSS 2111
11.2.4.4 STA power state transitions 2111
11.2.5 Power management in an MBSS 2111
11.2.6 SM power save 2112
11.2.7 Power management in a PBSS and DMG infrastructure BSS 2112
11.2.7.1 General 2112
11.2.7.2 Non-AP and non-PCP STA power management mode 2115
11.2.7.3 PCP power management mode 2119
11.2.7.4 ATIM frame usage for power management of non-AP STAs 2122
11.2.8 ATIM frame and frame transmission in IBSS, DMG infrastructure BSS, and PBSS 2124
11.2.9 Power management with general links 2125
11.3 STA authentication and association 2126
11.3.1 State variables 2126
11.3.2 State transition diagram for nonmesh STAs 2126
11.3.3 Frame filtering based on STA state 2127
11.3.4 Authentication and deauthentication 2130
11.3.4.1 General 2130
11.3.4.2 Authentication—originating STA 2130
11.3.4.3 Authentication—destination STA 2131
11.3.4.4 Deauthentication—originating STA 2131
11.3.4.5 Deauthentication—destination STA 2132
11.3.5 Association, reassociation, and disassociation 2132
11.3.5.1 General 2132
11.3.5.2 Non-AP and non-PCP STA association initiation procedures 2133
11.3.5.3 AP or PCP association receipt procedures 2135
11.3.5.4 Non-AP and non-PCP STA reassociation initiation procedures 2137
11.3.5.5 AP or PCP reassociation receipt procedures 2140
11.3.5.6 Non-AP and non-PCP STA disassociation initiation procedures 2142
11.3.5.7 Non-AP and non-PCP STA disassociation receipt procedure 2142
11.3.5.8 AP or PCP disassociation initiation procedure 2143
11.3.5.9 AP or PCP disassociation receipt procedure 2143
11.3.5.10 PBSS procedures for nonassociated STAs 2144
11.3.5.11 Service characteristic indication during association 2144
11.3.6 Additional mechanisms for an AP collocated with a mesh STA 2144
11.3.7 Communicating PBSS information 2145
11.3.8 Neighbor report information upon rejection with suggested BSS transition 2145
11.3.9 Authentication control 2145
11.3.9.1 General 2145
11.3.9.2 Centralized authentication control 2145
11.3.9.3 Distributed authentication control 2146
11.4 TS operation 2147
11.4.1 Introduction 2147
11.4.2 TSPEC construction 2149
11.4.3 TS life cycle 2150
11.4.4 TS setup 2151
11.4.4.1 General 2151
11.4.4.2 Non-AP-STA-initiated TS setup 2151
11.4.4.3 AP-initiated TS setup 2152
11.4.4.4 TS setup procedures for both AP and non-AP STA initiation 2153
11.4.4.5 TS renegotiation 2156
11.4.5 TS setup by resource request during a fast BSS transition 2156

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.4.6 PSMP management ... 2157
11.4.7 Failed TS setup ... 2158
11.4.8 Data transfer ... 2159
11.4.9 TS deletion ... 2159
11.4.9.1 Deletion of a TS established between an HC, DMG AP, or PCP and a non-AP and non-PCP STA ... 2159
11.4.9.2 Peer-to-peer TS deletion and deletion of an allocation ... 2160
11.4.10 TS timeout ... 2162
11.4.11 TS suspension ... 2165
11.4.12 TS reinstatement ... 2165
11.4.13 DMG allocation formats ... 2165
11.4.13.1 General ... 2165
11.4.13.2 Isochronous allocations ... 2165
11.4.13.3 Asynchronous allocations ... 2165
11.4.14 PTP TS operation ... 2166
11.5 Block ack operation ... 2167
11.5.1 Introduction ... 2167
11.5.2 Setup and modification of the block ack parameters ... 2167
11.5.2.1 General ... 2167
11.5.2.2 Procedure at the originator ... 2167
11.5.2.3 Procedure at the recipient ... 2168
11.5.2.4 Procedure common to both originator and recipient ... 2169
11.5.3 Teardown of the block ack mechanism ... 2170
11.5.3.1 General ... 2170
11.5.3.2 Procedure at the initiator of the block ack teardown ... 2170
11.5.3.3 Procedure at the recipient of the DELBA frame ... 2170
11.5.4 Error recovery upon a peer failure ... 2170
11.6 Higher layer timer synchronization ... 2172
11.6.1 Introduction ... 2172
11.6.2 Procedure at the STA ... 2172
11.7 TPC procedures ... 2173
11.7.1 General ... 2173
11.7.2 Association based on transmit power capability ... 2174
11.7.3 Peering based on transmit power capability ... 2174
11.7.4 Interpretation of transmit power capability ... 2175
11.7.5 Specification of regulatory and local maximum transmit power levels ... 2175
11.7.6 Transmit power selection ... 2176
11.7.7 Transmit power adaptation ... 2177
11.8 DFS procedures ... 2177
11.8.1 General ... 2177
11.8.2 Association based on supported channels ... 2178
11.8.2.1 Association based on supported channels in a non-DMG BSS ... 2178
11.8.2.2 Providing supported channels upon association in a DMG BSS ... 2178
11.8.3 Quieting channels for testing ... 2179
11.8.4 Testing channels for radar ... 2180
11.8.5 Discontinuing operations after detecting radar ... 2180
11.8.6 Detecting radar ... 2180
11.8.7 Requesting and reporting of measurements ... 2180
11.8.8 Selecting and advertising a new channel ... 2182
11.8.8.1 General ... 2182
11.8.8.2 Selecting and advertising a new channel in a non-DMG infrastructure BSS ... 2182
11.8.8.3 Selecting and advertising a new channel in an IBSS ... 2183
11.8.8.4 MBSS channel switching ... 2185

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.8.8.5 HT-greenfield transmissions in operating classes that include a behavior limit of DFS_50_100_Behavior ... 2187
11.8.8.6 Selecting and advertising a new channel in a DMG BSS ... 2188
11.8.9 Channel Switch Announcement element operation ... 2188
11.8.10 Future Channel Guidance operation ... 2188
11.9 Extended channel switching (ECS) ... 2189
11.9.1 General ... 2189
11.9.2 Advertising supported operating classes ... 2189
11.9.3 Selecting and advertising a new channel and/or operating class ... 2190
11.9.3.1 General ... 2190
11.9.3.2 Selecting and advertising a new channel in an infrastructure BSS ... 2190
11.9.3.3 Selecting and advertising a new channel in an IBSS ... 2191
11.9.3.4 Selecting and advertising a new channel in an MBSS ... 2192
11.10 Radio measurement procedures ... 2192
11.10.1 General ... 2192
11.10.2 Measurement on operating and nonoperating channels ... 2192
11.10.3 Measurement start time ... 2193
11.10.4 Measurement duration ... 2193
11.10.5 Station responsibility for conducting measurements ... 2194
11.10.6 Requesting and reporting of measurements ... 2195
11.10.7 Repeated Measurement Request frames ... 2197
11.10.8 Triggered autonomous reporting ... 2198
11.10.9 Specific measurement usage ... 2199
11.10.9.1 Beacon report ... 2199
11.10.9.2 Frame report ... 2203
11.10.9.3 Channel load report ... 2203
11.10.9.4 Noise Histogram report ... 2204
11.10.9.5 STA Statistics report ... 2205
11.10.9.6 LCI report (Location configuration information report) ... 2206
11.10.9.7 Measurement pause ... 2208
11.10.9.8 Transmit Stream/Category Measurement report ... 2208
11.10.9.9 Location Civic report ... 2210
11.10.9.10 Location Identifier report ... 2211
11.10.9.11 Fine Timing Measurement Range report ... 2213
11.10.10 Usage of the neighbor report ... 2214
11.10.10.1 General ... 2214
11.10.10.2 Requesting a neighbor report ... 2214
11.10.10.3 Responding to a neighbor report request ... 2215
11.10.11 Link measurement ... 2217
11.10.12 Measurement of the RPI histogram ... 2217
11.10.13 Operation of the Max Transmit Power field ... 2217
11.10.14 Multiple BSSID set ... 2218
11.10.15 Measurement Pilot frame generation and usage ... 2218
11.10.15.1 General ... 2218
11.10.15.2 Measurement Pilot frame generation by an AP ... 2219
11.10.15.3 Measurement pilot usage by a STA ... 2221
11.10.16 Access delay measurement ... 2221
11.10.17 BSS Available Admission Capacity ... 2221
11.10.18 AP Channel Report ... 2222
11.10.19 Multicast diagnostic reporting ... 2222
11.10.20 CCA request and report ... 2223
11.10.21 RPI Histogram request and report ... 2223
11.11 DSE procedures ... 2223
11.11.1 General ... 2223

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.11.2 Enablement and deenablement ... 2224
11.11.2.1 General ... 2224
11.11.2.2 Enablement requester STA ... 2225
11.11.2.3 Enablement responder STA ... 2225
11.11.2.4 Deenablement requester STA ... 2225
11.11.2.5 Deenablement responder STA ... 2226
11.11.3 Registered STA operation ... 2226
11.11.4 Enabling STA operation with DSE ... 2226
11.11.5 Dependent STA operation with DSE ... 2227
11.12 Group addressed management frame protection procedures ... 2229
11.13 SA Query procedures ... 2229
11.14 HT BSS Operation ... 2230
11.15 20/40 MHz BSS operation ... 2231
11.15.1 Rules for operation in 20/40 MHz BSS ... 2231
11.15.2 Basic 20/40 MHz BSS functionality ... 2231
11.15.3 Channel scanning and selection methods for 20/40 MHz operation ... 2232
11.15.3.1 General ... 2232
11.15.3.2 Scanning requirements for a 20/40 MHz BSS ... 2232
11.15.3.3 Channel management at the AP and in an IBSS ... 2234
11.15.4 40 MHz PPDU transmission restrictions ... 2235
11.15.4.1 Fields used to determine 40 MHz PPDU transmission restrictions ... 2235
11.15.4.2 Infrastructure non-AP STA restrictions ... 2236
11.15.4.3 AP restrictions ... 2237
11.15.4.4 Restrictions on non-AP STAs that are not infrastructure BSS members ... 2238
11.15.5 Scanning requirements for 40MC HT STA 2G4 ... 2238
11.15.6 Exemption from OBSS scanning ... 2239
11.15.7 Communicating 20/40 BSS coexistence information ... 2240
11.15.8 Support of DSSS/CCK in 40 MHz ... 2240
11.15.9 STA CCA sensing in a 20/40 MHz BSS ... 2240
11.15.10 NAV assertion in 20/40 MHz BSS ... 2241
11.15.11 Signaling 40 MHz intolerance ... 2241
11.15.12 Switching between 40 MHz and 20 MHz ... 2241
11.16 20/40 BSS Coexistence Management frame usage ... 2243
11.17 Public Action frame addressing ... 2244
11.18 STAs communicating Data frames outside the context of a BSS ... 2244
11.19 Timing advertisement ... 2245
11.19.1 Introduction ... 2245
11.19.2 Timing advertisement frame procedures ... 2245
11.19.3 UTC TSF Offset procedures ... 2245
11.20 Tunneled direct-link setup ... 2245
11.20.1 General ... 2245
11.20.2 TDLS payload ... 2247
11.20.3 TDLS Discovery ... 2247
11.20.4 TDLS direct-link establishment ... 2247
11.20.5 TDLS direct-link teardown ... 2249
11.20.6 TDLS channel switching ... 2250
11.20.6.1 General ... 2250
11.20.6.2 General behavior on the off-channel ... 2253
11.20.6.3 Setting up a 40 MHz direct link ... 2253
11.20.6.4 TDLS channel switching and power saving ... 2254
11.20.6.5 Setting up a wide bandwidth off-channel direct link ... 2254
11.21 Wireless network management procedures ... 2256
11.21.1 Wireless network management dependencies ... 2256

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.21.2 Event request and report procedures 2256
11.21.2.1 Event request and event report 2256
11.21.2.2 Transition event request and report 2258
11.21.2.3 RSNA event request and report 2259
11.21.2.4 Peer-to-peer link event request and report 2259
11.21.2.5 WNM log event request and report 2259
11.21.2.6 Vendor Specific event request and report 2260
11.21.3 Diagnostic request and report procedures 2260
11.21.3.1 Diagnostic request and diagnostic report 2260
11.21.3.2 Configuration Profile report 2261
11.21.3.3 Manufacturer information STA report 2262
11.21.3.4 Association diagnostic 2262
11.21.3.5 IEEE 802.1X authentication diagnostic 2262
11.21.4 Location track procedures 2263
11.21.4.1 Location track configuration procedures 2263
11.21.4.2 Location track notification procedures 2265
11.21.5 Timing measurement procedure 2268
11.21.6 Fine timing measurement (FTM) procedure 2269
11.21.6.1 Overview 2269
11.21.6.2 FTM capabilities 2271
11.21.6.3 Fine timing measurement procedure negotiation 2271
11.21.6.4 Measurement exchange 2273
11.21.6.5 Fine timing measurement parameter modification 2278
11.21.6.6 Fine timing measurement termination 2278
11.21.6.7 LCI and Location Civic retrieval using FTM procedure 2279
11.21.7 BSS transition management for network load balancing 2280
11.21.7.1 BSS transition capability 2280
11.21.7.2 BSS transition management query 2280
11.21.7.3 BSS transition management request 2281
11.21.7.4 BSS transition management response 2282
11.21.8 FMS multicast rate processing 2283
11.21.9 Collocated interference reporting 2284
11.21.10 QoS Traffic capability procedure 2285
11.21.11 AC Station Count 2286
11.21.12 TFS procedures 2286
11.21.12.1 TFS capability 2286
11.21.12.2 TFS non-AP STA operation 2287
11.21.12.3 TFS AP operation 2288
11.21.13 BSS max idle period management 2289
11.21.14 Proxy ARP service 2290
11.21.15 Channel usage procedures 2290
11.21.16 Group addressed transmission service 2291
11.21.16.1 General 2291
11.21.16.2 DMS procedures 2291
11.21.16.3 GCR procedures 2294
11.21.16.4 GLK-GCR 2305
11.21.17 WNM notification 2306
11.22 WLAN interworking with external networks procedures 2307
11.22.1 General 2307
11.22.2 Interworking capabilities and information 2307
11.22.3 Interworking procedures: generic advertisement service (GAS) 2307
11.22.3.1 Introduction 2307
11.22.3.2 GAS Protocol 2308
11.22.3.3 ANQP procedures 2319

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.22.3.4 Registered location query protocol (RLQP) procedures 2326
11.22.4 Interworking procedures: IEEE 802.21 MIS support 2327
11.22.5 Interworking procedures: interactions with SSPN 2327
11.22.5.1 General operation 2327
11.22.5.2 Authentication and cipher suites selection with SSPN 2328
11.22.5.3 Reporting and session control with SSPN 2328
11.22.6 Interworking procedures: emergency services support 2329
11.22.7 Interworking procedures: emergency alert system (EAS) support 2330
11.22.8 Interworking procedures: support for the advertisement of roaming consortiums 2331
11.22.9 Interworking procedures: support for QoS mapping from external networks 2332
11.23 Preassociation discovery (PAD) procedures 2332
11.23.1 General 2332
11.23.2 Unsolicited PAD procedure 2333
11.23.3 Solicited PAD procedure 2334
11.23.4 Service hash procedure 2334
11.23.5 Bloom filter hash function operation 2335
11.24 Quality-of-service Management frame (QMF) 2335
11.24.1 General 2335
11.24.1.1 Overview 2335
11.24.1.2 Default QMF policy 2336
11.24.2 QMF policy advertisement and configuration procedures 2339
11.24.2.1 Overview 2339
11.24.2.2 QMF policy change in an infrastructure BSS or in an MBSS 2339
11.24.2.3 QMF policy configuration in an infrastructure BSS 2341
11.24.2.4 QMF policy configuration in an IBSS or OCB 2341
11.24.2.5 QMF policy configuration in an MBSS 2341
11.24.3 Interpreting QMF access categories 2342
11.25 Robust AV streaming 2343
11.25.1 Robust AV streaming dependencies 2343
11.25.2 SCS procedures 2343
11.25.3 MSCS procedures 2344
11.26 Procedures to manage OBSS 2347
11.26.1 General 2347
11.26.2 QLoad Report element 2348
11.26.2.1 Introduction 2348
11.26.2.2 Calculating field values 2348
11.26.2.3 Requesting QLoad Reports using radio measurement requests 2350
11.26.3 HCCA TXOP negotiation 2350
11.26.4 HCCA AP timing synchronization for HCCA TXOP advertisement 2354
11.26.4.1 General 2354
11.26.4.2 Timing offset 2354
11.26.4.3 Clock drift adjustment 2354
11.27 DMG beamformed link and BSS maintenance 2355
11.27.1 Beamformed link maintenance 2355
11.27.2 PCP Handover 2357
11.27.2.1 General 2357
11.27.2.2 Explicit handover procedure 2358
11.27.2.3 Implicit handover procedure 2359
11.28 DMG BSS peer and service discovery 2359
11.28.1 Information Request and Response 2359
11.28.2 Peer Service Discovery 2360
11.29 Changing DMG BSS parameters 2361
11.29.1 General 2361

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.29.2 Moving the TBTT 2361
11.29.3 Changing beacon interval duration 2362
11.29.4 Maintaining synchronization in an AP or PCP cluster 2363
11.29.5 Recommending DMG BSS parameters to the AP or PCP 2363
11.30 Spatial sharing and interference mitigation for DMG STAs 2364
11.30.1 General 2364
11.30.2 Spatial sharing and interference assessment 2364
11.30.3 Achieving spatial sharing and interference mitigation 2365
11.30.4 PBSS and infrastructure BSS stability in OBSS scenarios 2367
11.31 Multi-band operation 2367
11.31.1 General 2367
11.31.2 General FST rules 2368
11.31.3 FST setup protocol 2369
11.31.3.1 General 2369
11.31.3.2 Transitioning between states 2371
11.31.3.3 FST TS switching 2376
11.31.4 FST teardown 2378
11.31.5 On-channel Tunneling (OCT) operation 2378
11.31.6 FST payload 2383
11.32 MMSL cluster operation 2383
11.32.1 Introduction 2383
11.32.2 MMSL cluster setup 2384
11.32.2.1 General 2384
11.32.2.2 MMSL cluster setup of non-AP and non-PCP MM-SME coordinated STA with AP or PCP 2385
11.32.2.3 MMSL cluster setup of non-AP and non-PCP STA with another non-AP and non-PCP STA 2385
11.33 DMG coexistence with non-IEEE-802.11 systems 2385
11.34 DMG relay procedures 2386
11.34.1 General 2386
11.34.2 Common relay setup procedures 2387
11.34.2.1 Introduction 2387
11.34.2.2 Relay capabilities and RDS discovery procedures 2387
11.34.2.3 RDS selection procedure 2387
11.34.2.4 RLS procedure 2388
11.34.3 Relay operation-type change procedure 2388
11.34.4 Relay teardown 2389
11.35 Quieting adjacent DMG BSSs 2389
11.35.1 General 2389
11.35.2 Procedure at the requester AP 2390
11.35.3 Procedure at the responder AP 2390
11.36 DMG beamforming 2391
11.37 DMG MAC sublayer attributes 2393
11.38 VHT BSS operation 2393
11.38.1 Basic VHT BSS functionality 2393
11.38.2 Channel selection methods for a VHT BSS 2397
11.38.3 Scanning requirements for VHT STA 2397
11.38.4 Channel switching methods for a VHT BSS 2398
11.38.5 NAV assertion in a VHT BSS 2400
11.38.6 VHT STA antenna indication 2401
11.38.7 Basic VHT-MCS and NSS set operation 2401
11.38.8 Extended NSS BW Support Signaling 2401
11.39 Group ID management operation 2401
11.40 Notification of operating mode changes 2402

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.41 Basic TVHT BSS functionality 2405
11.42 Operation under the control of a GDB 2406
11.42.1 General 2406
11.42.2 GDD enabling STA operation 2407
11.42.3 GDD dependent STA operation 2407
11.42.4 Channel availability query (CAQ) procedure 2409
11.42.4.1 Introduction 2409
11.42.4.2 CAQ requesting STA 2410
11.42.4.3 CAQ responding STA 2410
11.42.5 Channel schedule management (CSM) procedures 2412
11.42.5.1 Introduction 2412
11.42.5.2 CSM requesting STA 2413
11.42.5.3 CSM responding STA 2413
11.42.6 Contact verification signal (CVS) 2414
11.42.7 Network channel control (NCC) procedures 2414
11.42.7.1 Introduction 2414
11.42.7.2 NCC requesting STA 2415
11.42.7.3 NCC responding STA 2415
11.42.8 White space map (WSM) 2416
11.43 Beacon RSSI 2417
11.44 Estimated throughput 2417
11.45 Fast Initial Link Setup (FILS) procedures 2420
11.45.1 General 2420
11.45.2 FILS Discovery frame generation and usage 2420
11.45.2.1 FILS Discovery frame transmission 2420
11.45.2.2 FILS Discovery frame reception 2421
11.45.3 Higher layer setup during (re)association procedure 2422
11.45.3.1 General 2422
11.45.3.2 Higher layer protocol encapsulation 2422
11.45.3.3 FILS IP address configuration 2424
11.45.4 FILS authentication and higher layer setup capability indications 2425
11.45.5 DILS 2425
11.45.5.1 General 2425
11.45.5.2 AP procedures for DILS 2426
11.45.5.3 Non-AP STA procedures for DILS 2426
11.46 Support for energy limited STAs 2427
11.47 DCS procedure for CDMG BSS 2427
11.47.1 General 2427
11.47.2 Assessing current channel condition 2429
11.47.3 Requesting measurements for new operating channel 2429
11.47.4 Reporting measurements 2430
11.47.5 Requesting existing BSS to migrate to a new channel 2430
11.47.6 Networking on the target channel 2431
11.48 CMMG BSS operation 2431
11.48.1 Basic CMMG BSS functionality 2431
11.48.2 Channel selection methods for a CMMG BSS 2431
11.48.3 Scanning requirements for CMMG STAs 2432
11.48.4 Channel switching methods for a CMMG BSS 2432
11.48.5 NAV assertion in a CMMG BSS 2434
11.48.6 CMMG STAs antenna indication 2434
11.48.7 BSS basic CMMG-MCS and NSS set operation 2434
11.49 Reduced neighbor report 2435
11.50 GLK operation 2436
11.50.1 General 2436

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

11.50.2 Reported general link metrics 2436
11.51 EPD operation 2438
11.52 Beacon frame protection procedures 2438

12. Security 2439

12.1 Conventions 2439
12.2 Framework 2439
12.2.1 Classes of security algorithm 2439
12.2.2 Security methods 2439
12.2.3 RSNA STA capabilities 2439
12.2.4 RSNA establishment 2440
12.2.5 RSNA assumptions and constraints 2442
12.2.6 Requirements for the Protected Frame field 2443
12.2.7 Requirements for management frame protection 2443
12.2.8 Emergency service establishment in an RSN 2443
12.2.9 Requirements for Operating Channel Validation 2443
12.2.10 Requirements for support of MAC privacy enhancements 2444
12.3 Pre-RSNA security methods 2445
12.3.1 Status of Pre-RSNA security methods 2445
12.3.2 Wired equivalent privacy (WEP) 2445
12.3.2.1 WEP overview 2445
12.3.2.2 WEP MPDU format 2446
12.3.2.3 WEP state 2446
12.3.2.4 WEP procedures 2447
12.3.3 Pre-RSNA authentication 2448
12.3.3.1 Overview 2448
12.3.3.2 Open System authentication 2449
12.3.3.3 Shared Key authentication 2449
12.4 Authentication using a password 2453
12.4.1 SAE overview 2453
12.4.2 Assumptions on SAE 2453
12.4.3 Representation of a password 2454
12.4.4 Finite cyclic groups 2454
12.4.4.1 General 2454
12.4.4.2 Elliptic curve cryptography (ECC) groups 2455
12.4.4.3 Finite field cryptography (FFC) groups 2460
12.4.5 SAE protocol 2462
12.4.5.1 Message exchanges 2462
12.4.5.2 PWE and secret generation 2463
12.4.5.3 Construction of an SAE Commit message 2463
12.4.5.4 Processing of a peer's SAE Commit message 2464
12.4.5.5 Construction of an SAE Confirm message 2465
12.4.5.6 Processing of a peer's SAE Confirm message 2465
12.4.6 Anti-clogging tokens 2465
12.4.7 Framing of SAE 2466
12.4.7.1 General 2466
12.4.7.2 Data type conversion 2466
12.4.7.3 Authentication transaction sequence number for SAE 2467
12.4.7.4 Encoding and decoding of SAE Commit messages 2467
12.4.7.5 Encoding and decoding of SAE Confirm messages 2468
12.4.7.6 Status codes 2468
12.4.8 SAE finite state machine 2468
12.4.8.1 General 2468

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

12.4.8.2 States ... 2469
12.4.8.3 Events and output ... 2470
12.4.8.4 Timers ... 2471
12.4.8.5 Variables ... 2471
12.4.8.6 Behavior of state machine ... 2472
12.5 RSNA confidentiality and integrity protocols ... 2476
12.5.1 Overview ... 2476
12.5.2 Temporal key integrity protocol (TKIP) ... 2476
12.5.2.1 TKIP overview ... 2476
12.5.2.2 TKIP MPDU formats ... 2478
12.5.2.3 TKIP MIC ... 2479
12.5.2.4 TKIP countermeasures procedures ... 2482
12.5.2.5 TKIP mixing function ... 2485
12.5.2.6 TKIP replay protection procedures ... 2489
12.5.3 CTR with CBC-MAC protocol (CCMP) ... 2490
12.5.3.1 General ... 2490
12.5.3.2 CCMP MPDU format ... 2491
12.5.3.3 CCMP cryptographic encapsulation ... 2492
12.5.3.4 CCMP decapsulation ... 2498
12.5.4 Broadcast/multicast integrity protocol (BIP) ... 2500
12.5.4.1 BIP overview ... 2500
12.5.4.2 BIP MMPDU format ... 2501
12.5.4.3 BIP AAD construction ... 2501
12.5.4.4 BIP replay protection ... 2501
12.5.4.5 BIP transmission ... 2502
12.5.4.6 BIP reception ... 2503
12.5.5 GCM protocol (GCMP) ... 2504
12.5.5.1 GCMP overview ... 2504
12.5.5.2 GCMP MPDU format ... 2504
12.5.5.3 GCMP cryptographic encapsulation ... 2505
12.5.5.4 GCMP decapsulation ... 2507
12.6 RSNA security association management ... 2509
12.6.1 Security associations ... 2509
12.6.1.1 Security association definitions ... 2509
12.6.1.2 TPKSA ... 2515
12.6.1.3 Security association life cycle ... 2515
12.6.2 RSNA selection ... 2518
12.6.3 RSNA policy selection in an infrastructure BSS ... 2518
12.6.4 TSN policy selection in an infrastructure BSS ... 2520
12.6.5 RSNA policy selection in an IBSS ... 2520
12.6.6 TSN policy selection in an IBSS ... 2522
12.6.7 RSNA policy selection in an MBSS ... 2522
12.6.8 RSNA policy selection in a PBSS ... 2522
12.6.9 RSN management of the IEEE 802.1X Controlled Port ... 2522
12.6.10 RSNA authentication in an infrastructure BSS ... 2523
12.6.10.1 General ... 2523
12.6.10.2 Preauthentication and RSNA key management ... 2524
12.6.10.3 Cached PMKSAs and RSNA key management ... 2525
12.6.11 RSNA authentication in an IBSS ... 2526
12.6.12 RSNA authentication in an MBSS ... 2527
12.6.13 RSNA authentication in a PBSS ... 2527
12.6.14 RSNA key management in an infrastructure BSS ... 2528
12.6.15 RSNA key management in an IBSS ... 2528
12.6.16 RSNA key management in an MBSS ... 2529

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

12.6.17 RSNA key management in a PBSS 2529
12.6.18 RSNA security association termination 2529
12.6.19 Protection of robust Management frames 2530
12.6.20 Robust management frame selection procedure 2531
12.6.21 RSNA rekeying 2532
12.6.22 Multi-band RSNA 2532
12.6.22.1 General 2532
12.6.22.2 Nontransparent multi-band RSNA 2533
12.6.22.3 Transparent multi-band RSNA 2534
12.6.22.4 Multi-band RSNA with TDLS in a non-DMG BSS 2534
12.6.23 Protection of Beacon frames 2535
12.7 Keys and key distribution 2535
12.7.1 Key hierarchy 2535
12.7.1.1 General 2535
12.7.1.2 PRF 2536
12.7.1.3 Pairwise key hierarchy 2538
12.7.1.4 Group key hierarchy 2540
12.7.1.5 Integrity group key hierarchy 2541
12.7.1.6 FT key hierarchy 2542
12.7.1.7 Beacon protection key hierarchy 2547
12.7.2 EAPOL-Key frames 2547
12.7.3 EAPOL-Key frame construction and processing 2556
12.7.4 EAPOL-Key frame notation 2557
12.7.5 Nonce generation 2558
12.7.6 4-way handshake 2558
12.7.6.1 General 2558
12.7.6.2 4-way handshake message 1 2559
12.7.6.3 4-way handshake message 2 2560
12.7.6.4 4-way handshake message 3 2562
12.7.6.5 4-way handshake message 4 2564
12.7.6.6 4-way handshake implementation considerations 2565
12.7.6.7 Sample 4-way handshake 2565
12.7.6.8 4-way handshake analysis 2566
12.7.7 Group key handshake 2568
12.7.7.1 General 2568
12.7.7.2 Group key handshake message 1 2569
12.7.7.3 Group key handshake message 2 2570
12.7.7.4 Group key handshake implementation considerations 2571
12.7.7.5 Sample group key handshake 2571
12.7.8 TDLS PeerKey (TPK) security protocol 2572
12.7.8.1 General 2572
12.7.8.2 TPK handshake 2572
12.7.8.3 TPK handshake security assumptions 2574
12.7.8.4 TPK Security Protocol handshake messages 2574
12.7.9 RSNA Supplicant key management state machine 2578
12.7.9.1 General 2578
12.7.9.2 Supplicant state machine states 2578
12.7.9.3 Supplicant state machine variables 2579
12.7.9.4 Supplicant state machine procedures 2579
12.7.10 RSNA Authenticator key management state machine 2582
12.7.10.1 General 2582
12.7.10.2 Authenticator state machine states 2585
12.7.10.3 Authenticator state machine variables 2587
12.7.10.4 Authenticator state machine procedures 2588

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

12.8 Mapping EAPOL keys to IEEE 802.11 keys ... 2588
12.8.1 Mapping PTK to TKIP keys ... 2588
12.8.2 Mapping GTK to TKIP keys ... 2588
12.8.3 Mapping PTK to CCMP keys ... 2589
12.8.4 Mapping GTK to CCMP keys ... 2589
12.8.5 Mapping GTK to WEP-40 keys ... 2589
12.8.6 Mapping GTK to WEP-104 keys ... 2589
12.8.7 Mapping IGTK to BIP keys ... 2589
12.8.8 Mapping PTK to GCMP keys ... 2589
12.8.9 Mapping GTK to GCMP keys ... 2589
12.8.10 Mapping BIGTK to BIP keys ... 2589
12.9 Authenticated mesh peering exchange (AMPE) ... 2589
12.10 AP PeerKey support ... 2590
12.10.1 AP PeerKey overview ... 2590
12.10.2 AP PeerKey protocol ... 2590
12.11 Authentication for FILS ... 2593
12.11.1 General ... 2593
12.11.2 FILS authentication protocol ... 2594
12.11.2.1 General ... 2594
12.11.2.2 Discovery of a FILS AP ... 2594
12.11.2.3 Key establishment with FILS Shared Key authentication ... 2594
12.11.2.4 Key establishment with FILS Public Key authentication ... 2598
12.11.2.5 Key establishment with FILS authentication ... 2600
12.11.2.6 Key confirmation with FILS authentication ... 2602
12.11.2.7 AEAD cipher mode for FILS ... 2607

13. Fast BSS transition ... 2608

13.1 Overview ... 2608
13.2 Key holders ... 2608
13.2.1 Introduction ... 2608
13.2.2 Authenticator key holders ... 2609
13.2.3 Supplicant key holders ... 2610
13.3 Capability and policy advertisement ... 2611
13.4 FT initial mobility domain association ... 2611
13.4.1 Overview ... 2611
13.4.2 FT initial mobility domain association in an RSN ... 2611
13.4.3 FT initial mobility domain association in a non-RSN ... 2614
13.4.4 FT initial mobility domain association over FILS in an RSN ... 2615
13.5 FT protocol ... 2616
13.5.1 Overview ... 2616
13.5.2 Over-the-air FT protocol authentication in an RSN ... 2617
13.5.3 Over-the-DS FT protocol in an RSN ... 2618
13.5.4 Over-the-air FT protocol in a non-RSN ... 2621
13.5.5 Over-the-DS FT protocol in a non-RSN ... 2622
13.6 FT resource request protocol ... 2623
13.6.1 Overview ... 2623
13.6.2 Over-the-air fast BSS transition with resource request ... 2623
13.6.3 Over-the-DS fast BSS transition with resource request ... 2626
13.7 FT reassociation ... 2628
13.7.1 FT reassociation in an RSN ... 2628
13.7.2 FT reassociation in a non-RSN ... 2630
13.8 FT authentication sequence ... 2631
13.8.1 Overview ... 2631

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

13.8.2 FT authentication sequence: contents of first message 2632
13.8.3 FT authentication sequence: contents of second message 2633
13.8.4 FT authentication sequence: contents of third message 2633
13.8.5 FT authentication sequence: contents of fourth message 2634
13.9 FT security architecture state machines 2636
13.9.1 Introduction 2636
13.9.2 R0KH state machine 2636
13.9.2.1 General 2636
13.9.2.2 R0KH state machine states 2637
13.9.2.3 R0KH state machine variables 2638
13.9.2.4 R0KH state machine procedures 2638
13.9.3 R1KH state machine 2638
13.9.3.1 General 2638
13.9.3.2 R1KH state machine states 2640
13.9.3.3 R1KH state machine variables 2641
13.9.3.4 R1KH state machine procedures 2642
13.9.4 S0KH state machine 2642
13.9.4.1 General 2642
13.9.4.2 S0KH state machine states 2643
13.9.4.3 S0KH state machine variables 2643
13.9.4.4 S0KH state machine procedures 2643
13.9.5 S1KH state machine 2643
13.9.5.1 General 2643
13.9.5.2 S1KH state machine states 2646
13.9.5.3 S1KH state machine variables 2647
13.9.5.4 S1KH state machine procedures 2647
13.10 Remote request broker (RRB) communication 2647
13.10.1 Overview 2647
13.10.2 Remote request broker (RRB) 2648
13.10.3 Remote Request/Response frame definition 2648
13.11 Resource request procedures 2649
13.11.1 General 2649
13.11.2 Resource information container (RIC) 2650
13.11.3 Creation and handling of a resource request 2652
13.11.3.1 FTO procedures 2652
13.11.3.2 AP procedures 2653

14. MLME mesh procedures 2656

14.1 Mesh STA dependencies 2656
14.2 Mesh discovery 2656
14.2.1 General 2656
14.2.2 Mesh identifier 2656
14.2.3 Mesh profile 2657
14.2.4 Mesh STA configuration 2657
14.2.5 Supplemental information for the mesh discovery 2658
14.2.6 Scanning mesh BSSs 2658
14.2.7 Candidate peer mesh STA 2658
14.2.8 Establishing or becoming a member of a mesh BSS 2659
14.2.9 Establishing mesh peerings 2659
14.3 Mesh peering management (MPM) 2660
14.3.1 General 2660
14.3.2 State variable management 2661
14.3.3 Mesh authentication 2661

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

14.3.4 Mesh peering instance controller 2662
14.3.4.1 Overview 2662
14.3.4.2 Creating a new mesh peering instance 2662
14.3.4.3 Deleting mesh peering instances 2663
14.3.5 Mesh peering instance selection 2663
14.3.6 Mesh peering open 2664
14.3.6.1 Generating Mesh Peering Open frames 2664
14.3.6.2 Mesh Peering Open frame processing 2664
14.3.7 Mesh peering confirm 2665
14.3.7.1 Generating Mesh Peering Confirm frames 2665
14.3.7.2 Mesh Peering Confirm frame processing 2665
14.3.8 Mesh peering close 2665
14.3.8.1 Generating Mesh Peering Close frames 2665
14.3.8.2 Mesh Peering Close frame processing 2665
14.4 Mesh peering management finite state machine (MPM FSM) 2665
14.4.1 General 2665
14.4.2 States 2666
14.4.3 Events and actions 2666
14.4.4 Timers 2667
14.4.5 State transitions 2668
14.4.6 IDLE state 2669
14.4.7 OPN_SNT state 2670
14.4.8 CNF_RCVD state 2670
14.4.9 OPN_RCVD state 2671
14.4.10 ESTAB state 2672
14.4.11 HOLDING state 2672
14.5 Authenticated mesh peering exchange (AMPE) 2672
14.5.1 Overview 2672
14.5.2 Security capabilities selection 2673
14.5.2.1 Instance Pairwise Cipher Suite selection 2673
14.5.2.2 Group cipher suite selection 2674
14.5.3 Construction and processing AES-SIV-protected mesh peering Management frames 2674
14.5.4 Distribution of group transient keys in an MBSS 2675
14.5.5 Mesh peering Management frames for AMPE 2675
14.5.5.1 General 2675
14.5.5.2 Mesh peering open for AMPE 2675
14.5.5.3 Mesh peering confirm for AMPE 2676
14.5.5.4 Mesh peering close for AMPE 2677
14.5.6 AMPE finite state machine 2678
14.5.6.1 Overview 2678
14.5.6.2 Additional events and actions to MPM FSM 2678
14.5.6.3 State transitions 2678
14.5.7 Keys and key derivation algorithm for the authenticated mesh peering exchange (AMPE) 2680
14.6 Mesh group key handshake 2681
14.6.1 General 2681
14.6.2 Protection on mesh group key handshake frames 2682
14.6.3 Mesh Group Key Inform frame construction and processing 2683
14.6.4 Mesh Group Key Acknowledge frame construction and processing 2684
14.6.5 Mesh group key implementation considerations 2684
14.7 Mesh security 2685
14.8 Mesh path selection and metric framework 2685
14.8.1 General 2685

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

14.8.2 Extensible path selection framework 2685
14.8.3 Link metric reporting 2686
14.9 Path selection link metric 2686
14.9.1 General 2686
14.9.2 Airtime link metric and high PHY rate airtime link metric 2686
14.10 Hybrid wireless mesh protocol (HWMP) 2688
14.10.1 General 2688
14.10.2 Terminology 2688
14.10.3 On-demand path selection mode 2690
14.10.4 Proactive tree building mode 2691
14.10.4.1 General 2691
14.10.4.2 Proactive PREQ mechanism 2691
14.10.4.3 Proactive RANN mechanism 2692
14.10.5 Collocated STAs 2692
14.10.6 Parameters for extensible path selection framework 2693
14.10.7 Addressing of HWMP Mesh Path Selection frame 2693
14.10.8 General rules for processing HWMP elements 2695
14.10.8.1 General 2695
14.10.8.2 HWMP propagation 2695
14.10.8.3 HWMP sequence numbering 2695
14.10.8.4 Forwarding information 2696
14.10.8.5 Repeated attempts at path discovery 2698
14.10.8.6 Limiting the rate of HWMP SN increments 2698
14.10.9 Path request (PREQ) mechanism 2698
14.10.9.1 General 2698
14.10.9.2 Function 2698
14.10.9.3 Conditions for generating and sending a PREQ element 2699
14.10.9.4 PREQ element processing 2707
14.10.10 Path reply (PREP) mechanism 2708
14.10.10.1 General 2708
14.10.10.2 Function 2708
14.10.10.3 Conditions for generating and sending a PREP element 2709
14.10.10.4 PREP element processing 2712
14.10.11 Path error (PERR) mechanism 2713
14.10.11.1 General 2713
14.10.11.2 Function 2713
14.10.11.3 Conditions for generating and sending a PERR element 2713
14.10.11.4 PERR element processing 2716
14.10.12 Root announcement (RANN) mechanism 2717
14.10.12.1 General 2717
14.10.12.2 Function 2717
14.10.12.3 Conditions for generating and sending a RANN element 2718
14.10.12.4 RANN element reception 2719
14.10.13 Considerations for support of STAs without mesh functionality 2720
14.11 Interworking with the DS or an attached bridge 2720
14.11.1 Overview of interworking between a mesh BSS and a DS or an attached bridge 2720
14.11.2 Gate announcement (GANN) 2721
14.11.2.1 General 2721
14.11.2.2 Function 2721
14.11.2.3 Conditions for generating and sending a GANN element 2721
14.11.2.4 GANN element processing 2722
14.11.3 Data forwarding at proxy mesh gates 2723
14.11.3.1 General 2723

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

14.11.3.2 Forwarding of MSDUs from the MBSS to the DS 2723
14.11.3.3 Forwarding of MSDUs from the DS to the MBSS 2723
14.11.4 Proxy information and proxy update 2725
14.11.4.1 General 2725
14.11.4.2 Proxy information 2725
14.11.4.3 Proxy update (PXU) 2726
14.11.4.4 Proxy update confirmation (PXUC) 2728
14.11.5 Mesh STA collocation 2729
14.12 Intra-mesh congestion control 2729
14.12.1 General 2729
14.12.2 Congestion control signaling protocol 2729
14.13 Synchronization and beaconing in MBSSs 2730
14.13.1 TSF for MBSSs 2730
14.13.2 Extensible synchronization framework 2730
14.13.2.1 General 2730
14.13.2.2 Neighbor offset synchronization method 2731
14.13.3 Beaconing 2733
14.13.3.1 Beacon generation in MBSSs 2733
14.13.3.2 Beacon reception for mesh STA 2733
14.13.4 Mesh beacon collision avoidance (MBCA) 2734
14.13.4.1 Overview 2734
14.13.4.2 Beacon timing advertisement 2734
14.13.4.3 TBTT selection 2737
14.13.4.4 TBTT adjustment 2738
14.13.4.5 Frame transmission across reported TBTT 2739
14.13.4.6 Delayed beacon transmissions 2740
14.14 Power save in a mesh BSS 2740
14.14.1 General 2740
14.14.2 Mesh power management modes 2740
14.14.2.1 General 2740
14.14.2.2 Peer-specific mesh power management modes 2741
14.14.2.3 Nonpeer mesh power management modes 2742
14.14.3 Mesh power management mode indications and transitions 2742
14.14.3.1 General 2742
14.14.3.2 Transition to a higher activity level 2743
14.14.3.3 Transition to a lower activity level 2743
14.14.4 TIM transmissions in an MBSS 2743
14.14.5 TIM types 2743
14.14.6 Mesh awake window 2744
14.14.7 Power save support 2744
14.14.8 Operation in peer-specific and nonpeer mesh power management modes 2745
14.14.8.1 General 2745
14.14.8.2 Operation in active mode 2745
14.14.8.3 Operation in deep sleep mode for nonpeer mesh STAs 2745
14.14.8.4 Operation in light sleep mode for a mesh peering 2746
14.14.8.5 Operation in deep sleep mode for a mesh peering 2746
14.14.8.6 Conditions for doze state 2746
14.14.9 Mesh peer service periods 2746
14.14.9.1 General 2746
14.14.9.2 Initiation of a mesh peer service period 2747
14.14.9.3 Operation during a mesh peer service period 2748
14.14.9.4 Termination of a mesh peer service period 2748
14.14.10 MCCA use by power saving mesh STA 2748

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

15. DSSS PHY specification for the 2.4 GHz band designated for ISM applications 2749

15.1 Overview 2749
15.1.1 General 2749
15.1.2 Scope of DSSS PHY services 2749
15.1.3 DSSS PHY functions 2749
15.1.3.1 General 2749
15.1.3.2 PLME 2749
15.1.4 Service specification method and notation 2749
15.2 DSSS PHY specific service parameter list 2750
15.2.1 Introduction 2750
15.2.2 TXVECTOR parameters 2750
15.2.2.1 General 2750
15.2.2.2 TXVECTOR LENGTH 2750
15.2.2.3 TXVECTOR DATARATE 2750
15.2.2.4 TXVECTOR SERVICE 2750
15.2.2.5 TXVECTOR TXPWR_LEVEL_INDEX 2751
15.2.2.6 TXVECTOR TIME_OF_DEPARTURE_REQUESTED 2751
15.2.2.7 TXVECTOR TX_ANTENNA 2751
15.2.3 RXVECTOR parameters 2751
15.2.3.1 General 2751
15.2.3.2 RXVECTOR LENGTH 2751
15.2.3.3 RXVECTOR RSSI 2751
15.2.3.4 RXVECTOR SIGNAL 2752
15.2.3.5 RXVECTOR SERVICE 2752
15.2.3.6 PHY-RXEND.indication parameter RCPI 2752
15.2.3.7 RXVECTOR SQ 2752
15.2.3.8 RXVECTOR RX_ANTENNA 2752
15.2.4 TXSTATUS parameters 2752
15.2.4.1 General 2752
15.2.4.2 TXSTATUS TIME_OF_DEPARTURE 2753
15.2.4.3 TXSTATUS TIME_OF_DEPARTURE_ClockRate 2753
15.3 DSSS PHY 2753
15.3.1 Overview 2753
15.3.2 PPDU format 2753
15.3.3 PHY field definitions 2754
15.3.3.1 General 2754
15.3.3.2 PHY SYNC field 2754
15.3.3.3 PHY SFD 2754
15.3.3.4 PHY SIGNAL field 2754
15.3.3.5 PHY SERVICE field 2754
15.3.3.6 PHY LENGTH field 2754
15.3.3.7 PHY CRC field 2755
15.3.4 PHY/DSSS PHY data scrambler and descrambler 2756
15.3.5 PHY data modulation and modulation rate change 2757
15.3.6 Transmit PHY 2757
15.3.7 Receive PHY 2759
15.4 DSSS PLME 2762
15.4.1 PLME SAP sublayer management primitives 2762
15.4.2 DSSS PHY MIB 2763
15.4.3 DSSS PHY 2763
15.4.4 PHY operating specifications, general 2764
15.4.4.1 General 2764
15.4.4.2 Operating frequency range 2764

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

15.4.4.3 Channel Numbering of operating channels ... 2764
15.4.4.4 Spreading sequence ... 2765
15.4.4.5 Modulation and channel data rates ... 2765
15.4.4.6 Transmit and receive in-band and out-of-band spurious emissions ... 2766
15.4.4.7 TX-to-RX turnaround time ... 2766
15.4.4.8 RX-to-TX turnaround time ... 2766
15.4.4.9 Slot time ... 2766
15.4.4.10 Transmit and receive antenna connector impedance ... 2766
15.4.5 PHY transmit specifications ... 2766
15.4.5.1 Introduction ... 2766
15.4.5.2 Transmit power levels ... 2766
15.4.5.3 Minimum transmitted power level ... 2766
15.4.5.4 Transmit power level control ... 2766
15.4.5.5 Transmit spectrum mask ... 2767
15.4.5.6 Transmit center frequency tolerance ... 2767
15.4.5.7 Chip clock frequency tolerance ... 2767
15.4.5.8 Transmit power-on and power-down ramp ... 2767
15.4.5.9 RF carrier suppression ... 2768
15.4.5.10 Transmit modulation accuracy ... 2768
15.4.5.11 Time of Departure accuracy ... 2770
15.4.6 PHY receiver specifications ... 2771
15.4.6.1 Introduction ... 2771
15.4.6.2 Receiver minimum input level sensitivity ... 2771
15.4.6.3 Receiver maximum input level ... 2771
15.4.6.4 Receiver adjacent channel rejection ... 2771
15.4.6.5 CCA ... 2771
15.4.6.6 Received channel power indicator (RCPI) measurement ... 2772
15.4.6.7 DSSS PHY TXTIME calculation ... 2772

16. High rate direct sequence spread spectrum (HR/DSSS) PHY specification ... 2773

16.1 Overview ... 2773
16.1.1 General ... 2773
16.1.2 Scope of HR/DSSS PHY services ... 2773
16.1.3 HR/DSSS PHY functions ... 2773
16.1.3.1 General ... 2773
16.1.3.2 PLME ... 2774
16.1.4 Service specification method and notation ... 2774
16.2 HR/DSSS PHY ... 2774
16.2.1 Overview ... 2774
16.2.2 PPDU format ... 2774
16.2.2.1 General ... 2774
16.2.2.2 Long PPDU format ... 2774
16.2.2.3 Short PPDU format ... 2775
16.2.3 PPDU field definitions ... 2776
16.2.3.1 General ... 2776
16.2.3.2 Long PHY SYNC field ... 2776
16.2.3.3 Long PHY SFD ... 2776
16.2.3.4 Long PHY SIGNAL field ... 2776
16.2.3.5 Long PHY SERVICE field ... 2776
16.2.3.6 Long PHY LENGTH field ... 2777
16.2.3.7 PHY CRC (CRC-16) field ... 2778
16.2.3.8 Long PHY data modulation and modulation rate change ... 2780
16.2.3.9 Short PHY synchronization (shortSYNC) ... 2780

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

16.2.3.10 Short PHY SFD field (shortSFD) 2780
16.2.3.11 Short PHY SIGNAL field (shortSIGNAL) 2781
16.2.3.12 Short PHY SERVICE field (shortSERVICE) 2781
16.2.3.13 Short PHY LENGTH field (shortLENGTH) 2781
16.2.3.14 Short CRC-16 field (shortCRC) 2781
16.2.3.15 Short PHY data modulation and modulation rate change 2781
16.2.4 PHY/HR/DSSS PHY data scrambler and descrambler 2781
16.2.5 Transmit PHY 2782
16.2.6 Receive PHY 2783
16.3 HR/DSSS PLME 2786
16.3.1 PLME SAP sublayer management primitives 2786
16.3.2 HR/DSSS PHY MIB 2788
16.3.3 HR/DSSS PHY 2788
16.3.4 HR/DSSS TXTIME calculation 2788
16.3.5 Vector descriptions 2789
16.3.6 PHY operating specifications, general 2790
16.3.6.1 General 2790
16.3.6.2 Operating frequency range 2790
16.3.6.3 Channel Numbering of operating channels 2790
16.3.6.4 Modulation and channel data rates 2791
16.3.6.5 Spreading sequence and modulation for 1 Mb/s and 2 Mb/s 2791
16.3.6.6 Spreading sequences and modulation for CCK modulation at 5.5 Mb/s and 11 Mb/s 2792
16.3.6.7 Transmit and receive in-band and out-of-band spurious emissions 2794
16.3.6.8 TX-to-RX turnaround time 2794
16.3.6.9 RX-to-TX turnaround time 2794
16.3.6.10 Slot time 2794
16.3.6.11 Transmit and receive impedance at the antenna connector 2794
16.3.7 PHY transmit specifications 2795
16.3.7.1 Introduction 2795
16.3.7.2 Transmit power levels 2795
16.3.7.3 Transmit power level control 2795
16.3.7.4 Transmit spectrum mask 2795
16.3.7.5 Transmit center frequency tolerance 2796
16.3.7.6 Chip clock frequency tolerance 2796
16.3.7.7 Transmit power-on and power-down ramp 2796
16.3.7.8 RF carrier suppression 2797
16.3.7.9 Transmit modulation accuracy 2797
16.3.7.10 Time of Departure accuracy 2799
16.3.8 PHY receiver specifications 2799
16.3.8.1 Introduction 2799
16.3.8.2 Receiver minimum input level sensitivity 2799
16.3.8.3 Receiver maximum input level 2800
16.3.8.4 Receiver adjacent channel rejection 2800
16.3.8.5 CCA 2800
16.3.8.6 Received channel power indicator (RCPI) measurement 2801

17. Orthogonal frequency division multiplexing (OFDM) PHY specification 2802

17.1 Introduction 2802
17.1.1 General 2802
17.1.2 Scope of OFDM services 2802
17.1.3 OFDM PHY functions 2802
17.1.3.1 General 2802

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

17.1.3.2 PLME ... 2802
17.1.3.3 Service specification method ... 2803
17.2 OFDM PHY specific service parameter list ... 2803
17.2.1 Introduction ... 2803
17.2.2 TXVECTOR parameters ... 2803
17.2.2.1 General ... 2803
17.2.2.2 TXVECTOR LENGTH ... 2804
17.2.2.3 TXVECTOR DATARATE ... 2804
17.2.2.4 TXVECTOR SERVICE ... 2804
17.2.2.5 TXVECTOR TXPWR_LEVEL_INDEX ... 2804
17.2.2.6 TXVECTOR TIME_OF_DEPARTURE_REQUESTED ... 2804
17.2.2.7 TXVECTOR CH_BANDWIDTH_IN_NON_HT ... 2805
17.2.2.8 TXVECTOR DYN_BANDWIDTH_IN_NON_HT ... 2805
17.2.3 RXVECTOR parameters ... 2805
17.2.3.1 General ... 2805
17.2.3.2 RXVECTOR LENGTH ... 2806
17.2.3.3 RXVECTOR RSSI ... 2806
17.2.3.4 RXVECTOR DATARATE ... 2806
17.2.3.5 RXVECTOR SERVICE ... 2806
17.2.3.6 PHY-RXEND.indication parameter RCPI ... 2806
17.2.3.7 RXVECTOR CH_BANDWIDTH_IN_NON_HT ... 2807
17.2.3.8 RXVECTOR DYN_BANDWIDTH_IN_NON_HT ... 2807
17.2.4 TXSTATUS parameters ... 2807
17.2.4.1 General ... 2807
17.2.4.2 TXSTATUS TIME_OF_DEPARTURE ... 2808
17.2.4.3 TXSTATUS TIME_OF_DEPARTURE_ClockRate ... 2808
17.3 OFDM PHY ... 2808
17.3.1 Introduction ... 2808
17.3.2 PPDU format ... 2808
17.3.2.1 General ... 2808
17.3.2.2 Overview of the PPDU encoding process ... 2809
17.3.2.3 Modulation-dependent parameters ... 2810
17.3.2.4 Timing-related parameters ... 2811
17.3.2.5 Mathematical conventions in the signal descriptions ... 2811
17.3.2.6 Discrete time implementation considerations ... 2813
17.3.3 PHY preamble (SYNC) ... 2814
17.3.4 SIGNAL field ... 2815
17.3.4.1 General ... 2815
17.3.4.2 RATE field ... 2816
17.3.4.3 PHY LENGTH field ... 2816
17.3.4.4 Parity (P), Reserved (R), and SIGNAL TAIL fields ... 2817
17.3.5 DATA field ... 2817
17.3.5.1 General ... 2817
17.3.5.2 SERVICE field ... 2817
17.3.5.3 PPDU TAIL field ... 2817
17.3.5.4 Pad bits (PAD) ... 2817
17.3.5.5 PHY DATA scrambler and descrambler ... 2818
17.3.5.6 Convolutional encoder ... 2821
17.3.5.7 Data interleaving ... 2823
17.3.5.8 Subcarrier modulation mapping ... 2823
17.3.5.9 Pilot subcarriers ... 2826
17.3.5.10 OFDM modulation ... 2826
17.3.6 CCA ... 2828
17.3.7 PHY data modulation and modulation rate change ... 2828

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

17.3.8 PHY operating specifications (general) ... 2828
17.3.8.1 General ... 2828
17.3.8.2 Outline description ... 2829
17.3.8.3 Regulatory requirements ... 2830
17.3.8.4 Operating channel frequencies ... 2830
17.3.8.5 Transmit and receive in-band and out-of-band spurious emissions ... 2831
17.3.8.6 Slot time ... 2831
17.3.8.7 Transmit and receive impedance at the antenna connector ... 2831
17.3.9 PHY transmit specifications ... 2831
17.3.9.1 General ... 2831
17.3.9.2 Transmit power levels ... 2831
17.3.9.3 Transmit spectrum mask ... 2831
17.3.9.4 Transmission spurious ... 2833
17.3.9.5 Transmit center frequency tolerance ... 2833
17.3.9.6 Symbol clock frequency tolerance ... 2833
17.3.9.7 Modulation accuracy ... 2833
17.3.9.8 Transmit modulation accuracy test ... 2834
17.3.9.9 Time of Departure accuracy ... 2836
17.3.10 PHY receiver specifications ... 2836
17.3.10.1 Introduction ... 2836
17.3.10.2 Receiver minimum input sensitivity ... 2836
17.3.10.3 Adjacent channel rejection ... 2837
17.3.10.4 Nonadjacent channel rejection ... 2837
17.3.10.5 Receiver maximum input level ... 2838
17.3.10.6 CCA requirements ... 2838
17.3.10.7 Received channel power indicator (RCPI) measurement ... 2838
17.3.11 Transmit PHY ... 2839
17.3.12 Receive PHY ... 2842
17.4 OFDM PLME ... 2844
17.4.1 PLME SAP sublayer management primitives ... 2844
17.4.2 OFDM PHY MIB ... 2846
17.4.3 OFDM TXTIME calculation ... 2846
17.4.4 OFDM PHY ... 2847

18. Extended Rate PHY (ERP) specification ... 2848

18.1 Overview ... 2848
18.1.1 General ... 2848
18.1.2 Introduction ... 2848
18.1.3 Operational modes ... 2849
18.1.4 Scope of ERP PHY services ... 2849
18.1.5 ERP functions ... 2850
18.2 PHY-specific service parameter list ... 2850
18.3 Extended Rate PHY sublayer ... 2852
18.3.1 Introduction ... 2852
18.3.2 PPDU format ... 2852
18.3.2.1 General ... 2852
18.3.2.2 Long preamble PPDU format ... 2852
18.3.2.3 Short preamble PPDU format ... 2852
18.3.2.4 ERP-OFDM PPDU format ... 2853
18.3.3 PHY data modulation and rate change ... 2853
18.3.3.1 Long and short preamble formats ... 2853
18.3.3.2 ERP-OFDM format ... 2853
18.3.4 CCA ... 2853

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

18.3.5 PHY receive procedure 2854
18.4 ERP operating specifications (general) 2854
18.4.1 Introduction 2854
18.4.2 Regulatory requirements 2854
18.4.3 Operating channel frequencies 2854
18.4.4 Transmit and receive in-band and out-of-band spurious emissions 2854
18.4.5 SIFS 2855
18.4.6 CCA performance 2855
18.4.7 PHY transmit specifications 2855
18.4.7.1 General 2855
18.4.7.2 Transmit power levels 2855
18.4.7.3 Transmit spectral mask 2855
18.4.7.4 Transmit center frequency tolerance 2855
18.4.7.5 Symbol clock frequency tolerance 2855
18.4.7.6 Time of Departure accuracy 2856
18.4.8 PHY receive specifications 2856
18.4.8.1 General 2856
18.4.8.2 Receiver minimum input level sensitivity 2856
18.4.8.3 Adjacent channel rejection 2856
18.4.8.4 Receive maximum input level capability 2856
18.5 ERP PLME 2856
18.5.1 PLME SAP 2856
18.5.2 MIB 2856
18.5.3 TXTIME 2858
18.5.3.1 General 2858
18.5.3.2 ERP-OFDM TXTIME calculations 2858
18.5.4 ERP 2859

19. High-throughput (HT) PHY specification 2860

19.1 Introduction 2860
19.1.1 Introduction to the HT PHY 2860
19.1.2 Scope of HT PHY services 2861
19.1.3 HT PHY functions 2861
19.1.3.1 General 2861
19.1.3.2 PHY management entity (PLME) 2861
19.1.3.3 Service specification method 2861
19.1.4 PPDU formats 2861
19.2 HT PHY service interface 2862
19.2.1 Introduction 2862
19.2.2 TXVECTOR and RXVECTOR parameters 2862
19.2.3 PHYCONFIG_VECTOR parameters 2869
19.2.4 Effect of CH_BANDWIDTH, CH_OFFSET, and MCS parameters on PPDU format 2869
19.2.5 Support for NON_HT formats 2870
19.2.6 TXSTATUS parameters 2872
19.3 HT PHY 2872
19.3.1 Introduction 2872
19.3.2 PPDU format 2873
19.3.3 Transmitter block diagram 2875
19.3.4 Overview of the PPDU encoding process 2877
19.3.5 Modulation and coding scheme (MCS) 2879
19.3.6 Timing-related parameters 2880
19.3.7 Mathematical description of signals 2882

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

19.3.8 Transmission in the upper/lower 20 MHz of a 40 MHz channel 2885
19.3.9 HT preamble 2885
19.3.9.1 Introduction 2885
19.3.9.2 HT-mixed format preamble 2886
19.3.9.3 Non-HT portion of the HT-mixed format preamble 2886
19.3.9.4 HT portion of HT-mixed format preamble 2889
19.3.9.5 HT-greenfield format preamble 2899
19.3.10 Transmission of NON_HT format PPDUs with more than one transmit chain .. 2901
19.3.11 Data field 2901
19.3.11.1 General 2901
19.3.11.2 SERVICE field 2902
19.3.11.3 Scrambler 2902
19.3.11.4 Coding 2902
19.3.11.5 Encoder parsing operation for two BCC FEC encoders 2902
19.3.11.6 BCC coding and puncturing 2903
19.3.11.7 LDPC codes 2903
19.3.11.8 Data interleaver 2907
19.3.11.9 Constellation mapping 2910
19.3.11.10 Pilot subcarriers 2911
19.3.11.11 OFDM modulation 2913
19.3.11.12 Non-HT duplicate transmission 2918
19.3.12 Beamforming 2918
19.3.12.1 General 2918
19.3.12.2 Implicit feedback beamforming 2919
19.3.12.3 Explicit feedback beamforming 2922
19.3.13 HT Preamble format for sounding PPDUs 2926
19.3.13.1 General 2926
19.3.13.2 Sounding with a NDP 2927
19.3.13.3 Sounding PPDU for calibration 2927
19.3.13.4 Sounding PPDU for channel quality assessment 2927
19.3.14 Regulatory requirements 2928
19.3.15 Channel numbering and channelization 2929
19.3.15.1 General 2929
19.3.15.2 Channel allocation in the 2.4 GHz band 2929
19.3.15.3 Channel allocation in the 5 GHz band 2929
19.3.15.4 40 MHz channelization 2929
19.3.16 Slot time 2930
19.3.17 Transmit and receive impedance at the antenna connector 2930
19.3.18 PHY transmit specification 2930
19.3.18.1 Transmit spectrum mask 2930
19.3.18.2 Spectral flatness 2932
19.3.18.3 Transmit power 2933
19.3.18.4 Transmit center frequency tolerance 2933
19.3.18.5 Packet alignment 2933
19.3.18.6 Symbol clock frequency tolerance 2933
19.3.18.7 Modulation accuracy 2933
19.3.18.8 Time of Departure accuracy 2935
19.3.19 HT PHY receiver specification 2936
19.3.19.1 Receiver minimum input sensitivity 2936
19.3.19.2 Adjacent channel rejection 2936
19.3.19.3 Nonadjacent channel rejection 2937
19.3.19.4 Receiver maximum input level 2937
19.3.19.5 CCA sensitivity 2937
19.3.19.6 Received channel power indicator (RCPI) measurement 2939

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

19.3.19.7 Reduced interframe space (RIFS) 2939
19.3.20 PHY transmit procedure 2939
19.3.21 PHY receive procedure 2942
19.4 HT PLME 2946
19.4.1 PLME SAP sublayer management primitives 2946
19.4.2 PHY MIB 2951
19.4.3 TXTIME calculation 2951
19.4.4 HT PHY 2952
19.5 Parameters for HT-MCSs 2953

20. Directional multi-gigabit (DMG) PHY specification 2962

20.1 DMG PHY introduction 2962
20.1.1 Scope of DMG PHY services 2962
20.1.2 DMG PHY functions 2962
20.1.2.1 PHY management entity (PLME) 2962
20.1.2.2 Service specification method 2962
20.2 DMG PHY service interface 2962
20.2.1 Introduction 2962
20.2.2 TXVECTOR and RXVECTOR parameters 2963
20.2.3 PHYCONFIG_VECTOR parameters 2965
20.2.4 TXSTATUS parameters 2965
20.3 Common parameters 2965
20.3.1 Channelization 2965
20.3.2 Transmit mask 2966
20.3.3 Common requirements 2966
20.3.3.1 Introduction 2966
20.3.3.2 Center frequency tolerance 2966
20.3.3.3 Symbol clock tolerance 2967
20.3.3.4 Transmit center frequency leakage 2967
20.3.3.5 Transmit rampup and rampdown 2967
20.3.3.6 Antenna setting 2967
20.3.3.7 Maximum input requirement 2967
20.3.3.8 Receive minimum input sensitivity 2967
20.3.4 Timing-related parameters 2969
20.3.5 Mathematical conventions in the signal description 2969
20.3.5.1 General 2969
20.3.6 Common preamble 2970
20.3.6.1 General 2970
20.3.6.2 Short Training field 2971
20.3.6.3 Channel Estimation field 2971
20.3.7 HCS calculation for headers of DMG control mode and DMG SC mode 2972
20.3.8 Common LDPC parity matrices 2972
20.3.8.1 General 2972
20.3.8.2 Rate 1/2 LDPC code matrix H = 336 rows x 672 columns, Z = 42 .. 2973
20.3.8.3 Rate 5/8 LDPC code matrix H = 252 rows x 672 columns, Z = 42 .. 2973
20.3.8.4 Rate 3/4 LDPC code matrix H = 168 rows x 672 columns, Z = 42 .. 2973
20.3.8.5 Rate 13/16 LDPC code matrix H = 126 rows x 672 columns, Z = 42 2974
20.3.9 Scrambler 2974
20.3.10 Received channel power indicator (RCPI) measurement 2974
20.4 DMG control mode 2975
20.4.1 Introduction 2975
20.4.2 PPDU format 2975

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

20.4.3 Transmission 2975
20.4.3.1 Preamble 2975
20.4.3.2 Header 2976
20.4.3.3 Data field 2977
20.4.4 Performance requirements 2978
20.4.4.1 Transmit requirements 2978
20.4.4.2 Receive requirements 2979
20.5 DMG SC mode 2979
20.5.1 Introduction 2979
20.5.2 PPDU format 2979
20.5.3 Transmission 2980
20.5.3.1 Header 2980
20.5.3.2 Data field 2985
20.5.4 Performance requirements 2992
20.5.4.1 Transmit requirements 2992
20.5.4.2 Receive requirements 2993
20.6 DMG low-power SC mode 2994
20.6.1 Introduction 2994
20.6.2 Transmission 2994
20.6.2.1 Preamble 2994
20.6.2.2 Header 2994
20.6.2.3 Data field 2994
20.7 PHY transmit procedure 2997
20.8 PHY receive procedure 3000
20.9 Beamforming 3001
20.9.1 Beamforming concept 3001
20.9.2 Beamforming frame format 3001
20.9.2.1 Sector-level sweep 3001
20.9.2.2 Beam refinement 3001
20.10 Golay sequences 3005
20.11 DMG PLME 3007
20.11.1 PLME SAP sublayer management primitives 3007
20.11.2 DMG PHY MIB 3007
20.11.3 TXTIME calculation 3007
20.11.4 DMG PHY 3008

21. Very high throughput (VHT) PHY specification 3010

21.1 Introduction 3010
21.1.1 Introduction to the VHT PHY 3010
21.1.2 Scope of VHT PHY services 3011
21.1.3 VHT PHY functions 3011
21.1.3.1 General 3011
21.1.3.2 PHY management entity (PLME) 3011
21.1.3.3 Service specification method 3011
21.1.4 PPDU formats 3011
21.2 VHT PHY service interface 3012
21.2.1 Introduction 3012
21.2.2 TXVECTOR and RXVECTOR parameters 3012
21.2.3 PHYCONFIG_VECTOR parameters 3020
21.2.4 Effects of CH_BANDWIDTH parameter on PPDU format 3021
21.2.5 Support for NON_HT and HT formats 3023
21.2.5.1 General 3023

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

21.2.5.2 Support for NON_HT format when NON_HT_MODULATION is OFDM ... 3025
21.2.5.3 Support for HT formats ... 3026
21.2.6 TXSTATUS parameters ... 3027
21.3 VHT PHY ... 3027
21.3.1 Introduction ... 3027
21.3.2 VHT PPDU format ... 3027
21.3.3 Transmitter block diagram ... 3028
21.3.4 Overview of the PPDU encoding process ... 3036
21.3.4.1 General ... 3036
21.3.4.2 Construction of L-STF ... 3036
21.3.4.3 Construction of the L-LTF ... 3037
21.3.4.4 Construction of L-SIG ... 3037
21.3.4.5 Construction of VHT-SIG-A ... 3038
21.3.4.6 Construction of VHT-STF ... 3038
21.3.4.7 Construction of VHT-LTF ... 3038
21.3.4.8 Construction of VHT-SIG-B ... 3039
21.3.4.9 Construction of the Data field in a VHT SU PPDU ... 3040
21.3.4.10 Construction of the Data field in a VHT MU PPDU ... 3041
21.3.5 VHT modulation and coding scheme (VHT-MCS) ... 3042
21.3.6 Timing-related parameters ... 3042
21.3.7 Mathematical description of signals ... 3045
21.3.7.1 Notation ... 3045
21.3.7.2 Subcarrier indices in use ... 3046
21.3.7.3 Channel frequencies ... 3046
21.3.7.4 Transmitted signal ... 3048
21.3.7.5 Definition of tone rotation ... 3052
21.3.8 VHT preamble ... 3052
21.3.8.1 Introduction ... 3052
21.3.8.2 Non-VHT portion of VHT format preamble ... 3053
21.3.8.3 VHT portion of VHT format preamble ... 3056
21.3.9 Transmission of NON_HT and HT PPDUs with multiple transmit chains ... 3069
21.3.9.1 Transmission of 20 MHz NON_HT PPDUs with more than one transmit chain ... 3069
21.3.9.2 Transmission of HT PPDUs with more than four transmit chains ... 3069
21.3.10 Data field ... 3069
21.3.10.1 General ... 3069
21.3.10.2 SERVICE field ... 3070
21.3.10.3 CRC calculation for VHT-SIG-B ... 3071
21.3.10.4 Scrambler ... 3071
21.3.10.5 Coding ... 3072
21.3.10.6 Stream parser ... 3074
21.3.10.7 Segment parser ... 3076
21.3.10.8 BCC interleaver ... 3077
21.3.10.9 Constellation mapping ... 3079
21.3.10.10 Pilot subcarriers ... 3087
21.3.10.11 OFDM modulation ... 3088
21.3.10.12 Non-HT duplicate transmission ... 3090
21.3.11 SU-MIMO and DL-MU-MIMO Beamforming ... 3091
21.3.11.1 General ... 3091
21.3.11.2 Beamforming Feedback Matrix V ... 3091
21.3.11.3 Maximum Number of Total Spatial Streams in VHT MU PPDUs ... 3092
21.3.11.4 Group ID ... 3092
21.3.12 VHT preamble format for sounding PPDUs ... 3093

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

21.3.13 Regulatory requirements ... 3093
21.3.14 Channelization ... 3093
21.3.15 Slot time ... 3095
21.3.16 Transmit and receive port impedance ... 3095
21.3.17 VHT transmit specification ... 3095
21.3.17.1 Transmit spectrum mask ... 3095
21.3.17.2 Spectral flatness ... 3098
21.3.17.3 Transmit center frequency and symbol clock frequency tolerance ... 3100
21.3.17.4 Modulation accuracy ... 3100
21.3.17.5 Time of Departure accuracy ... 3102
21.3.18 VHT receiver specification ... 3103
21.3.18.1 Receiver minimum input sensitivity ... 3103
21.3.18.2 Adjacent channel rejection ... 3103
21.3.18.3 Nonadjacent channel rejection ... 3104
21.3.18.4 Receiver maximum input level ... 3105
21.3.18.5 CCA sensitivity ... 3105
21.3.18.6 RSSI ... 3107
21.3.19 PHY transmit procedure ... 3107
21.3.20 PHY receive procedure ... 3110
21.4 VHT PLME ... 3114
21.4.1 PLME SAP sublayer management primitives ... 3114
21.4.2 PHY MIB ... 3117
21.4.3 TXTIME and PSDU_LENGTH calculation ... 3117
21.4.4 VHT PHY ... 3119
21.5 Parameters for VHT-MCSs ... 3120

22. Television very high throughput (TVHT) PHY specification ... 3137

22.1 Introduction ... 3137
22.1.1 Introduction to the TVHT PHY ... 3137
22.1.2 Scope of TVHT PHY services ... 3138
22.1.3 TVHT PHY functions ... 3138
22.1.3.1 General ... 3138
22.1.3.2 PHY management entity (PLME) ... 3138
22.1.3.3 Service specification method ... 3138
22.1.4 PPDU formats ... 3139
22.2 TVHT PHY service interface ... 3139
22.2.1 Introduction ... 3139
22.2.2 TXVECTOR and RXVECTOR parameters ... 3139
22.2.3 Effects of CH_BANDWIDTH parameter on PPDU format ... 3146
22.2.4 Support for NON_HT and HT formats ... 3147
22.3 TVHT PHY sublayer ... 3150
22.3.1 Introduction ... 3150
22.3.2 VHT PPDU format in TVWS bands ... 3150
22.3.3 Transmitter block diagram ... 3151
22.3.4 Overview of the PPDU encoding process ... 3152
22.3.4.1 General ... 3152
22.3.4.2 Construction of L-STF ... 3152
22.3.4.3 Construction of the L-LTF ... 3152
22.3.4.4 Construction of L-SIG ... 3153
22.3.4.5 Construction of TVHT-SIG-A ... 3153
22.3.4.6 Construction of TVHT-STF ... 3154
22.3.4.7 Construction of TVHT-LTF ... 3154
22.3.4.8 Construction of TVHT-SIG-B ... 3154

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

22.3.4.9 Construction of the Data field in an SU PPDU 3155
22.3.4.10 Construction of the Data field in an MU PPDU 3155
22.3.5 Modulation and coding scheme (MCS) 3156
22.3.6 Timing-related parameters 3156
22.3.7 Mathematical description of signals 3157
22.3.8 TVHT preamble 3161
22.3.8.1 Introduction 3161
22.3.8.2 Non-TVHT portion of TVHT format preamble 3161
22.3.8.3 TVHT portion of TVHT format preamble 3162
22.3.9 Transmission of NON_HT and HT PPDUs with multiple antennas 3164
22.3.10 Data field 3164
22.3.10.1 General 3164
22.3.10.2 SERVICE field 3164
22.3.10.3 CRC calculation for TVHT-SIG-B 3164
22.3.10.4 Scrambler 3164
22.3.10.5 Coding 3164
22.3.10.6 Stream parser 3164
22.3.10.7 Segment parser 3165
22.3.10.8 BCC interleaver 3165
22.3.10.9 Constellation mapping 3165
22.3.10.10 Pilot subcarriers 3166
22.3.10.11 OFDM modulation transmission in VHT format 3166
22.3.10.12 Non-HT duplicate transmission 3167
22.3.11 SU-MIMO and MU-MIMO Beamforming 3167
22.3.11.1 General 3167
22.3.11.2 Beamforming Feedback Matrix V 3167
22.3.11.3 Group ID 3167
22.3.12 TVHT preamble format for sounding PPDUs 3167
22.3.13 Regulatory requirements 3168
22.3.14 Channelization 3168
22.3.15 Slot time 3170
22.3.16 Transmit and receive port impedance 3170
22.3.17 TVHT transmit specification 3170
22.3.17.1 Transmit spectrum mask 3170
22.3.17.2 Spectral flatness 3171
22.3.17.3 Transmit center frequency and symbol clock frequency tolerance 3172
22.3.17.4 Modulation accuracy 3173
22.3.17.5 Time of Departure accuracy 3173
22.3.18 TVHT receiver specification 3173
22.3.18.1 General 3173
22.3.18.2 Receiver minimum input sensitivity 3174
22.3.18.3 Adjacent channel rejection 3174
22.3.18.4 Nonadjacent channel rejection 3175
22.3.18.5 Receiver maximum input level 3175
22.3.18.6 CCA sensitivity 3176
22.3.18.7 RSSI 3177
22.3.19 PHY transmit procedure 3177
22.3.20 PHY receive procedure 3177
22.4 TVHT PLME 3178
22.4.1 PLME SAP sublayer management primitives 3178
22.4.2 PHY MIB 3178
22.4.3 TXTIME and PSDU_LENGTH calculation 3178
22.4.4 TVHT PHY 3178
22.5 Parameters for TVHT-MCSs 3179

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

23. Sub 1 GHz (S1G) PHY specification 3186

23.1 Introduction 3186
23.1.1 Introduction to the S1G PHY 3186
23.1.2 Scope of S1G PHY services 3187
23.1.3 S1G PHY features 3187
23.1.3.1 General 3187
23.1.3.2 PHY management entity (PLME) 3187
23.1.3.3 Service specification method 3187
23.1.4 PPDU formats 3188
23.2 S1G PHY service interface 3188
23.2.1 Introduction 3188
23.2.2 TXVECTOR and RXVECTOR parameters 3189
23.2.3 Effect of CH_BANDWIDTH parameter on PPDU format 3197
23.3 S1G PHY sublayer 3198
23.3.1 Introduction 3198
23.3.2 S1G PPDU format 3198
23.3.3 Transmitter block diagram 3200
23.3.4 Overview of the PPDU encoding process 3201
23.3.4.1 General 3201
23.3.4.2 Construction of the Preamble part in an S1G_LONG PPDU 3201
23.3.4.3 Construction of the Preamble part in an S1G_SHORT PPDU 3204
23.3.4.4 Construction of the Preamble part in an S1G_1M PPDU 3206
23.3.4.5 Construction of Preambles for S1G_DUP_2M and S1G_DUP_1M 3208
23.3.4.6 Construction of Data field in S1G SU PPDUs for all cases except 1 MHz MCS 10 3208
23.3.4.7 Construction of the Data field in an S1G SU PPDU (1 MHz MCS 10 mode) 3210
23.3.4.8 Construction of the Data field in an S1G MU PPDU 3211
23.3.5 Modulation and coding scheme 3212
23.3.6 Timing-related parameters 3212
23.3.7 Mathematical description of signals 3216
23.3.8 S1G preamble 3222
23.3.8.1 Introduction 3222
23.3.8.2 Formats for greater than or equal to 2 MHz 3222
23.3.8.3 Format for 1 MHz 3244
23.3.9 Data field 3249
23.3.9.1 General 3249
23.3.9.2 SERVICE field 3249
23.3.9.3 Scrambler 3249
23.3.9.4 Coding 3250
23.3.9.5 Repetition for 1 MHz MCS 10 3252
23.3.9.6 Stream parser 3252
23.3.9.7 Segment parser 3252
23.3.9.8 BCC interleaver 3253
23.3.9.9 Constellation mapping 3253
23.3.9.10 Pilot subcarriers 3254
23.3.9.11 OFDM modulation 3259
23.3.9.12 S1G 1 MHz and 2 MHz duplicate transmission 3261
23.3.10 SU-MIMO and DL-MU-MIMO Beamforming 3263
23.3.10.1 General 3263
23.3.10.2 Beamforming Feedback Matrix V 3263
23.3.10.3 Maximum Number of Total Spatial Streams in S1G MU PPDUs 3264

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

23.3.10.4 Group ID ... 3264
23.3.11 S1G preamble format for NDPs ... 3264
23.3.12 NDP CMAC PPDUs ... 3266
23.3.12.1 General ... 3266
23.3.12.2 NDP CMAC PPDU details ... 3267
23.3.13 Regulatory requirements ... 3278
23.3.14 Channelization ... 3278
23.3.15 Slot time ... 3279
23.3.16 Transmit and receive port impedance ... 3279
23.3.17 S1G transmit specification ... 3279
23.3.17.1 Transmit spectrum mask ... 3279
23.3.17.2 Spectral flatness ... 3282
23.3.17.3 Transmit center frequency and symbol clock frequency tolerance ... 3284
23.3.17.4 Modulation accuracy ... 3284
23.3.17.5 Time of Departure accuracy ... 3286
23.3.18 S1G receiver specification ... 3287
23.3.18.1 Receiver minimum input sensitivity ... 3287
23.3.18.2 Adjacent channel rejection ... 3287
23.3.18.3 Nonadjacent channel rejection ... 3288
23.3.18.4 Receiver maximum input level ... 3288
23.3.18.5 CCA sensitivity ... 3289
23.3.18.6 RSSI ... 3294
23.3.19 PHY transmit procedure ... 3295
23.3.20 PHY receive procedure ... 3299
23.4 S1G PMLE ... 3306
23.4.1 PLME_SAP sublayer management primitives ... 3306
23.4.2 PHY MIB ... 3308
23.4.3 TXTIME and PSDU_LENGTH calculation ... 3308
23.4.4 PHY characteristics ... 3311
23.5 Parameters for S1G-MCSs ... 3311

24. China directional multi-gigabit (CDMG) PHY specification ... 3319

24.1 CDMG PHY introduction ... 3319
24.1.1 Scope ... 3319
24.1.2 CDMG PHY functions ... 3319
24.1.2.1 General ... 3319
24.1.2.2 PHY management entity ... 3319
24.1.2.3 Service specification method ... 3319
24.2 CDMG PHY service interface ... 3319
24.2.1 Introduction ... 3319
24.2.2 TXVECTOR and RXVECTOR parameters ... 3320
24.2.3 TXSTATUS parameters ... 3322
24.3 Common parameters ... 3322
24.3.1 Channelization ... 3322
24.3.2 Transmit mask ... 3322
24.3.3 Common requirements ... 3323
24.3.3.1 Introduction ... 3323
24.3.3.2 Center frequency tolerance ... 3323
24.3.3.3 Symbol clock tolerance ... 3323
24.3.3.4 Transmit center frequency leakage ... 3323
24.3.3.5 Transmit rampup and rampdown ... 3323
24.3.3.6 Antenna setting ... 3324
24.3.3.7 Maximum input requirement ... 3324

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

24.3.3.8 Receiver minimum input sensitivity 3324
24.3.4 Timing-related parameters 3325
24.3.5 Mathematical conventions in the signal description 3326
24.3.6 Common preamble 3326
24.3.6.1 General 3326
24.3.6.2 Short training field 3326
24.3.6.3 Channel estimation field 3326
24.3.7 HCS calculation for headers of CDMG control mode and CDMG SC mode 3327
24.3.8 Common LDPC parity matrices 3327
24.3.9 Scrambler 3327
24.3.10 Received channel power indicator (RCPI) measurement 3327
24.4 CDMG control mode 3328
24.4.1 Introduction 3328
24.4.2 PPDU format 3328
24.4.3 Transmission 3328
24.4.3.1 Preamble 3328
24.4.3.2 Header 3329
24.4.3.3 Data field 3330
24.4.4 Performance requirements 3330
24.4.4.1 Transmit requirements 3330
24.4.4.2 Receive requirements 3330
24.5 CDMG SC mode 3331
24.5.1 Introduction 3331
24.5.2 PPDU format 3331
24.5.3 Transmission 3331
24.5.3.1 Header 3331
24.5.3.2 The Data field 3334
24.5.4 Performance requirements 3336
24.5.4.1 Transmit requirements 3336
24.5.4.2 Receive requirements 3337
24.6 CDMG low-power SC mode 3338
24.6.1 Introduction 3338
24.6.2 Transmission 3338
24.6.2.1 Preamble 3338
24.6.2.2 Header 3338
24.6.2.3 Data field 3338
24.7 PHY transmit procedure 3339
24.8 PHY receive procedure 3341
24.9 Beamforming 3341
24.9.1 Beamforming concept 3341
24.9.2 Beamforming frame format 3341
24.9.2.1 Sector-level sweep 3341
24.9.2.2 Beam refinement 3341
24.10 CDMG PLME 3343
24.10.1 PLME SAP sublayer management primitives 3343
24.10.2 CDMG PHY MIB 3343
24.10.3 TXTIME calculation 3344
24.10.4 PHY characteristics 3344

25. China millimeter-wave multi-gigabit (CMMG) PHY specification 3345

25.1 Introduction 3345
25.1.1 Introduction to CMMG PHY 3345
25.1.2 Scope of CMMG PHY services 3345

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

25.1.3 CMMG PHY functions ... 3346
25.1.3.1 General ... 3346
25.1.3.2 PHY management entity (PLME) ... 3346
25.1.3.3 Service specification method ... 3346
25.1.3.4 PPDU formats ... 3346
25.2 CMMG PHY service interface ... 3346
25.2.1 Introduction ... 3346
25.2.2 TXVECTOR and RXVECTOR parameters ... 3347
25.3 Common parameters ... 3350
25.3.1 Introduction ... 3350
25.3.2 Common requirements ... 3350
25.3.2.1 Introduction ... 3350
25.3.2.2 Transmit RF delay ... 3350
25.3.2.3 Center frequency tolerance ... 3350
25.3.3 Time-related parameters ... 3352
25.3.4 Mathematical conventions in the signal description ... 3354
25.3.4.1 Notation ... 3354
25.3.4.2 Subcarrier indices in use ... 3354
25.3.4.3 Transmitted signal ... 3354
25.3.4.4 Definition of tone rotation for OFDM mode transmission ... 3356
25.3.4.5 The windowing function ... 3357
25.3.5 CMMG PHY preamble ... 3357
25.3.5.1 General ... 3357
25.3.5.2 CMMG Short Training field ... 3357
25.3.5.3 CMMG Channel Estimation field ... 3358
25.3.6 CRC calculation ... 3360
25.3.7 Scrambler ... 3361
25.3.8 Common LDPC parity matrices ... 3362
25.3.8.1 Introduction ... 3362
25.3.8.2 General ... 3362
25.3.9 CMMG SIG ... 3364
25.3.9.1 General ... 3364
25.3.9.2 Encoding of SIG ... 3367
25.3.10 CMMG duplication transmission on a 1080 MHz channel ... 3367
25.3.11 hFilt definition ... 3368
25.3.12 Encoding of Data field ... 3368
25.3.13 Received channel power indicator (RCPI) measurement ... 3369
25.4 CMMG control mode ... 3370
25.4.1 Introduction ... 3370
25.4.2 PPDU format ... 3370
25.4.3 CMMG preamble transmission ... 3370
25.4.4 CMMG control mode SIG transmission ... 3370
25.4.4.1 General ... 3370
25.4.4.2 Generation of CRC bits ... 3370
25.4.4.3 Scrambler ... 3370
25.4.4.4 Encoding ... 3370
25.4.4.5 Modulation ... 3371
25.4.4.6 Spreading ... 3371
25.4.5 CMMG control mode Data field ... 3371
25.4.5.1 General ... 3371
25.4.5.2 Scrambler ... 3372
25.4.5.3 Encoding ... 3372
25.4.5.4 Modulation ... 3372
25.4.5.5 Spreading ... 3372

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

25.4.6 CMMG control mode performance requirements ... 3372
25.4.6.1 Transmit requirements ... 3372
25.4.6.2 Receive requirements ... 3373
25.5 CMMG SC mode ... 3373
25.5.1 Introduction ... 3373
25.5.2 Transmitter block diagram ... 3373
25.5.3 Overview of the PPDU encoding process ... 3374
25.5.3.1 General ... 3374
25.5.3.2 Construction of CMMG SC mode SIG ... 3374
25.5.3.3 Construction of CMMG SC mode PPDUs ... 3375
25.5.4 CMMG SC mode PPDU format ... 3375
25.5.5 CMMG SC mode SIG transmission ... 3375
25.5.5.1 SIG field ... 3375
25.5.5.2 Generation of the CRC bits of SIG ... 3375
25.5.5.3 Scrambler ... 3375
25.5.5.4 Encoding and modulations ... 3376
25.5.6 Data field transmission ... 3376
25.5.6.1 General ... 3376
25.5.6.2 Scrambler ... 3376
25.5.6.3 Encoding ... 3377
25.5.6.4 Symbol block padding zeros ... 3377
25.5.6.5 Stream parser ... 3378
25.5.6.6 Constellation mapping ... 3378
25.5.6.7 Spatial expansion ... 3380
25.5.6.8 Duplication transmission ... 3382
25.5.7 Performance requirements ... 3382
25.5.7.1 Transmit requirements ... 3382
25.5.7.2 Receive requirements ... 3384
25.6 CMMG OFDM mode ... 3384
25.6.1 Introduction ... 3384
25.6.2 CMMG OFDM mode PPDU format ... 3384
25.6.3 Transmission block diagram ... 3385
25.6.4 Overview of CMMG OFDM mode PPDU encoding process ... 3386
25.6.4.1 General ... 3386
25.6.4.2 Construction of CMMG OFDM mode SIG ... 3386
25.6.4.3 Construction of CMMG OFDM mode PPDU ... 3386
25.6.4.4 Construction of OSTF ... 3387
25.6.4.5 Construction of OCEF ... 3387
25.6.5 CMMG OFDM mode SIG fields ... 3387
25.6.5.1 SIG fields ... 3387
25.6.5.2 Modulation ... 3387
25.6.5.3 Duplication ... 3388
25.6.5.4 Symbol blocking, CSD, and GI insertion ... 3388
25.6.5.5 Symbol rate change ... 3388
25.6.6 OSTF definition ... 3388
25.6.7 OCEF definition ... 3389
25.6.8 Data fields ... 3391
25.6.8.1 General ... 3391
25.6.8.2 Scrambler ... 3391
25.6.8.3 Encoding ... 3392
25.6.8.4 OFDM symbol padding zeros ... 3392
25.6.8.5 Stream parser ... 3392
25.6.8.6 Subcarrier modulation mapping ... 3393
25.6.8.7 Tone mapping ... 3396

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

25.6.8.8 Space-time block coding ... 3396
25.6.8.9 Pilot subcarriers ... 3397
25.6.8.10 Cyclic shift diversity (CSD) for OFDM mode data fields transmission ... 3398
25.6.8.11 OFDM modulation ... 3398
25.6.8.12 Duplication transmission ... 3400
25.6.8.13 Beamforming ... 3400
25.6.8.14 CMMG preamble format for sounding PPDU ... 3401
25.6.9 Performance requirements ... 3402
25.6.9.1 Transmit requirements ... 3402
25.6.9.2 TX flatness ... 3404
25.6.9.3 Receive requirements ... 3404
25.7 Analog beamforming PHY frame format ... 3404
25.7.1 TX sector sweep ... 3404
25.7.2 Beam refinement ... 3405
25.7.2.1 General ... 3405
25.7.2.2 BRP PPDU structure ... 3405
25.7.2.3 BRP PPDU SIG fields ... 3405
25.7.2.4 Beam refinement AGC field ... 3405
25.7.2.5 Beam refinement TRN-R subfield ... 3406
25.7.2.6 Beam refinement TRN-T subfield ... 3406
25.7.2.7 Channel measurement ... 3406
25.7.2.8 BRP resampling in an OFDM mode packet ... 3407
25.8 ZCZ sequence ... 3407
25.9 Regulatory requirements ... 3411
25.10 Channelization ... 3412
25.11 Transmit spectrum mask ... 3413
25.12 PHY transmit procedure ... 3413
25.12.1 PHY transmit procedure for a CMMG SC mode transmission ... 3413
25.12.2 PHY transmit procedure for a CMMG OFDM mode transmission ... 3414
25.13 Receive procedure ... 3416
25.14 CMMG PLME ... 3419
25.14.1 PLME SAP sublayer management primitive ... 3419
25.14.2 PHY MIB ... 3419
25.14.3 TXTIME calculation ... 3420
25.14.4 PHY characteristics ... 3421
25.15 Parameters for CMMG-MCSs ... 3421
25.15.1 General ... 3421
25.15.2 Parameters for CMMG-MCSs with SC mode transmission ... 3422
25.15.3 Parameters for CMMG-MCSs with OFDM mode transmission ... 3425

Annex A (informative) Bibliography ... 3429

Annex B (normative) Protocol Implementation Conformance Statement (PICS) proforma ... 3433
B.1 Introduction ... 3433
B.2 Abbreviations and special symbols ... 3433
B.2.1 Symbols for Status column ... 3433
B.2.2 General abbreviations for Item and Support columns ... 3433
B.3 Instructions for completing the PICS proforma ... 3434
B.3.1 General structure of the PICS proforma ... 3434
B.3.2 Additional information ... 3435
B.3.3 Exception information ... 3435
B.3.4 Conditional status ... 3435
B.4 PICS proforma—IEEE Std 802.11-2020 ... 3437

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

B.4.1 Implementation identification ... 3437
B.4.2 Protocol summary ... 3437
B.4.3 IUT configuration ... 3438
B.4.4 MAC protocol ... 3440
B.4.5 Direct sequence PHY functions ... 3459
B.4.6 OFDM PHY functions ... 3462
B.4.7 High rate, direct sequence PHY functions ... 3473
B.4.8 Regulatory domain extensions ... 3477
B.4.9 ERP functions ... 3478
B.4.10 Spectrum management extensions ... 3481
B.4.11 Operating classes extensions ... 3484
B.4.12 QoS base functionality ... 3484
B.4.13 QoS enhanced distributed channel access (EDCA) ... 3485
B.4.14 QoS hybrid coordination function (HCF) controlled channel access (HCCA) 3486
B.4.15 Radio management extensions ... 3487
B.4.16 DSE functions ... 3492
B.4.17 High-throughput (HT) features ... 3495
B.4.18 Tunneled direct-link setup extensions ... 3504
B.4.19 WNM extensions ... 3505
B.4.20 Interworking (IW) with external networks extensions ... 3509
B.4.21 Mesh protocol capabilities ... 3511
B.4.22 QMF extensions ... 3514
B.4.23 RobustAVT extensions ... 3515
B.4.24 DMG features ... 3516
B.4.25 Very high throughput (VHT) features ... 3524
B.4.26 TVWS functions ... 3531
B.4.27 FILS features ... 3537
B.4.28 Sub 1 GHz (S1G) features ... 3538
B.4.30 CDMG features ... 3550
B.4.29 S1G relay features ... 3550
B.4.31 CMMG features ... 3552
B.4.32 Preassociation discovery extensions ... 3553

Annex C (normative) ASN.1 encoding of the MAC and PHY MIB ... 3554
C.1 General ... 3554
C.2 Guidelines for IEEE 802.11 MIB authors/editors ... 3554
C.3 MIB detail ... 3554

Annex D (normative) Regulatory references ... 4103
D.1 External regulatory references ... 4103
D.2 Radio performance specifications ... 4105
D.2.1 Transmit and receive in-band and out-of-band spurious emissions ... 4105
D.2.2 Transmit power levels ... 4105
D.2.3 Transmit spectrum mask ... 4107
D.2.4 Transmit Mask M ... 4108
D.2.5 CCA-ED threshold ... 4109

Annex E (normative) Country elements and operating classes ... 4110
E.1 Country information and operating classes ... 4110
E.2 Band-specific operating requirements ... 4125
E.2.1 General ... 4125
E.2.2 3650–3700 MHz band in the United States ... 4125
E.2.3 5.9 GHz band in the United States (5.850–5.925 GHz) ... 4126
E.2.4 5.9 GHz band in Europe (5.855–5.925 GHz) ... 4126

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

E.2.5 TVWS band in the United States and Canada (54–698 MHz) 4126
E.2.6 TVWS band in Europe 4129

Annex F (normative) HT LDPC matrix definitions 4130

Annex G (normative) Frame exchange sequences 4133
G.1 General 4133
G.2 Basic sequences 4135
G.3 EDCA and HCCA sequences 4135
G.4 HT, VHT, and S1G sequences 4138

Annex H (normative) Usage of Ethertype 89-0d 4148

Annex I (informative) Examples of encoding a frame for OFDM PHYs and DMG PHYs 4149
I.1 Example 1—BCC encoding 4149
I.1.1 Introduction 4149
I.1.2 The message for the BCC example 4150
I.1.3 Generation of the preamble 4151
I.1.4 Generation of the SIGNAL field 4156
I.1.5 Generating the DATA bits for the BCC example 4160
I.1.6 Generating the first DATA symbol for the BCC example 4164
I.1.7 Generating the additional DATA symbols 4170
I.1.8 The entire packet for the BCC example 4170
I.2 Generating encoded DATA bits—LDPC example 1 4178
I.2.1 General 4178
I.2.2 The message for LDPC example 1 4178
I.2.3 Prepending the SERVICE field for LDPC example 1 4180
I.2.4 Scrambling LDPC example 1 4181
I.2.5 Inserting shortening bits for LDPC example 1 4182
I.2.6 Encoding data for LDPC example 1 4185
I.2.7 Removing shortening bits and puncturing for LDPC example 1 4187
I.3 Generating encoded DATA bits—LDPC example 2 4189
I.3.1 General 4189
I.3.2 The message for LDPC example 2 4190
I.3.3 Prepending the SERVICE field for LDPC example 2 4191
I.3.4 Scrambling LDPC example 2 4193
I.3.5 Inserting the shortening bits for LDPC example 2 4195
I.3.6 Encoding the data for LDPC example 2 4197
I.3.7 Removing shortening bits and repetition for LDPC example 2 4200
I.4 DMG example data vectors 4204
I.5 DMG Example 1—DMG control mode encoding 4205
I.5.1 DMG control mode preamble 4205
I.5.2 Control mode header 4205
I.5.3 DMG control mode payload 4208
I.6 DMG Example 2—DMG SC mode encoding 4209
I.6.1 DMG SC mode preamble 4209
I.6.2 DMG SC mode header 4209
I.6.3 DMG SC mode payload 4212
I.7 DMG Example 3—DMG low-power SC mode encoding 4217
I.7.1 DMG low-power SC mode preamble 4217
I.7.2 DMG low-power SC mode header 4217
I.7.3 DMG low-power SC mode MCS 26 payload 4217
I.7.4 DMG low-power SC mode MCS 30 payload 4219

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Annex J (informative) RSNA reference implementations and test vectors 4221
J.1 TKIP temporal key mixing function reference implementation and test vector 4221
J.1.1 TKIP temporal key mixing function reference implementation 4221
J.1.2 Test vectors 4232
J.2 Michael reference implementation and test vectors 4233
J.2.1 Michael test vectors 4233
J.2.2 Sample code for michael 4234
J.3 PRF reference implementation and test vectors 4241
J.3.1 PRF reference code 4241
J.3.2 PRF test vectors 4242
J.4 Suggested pass-phrase-to-PSK mapping 4242
J.4.1 Introduction 4242
J.4.2 Test vectors 4243
J.5 Suggestions for random number generation 4243
J.5.1 General 4243
J.5.2 Software sampling 4244
J.5.3 Hardware-assisted solution 4245
J.6 Additional test vectors 4246
J.6.1 Notation 4246
J.6.2 WEP cryptographic encapsulation 4246
J.6.3 TKIP test vector 4247
J.6.4 CCMP test vectors 4248
J.6.5 PRF test vectors 4252
J.7 Key hierarchy test vectors for pairwise keys 4254
J.7.1 General 4254
J.7.2 CCMP-128 pairwise key derivation 4254
J.7.3 TKIP pairwise key derivation 4254
J.8 Test vectors for AES-128-CMAC 4255
J.9 Management frame protection test vectors 4255
J.9.1 BIP with broadcast Deauthentication frame 4255
J.9.2 CCMP-128 with individually addressed Deauthentication frame 4257
J.10 SAE test vector 4258
J.11 GCMP 4262
J.11.1 GCMP test vectors 4262
J.11.2 Example of encryption C code 4264

Annex K (informative) TSPECs and Admission control 4278
K.1 Example use of TSPEC for admission control 4278
K.2 Recommendation for implementation of contention based admission control 4279
K.2.1 Use of ACM (admission control mandatory) subfield 4279
K.2.2 Deriving medium time 4279
K.3 Guidelines and reference design for sample scheduler and admission control unit 4282
K.3.1 Guidelines for deriving service schedule parameters 4282
K.3.2 Reference design for sample scheduler and admission control unit 4282
K.4 TSPEC construction 4285
K.4.1 General 4285
K.4.2 Surplus Bandwidth Allocation 4285
K.4.3 Minimum and Maximum Service Interval 4289
K.4.4 Minimum, Mean, and Peak Data Rate 4290

Annex L (informative) Examples and sample code for encoding a TIM Partial Virtual Bitmap 4292
L.1 Introduction 4292
L.2 Examples 4292
L.3 Sample C code 4300

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Annex M (informative) EPD and LPD headers and the integration function ... 4306
M.1 Introduction ... 4306
M.2 Integration function header conversions ... 4306
M.3 A-MSDU subframes ... 4306
M.4 Integration service versus bridging ... 4308

Annex N (informative) AP functional description ... 4309
N.1 Introduction ... 4309
N.2 Terminology ... 4309
N.3 Primary ACM_STA functions ... 4313
N.4 Primary AP functions ... 4313
N.5 Primary DS functions ... 4315
N.6 Primary portal function ... 4315

Annex O (informative) Additional HT, VHT, and S1G information ... 4316
O.1 HT, VHT, and S1G waveform generator tool ... 4316
O.2 A-MPDU deaggregation ... 4317
O.3 Example of an RD exchange sequence ... 4318
O.4 Illustration of determination of NDP addresses ... 4319
O.5 20/40 MHz BSS establishment and maintenance ... 4320
O.5.1 Signaling 20/40 MHz BSS capability and operation ... 4320
O.5.2 Establishing a 20/40 MHz BSS ... 4320
O.5.3 Monitoring channels for other BSS operation ... 4321

Annex P (informative) Location and Time Difference accuracy test ... 4323
P.1 Location via Time Difference of arrival ... 4323
P.2 Time Difference of departure accuracy test ... 4323
P.3 Differential Distance Computation using Fine Timing Measurement frames ... 4325

Annex Q (informative) Example use of the Destination URI for Event and Diagnostic Reports ... 4327
Q.1 Destination URI payload ... 4327
Q.2 Use of HTTP (or HTTPS) for Destination URI of Event and Diagnostic Reports ... 4327

Annex R (informative) Interworking with external networks ... 4328
R.1 General ... 4328
R.2 Network discovery and selection ... 4328
R.2.1 General ... 4328
R.2.2 Airport ... 4328
R.2.3 Shopping ... 4329
R.2.4 Sales meeting ... 4330
R.2.5 Museum ... 4330
R.2.6 Emergency call ... 4331
R.2.7 Emergency alert ... 4332
R.3 QoS mapping guidelines for interworking with external networks ... 4332
R.3.1 General ... 4332
R.3.2 Determination of the mapping for a STA ... 4333
R.3.3 QoS mapping and GLK ... 4334
R.4 Interworking and SSPN interface support ... 4335
R.4.1 General ... 4335
R.4.2 SSPN interface parameters ... 4335
R.5 Interworking with external networks and emergency call support ... 4339
R.5.1 General ... 4339
R.5.2 Background on emergency call support over IEEE 802.11 infrastructure ... 4340
R.5.3 System aspects for emergency call support ... 4340

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

R.5.4 Description of the Expedited Bandwidth Request element ... 4342
R.5.5 Access to emergency services in an RSN ... 4342
R.6 Peer information ... 4343
R.7 Calculating Estimated Throughput ... 4344

Annex S (informative) Mesh BSS operation ... 4347
S.1 Clarification of mesh Data frame format ... 4347
S.2 Operational considerations for interworking ... 4347
S.3 Power save parameters selection ... 4347
S.3.1 General ... 4347
S.3.2 Selecting the mesh power management mode based on traffic load ... 4348
S.3.3 Scanning of mesh BSSs ... 4348
S.3.4 Default parameters ... 4349
S.3.5 MSDU forwarding in an MBSS containing mesh STAs in light or deep sleep mode ... 4349
S.3.6 Synchronization maintenance of mesh STAs in deep sleep mode ... 4349
S.4 SIV key wrapping test vector ... 4350
S.5 Airtime link metric usage example ... 4351
S.6 Link metric report example ... 4351
S.7 Generation of proactive PREP elements in the proactive PREQ mechanism of HWMP ... 4352
S.7.1 General ... 4352
S.7.2 Additions to forwarding information ... 4352
S.7.3 Actions when sending Data frames as source mesh STA ... 4352
S.7.4 Actions on receipt of a proactive PREQ element ... 4353
S.7.5 Generation of proactive PREP elements ... 4353
S.8 Generation of PREQ elements in proactive RANN mechanism of HWMP ... 4353
S.8.1 General ... 4353
S.8.2 Additions to forwarding information ... 4353
S.8.3 Actions when sending Data frames as source mesh STA ... 4354
S.8.4 Actions on receipt of proactive RANN element ... 4354
S.8.5 Actions on receipt of a PREP element ... 4354

Annex T (informative) Overlapping BSS (OBSS) management ... 4355
T.1 Introduction ... 4355
T.2 QLoad Report element ... 4355
T.2.1 General ... 4355
T.2.2 Calculating medium time ... 4356
T.2.3 Calculation of potential traffic self ... 4356
T.2.4 Calculation of allocated traffic self ... 4358
T.2.5 Calculation of allocated traffic shared ... 4359
T.2.6 Calculation of EDCA Access Factor ... 4359
T.2.7 EDCA Overhead Factor ... 4360
T.2.8 Calculation of HCCA Access Factor ... 4360
T.3 Channel selection using QLoad report ... 4361
T.3.1 General ... 4361
T.3.2 AP with admission control mandatory ... 4361
T.3.3 AP with an HC ... 4361
T.3.4 Channel selection procedures ... 4362
T.4 Sharing in an OBSS situation ... 4363
T.4.1 General ... 4363
T.4.2 Sharing schemes ... 4364
T.5 Mitigating consequences of OBSS sharing in presence of noncollaborating devices ... 4366

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Annex U (informative) Functions of the centralized coordination service root (CCSR) 4367

Annex V (informative) TSPEC aggregation for DMG BSSs 4368

Annex W (informative) Informative procedures for CDMG STAs 4370
W.1 Selection of candidate SPs for spatial sharing 4370
W.2 N-phase beamforming codebook for CDMG STAs 4370
W.2.1 General 4370
W.2.2 1-D (one-dimensional) antenna array 4370
W.2.3 2-D (two-dimensional) antenna array 4372
W.3 Beam tracking and switching for enhanced beam tracking mechanism 4372

Annex X (informative) Link rate considerations 4374

Annex Y (informative) Preassociation discovery (PAD) additional information 4375
Y.1 Preassociation discovery usage models 4375
Y.2 Background search 4375
Y.3 Immediate search 4376

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Tables

Table 4-1—GDD mechanisms and timescales 252
Table 6-1—Supported TS management primitives 418
Table 6-2—Reason codes for network down 717
Table 6-3—Reason codes for ESS link down 718
Table 6-4—ESS description 720
Table 6-5—Trigger support values 720
Table 6-6—Event Capability Set 723
Table 6-7—ESS Link Parameter Set 724
Table 8-1—PHY SAP peer-to-peer service primitives 739
Table 8-2—PHY SAP inter-(sub)layer service primitives 740
Table 8-3—PHY SAP service primitive parameters 740
Table 8-4—Vector descriptions 741
Table 8-5—The channel-list parameter entries 749
Table 9-1—Valid type and subtype combinations 759
Table 9-2—Control Frame Extension 761
Table 9-3—To/From DS combinations in Data frames 762
Table 9-4—To/From DS combinations in Management frames 762
Table 9-6—Dynamic Indication subfield encoding 766
Table 9-7—Poll Type subfield encoding 766
Table 9-5—Bandwidth Indication subfield encoding 766
Table 9-8—Frame Control field BSS BW setting 767
Table 9-9—Duration/ID field encoding 768
Table 9-10—QoS Control field 771
Table 9-11—QoS Control field for frames transmitted within a DMG PPDU 772
Table 9-12—TID subfield 772
Table 9-13—Ack policy 773
Table 9-14—AC Constraint subfield values 778
Table 9-15—RDG/More PPDU subfield values 778
Table 9-16—Subfields of Link Adaptation Control subfield 779
Table 9-17—Subfields of the MAI subfield 779
Table 9-18—ASEL Command and ASEL Data subfields 780
Table 9-19—Calibration control subfields 781
Table 9-20—CSI/Steering subfield values 781
Table 9-21—VHT variant HT Control field subfields 782
Table 9-22—MFB subfield in the VHT variant HT Control field 784
Table 9-23—Subfields corresponding to link adaptation 785
Table 9-24—MFB subfield in the CMMG variant HT Control field 786
Table 9-25—Maximum data unit sizes (in octets) and durations (in microseconds) 787
Table 9-26—Valid values for the Address Extension Mode subfield 789
Table 9-27—BlockAckReq frame variant encoding 801
Table 9-28—BlockAck frame variant encoding 804
Table 9-29—STA Info subfields 813
Table 9-31—SYNRA Type field encoding 817
Table 9-30—Address field contents 817
Table 9-32—Beacon frame body 825
Table 9-33—Disassociation frame body 829
Table 9-34—Association Request frame body 830
Table 9-35—Association Response frame body 832
Table 9-36—Reassociation Request frame body 835
Table 9-37—Reassociation Response frame body 839
Table 9-38—Probe Request frame body 843
Table 9-39—Probe Response frame body 845

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-40—Authentication frame body 851
Table 9-41—Presence of fields and elements in Authentication frames 852
Table 9-42—Deauthentication frame body 856
Table 9-43—Action frame body and Action No Ack frame body 856
Table 9-44—Timing Advertisement frame body 857
Table 9-45—DMG Beacon frame body 858
Table 9-46—Minimum and full set of optional elements 863
Table 9-47—Valid address field usage for Mesh Data and Multihop Action frames 865
Table 9-48—Unified Scaling Factor subfield encoding 871
Table 9-49—Reason codes 871
Table 9-50—Status codes 875
Table 9-51—Category values 881
Table 9-52—MCS subfield of the Originator Preferred MCS field 883
Table 9-53—Settings of the Max SP Length subfield 885
Table 9-54—Settings of the Channel Width field 887
Table 9-55—Subfields of the MIMO Control field 890
Table 9-56—CSI Report field (20 MHz) 891
Table 9-58—Number of matrices and carrier grouping 892
Table 9-57—CSI Report field (40 MHz) 892
Table 9-59—Noncompressed Beamforming Report field (20 MHz) 893
Table 9-60—Noncompressed Beamforming Report field (40 MHz) 894
Table 9-61—Order of angles in the Compressed Beamforming Report field 895
Table 9-62—Quantization of angles 896
Table 9-63—Compressed Beamforming Report field (20 MHz) 896
Table 9-64—Compressed Beamforming Report field (40 MHz) 897
Table 9-65—Venue group codes and descriptions 901
Table 9-66—Venue type assignments 902
Table 9-67—Band ID field 907
Table 9-68—The BSS Type subfield when the Discovery mode field is 0 907
Table 9-69—The BSS Type subfield when the Discovery mode field is 1 908
Table 9-70—Subfields of the VHT MIMO Control field 909
Table 9-71—Order of angles in the compressed beamforming feedback matrix when used in a non-S1G band 911
Table 9-72—Order of angles in the compressed beamforming feedback matrix for SU type feedback when used in an S1G band 913
Table 9-73—Order of angles in the compressed beamforming feedback matrix for MU type feedback when used in an S1G band 913
Table 9-74—Quantization of angles 914
Table 9-75—VHT Compressed Beamforming Report information 914
Table 9-76—Subcarrier indices for which a compressed beamforming feedback matrix is sent back 915
Table 9-77—Average SNR of Space-Time Stream i subfield 921
Table 9-78—MU Exclusive Beamforming Report information 923
Table 9-79—Number of subcarriers and subcarrier mapping 924
Table 9-80—Subfield values of the Operating Mode field 927
Table 9-81—Setting of the Channel Width subfield and 160/80+80 BW subfield at a VHT STA transmitting the Operating Mode field 928
Table 9-82—WSM Type definition 931
Table 9-83—Subfields of the Sync Control field 932
Table 9-84—Next TWT Subfield Size subfield encoding 933
Table 9-85—Subfields of the CMMG MIMO Control field 934
Table 9-86—Order of angles in the CMMG Compressed Beamforming Report field 935
Table 9-87—Quantization of angles 935
Table 9-88—Compressed Beamforming Report field 936
Table 9-89—Subcarrier indices for which a compressed beamforming feedback matrix is sent back 937

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-90—Average SNR of Space-Time Stream i subfield 938
Table 9-91—Subfield values of the CMMG Operating Mode field 939
Table 9-92—Element IDs 940
Table 9-93—BSS membership selector value encoding 950
Table 9-94—Block Control field encoding 955
Table 9-95—Coverage Class field parameters 962
Table 9-96—Values of the Secondary Channel Offset field 968
Table 9-97—Summary of use of Enable, Request, and Report bits 969
Table 9-98—Measurement type definitions for measurement requests 970
Table 9-99—Optional subelement IDs for Channel Load request 972
Table 9-100—Reporting Condition subfield for Channel Load report 973
Table 9-101—Optional subelement IDs for Noise Histogram request 974
Table 9-102—Reporting Condition subfield for Noise Histogram report 975
Table 9-103—Measurement Mode definitions for Beacon request 976
Table 9-104—Optional subelement IDs for Beacon request 977
Table 9-105—Reporting Condition subfield for Beacon report 978
Table 9-106—Reporting Detail values 979
Table 9-107—Optional subelement IDs for Frame request 980
Table 9-108—Group Identity for a STA Statistics request 981
Table 9-109—Optional subelement IDs for STA Statistics request 981
Table 9-110—Location Subject field definition 985
Table 9-111—Optional subelement IDs for LCI request 985
Table 9-112—Optional subelement IDs for Transmit Stream/Category Measurement Request 988
Table 9-113—Delayed MSDU Range Definitions 990
Table 9-114—Optional subelement IDs for Measurement Pause request 991
Table 9-115—Optional subelement IDs for STA Multicast Diagnostics request 992
Table 9-116—Civic Location Type field values 993
Table 9-117—Location Service Interval Units 993
Table 9-118—Optional subelement IDs for Location Civic request 994
Table 9-119—Optional subelement IDs for Location Identifier request 995
Table 9-120—Optional subelement IDs for Directional Channel Quality request 996
Table 9-121—Reporting Condition subfield for Directional Channel Quality report 997
Table 9-122—Optional subelement IDs for Directional Measurement request 998
Table 9-123—Optional subelement IDs for Directional Statistics request 999
Table 9-124—FTM Range subelement IDs for Fine Timing Measurement Range request 1000
Table 9-125—Measurement Type field definitions for measurement reports 1002
Table 9-126—RPI definitions for an RPI histogram report 1005
Table 9-127—Optional subelement IDs for Channel Load report 1006
Table 9-129—Optional subelement IDs for Noise Histogram report 1008
Table 9-128—IPI Definitions for a Noise Histogram report 1008
Table 9-130—Optional subelement IDs for Beacon report 1010
Table 9-131—Optional subelement IDs for Frame report 1012
Table 9-132—Group Identity for a STA Statistics report 1014
Table 9-133—Optional subelement IDs for STA Statistics report 1021
Table 9-134—Subelement IDs for LCI Report 1023
Table 9-135—Delay definitions for a Transmit Stream/Category Measurement report for a Bin 0 Range field value of 10 TU 1032
Table 9-136—Optional subelement IDs for Transmit Stream/Category Measurement report 1032
Table 9-137—Optional subelement IDs for Multicast Diagnostics report 1034
Table 9-138—Summary of fields used in the STA Multicast Diagnostics report 1035
Table 9-139—Subelement IDs for Location Civic report 1035
Table 9-140—Location Shape IDs 1037
Table 9-141—Map types 1041
Table 9-142—Subelement IDs for Location Identifier report 1042

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-143—URI/FQDN Descriptor field values 1043
Table 9-144—Optional subelement IDs for Directional Channel Quality report 1045
Table 9-145—Optional subelement IDs for Directional Measurement report 1046
Table 9-146—Optional subelement IDs for Directional Statistics report 1047
Table 9-148—Optional subelement IDs for Fine Timing Measurement Range report 1049
Table 9-147—Error Code field values 1049
Table 9-149—Cipher suite selectors 1053
Table 9-150—Cipher suite usage 1054
Table 9-151—AKM suite selectors 1055
Table 9-152—PTKSA/GTKSA replay counters usage 1059
Table 9-153—Extended Capabilities field 1061
Table 9-154—ACI-to-AC coding 1069
Table 9-155—Default EDCA Parameter Set element parameter values if dot11OCBActivated is false or the STA is a non-sensor STA 1070
Table 9-156—Default EDCA parameter set for STA operation if dot11OCBActivated is true 1071
Table 9-157—Default EDCA Parameter Set element parameter values if the STA is a sensor STA 1071
Table 9-158—Direction subfield encoding 1072
Table 9-160—TS Info Ack Policy subfield encoding 1073
Table 9-161—Setting of Schedule subfield 1073
Table 9-159—Access Policy subfield 1073
Table 9-162—Reliability subfield values 1077
Table 9-163—User Priority field of TCLAS element 1078
Table 9-164—Frame classifier type 1079
Table 9-165—Classifier Mask for Classifier Type 6 1080
Table 9-166—Classifier Mask for Classifier Type 7 1081
Table 9-167—Classifier Mask for Classifier Type 8 1081
Table 9-169—Map from location of Classifier Mask subfield to target subfield 1082
Table 9-168—Classifier Mask for Classifier Type 9 1082
Table 9-170—Classifier parameters for Classifier Type 4 1084
Table 9-171—Encoding of Processing subfield 1092
Table 9-172—Reachability field 1095
Table 9-173—Optional subelement IDs for Neighbor Report 1096
Table 9-174—Preference field values 1099
Table 9-175—HT/VHT Operation Information subfields 1100
Table 9-176—RCPI values 1101
Table 9-177—Optional subelement IDs for Measurement Pilot Transmission 1104
Table 9-178—Available Admission Capacity Bitmask definition 1105
Table 9-179—RM Enabled Capabilities definition 1107
Table 9-180—Optional subelement IDs for Multiple BSSID 1111
Table 9-181—Subelement IDs 1113
Table 9-182—Timeout Interval Type field value 1116
Table 9-183—Resource type code in RIC Descriptor element 1117
Table 9-184—Subfields of the HT Capability Information field 1122
Table 9-185—Subfields of the A-MPDU Parameters field 1124
Table 9-186—Transmit MCS Set 1125
Table 9-187—Subfields of the HT Extended Capabilities field 1126
Table 9-188—Subfields of the Transmit Beamforming Capabilities field 1127
Table 9-189—ASEL Capability field subfields 1129
Table 9-190—HT Operation element fields and subfields 1130
Table 9-191—Encoding of the Timing Capabilities field 1136
Table 9-192—Time Value field format when Timing Capabilities is 2 1136
Table 9-194—Transition Event Request subelement 1140
Table 9-193—Event Type field definitions for event requests and reports 1140
Table 9-195—RSNA Event Request subelement 1143

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-196—Peer-to-Peer Link Event Request subelement 1145
Table 9-197—Event Report Status 1147
Table 9-198—Transition and Transition Query reasons 1148
Table 9-199—Peer Status definitions 1150
Table 9-201—Association Diagnostic request contents 1152
Table 9-200—Diagnostic Request/Report Type definitions 1152
Table 9-203—Diagnostic subelement ID values 1153
Table 9-202—IEEE 802.1X Authentication Diagnostic request contents 1153
Table 9-204—Credentials values 1154
Table 9-205—Collocated Radio Type 1156
Table 9-206—Device Type definitions 1157
Table 9-207—Power Save Mode definition 1160
Table 9-208—Tx Power Modes 1161
Table 9-209—Manufacturer Information STA report contents 1163
Table 9-210—Configuration Profile report contents 1163
Table 9-211—Association Diagnostic report contents 1164
Table 9-212—IEEE 802.1X Authentication Diagnostic report contents 1164
Table 9-213—Optional subelement IDs for Location Parameters 1165
Table 9-214—Report Interval Units field 1166
Table 9-215—Motion Indicator field 1169
Table 9-216—Speed Units 1170
Table 9-217—Indication Parameter values 1172
Table 9-218—Optional subelement IDs for FMS Request subelements 1175
Table 9-219—Optional subelement IDs for FMS Response subelements 1177
Table 9-220—FMS Element Status and TFS Response Status definition 1177
Table 9-221—QoS Traffic Capability Bitmask/Flags definition 1179
Table 9-222—TFS Action Code field values 1181
Table 9-223—Optional subelement IDs for TFS Request parameters 1182
Table 9-224—Optional subelement IDs for TFS Response parameters 1183
Table 9-225—Action Type definitions 1184
Table 9-226—WNM Sleep Mode Response Status definition 1185
Table 9-227—Status field values 1186
Table 9-228—Usage Mode definitions 1189
Table 9-229—DMS Request Type field 1191
Table 9-230—Optional subelement IDs for DMS Descriptor 1191
Table 9-231—GATS Retransmission Policy field values 1192
Table 9-232—GCR Delivery Method field values 1192
Table 9-233—Response Type field values 1193
Table 9-234—Optional subelement IDs for DMS Status 1194
Table 9-235—Optional subelement IDs for U-APSD coexistence 1196
Table 9-236—Access network type 1197
Table 9-237—Advertisement protocol ID definitions 1200
Table 9-238—Precedence Level field description 1201
Table 9-239—Active Path Selection Protocol Identifier field values 1204
Table 9-241—Congestion Control Mode Identifier field values 1205
Table 9-240—Active Path Selection Metric Identifier field values 1205
Table 9-243—Authentication Protocol Identifier field values 1206
Table 9-242—Synchronization Method Identifier field values 1206
Table 9-244—Mesh Peering Protocol Identifier field values 1210
Table 9-245—MCCA Reply Code field values 1215
Table 9-246—SCS Request Type definitions 1230
Table 9-247—Optional subelement IDs for SCS Descriptor element 1231
Table 9-248—Sharing Policy definitions 1232
Table 9-249—Optional subelement IDs for QLoad Report element 1232

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-250—Protocol ID definitions 1234
Table 9-251—Subfields of the A-MPDU Parameters subfield 1237
Table 9-253—Maximum Number Of Basic A-MSDU Subframes In A-MSDU subfield 1241
Table 9-252—Mapping of Extended SC MCS to Maximum Supported Rx/Tx MCS subfield values 1241
Table 9-254—Maximum Number Of Short A-MSDU Subframes In A-MSDU subfield 1242
Table 9-256—FBCK-TYPE field description 1245
Table 9-255—FBCK-REQ field description 1245
Table 9-257—AllocationType subfield values 1248
Table 9-258—Protected Period subfield value for a CDMG STA operating on a 2.16 GHz channel 1250
Table 9-259—Protected Period subfield value for a CDMG STA operating on a 1.08 GHz channel 1250
Table 9-260—Allocation Format subfield values 1252
Table 9-261—Allocation Period field values 1253
Table 9-262—TSCONST Period values 1254
Table 9-263—Channel Measurement Feedback element format 1256
Table 9-264—Channel measurement 1257
Table 9-265—STA Role subfield values 1259
Table 9-266—Activity field values 1263
Table 9-267—Session Type subfield values 1265
Table 9-268—MMS Element Owner subfield definition 1272
Table 9-269—Single AID subfield definition 1272
Table 9-270—LLC Header Copy field size 1274
Table 9-271—Subfields of the VHT Capabilities Information field 1278
Table 9-272—Setting of the Supported Channel Width Set subfield and Extended NSS BW Support subfield at a STA transmitting the VHT Capabilities Information field 1281
Table 9-273—Supported VHT-MCS and NSS Set subfields 1282
Table 9-274—VHT Operation Information subfields 1285
Table 9-275—BSS bandwidth when the VHT Operation Information field Channel Width subfield is 1 1286
Table 9-276—Meaning of Local Maximum Transmit Power Count subfield 1289
Table 9-277—Definition of Local Maximum Transmit Power Unit Interpretation subfield 1289
Table 9-278—Status Indication subfield values 1294
Table 9-279—Burst Duration subfield encoding 1294
Table 9-280—Format And Bandwidth subfield 1296
Table 9-281—TBTT Information field contents 1299
Table 9-282—TVHT Operation Information subfields 1301
Table 9-283—Access Category subfield encoding 1302
Table 9-284—Data Format subfield encoding 1303
Table 9-285—BA Window Size subfield encoding 1303
Table 9-286—CAG Information Type definitions 1305
Table 9-287—BSS Delay Criterion subfield 1307
Table 9-288—PHY Support Criterion subfield 1307
Table 9-289—Key Type and Public Key Indicator subfields 1311
Table 9-290—IPv4 subfield settings 1313
Table 9-291—IPv6 subfield settings 1313
Table 9-292—IP Address Response Control subfield with B0 = 0 1314
Table 9-293—IP Address Response Control subfield with B0 = 1 1315
Table 9-294—DNS Info Control subfield settings 1316
Table 9-295—MAC Address Filter field 1318
Table 9-296—Interpretation of RAW Type and RAW Type Options 1321
Table 9-297—TWT Setup Command field values 1334
Table 9-298—TWT Unit subfield encoding 1337
Table 9-299—Action field 1339
Table 9-300—Subfields of the S1G Capabilities Information field 1342
Table 9-301—Supported S1G-MCS and NSS Set subfields 1348

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-302—Mapping between Maximum Transmission Width subfield and maximum permitted PPDU bandwidth 1350
Table 9-303—Hierarchy Identifier subfield 1353
Table 9-304—Enable Relay Function subfield values 1355
Table 9-305—Probe Response Option Bitmap subfield 0 (Default Bitmap) 1359
Table 9-306—Probe Response Option Bitmap subfield 1 1360
Table 9-307—Probe Response Option Bitmap subfield 2 1360
Table 9-308—Probe Response Option Bitmap subfield 3 1361
Table 9-309—Probe Response Option Bitmap subfield 4 1361
Table 9-310—Probe Response Option Bitmap subfield 5 1362
Table 9-311—S1G Operation Information field 1364
Table 9-312—AllocationType subfield values for CDMG STAs 1373
Table 9-313—Subfields of the CMMG Capabilities Info field 1382
Table 9-314—Subfields of the A-MPDU Parameters field 1385
Table 9-315—Supported CMMG-MCS and NSS Set subfields 1386
Table 9-316—Subfields of the Transmit Beamforming Capabilities field 1387
Table 9-317—CMMG Operation Information field format 1390
Table 9-318—Activity field values 1391
Table 9-319—GLK-GCR Retransmission Policy subfield 1393
Table 9-320—False Positive Probability Range subfield values 1396
Table 9-321—Extended RSN Capabilities field 1400
Table 9-322—Optional subelement IDs for MSCS Descriptor element 1401
Table 9-323—General TLV format 1404
Table 9-324—Device Class field definition 1405
Table 9-325—Device Identification Information field definition 1406
Table 9-326—Device Location Information field definition 1406
Table 9-327—Channel Schedule Descriptor Tuple attribute definition 1406
Table 9-328—Channel Schedule Descriptor Value fields 1407
Table 9-329—WSM information values 1408
Table 9-330—WSM Information Value fields 1408
Table 9-331—ANQP-element definitions 1409
Table 9-332—Network Authentication Type Indicator definitions 1413
Table 9-333—IPv6 Address field values 1416
Table 9-334—IPv4 Address field values 1416
Table 9-335—Authentication Parameter types 1418
Table 9-336—Authentication Parameter format for the Expanded EAP method 1419
Table 9-337—Vendor Specific Authentication Parameters 1420
Table 9-338—Advice of Charge Type field values 1425
Table 9-339—Local Content State values 1426
Table 9-340—Local MAC Address Policy field bits 1431
Table 9-341—RLQP-element definitions 1433
Table 9-342—Reason Result Code field values 1434
Table 9-343—Reason Result Code field values 1436
Table 9-344—Encoding of BeamLink Maintenance Unit Index 1442
Table 9-345—The Beamformed Link Maintenance negotiation 1443
Table 9-346—Spectrum Management Action field values 1444
Table 9-347—QoS Action field values 1447
Table 9-348—Encoding of the ADDTS Request frame variant 1447
Table 9-349—Encoding of the ADDTS Response frame variant 1447
Table 9-350—Basic ADDTS Request frame variant Action field format 1448
Table 9-351—DMG ADDTS Request frame variant Action field format 1449
Table 9-352—Basic ADDTS Response frame variant Action field format 1450
Table 9-353—DMG ADDTS Response frame variant Action field format 1451
Table 9-354—DELTS frame Action field format 1452

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-355—Schedule frame Action field format 1453
Table 9-356—QoS Map Configure frame Action field format 1453
Table 9-357—ADDTS Reserve Request frame Action field format 1454
Table 9-358—ADDTS Reserve Response frame Action field format 1454
Table 9-359—Block Ack Action field values 1455
Table 9-360—ADDBA Request frame Action field format 1456
Table 9-361—ADDBA Response frame Action field format 1457
Table 9-362—DELBA frame Action field format 1458
Table 9-363—Radio Measurement Action field values 1459
Table 9-364—Public Action field values 1463
Table 9-365—20/40 BSS Coexistence Management frame Action field format 1465
Table 9-366—Optional subelement IDs for Measurement Pilot frame 1466
Table 9-367—Reason Result Code field values 1467
Table 9-368—Reason Result Code field values 1468
Table 9-369—Reason Result Code field values 1472
Table 9-370—GAS Initial Request frame Action field format 1473
Table 9-371—GAS Initial Response frame Action field format 1474
Table 9-373—GAS Comeback Response frame Action field format 1476
Table 9-372—GAS Comeback Request frame Action field(format 1476
Table 9-374—TDLS Discovery Response frame Action field format 1478
Table 9-375—Location Parameters Element field for Location Track Notification frame 1479
Table 9-376—QLoad Request frame Action field format 1481
Table 9-377—QLoad Report frame Action field format 1481
Table 9-378—Public Key Frame Usage field values 1484
Table 9-379—Reason Result Code field values 1485
Table 9-380—Channel Schedule Management Mode field values 1486
Table 9-381—QAB Request frame Action field format 1492
Table 9-382—QAB Response frame Action field format 1493
Table 9-383—FILS Discovery frame format 1494
Table 9-384—BSS Operating Channel Width 1497
Table 9-385—Maximum Number of Spatial Streams 1497
Table 9-386—PHY Index subfield 1497
Table 9-387—FILS Minimum Rate 1498
Table 9-388—Cipher suite selector definitions 1499
Table 9-389—AKM suite selector definitions 1499
Table 9-390—Optional subelement IDs for DCS Measurement Request frame 1501
Table 9-391—Optional subelement IDs for DCS Measurement Response frame 1502
Table 9-392—Extended Notification Period Request frame Action field format 1504
Table 9-393—Extended Notification Period Response frame Action field format 1505
Table 9-394—Extended Channel Splitting Request frame Action field format 1505
Table 9-395—Extended Channel Splitting Response frame Action field format 1506
Table 9-397—Group Addressed GAS Response frame Action field format 1507
Table 9-396—Group Addressed GAS Request frame Action field format 1507
Table 9-398—FT Action field values 1509
Table 9-400—FT Response frame body 1510
Table 9-399—FT Request frame body 1510
Table 9-401—FT Confirm frame body 1511
Table 9-402—FT Ack frame body 1512
Table 9-403—SA Query Action field values 1512
Table 9-404—Public Action field values defined for Protected Dual of Public Action frames 1514
Table 9-405—HT Action field values 1515
Table 9-406—Notify Channel Width frame Action field format 1515
Table 9-407—SM Power Save frame Action field format 1516
Table 9-408—PSMP frame Action field format 1516

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-409—CSI frame Action field format ... 1517
Table 9-410—Noncompressed Beamforming frame Action field format ... 1517
Table 9-411—Compressed Beamforming frame Action field format ... 1518
Table 9-412—Antenna Selection Indices Feedback frame Action field format ... 1518
Table 9-414—Information for TDLS Setup Request Action field ... 1519
Table 9-413—TDLS Action field values ... 1519
Table 9-415—Information for TDLS Setup Response Action field ... 1521
Table 9-416—Information for TDLS Setup Confirm Action field ... 1523
Table 9-417—Information for TDLS Teardown Action field ... 1524
Table 9-418—Information for TDLS Peer Traffic Indication Action field ... 1524
Table 9-419—Information for TDLS Channel Switch Request Action field ... 1525
Table 9-421—Information for TDLS Peer PSM Request Action field ... 1526
Table 9-422—Information for TDLS Peer PSM Response Action field ... 1526
Table 9-420—Information for TDLS Channel Switch Response Action field ... 1526
Table 9-423—Information for TDLS Peer Traffic Response Action field ... 1527
Table 9-425—WNM Action field values ... 1528
Table 9-424—Information for TDLS Discovery Request Action field ... 1528
Table 9-427—Location Parameters Element field for Location Configuration Response frame ... 1532
Table 9-426—Location Parameters Element field for Location Configuration Request frame ... 1532
Table 9-428—BTM status code definitions ... 1536
Table 9-429—Optional subelement IDs for WNM Sleep Mode parameters ... 1542
Table 9-430—QoS Traffic Capability Flags definition ... 1545
Table 9-431—WNM notification type ... 1548
Table 9-432—Optional subelement IDs for WNM Notification Request ... 1549
Table 9-434—Unprotected WNM Action field values ... 1550
Table 9-433—WNM Notification Response Status ... 1550
Table 9-435—Self-protected Action field values ... 1552
Table 9-436—Mesh Peering Open frame Action field format ... 1553
Table 9-437—Mesh Peering Confirm frame Action field format ... 1554
Table 9-439—Mesh Group Key Inform frame Action field format ... 1556
Table 9-438—Mesh Peering Close frame Action field format ... 1556
Table 9-440—Mesh Group Key Acknowledge frame Action field format ... 1557
Table 9-441—Mesh Action field values ... 1557
Table 9-442—Mesh Link Metric Report frame Action field format ... 1558
Table 9-444—Gate Announcement frame Action field format ... 1559
Table 9-443—HWMP Mesh Path Selection frame Action field format ... 1559
Table 9-445—Congestion Control Notification frame Action field format ... 1560
Table 9-446—MCCA Setup Request frame Action field format ... 1560
Table 9-447—MCCA Setup Reply frame Action field format ... 1561
Table 9-448—MCCA Advertisement Request frame Action field format ... 1561
Table 9-449—MCCA Advertisement frame Action field format ... 1562
Table 9-450—MCCA Teardown frame Action field format ... 1562
Table 9-451—TBTT Adjustment Request frame Action field format ... 1563
Table 9-452—TBTT Adjustment Response frame Action field format ... 1563
Table 9-453—Multihop Action field values ... 1564
Table 9-454—Proxy Update frame Action field format ... 1564
Table 9-455—Proxy Update Confirmation frame Action field format ... 1565
Table 9-456—Robust AV streaming Robust Action field values ... 1565
Table 9-457—DMG Action field values ... 1569
Table 9-458—Power Save Configuration Request frame Action field format ... 1570
Table 9-459—Power Save Configuration Response frame Action field format ... 1570
Table 9-460—Information Request frame Action field format ... 1571
Table 9-461—Information Response frame Action field format ... 1572
Table 9-462—Handover Request frame Action field format ... 1573

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-463—Handover Response frame Action field format ... 1573
Table 9-464—Relay Search Request frame Action field format ... 1574
Table 9-465—Relay Search Response frame Action field format ... 1574
Table 9-466—Multi-relay Channel Measurement Request frame Action field format ... 1575
Table 9-467—Multi-relay Channel Measurement Report frame Action field format ... 1576
Table 9-468—RLS Request frame Action field format ... 1577
Table 9-469—RLS Response frame Action field format ... 1578
Table 9-470—RLS Announcement frame Action field format ... 1578
Table 9-471—RLS Teardown frame Action field format ... 1579
Table 9-473—Relay Ack Response frame Action field format ... 1580
Table 9-472—Relay Ack Request frame Action field format ... 1580
Table 9-474—TPA Request frame Action field format ... 1581
Table 9-475—TPA Response frame Action field format ... 1581
Table 9-476—TPA Report frame Action field format ... 1582
Table 9-477—ROC Request frame Action field format ... 1582
Table 9-478—ROC Response frame Action field format ... 1583
Table 9-480—FST Setup Request frame Action field format ... 1584
Table 9-479—FST Action field values ... 1584
Table 9-481—FST Setup Response frame Action field format ... 1585
Table 9-482—FST Teardown frame Action field format ... 1586
Table 9-483—FST Ack Request frame Action field format ... 1586
Table 9-484—FST Ack Response frame Action field format ... 1587
Table 9-485—On-channel Tunnel Request frame Action field format ... 1587
Table 9-486—Unprotected DMG Action field values ... 1588
Table 9-487—Announce frame Action field format ... 1589
Table 9-488—BRP frame Action field format ... 1590
Table 9-489—VHT Action field values ... 1591
Table 9-490—VHT Compressed Beamforming frame Action field format ... 1592
Table 9-491—Group ID Management frame Action field format ... 1592
Table 9-492—Operating Mode Notification frame Action field format ... 1593
Table 9-493—FILS Action frame values ... 1593
Table 9-494—Unprotected S1G Action field values ... 1594
Table 9-496—AID Switch Response frame Action field format ... 1595
Table 9-495—AID Switch Request frame Action field format ... 1595
Table 9-497—Sync Control frame Action field format ... 1596
Table 9-498—STA Information Announcement frame Action field format ... 1596
Table 9-499—EDCA Parameter Set frame Action field format ... 1597
Table 9-500—EL Operation Action field format ... 1597
Table 9-502—TWT Teardown frame Action field format ... 1598
Table 9-501—TWT Setup frame Action field format ... 1598
Table 9-503—Sectorized Group ID List frame Action field format ... 1599
Table 9-504—Sector ID Feedback frame Action field format ... 1599
Table 9-505—TWT Information frame Action field format ... 1600
Table 9-506—S1G Action field values ... 1601
Table 9-507—Reachable Address Update frame Action field format ... 1601
Table 9-508—Relay Activation Request frame Action field format ... 1602
Table 9-509—Relay Activation Response frame Action field format ... 1602
Table 9-510—Header Compression frame Action field format ... 1603
Table 9-511—Flow Control Action field format ... 1604
Table 9-512—Flow Suspension frame Action field format ... 1604
Table 9-514—Control Response MCS Negotiation Action field values ... 1605
Table 9-515—Control Response Negotiation Request frame Action field format ... 1605
Table 9-513—Flow Resumption frame Action field format ... 1605
Table 9-516—Control Response MCS Negotiation Response frame Action field format ... 1606

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 9-517—Command values 1606
Table 9-519—Notification Period Response frame Action field format 1607
Table 9-518—CDMG Action field values 1607
Table 9-520—Channel Splitting Response frame Action field format 1608
Table 9-521—CDMG Allocation Response frame Action field format 1609
Table 9-522—CMMG Action field values 1610
Table 9-523—CMMG Compressed Beamforming frame Action field format 1610
Table 9-524—CMMG Operating Mode Notification frame Action field format 1611
Table 9-525—GLK Action field values 1611
Table 9-526—GLK Groupcast Mode Change Notification frame format 1612
Table 9-527—MPDU delimiter fields (non-DMG) 1614
Table 9-528—MPDU delimiter fields (DMG) 1614
Table 9-529—A-MPDU contexts 1616
Table 9-530—A-MPDU contents in the data enabled immediate response context 1617
Table 9-531—A-MPDU contents in the data enabled no immediate response context 1618
Table 9-532—A-MPDU contents in the PSMP context 1618
Table 9-533—A-MPDU contents in the control response context 1618
Table 9-534—A-MPDU contents in the S-MPDUcontext 1618
Table 9-536—From DS values in PV1 frames 1620
Table 9-535—PV1 frame types 1620
Table 9-537—Ack Policy Indicator subfield in the Frame Control field for PV1 frames 1621
Table 9-538—PV1 Control frame subtypes 1623
Table 9-539—PV1 Management frame subtypes 1626
Table 10-1—UP-to-AC mappings 1634
Table 10-2—RESPONSE_INDICATION value for NDP CMAC PPDUs 1650
Table 10-3—NormalTXTime duration based on RXVECTOR parameters 1652
Table 10-4—Dual CTS rules 1658
Table 10-5—Transmitter sequence number spaces 1666
Table 10-6—Receiver caches 1667
Table 10-7—Setting the TXVECTOR parameter RESPONSE_INDICATION 1670
Table 10-8—Determination of the EstimatedAckTxTime based on properties of the PPDU causing the EIFS 1682
Table 10-9—Modulation classes 1707
Table 10-10—Non-HT reference rate 1708
Table 10-11—Example of rate selection for VHT PPDUs 1711
Table 10-12—A-MSDU STA behavior for RSN associations 1718
Table 10-13—Settings for the TXVECTOR parameters GROUP_ID and PARTIAL_AID for VHT STAs 1729
Table 10-14—Settings for the TXVECTOR parameter PARTIAL_AID for CMMG STAs 1730
Table 10-15—Settings for the TXVECTOR parameter PARTIAL_AID for an NDP 1733
Table 10-16—Settings for the TXVECTOR parameter PARTIAL_AID for non-1 MHz PPDUs and non-NDPs 1733
Table 10-17—Channels indicated idle by the channel-list parameter for VHT or TVHT BSSs 1744
Table 10-18—Channels indicated idle by the channel-list parameter for S1G BSSs 1745
Table 10-19—Modulation classes eligible for TXOP termination 1753
Table 10-20—Rate and modulation class of a final transmission in a TXOP 1754
Table 10-21—Channels indicated idle by the channel-list parameter for CMMG BSSs 1756
Table 10-22—Protection requirements for HT Protection field values nonmember protection mode and non-HT mixed mode 1811
Table 10-23—Applicable HT protection mechanisms 1812
Table 10-24—STA type requirements for transmit beamforming with implicit feedback 1842
Table 10-25—Transmit beamforming support required with implicit feedback 1842
Table 10-26—Rules for HT beamformee immediate feedback transmission responding to non-NDP sounding 1851

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 10-27—Rules for HT beamformee immediate feedback transmission responding to NDP sounding 1852
Table 10-29—Rules for CMMG beamformee immediate feedback transmission responding to NDP sounding 1855
Table 10-28—Rules for CMMG beamformee immediate feedback transmission responding to non-NDP sounding 1855
Table 10-30—Mandatory and optional procedures in the Beamforming mechanism 1932
Table 10-31—Beam tracking time limit determination 1966
Table 10-32—S1G BSS operating channel width 1982
Table 11-1—Encoding of the Supported Channel Width Set field 2073
Table 11-2—Bufferable/nonbufferable classification of MMPDUs 2078
Table 11-3—Power states for an A-BI 2114
Table 11-4—Power states for a D-BI 2115
Table 11-5—Types of block ack agreement based on capabilities and ADDBA conditions for non-DMG STAs 2169
Table 11-6—Types of block ack agreement based on capabilities and ADDBA conditions for DMG STAs 2169
Table 11-7—Allowed measurement requests 2181
Table 11-8—Measurement Duration 2194
Table 11-9—Allowed measurement requests 2195
Table 11-10—Measurement pilot activated definition 2218
Table 11-11—DSE STA attributes 2224
Table 11-12—STA recovery procedures for a changed retransmission policy 2301
Table 11-13—Non-AP STA recovery procedures for a changed delivery method 2302
Table 11-14—ANQP usage 2320
Table 11-15—ESR and UESA field settings 2330
Table 11-16—Default QMF policy 2337
Table 11-17—QMF policy description for valid combination of optional fields in the QACM field 2342
Table 11-18—Contents of HCCA TXOP Response frame 2353
Table 11-19—Exceptions for the initiator 2372
Table 11-20—FST status at state transition 2374
Table 11-21—Setting of Single AID field 2384
Table 11-22—DMG MAC sublayer attribute values 2393
Table 11-23—VHT BSS bandwidth 2394
Table 11-24—Setting of Channel Center Frequency Segment 0, Channel Center Frequency Segment 1, and Channel Center Frequency Segment 2 subfields 2395
Table 11-25—Extended NSS channel width 2396
Table 11-26—TVHT BSS bandwidth 2405
Table 11-28—CMMG BSS operating channel width 2431
Table 12-1—Hash algorithm based on length of prime 2454
Table 12-2—Unique curve parameter 2459
Table 12-3—AAD length for PV0 MPDUs 2494
Table 12-4—AAD length for PV1 MPDUs 2495
Table 12-5—Robust management frame selection in an infrastructure BSS 2519
Table 12-6—Robust management frame selection in an IBSS 2521
Table 12-7—Cipher suite key lengths 2550
Table 12-8—Key RSC field 2551
Table 12-9—KDE selectors 2552
Table 12-10—Integrity and key wrap algorithms 2556
Table 13-1—FT authentication elements 2632
Table 13-2—Remote Request/Response Payload format 2648
Table 13-3—Resource types and resource descriptor definitions 2650
Table 14-1—State variables for mesh STAs 2661
Table 14-2—MPM finite state machine 2668

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 14-3—AMPE finite state machine ... 2679
Table 14-4—Airtime cost constants for airtime link metric and high PHY rate airtime link metric ... 2687
Table 14-5—Parameters of the airtime link metric and high PHY rate airtime link metric for extensible path selection framework ... 2687
Table 14-6—Precursor and next hop examples (forward path) ... 2690
Table 14-7—Precursor and next hop examples (reverse path) ... 2690
Table 14-8—Parameters of HWMP for extensible path selection framework ... 2693
Table 14-9—Data for creation and update of forwarding information due to PREQ element and PREP element ... 2697
Table 14-10—Validation and invalidation of the forwarding information ... 2698
Table 14-11—Contents of a PREQ element in Case A ... 2699
Table 14-12—Contents of a PREQ element in Case B ... 2700
Table 14-13—Contents of a PREQ element in Case C ... 2701
Table 14-14—Contents of a PREQ element in Case D ... 2702
Table 14-15—Contents of a PREQ element in Case E1 ... 2704
Table 14-16—Contents of a PREQ element in Case E2 ... 2705
Table 14-17—Contents of a PREQ element in Case E3 ... 2706
Table 14-18—Contents of a PREP element in Case A ... 2709
Table 14-20—Contents of a PREP element in Case C ... 2710
Table 14-19—Contents of a PREP element in Case B ... 2710
Table 14-21—Contents of a PREP element in Case D ... 2711
Table 14-23—Contents of a PERR element in Case B ... 2714
Table 14-22—Contents of a PERR element in Case A ... 2714
Table 14-24—Contents of a PERR element in Case C ... 2715
Table 14-25—Contents of a PERR element in Case D ... 2716
Table 14-26—Contents of a RANN element in Case A ... 2718
Table 14-27—Contents of a RANN element in Case B ... 2719
Table 14-28—Contents of a GANN element in Case A ... 2721
Table 14-29—Contents of a GANN element in Case B ... 2722
Table 14-30—Contents of a PXU element ... 2726
Table 14-31—Contents of a PXUC element ... 2728
Table 14-32—Peer-specific mesh power management mode definition ... 2741
Table 14-33—Mesh peer service period triggering with RSPI and EOSP subfield combinations in peer trigger frame ... 2747
Table 15-1—TXVECTOR parameters ... 2750
Table 15-2—RXVECTOR parameters ... 2751
Table 15-3—TXSTATUS parameters ... 2752
Table 15-4—MIB attribute default values/ranges ... 2762
Table 15-5—DSSS PHY characteristics ... 2763
Table 15-6—DSSS PHY frequency channel plan ... 2764
Table 15-7—1 Mb/s DBPSK encoding table ... 2765
Table 15-8—2 Mb/s DQPSK encoding table ... 2765
Table 16-1—SERVICE field definitions ... 2777
Table 16-2—Example of LENGTH calculations for CCK ... 2778
Table 16-3—MIB attribute default values/ranges ... 2787
Table 16-4—HR/DSSS PHY characteristics ... 2788
Table 16-5—Parameter vectors ... 2789
Table 16-6—HR/DSSS PHY frequency channel plan ... 2791
Table 16-7—1 Mb/s DBPSK encoding table ... 2792
Table 16-8—2 Mb/s DQPSK encoding table ... 2792
Table 16-9—DQPSK encoding table ... 2793
Table 16-10—5.5 Mb/s CCK encoding table ... 2793
Table 16-11—QPSK encoding table ... 2794
Table 17-1—TXVECTOR parameters ... 2803

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 17-2—RXVECTOR parameters 2805
Table 17-3—TXSTATUS parameters 2807
Table 17-4—Modulation-dependent parameters 2810
Table 17-5—Timing-related parameters 2811
Table 17-6—Contents of the SIGNAL field 2816
Table 17-7—Contents of the first 7 bits of the scrambling sequence 2819
Table 17-8—TXVECTOR parameter CH_BANDWIDTH_IN_NON_HT values 2819
Table 17-9—RXVECTOR parameter CH_BANDWIDTH_IN_NON_HT values 2820
Table 17-10—DYN_BANDWIDTH_IN_NON_HT values 2820
Table 17-11—Modulation-dependent normalization factor K_{MOD} 2825
Table 17-12—BPSK encoding table 2825
Table 17-13—QPSK encoding table 2825
Table 17-14—16-QAM encoding table 2826
Table 17-15—64-QAM encoding table 2826
Table 17-16—Major parameters of the OFDM PHY 2829
Table 17-17—Allowed relative constellation error versus data rate 2834
Table 17-18—Receiver performance requirements 2836
Table 17-19—Optional enhanced receiver performance requirements 2837
Table 17-20—MIB attribute default values/ranges 2844
Table 17-21—OFDM PHY characteristics 2847
Table 18-1—TXVECTOR parameters 2850
Table 18-2—TXSTATUS parameters 2851
Table 18-3—RXVECTOR parameters 2851
Table 18-4—MIB attribute default values/ranges 2857
Table 18-5—ERP characteristics 2859
Table 19-1—TXVECTOR and RXVECTOR parameters 2862
Table 19-2—Interpretation of FORMAT, CH_BANDWIDTH, and CH_OFFSET parameters 2869
Table 19-3—Mapping of the HT PHY parameters for NON_HT operation 2870
Table 19-4—TXSTATUS parameters 2872
Table 19-5—Elements of the HT PPDU 2873
Table 19-6—Timing-related constants 2880
Table 19-7—Frequently used parameters 2881
Table 19-8—Value of tone scaling factor 2884
Table 19-9—Cyclic shift for non-HT portion of PPDU 2887
Table 19-10—Cyclic shift values of HT portion of PPDU 2890
Table 19-11—HT-SIG fields 2890
Table 19-12—Determining the number of space-time streams 2895
Table 19-13—Number of HT-DLTFs required for data space-time streams 2896
Table 19-14—Number of HT-ELTFs required for extension spatial streams 2896
Table 19-15—LDPC parameters 2904
Table 19-16—PPDU encoding parameters 2905
Table 19-17—Number of rows and columns in the interleaver 2909
Table 19-18—Constellation mapper output to spatial mapper input for STBC 2910
Table 19-19—Pilot values for 20 MHz transmission 2912
Table 19-20—Pilots values for 40 MHz transmission (excluding MCS 32) 2912
Table 19-21—Maximum available space-time streams 2928
Table 19-22—Allowed relative constellation error versus constellation size and coding rate 2934
Table 19-23—Receiver minimum input level sensitivity 2936
Table 19-24—HT PHY MIB attributes 2947
Table 19-25—HT PHY characteristics 2952
Table 19-26—Symbols used in MCS parameter tables 2953
Table 19-27—MCS parameters for mandatory 20 MHz, $N_{SS} = 1$, $N_{ES} = 1$ 2953
Table 19-28—MCS parameters for optional 20 MHz, $N_{SS} = 2$, $N_{ES} = 1$, EQM 2954
Table 19-29—MCS parameters for optional 20 MHz, $N_{SS} = 3$, $N_{ES} = 1$, EQM 2954

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 19-30—MCS parameters for optional 20 MHz, N_{SS} = 4, N_{ES} = 1, EQM 2955
Table 19-31—MCS parameters for optional 40 MHz, N_{SS} = 1, N_{ES} = 1 2955
Table 19-32—MCS parameters for optional 40 MHz, N_{SS} = 2, N_{ES} = 1, EQM 2956
Table 19-33—MCS parameters for optional 40 MHz, N_{SS} = 3, EQM 2956
Table 19-34—MCS parameters for optional 40 MHz, N_{SS} = 4, EQM 2957
Table 19-35—MCS parameters for optional 40 MHz MCS 32 format, N_{SS} = 1, N_{ES} = 1 2957
Table 19-36—MCS parameters for optional 20 MHz, N_{SS} = 2, N_{ES} = 1, UEQM 2957
Table 19-37—MCS parameters for optional 20 MHz, N_{SS} = 3, N_{ES} = 1, UEQM 2958
Table 19-38—MCS parameters for optional 20 MHz, N_{SS} = 4, N_{ES} = 1, UEQM 2958
Table 19-39—MCS parameters for optional 40 MHz, N_{SS} = 2, N_{ES} = 1, UEQM 2959
Table 19-40—MCS parameters for optional 40 MHz, N_{SS} = 3, UEQM 2960
Table 19-41—MCS parameters for optional 40 MHz, N_{SS} = 4, UEQM 2960
Table 20-1—TXVECTOR and RXVECTOR parameters 2963
Table 20-2—TXSTATUS parameters 2965
Table 20-3—Receiver minimum input level sensitivity 2968
Table 20-4—Timing-related parameters 2969
Table 20-5—Frequently used parameters 2969
Table 20-6—Rate 1/2 LDPC code matrix (Each nonblank element i in the table is the cyclic permutation matrix Pi of size Z × Z; blank entries represent the zero matrix of size Z × Z) 2973
Table 20-7—Rate 5/8 LDPC code matrix (Each nonblank element i in the table is the cyclic permutation matrix Pi of size Z × Z; blank entries represent the zero matrix of size Z × Z) 2973
Table 20-8—Rate 3/4 LDPC code matrix (Each nonblank element i in the table is the cyclic permutation matrix Pi of size Z × Z; blank entries represent the zero matrix of size Z × Z) 2973
Table 20-9—Rate 13/16 LDPC code matrix (Each nonblank element i in the table is the cyclic permutation matrix Pi of size Z × Z; blank entries represent the zero matrix of size Z × Z) 2974
Table 20-10—DMG control mode modulation and coding scheme 2975
Table 20-11—DMG control mode header fields 2976
Table 20-12—DMG control mode EVM requirements 2979
Table 20-13—DMG SC mode header fields 2980
Table 20-14—Parameters for computing Length field value in SC header when Extended SC MCS Indication field is set to 1 2982
Table 20-15—DMG SC mode modulation and coding schemes 2983
Table 20-16—DMG SC mode modulation and coding schemes when π/2-8-PSK Applied field is 1 2983
Table 20-17—Examples of length recovery 2985
Table 20-18—LDPC code rates 2986
Table 20-19—Values of NCBPB 2991
Table 20-20—DMG SC mode EVM requirements 2992
Table 20-21—DMG low-power SC mode modulation and coding schemes 2994
Table 20-22—Zero filling for DMG SC mode BRP PPDUs 3004
Table 20-23—The sequence Ga128(n) 3006
Table 20-24—The sequence Gb128(n) 3006
Table 20-25—The sequence Ga64(n) 3006
Table 20-26—The sequence Gb64(n) 3006
Table 20-27—The sequence Ga32(n) 3006
Table 20-29—DMG PHY MIB attribute default values 3007
Table 20-28—The sequence Gb32(n) 3007
Table 20-30—DMG PHY characteristics 3008
Table 21-1—TXVECTOR and RXVECTOR parameters 3012
Table 21-2—Interpretation of FORMAT, NON_HT_MODULATION, CH_BANDWIDTH, and CH_OFFSET parameters 3021

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 21-3—Mapping of VHT PHY parameters for NON_HT operation ... 3026
Table 21-4—Fields of the VHT PPDU ... 3027
Table 21-5—Timing-related constants ... 3042
Table 21-6—Frequently used parameters ... 3044
Table 21-7—Center frequency of the portion of the PPDU transmitted in frequency segment iSeg ... 3048
Table 21-8—Tone scaling factor and guard interval duration values for PHY fields ... 3050
Table 21-9—CH_BANDWIDTH and ... 3052
Table 21-10—Cyclic shift values for L-STF, L-LTF, L-SIG, and VHT-SIG-A fields of the PPDU ... 3053
Table 21-11—Cyclic shift values for the VHT modulated fields of a PPDU ... 3056
Table 21-12—Fields in the VHT-SIG-A field ... 3058
Table 21-13—Number of VHT-LTFs required for different numbers of space-time streams ... 3062
Table 21-14—Fields in the VHT-SIG-B field ... 3065
Table 21-15—VHT-SIG-B bits (before Tail field) in NDP for various channel widths ... 3066
Table 21-16—SERVICE field ... 3070
Table 21-17—Number of rows and columns in the interleaver ... 3077
Table 21-18—J(iSS) values ... 3078
Table 21-19—LDPC tone mapping distance for each bandwidth ... 3084
Table 21-20—Constellation mapper output to spatial mapper input for STBC ... 3086
Table 21-21—Pilot values for 80 MHz transmission ... 3088
Table 21-22—Fields to specify VHT channels ... 3094
Table 21-23—Maximum transmit spectral flatness deviations ... 3099
Table 21-24—Allowed relative constellation error versus constellation size and coding rate ... 3101
Table 21-25—Receiver minimum input level sensitivity ... 3103
Table 21-26—Minimum required adjacent and nonadjacent channel rejection levels ... 3104
Table 21-27—VHT PHY MIB attributes ... 3114
Table 21-28—VHT PHY characteristics ... 3119
Table 21-29—VHT-MCSs for mandatory 20 MHz, NSS = 1 ... 3120
Table 21-30—VHT-MCSs for optional 20 MHz, NSS = 2 ... 3121
Table 21-31—VHT-MCSs for optional 20 MHz, NSS = 3 ... 3121
Table 21-32—VHT-MCSs for optional 20 MHz, NSS = 4 ... 3122
Table 21-33—VHT-MCSs for optional 20 MHz, NSS = 5 ... 3122
Table 21-34—VHT-MCSs for optional 20 MHz, NSS = 6 ... 3123
Table 21-35—VHT-MCSs for optional 20 MHz, NSS = 7 ... 3123
Table 21-36—VHT-MCSs for optional 20 MHz, NSS = 8 ... 3124
Table 21-37—VHT-MCSs for mandatory 40 MHz, NSS = 1 ... 3124
Table 21-38—VHT-MCSs for optional 40 MHz, NSS = 2 ... 3125
Table 21-39—VHT-MCSs for optional 40 MHz, NSS = 3 ... 3125
Table 21-40—VHT-MCSs for optional 40 MHz, NSS = 4 ... 3126
Table 21-41—VHT-MCSs for optional 40 MHz, NSS = 5 ... 3126
Table 21-42—VHT-MCSs for optional 40 MHz, NSS = 6 ... 3127
Table 21-43—VHT-MCSs for optional 40 MHz, NSS = 7 ... 3127
Table 21-44—VHT-MCSs for optional 40 MHz, NSS = 8 ... 3128
Table 21-45—VHT-MCSs for mandatory 80 MHz, NSS = 1 ... 3128
Table 21-46—VHT-MCSs for optional 80 MHz, NSS = 2 ... 3129
Table 21-47—VHT-MCSs for optional 80 MHz, NSS = 3 ... 3129
Table 21-48—VHT-MCSs for optional 80 MHz, NSS = 4 ... 3130
Table 21-49—VHT-MCSs for optional 80 MHz, NSS = 5 ... 3130
Table 21-50—VHT-MCSs for optional 80 MHz, NSS = 6 ... 3131
Table 21-51—VHT-MCSs for optional 80 MHz, NSS = 7 ... 3131
Table 21-52—VHT-MCSs for optional 80 MHz, NSS = 8 ... 3132
Table 21-53—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 1 ... 3132
Table 21-54—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 2 ... 3133
Table 21-55—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 3 ... 3133
Table 21-56—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 4 ... 3134

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 21-57—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 5 3134
Table 21-58—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 6 3135
Table 21-59—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 7 3135
Table 21-60—VHT-MCSs for optional 160 MHz and 80+80 MHz, NSS = 8 3136
Table 22-1—TXVECTOR and RXVECTOR parameters 3140
Table 22-2—PPDU format as a function of CH_BANDWIDTH parameter 3146
Table 22-4—RATE field in L-SIG 3148
Table 22-3—Modulation-dependent parameters for Non-HT duplicate mode in TVWS band 3148
Table 22-5—Timing-related constants in Non-HT PPDU 3149
Table 22-6—Tone location in Non-HT PPDU 3149
Table 22-7—Fields of the VHT PPDU in TVWS bands 3151
Table 22-8—Timing-related parameters 3156
Table 22-9—Tone location 3157
Table 22-10—Center frequency of a PPDU transmitted in frequency segment iSeg 3159
Table 22-11—Tone scaling factor and guard interval duration values for PHY fields 3160
Table 22-12—Transmission mode and Gamma subk,m 3160
Table 22-13—B0-B1 (BW) in TVHT-SIG-A1 3163
Table 22-14—Number of rows and columns in the interleaver 3165
Table 22-15—LDPC Tone Mapping Distance for each transmission mode 3165
Table 22-16—Parameters for Non-HT duplicate transmissions 3167
Table 22-17—Fields to specify TVHT channels 3168
Table 22-18—Spectral mask frequency scaling factor for contiguous transmission 3170
Table 22-19—Spectral mask frequency scaling factor for TVHT_MODE_4N 3170
Table 22-20—Spectral mask frequency scaling factor for TVHT_MODE_2N 3171
Table 22-21—Maximum transmit spectral flatness deviations 3171
Table 22-22—Receiver minimum input level sensitivity 3174
Table 22-23—Minimum required adjacent and nonadjacent channel rejection levels 3175
Table 22-24—Conditions for CCA BUSY on the primary channel 3176
Table 22-25—TVHT PHY characteristics 3178
Table 22-26—TVHT-MCSs for TVHT_MODE_1, NSS = 1 3179
Table 22-27—TVHT-MCSs for TVHT_MODE_1, NSS = 2 3180
Table 22-28—TVHT-MCSs for TVHT_MODE_1, NSS = 3 3180
Table 22-29—TVHT-MCSs for TVHT_MODE_1, NSS = 4 3181
Table 22-30—TVHT-MCSs for TVHT_MODE_2C and TVHT_MODE_2N, NSS = 1 3181
Table 22-31—TVHT-MCSs for TVHT_MODE_2C and TVHT_MODE_2N, NSS = 2 3182
Table 22-32—TVHT-MCSs for TVHT_MODE_2C and TVHT_MODE_2N, NSS = 3 3182
Table 22-33—TVHT-MCSs for TVHT_MODE_2C and TVHT_MODE_2N, NSS = 4 3183
Table 22-34—TVHT-MCSs for TVHT_MODE_4C and TVHT_MODE_4N, NSS = 1 3183
Table 22-35—TVHT-MCSs for TVHT_MODE_4C and TVHT_MODE_4N, NSS = 2 3184
Table 22-36—TVHT-MCSs for TVHT_MODE_4C and TVHT_MODE_4N, NSS = 3 3184
Table 22-37—TVHT-MCSs for TVHT_MODE_4C and TVHT_MODE_4N, NSS = 4 3185
Table 23-1—TXVECTOR and RXVECTOR parameters 3189
Table 23-2—PPDU format as a function of CH_BANDWIDTH parameter 3197
Table 23-3—Fields of the S1G PPDU 3199
Table 23-4—Timing-related constants 3212
Table 23-5—Timing-related constants for SIG/SIG-A field in ≥ 2 MHz PPDUs 3214
Table 23-6—Frequently used parameters 3215
Table 23-7—Tone scaling factor and guard interval duration values for PHY fields 3219
Table 23-8—CH_BANDWIDTH and Gamma sub$_{k, BW}$ 3221
Table 23-9—Cyclic shift values for the S1G_SHORT preamble PPDU 3223
Table 23-10—Number of LTFs required for different numbers of space-time streams 3224
Table 23-11—Fields in the SIG field of short preamble 3227
Table 23-12—Per antenna cyclic shift values of S1G_LONG preamble PPDU 3231
Table 23-13—Fields in the SIG-A field of S1G_LONG preamble SU PPDU 3234

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 23-14—Fields in the SIG-A field of S1G_LONG preamble MU PPDU 3236
Table 23-15—Per space-time stream cyclic shift values of S1G_LONG preamble PPDU 3238
Table 23-16—Fields in the SIG-B field for MU PPDU 3240
Table 23-17—Cyclic shift values of S1G_1M PPDU 3244
Table 23-18—Fields in the SIG field of S1G_1M PPDU 3247
Table 23-19—SERVICE field 3249
Table 23-20—Number of rows and columns in the interleaver for 1 MHz 3253
Table 23-21—Traveling pilot positions for NSTS=1, 1 MHz S1G PPDU 3255
Table 23-22—Traveling pilot positions for NSTS=1, 2 MHz S1G PPDU 3255
Table 23-23—Traveling pilot positions for NSTS=1, 4 MHz S1G PPDU 3256
Table 23-24—Traveling pilot positions for NSTS=1, 8 MHz S1G PPDU 3256
Table 23-25—Traveling pilot positions for NSTS=2 and STBC=1, 1 MHz S1G PPDU 3257
Table 23-26—Traveling pilot positions for NSTS=2 and STBC=1, 2 MHz S1G PPDU 3257
Table 23-27—Traveling pilot positions for NSTS=2 and STBC=1, 4 MHz S1G PPDU 3258
Table 23-28—Traveling pilot positions for NSTS=2 and STBC=1, 8 MHz S1G PPDU 3258
Table 23-29—NDP CMAC PPDU Type field values 3266
Table 23-30—Preferred MCS subfield values for NDP_1M PS-Poll frame 3269
Table 23-31—Preferred MCS subfield values for NDP_2M PS-Poll frame 3270
Table 23-32—Maximum spectral flatness deviations 3282
Table 23-33—Allowed relative constellation error versus constellation size and coding rate 3285
Table 23-34—Receiver minimum input level sensitivity 3287
Table 23-35—Minimum required adjacent and nonadjacent channel rejection levels 3288
Table 23-37—Additional conditions for CCA BUSY on the primary 2 MHz in type 2 channelization .. 3291
Table 23-36—Additional conditions for CCA BUSY on the primary 2 MHz in type 1 channelization .. 3291
Table 23-38—Additional conditions for CCA BUSY on the primary 2 MHz in type 2 channelization for 8/16 MHz intended channel width 3293
Table 23-39—S1G PHY MIB attributes 3306
Table 23-40—S1G PHY characteristics 3311
Table 23-41—S1G-MCSs for 1 MHz, Nss = 1 3312
Table 23-42—S1G-MCSs for 1 MHz, Nss = 2 3312
Table 23-43—S1G-MCSs for 1 MHz, Nss = 3 3313
Table 23-44—S1G-MCSs for 1 MHz, Nss = 4 3313
Table 23-45—S1G-MCSs for 2 MHz, Nss = 1 3313
Table 23-46—S1G-MCSs for 2 MHz, Nss = 2 3314
Table 23-47—S1G-MCSs for 2 MHz, Nss = 3 3314
Table 23-48—S1G-MCSs for 2 MHz, Nss = 4 3314
Table 23-49—S1G-MCSs for 4 MHz, Nss = 1 3315
Table 23-50—S1G-MCSs for 4 MHz, Nss = 2 3315
Table 23-51—S1G-MCSs for 4 MHz, Nss = 3 3315
Table 23-52—S1G-MCSs for 4 MHz, Nss = 4 3316
Table 23-53—S1G-MCSs for 8 MHz, Nss = 1 3316
Table 23-54—S1G-MCSs for 8 MHz, Nss = 2 3316
Table 23-55—S1G-MCSs for 8 MHz, Nss = 3 3317
Table 23-56—S1G-MCSs for 8 MHz, Nss = 4 3317
Table 23-57—S1G-MCSs for 16 MHz, Nss = 1 3317
Table 23-58—S1G-MCSs for 16 MHz, Nss = 2 3318
Table 23-59—S1G-MCSs for 16 MHz, Nss = 3 3318
Table 23-60—S1G-MCSs for 16 MHz, Nss = 4 3318
Table 24-1—TXVECTOR and RXVECTOR parameters 3320
Table 24-2—TXSTATUS parameters 3322
Table 24-3—Receiver minimum input level sensitivity 3324
Table 24-4—Timing-related parameters 3325
Table 24-5—CDMG control mode modulation and coding scheme 3328
Table 24-1—CDMG control mode header fields 3329

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 24-2—CDMG robust PHY modes 3331
Table 24-3—CDMG SC mode header fields 3332
Table 24-4—CDMG SC mode modulation and coding schemes 3333
Table 24-5—CDMG SC mode EVM requirements 3336
Table 24-6—CDMG low-power SC mode modulation and coding schemes 3338
Table 24-7—Zero filling for SC BRP PPDUs with MCSs 1 to 9 3342
Table 24-1—CDMG PHY MIB attribute default values 3343
Table 24-1—CDMG PHY characteristics 3344
Table 25-1—TXVECTOR and RXVECTOR parameters 3347
Table 25-2—Receiver sensitivity 3351
Table 25-3—Time-related parameters 3352
Table 25-4—Frequently used parameters 3353
Table 25-5—CH_BANDWIDTH and Ƴk,CBW 3356
Table 25-6—Base matrix prototypes for codeword block length nz bits, subblock size is z bits 3363
Table 25-7—Fields in the CMMG SIG field 3364
Table 25-8—Modulation and coding scheme for the CMMG control mode 3370
Table 25-9—The Barker(L) sequences 3371
Table 25-10—EVM requirement for control mode 3373
Table 25-11—Cyclic shift values for the CMMG SIG field 3376
Table 25-12—Values of mSE 3377
Table 25-13—Values of NCBPB 3377
Table 25-14—Values of NDSPB and NUWPB 3380
Table 25-15—Constellation mapper output to spatial mapper input 3381
Table 25-16—EVM requirements for SC mode 3383
Table 25-17—Number of OCEFs required for different numbers of space-time streams 3389
Table 25-18—Modulation-dependent normalization factor 3393
Table 25-19—BPSK encoding table 3393
Table 25-20—QPSK encoding table 3394
Table 25-21—16-QAM encoding table 3394
Table 25-22—64-QAM encoding table 3394
Table 25-23—Value of tone mapping parameter 3396
Table 25-25—Pilot values for CBW540 MHz transmission 3397
Table 25-26—Pilot values for CBW1080 MHz transmission 3397
Table 25-24—Constellation mapper output to spatial mapper input for STBC 3397
Table 25-27—Cyclic shift values for the data fields of an OFDM mode PPDU 3398
Table 25-28—Maximum available space-time streams 3402
Table 25-29—EVM requirements for OFDM 3403
Table 25-30—The sequence set Zi32, i=1,2,3,4 3409
Table 25-31—The sequence set Zi64, i=1,2,3,4 3409
Table 25-32—The sequence set Zi128, i=1,2,3,4 3410
Table 25-33—The sequence set Zi256, i=1,2,3,4 3410
Table 25-34—The sequence set Zi512, i=1,2,3,4 3411
Table 25-35—Fields to specify CMMG channels 3412
Table 25-36—CMMG PHY MIB attributes 3419
Table 25-37—CMMG PHY characteristics 3421
Table 25-38—CMMG SC MCSs for mandatory 540 MHz, Nss=1 3422
Table 25-39—CMMG SC MCSs for optional 540 MHz, Nss=2 (Optional) 3422
Table 25-42—CMMG SC MCSs for mandatory 1080 MHz, Nss=1 3423
Table 25-40—CMMG SC MCSs for optional 540 MHz, Nss=3 (Optional) 3423
Table 25-41—CMMG SC MCSs for optional 540 MHz, Nss=4 (Optional) 3423
Table 25-43—CMMG SC MCSs for optional 1080 MHz, Nss=2 (Optional) 3424
Table 25-44—CMMG SC MCSs for optional 1080 MHz, Nss=3 (Optional) 3424
Table 25-46—CMMG OFDM MCSs for optional 540 MHz, Nss=1 (Optional) 3425
Table 25-45—CMMG SC MCSs for optional 1080 MHz, Nss=4 (Optional) 3425

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table 25-47—CMMG OFDM MCSs for optional 540 MHz, Nss=2 (Optional) 3426
Table 25-48—CMMG OFDM MCSs for optional 540 MHz, Nss=3 (Optional) 3426
Table 25-49—CMMG OFDM MCSs for optional 540 MHz, Nss=4 (Optional) 3426
Table 25-50—CMMG OFDM MCSs for optional 1080 MHz, Nss=1 (Optional) 3427
Table 25-51—CMMG OFDM MCSs for optional 1080 MHz, Nss=2 (Optional) 3427
Table 25-52—CMMG OFDM MCSs for optional 1080 MHz, Nss=3 (Optional) 3428
Table 25-53—CMMG OFDM MCSs for optional 1080 MHz, Nss=4 (Optional) 3428
Table D-1—Regulatory requirement list 4103
Table D-2—Behavior limits 4104
Table D-4—Maximum STA transmit power and maximum BW allowed for the S1G band 4106
Table D-3—Maximum STA transmit power classification for the 5.85–5.925 GHz band in the United States 4106
Table D-5—Spectrum mask data for 5 MHz channel spacing 4107
Table D-6—Spectrum mask data for 10 MHz channel spacing 4107
Table D-7—Spectrum mask data for 20 MHz channel spacing 4108
Table E-1—Operating classes in the United States 4111
Table E-2—Operating classes in Europe 4113
Table E-3—Operating classes in Japan 4114
Table E-4—Global operating classes 4117
Table E-5—S1G operating classes 4121
Table E-6—Operating classes in China 4123
Table E-7—DSE timer limits 4126
Table E-8—TVWS GDD timer limits 4127
Table E-9—Device Identification Information Value fields 4128
Table E-10—WSM Information Value fields 4128
Table E-11—TVWS GDD timer limits 4129
Table F-1—Matrix prototypes for codeword block length n = 648 bits, subblock size is Z = 27 bits 4130
Table F-2—Matrix prototypes for codeword block length n = 1296 bits, subblock size is Z = 54 bits 4131
Table F-3—Matrix prototypes for codeword block length n = 1944 bits, subblock size is Z = 81 bits 4132
Table G-1—Attributes applicable to frame exchange sequence definition 4133
Table H-1—Payload Type field values 4148
Table I-1—The message for the BCC example 4150
Table I-2—Frequency domain representation of the short sequences 4151
Table I-3—One period of IFFT of the short sequences 4151
Table I-4—Time domain representation of the short sequence 4152
Table I-5—Frequency domain representation of the long sequences 4154
Table I-6—Time domain representation of the long sequence 4154
Table I-7—Bit assignment for SIGNAL field 4156
Table I-8—SIGNAL field bits after encoding 4157
Table I-9—SIGNAL field bits after interleaving 4157
Table I-10—Frequency domain representation of SIGNAL field 4158
Table I-11—Frequency domain representation of SIGNAL field with pilots inserted 4158
Table I-12—Time domain representation of SIGNAL field 4159
Table I-13—The DATA bits before scrambling 4160
Table I-14—Scrambling sequence for seed 1011101 4162
Table I-15—The DATA bits after scrambling 4162
Table I-16—The BCC encoded DATA bits 4164
Table I-17—First permutation 4166
Table I-19—Interleaved bits of first DATA symbol 4167
Table I-18—Second permutation 4167
Table I-20—Frequency domain of first DATA symbol 4169
Table I-21—Polarity of the pilot subcarriers 4170
Table I-22—Time domain representation of the short training sequence 4170
Table I-23—Time domain representation of the long training sequence 4172

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Table I-24—Time domain representation of the SIGNAL field (1 symbol) 4173
Table I-25—Time domain representation of the DATA field: symbol 1of 6 4174
Table I-26—Time domain representation of the DATA field: symbol 2 of 6 4174
Table I-27—Time domain representation of the DATA field: symbol 3 of 6 4175
Table I-28—Time domain representation of the DATA field: symbol 4 of 6 4176
Table I-29—Time domain representation of the DATA field: symbol 5 of 6 4177
Table I-30—Time domain representation of the DATA field: symbol 6 of 6 4177
Table I-31—Message for LDPC example 1 4179
Table I-32—DATA bits for LDPC example 1 before scrambling 4180
Table I-33—DATA bits for LDPC example 1 after scrambling 4181
Table I-34—DATA bits for LDPC example 1 after insertion of shortening bits 4183
Table I-35—DATA bits for LDPC example 1 after LDPC encoding 4185
Table I-36—DATA bits after puncturing and removal of shortening bits 4188
Table I-37—Message for LDPC example 2 4190
Table I-38—DATA bits for LDPC example 2 before scrambling 4191
Table I-39—DATA bits for LDPC example 2 after scrambling 4193
Table I-40—DATA bits for LDPC example 2 after insertion of shortening bits 4195
Table I-41—DATA bits for LDPC example 2 after LDPC encoding 4197
Table I-42—DATA bits after removal of shortening bits and copying of repetition bits 4201
Table I-43—DMG control mode header settings 4207
Table I-44—DMG SC control header settings 4211
Table J-1—Test vectors for block function 4233
Table J-2—Test vectors for michael 4234
Table J-3—Notation example 4246
Table J-4—Sample plaintext MPDU 4246
Table J-7—Sample TKIP parameters 4247
Table J-5—ARC4 encryption 4247
Table J-6—Expanded MPDU after WEP encapsulation 4247
Table J-8—Sample plaintext and cipher text MPDUs, using parameter from Table J-7 4248
Table J-9—RSN PRF Test Vector 1 4252
Table J-10—RSN PRF Test Vector 2 4253
Table J-11—RSN PRF Test Vector 3 4253
Table J-12—RSN PRF Test Vector 4 4253
Table J-13—Sample values for pairwise key derivations 4254
Table J-14—Sample derived CCMP-128 temporal key (TK) 4254
Table J-15—Sample derived PTK 4254
Table K-1—Admissible TSPECs 4278
Table K-2—SBA vs Packets/s 4287
Table K-3—HCCA SBA for video streams 4288
Table M-1—EPD and LPD MSDU headers 4307
Table Q-1—Destination URI payload 4327
Table R-1—Suggested default priority code point to UP mapping 4334
Table R-2—Suggested default UP to priority code point mapping 4334
Table R-3—SSPN Interface information or permission parameters 4336
Table S-1—Default parameters for mesh STAs that intend to operate in light or deep sleep mode for mesh peerings 4349

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figures

Figure 1—The evolution of numbering in IEEE Std 802.11 12
Figure 4-1—BSSs 221
Figure 4-2—DSs and APs 222
Figure 4-3—ESS 223
Figure 4-4—A representative signal intensity map 224
Figure 4-5—Collocated coverage areas 225
Figure 4-6—Connecting to other IEEE 802 LANs 225
Figure 4-7—CCSS and ECAPC 227
Figure 4-8—SSPN interface service architecture 242
Figure 4-9—Example MBSS containing mesh STAs, mesh gates, APs, and portals 244
Figure 4-10—Example device consisting of mesh STA and AP STA to connect an MBSS and an infrastructure BSS 245
Figure 4-11—MAC data transport over an MBSS 247
Figure 4-12—DMG relay in a DMG BSS 249
Figure 4-13—Multiple APs and multiple GDBs 251
Figure 4-14—Example of GLK IBSS or PBSS 256
Figure 4-15—Example of infrastructure BSS with general links 258
Figure 4-16—Example of an ESS and extended network with general links 259
Figure 4-17—IEEE 802.11 architecture for infrastructure BSS and PBSS 262
Figure 4-18—IEEE 802.11 Infrastructure model 263
Figure 4-19—Unsolicited PAD architecture 274
Figure 4-20—Solicited PAD architecture 274
Figure 4-21—IEEE 802.11 architecture (again) 277
Figure 4-22—Logical architecture of an IBSS 277
Figure 4-23—Logical architecture of a PBSS 278
Figure 4-24—Portion of the ISO/IEC basic reference model covered in this standard 279
Figure 4-25—Interworking reference model 280
Figure 4-26—ESS link illustration 280
Figure 4-27—Reference model for supporting multiple MAC sublayers 281
Figure 4-28—Reference model for a multi-band capable device (transparent FST) 282
Figure 4-29—Reference model for a multi-band capable device (nontransparent FST) 282
Figure 4-30—Establishing the IEEE 802.11 association 285
Figure 4-31—IEEE 802.1X EAP authentication 285
Figure 4-32—Establishing pairwise and group keys 286
Figure 4-33—Delivery of subsequent group keys 287
Figure 4-34—Example using SAE authentication 287
Figure 4-35—FILS authentication using TTP 289
Figure 4-36—Sample 4-way handshakes in an IBSS 290
Figure 4-37—Example using IEEE 802.1X authentication 292
Figure 4-38—Example of RSNA setup in a PBSS 293
Figure 5-1—MAC data plane architecture 300
Figure 5-2—MAC data plane architecture (transparent FST) 301
Figure 5-3—Role-specific behavior block for a non-GLK non-AP STA 302
Figure 5-4—Role-specific behavior block for a non-GLK AP 302
Figure 5-5—Role-specific behavior block for mesh STA 303
Figure 5-6—Role-specific behavior block for mesh gate 303
Figure 5-7—S1G relay data plane architecture 304
Figure 5-8—Role-specific behavior block for a GLK STA 305
Figure 5-9—Role-specific behavior block for a mixed-mode GLK AP 306
Figure 5-10—Role-specific behavior block for a GLK mesh STA 306
Figure 6-1—GET and SET operations 315

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 6-2—Layer management model 398
Figure 6-3—Measurement request—accepted 399
Figure 6-5—TPC adaptation 399
Figure 6-4—Measurement request—rejected 400
Figure 6-6—Channel switching 400
Figure 6-7—TDLS direct-link establishment 482
Figure 6-8—TDLS direct-link teardown 487
Figure 6-9—TPU 489
Figure 6-10—TDLS channel switching 492
Figure 6-11—TDLS peer PSM 495
Figure 6-12—Event protocol exchange 498
Figure 6-13—Diagnostic protocol exchange 503
Figure 6-14—Location configuration request and response protocol exchange 507
Figure 6-15—Location track notification protocol exchange 510
Figure 6-16—Timing measurement primitives and timestamps capture 512
Figure 6-17—Fine timing measurement primitives and timestamps capture 517
Figure 6-18—BSS transition management request—accepted 525
Figure 6-19—FMS setup protocol exchange 532
Figure 6-20—Collocated interference protocol exchange 536
Figure 6-21—TFS request and response exchange 540
Figure 6-22—WNM sleep mode request and response exchange 543
Figure 6-23—TIM broadcast setup protocol exchange 547
Figure 6-24—QoS traffic capability update protocol exchange 551
Figure 6-25—Channel usage request protocol exchange 553
Figure 6-26—DMS or GCR setup protocol exchange 557
Figure 6-27—Example SCS setup and termination protocol exchange 610
Figure 6-28—Operation of OCT 627
Figure 6-29—MSGCF state machine 713
Figure 7-1—DS architecture 735
Figure 8-1—The channel-list parameter entry for 40 MHz, 80 MHz, and 160 MHz channel width 750
Figure 8-2—The channel-list parameter entry for 80+80 MHz channel width 750
Figure 8-3—TVHT channel-list parameter entry and channel bandwidth for TVHT_W, TVHT_2W, and TVHT_W+W 750
Figure 8-4—TVHT channel-list parameter entry and channel bandwidth for TVHT_4W and TVHT_2W+2W 751
Figure 8-5—The channel-list parameter entries for the 1 MHz, 2 MHz, 4 MHz, 8 MHz, and 16 MHz channel width 751
Figure 9-1—Representation of a 48-bit MAC address 756
Figure 9-2—MAC frame format 757
Figure 9-3—Frame Control field format in non-S1G PPDUs when Type subfield is not equal to 1 or Subtype subfield is not equal to 6 758
Figure 9-4—Frame Control field format in non-S1G PPDUs when Type subfield is equal to 1 and Subtype subfield is equal to 6 758
Figure 9-5—Frame Control field format in S1G PPDUs when Type subfield is equal to 0 or 2 759
Figure 9-6—Frame Control field format when Type subfield is equal to 3 and Subtype subfield is equal to 1 759
Figure 9-7—Sequence Control field format 770
Figure 9-8—Sequence Number field format in QMFs 770
Figure 9-9—QoS AP PS Buffer State subfield format 775
Figure 9-10—Buffered AC subfield format 777
Figure 9-11—Non-CMMG variant HT Control field format 777
Figure 9-12—HT Control Middle subfield of the HT variant HT Control field format 778
Figure 9-13—Link Adaptation Control subfield format 779

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-14—MAI subfield format 779
Figure 9-15—ASELC subfield format 780
Figure 9-16—HT Control Middle subfield of the VHT variant HT Control field format 782
Figure 9-17—MSI/STBC subfield format when the Unsolicited MFB subfield is 1 783
Figure 9-18—MFB subfield format in the VHT variant HT Control field 783
Figure 9-19—MFB subfield format in the VHT variant HT Control field when carried in S1G PPDU 784
Figure 9-20—CMMG variant HT Control field format 785
Figure 9-21—MFB subfield in the CMMG variant HT Control field format 786
Figure 9-22—MSI/STBC subfield format when the Unsolicited MFB subfield is 1 786
Figure 9-23—Mesh Control field format 789
Figure 9-24—Mesh Flags subfield format 789
Figure 9-25—Mesh Address Extension subfield format 790
Figure 9-26—Frame Control field subfield values within Control frames carried in a non-S1G PPDU 796
Figure 9-27—Frame Control field format in Control frames carried in an S1G PPDU when Subtype subfield is not equal to 3 and not equal to 10 796
Figure 9-28—Frame Control field format in Control frames carried in an S1G PPDU when Subtype subfield is equal to 3 797
Figure 9-29—Frame Control field format in Control frames carried in an S1G PPDU when Subtype subfield is equal to 10 797
Figure 9-30—RTS frame format 797
Figure 9-31—CTS frame format 798
Figure 9-32—Ack frame format 798
Figure 9-33—PS-Poll frame format 799
Figure 9-34—CF-End frame format 799
Figure 9-35—BlockAckReq frame format 800
Figure 9-36—BAR Control field format 800
Figure 9-37—Block Ack Starting Sequence Control subfield format 801
Figure 9-38—BAR Information field format (Multi-TID BlockAckReq) 802
Figure 9-39—Per TID Info subfield format 802
Figure 9-41—BlockAck frame format 803
Figure 9-42—BA Control field format 803
Figure 9-40—BAR Information field format (GCR BlockAckReq) 803
Figure 9-43—BA Information field format (Compressed BlockAck) 805
Figure 9-44—BA Information field format (Multi-TID BlockAck) 805
Figure 9-45—BA Information field format (Extended Compressed BlockAck) 806
Figure 9-46—BA Information field format (GCR BlockAck) 806
Figure 9-47—BA Information field format (GLK-GCR BlockAck) 807
Figure 9-48—Control Wrapper frame format 807
Figure 9-49—Poll frame format 808
Figure 9-50—SPR frame format 808
Figure 9-51—Grant frame format 809
Figure 9-52—DMG CTS frame format 809
Figure 9-53—DMG DTS frame format 810
Figure 9-54—SSW frame format 810
Figure 9-55—SSW-Feedback frame format 811
Figure 9-56—SSW-Ack frame format 811
Figure 9-57—Grant Ack frame format 812
Figure 9-58—VHT NDP Announcement frame format 812
Figure 9-59—Sounding Dialog Token field format 813
Figure 9-60—STA Info field format in a non-S1G STA 813
Figure 9-62—Beamforming Report Poll frame format 814
Figure 9-63—TACK frame format 814
Figure 9-61—STA Info field format in an S1G STA 814

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-64—Next TWT Info/Suspend Duration field format 815
Figure 9-65—Data frame format 815
Figure 9-66—Format of an RA field carrying a SYNRA 817
Figure 9-67—Basic SYNRA Control subfield format 818
Figure 9-69—Basic A-MSDU subframe structure 820
Figure 9-68—A-MSDU structure 820
Figure 9-71—Short A-MSDU subframe structure 821
Figure 9-72—Dynamic A-MSDU subframe structure 821
Figure 9-70—A-MSDU subframe structure for Mesh Data 821
Figure 9-74—Management frame format 822
Figure 9-73—Subframe Control field format 822
Figure 9-75—Extension frame format 857
Figure 9-76—DMG Beacon frame format 857
Figure 9-77—Beacon Interval Control field format 860
Figure 9-78—Clustering Control field format if the Discovery Mode field is 0 862
Figure 9-79—Clustering Control field format if the Discovery Mode field is 1 862
Figure 9-80—S1G Beacon frame format 863
Figure 9-82—Authentication Algorithm Number field format 867
Figure 9-83—Authentication Transaction Sequence Number field format 867
Figure 9-81—Example addressing for a mesh Data frame 867
Figure 9-84—Beacon Interval field format 868
Figure 9-85—Capability Information field format (non-DMG STA) 868
Figure 9-86—Capability Information field format (DMG STA) 868
Figure 9-87—Current AP Address field format 870
Figure 9-88—Listen Interval field format carried in a non-S1G PPDU 870
Figure 9-89—Listen Interval field format carried in an S1G PPDU 870
Figure 9-90—Reason Code field format 871
Figure 9-91—AID field format 874
Figure 9-92—Status Code field format 875
Figure 9-93—Timestamp field format 880
Figure 9-94—Action field format 880
Figure 9-95—Dialog Token field format 882
Figure 9-96—Block Ack Parameter Set field format 882
Figure 9-97—Block Ack Timeout Value field format 883
Figure 9-98—Originator Preferred MCS field format 883
Figure 9-99—DELBA Parameter Set field format 884
Figure 9-100—QoS Info field format when sent by an AP 884
Figure 9-102—Measurement Pilot Interval field format 885
Figure 9-101—QoS Info field format when set by a non-AP STA 885
Figure 9-103—Max Transmit Power field format 886
Figure 9-104—Transmit Power Used field format 886
Figure 9-105—Channel Width field 886
Figure 9-106—Operating Class and Channel field format 887
Figure 9-107—SM Power Control field format 887
Figure 9-108—PSMP Parameter Set field format 888
Figure 9-109—PSMP STA Info field format (group addressed) 888
Figure 9-110—PSMP STA Info field format (individually addressed) 889
Figure 9-111—MIMO Control field format 890
Figure 9-112—CSI matrix coding 893
Figure 9-113—V matrix coding (noncompressed beamforming) 895
Figure 9-114—First example of Compressed Beamforming Report field encoding 897
Figure 9-116—Antenna Selection Indices field format 898
Figure 9-117—Organization Identifier field format 898

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-115—Second example of Compressed Beamforming Report field encoding 898
Figure 9-118—Identification field format 899
Figure 9-119—Mask field format 899
Figure 9-120—MCS Index field format when the MCS Selector field is 3, 4, 5, or 6 900
Figure 9-121—GAS Query Response Fragment ID field format 901
Figure 9-122—Venue Info field format 901
Figure 9-123—Target Channel field format 904
Figure 9-124—Operating Class field format 904
Figure 9-125—Send-Confirm field format 904
Figure 9-126—Anti-Clogging Token field format 905
Figure 9-127—Scalar field format 905
Figure 9-128—FFE field format 905
Figure 9-129—Confirm field format 905
Figure 9-130—Finite Cyclic Group field format 906
Figure 9-131—TXOP Reservation field format 906
Figure 9-132—Relay Capable STA Info field format 906
Figure 9-133—DMG Parameters 907
Figure 9-134—VHT MIMO Control field format 908
Figure 9-135—Operating Mode field format when it is carried in a non-S1G PPDU 926
Figure 9-136—Operating Mode field format when it is carried in an S1G PPDU 927
Figure 9-137—Membership Status Array field format 930
Figure 9-138—User Position Array field format 930
Figure 9-139—Device Location Information Body field format 931
Figure 9-140—Sync Control field format 932
Figure 9-141—Suspend Duration field format 932
Figure 9-142—TWT Information field format 933
Figure 9-143—CMMG MIMO Control field format 934
Figure 9-144—CMMG Operating Mode field format 939
Figure 9-145—Element format 940
Figure 9-146—SSID element format 949
Figure 9-147—Supported Rates and BSS Membership Selectors element format 950
Figure 9-148—DSSS Parameter Set element format 951
Figure 9-149—TIM element format 951
Figure 9-150—Bitmap Control field format when TIM is carried in a non-S1G PPDU 952
Figure 9-151—Bitmap Control field format when TIM is carried in an S1G PPDU 952
Figure 9-152—Hierarchical structure of traffic-indication virtual bitmap carried in an S1G PPDU 953
Figure 9-153—Partial Virtual Bitmap field format 955
Figure 9-154—Encoded Block subfield format 955
Figure 9-155—Block Control subfield format 955
Figure 9-156—Encoded Block Information (Block Bitmap mode) 956
Figure 9-157—Encoded Block Information (Single AID mode) 956
Figure 9-158—Encoded Block Information (OLB mode) 957
Figure 9-159—Encoded Block Information (ADE Block) 957
Figure 9-160—IBSS Parameter Set element format 959
Figure 9-161—Challenge Text element format 959
Figure 9-162—Country element format 959
Figure 9-165—Triplet field format if dot11OperatingClassRequired is true 960
Figure 9-166—Format of m-th Operating/Subband Sequence field 960
Figure 9-163—Subband Triplet Sequence format 960
Figure 9-164—Subband Triplet field format 960
Figure 9-167—Request element format 962
Figure 9-168—Extended Request element format 962
Figure 9-169—ERP element format 963

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-170—ERP Parameters field format 963
Figure 9-171—Extended Supported Rates and BSS Membership Selectors element format 964
Figure 9-172—Power Constraint element format 964
Figure 9-173—Power Capability element format 965
Figure 9-174—TPC Request element format 965
Figure 9-175—TPC Report element format 966
Figure 9-176—Supported Channels element format 966
Figure 9-177—Channel Switch Announcement element format 967
Figure 9-178—Secondary Channel Offset element format 967
Figure 9-179—Measurement Request element format 968
Figure 9-180—Measurement Request Mode field format 969
Figure 9-181—Measurement Request field format for a Basic request 970
Figure 9-182—Measurement Request field format for a CCA request 971
Figure 9-183—Measurement Request field format for an RPI Histogram request 971
Figure 9-184—Measurement Request field format for Channel Load request 972
Figure 9-185—Channel Load Reporting subelement Data field format 973
Figure 9-186—Measurement Request field format for Noise Histogram request 973
Figure 9-187—Noise Histogram Reporting subelement Data field format 974
Figure 9-188—Measurement Request field format for Beacon request 975
Figure 9-189—Beacon Reporting subelement Data field format 977
Figure 9-190—Measurement Request field format for Frame request 979
Figure 9-191—Measurement Request field format for STA Statistics request 980
Figure 9-192—Triggered Reporting subelement format for STA Counters 982
Figure 9-193—STA Counter Trigger Condition field format 982
Figure 9-194—Triggered Reporting subelement format for QoS STA Counters 983
Figure 9-195—QoS STA Counter Trigger Condition field format 983
Figure 9-196—Triggered Reporting subelement format for RSNA Counters 984
Figure 9-197—RSNA Trigger Condition field format 984
Figure 9-198—Measurement Request field format for LCI request 985
Figure 9-199—Azimuth Request subelement format 986
Figure 9-200—Azimuth Request field format 986
Figure 9-201—Originator Requesting STA MAC Address subelement format 986
Figure 9-202—Target MAC Address subelement format 987
Figure 9-203—Maximum Age subelement format 987
Figure 9-204—Measurement Request field format for Transmit Stream/Category Measurement Request 987
Figure 9-205—Traffic Identifier field format 988
Figure 9-206—Triggered Reporting subelement format 988
Figure 9-207—Triggered Reporting field format 989
Figure 9-208—Trigger Conditions bit-field format 989
Figure 9-209—Delay Threshold subfield format 990
Figure 9-210—Measurement Request field format for Measurement Pause request 990
Figure 9-211—Measurement Request field format for a Multicast Diagnostics request 991
Figure 9-212—Multicast Triggered Reporting subelement format 992
Figure 9-213—Multicast Trigger Condition field format 992
Figure 9-214—Location Civic Request field format 993
Figure 9-215—Location Identifier request field format 994
Figure 9-216—Measurement Request field format for Directional Channel Quality request 995
Figure 9-217—Directional Channel Quality Reporting subelement Data field format 996
Figure 9-218—Measurement Request field format for Directional Measurement request 997
Figure 9-219—Measurement Request field format for Directional Statistics request 998
Figure 9-221—Measurement Request field format for a Fine Timing Measurement Range request 999
Figure 9-220—Directional Statistics Bitmap field format 999

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-222—Measurement Report element format 1001
Figure 9-223—Measurement Report Mode field format 1001
Figure 9-224—Measurement Report field format for a Basic report 1003
Figure 9-225—Map field format 1003
Figure 9-226—Measurement Report field format for a CCA report 1004
Figure 9-227—Measurement Report field format for an RPI histogram report 1004
Figure 9-228—Measurement Report field format for Channel Load report 1005
Figure 9-229—Measurement Report field format for Noise Histogram report 1007
Figure 9-230—Measurement Report field format for Beacon report 1009
Figure 9-231—Reported Frame Information field format 1009
Figure 9-232—Data field format 1011
Figure 9-233—Measurement Report field format for Frame report 1012
Figure 9-234—Frame Count Report subelement format 1013
Figure 9-235—Frame Report Entry field format 1013
Figure 9-236—Measurement Report field format for STA Statistics report 1014
Figure 9-237—Measurement Report field format for dot11Counters Group 1019
Figure 9-238—Measurement Report field format for dot11MACStatistics Group 1019
Figure 9-239—Measurement Report field format for dot11QosCounters Group for UPx 1020
Figure 9-240—Measurement Report field format for dot11BSSAverageAccessDelay Group 1020
Figure 9-241—Measurement Report field format for RSNA Counters Group 1021
Figure 9-242—Data field format of the Reporting Reason subelement for STA Counters 1022
Figure 9-243—Data field format of the Reporting Reason subelement for QoS STA Counters 1022
Figure 9-244—Data field format of the Reporting Reason subelement for RSNA Counters 1022
Figure 9-245—Format of Location Configuration Information Report 1023
Figure 9-246—LCI subelement format 1023
Figure 9-247—LCI field format 1024
Figure 9-248—Azimuth Report subelement format 1025
Figure 9-249—Azimuth Report subfield format 1026
Figure 9-250—Z subelement format 1026
Figure 9-251—STA Floor Info field format 1026
Figure 9-252—Relative Location Error subelement format 1027
Figure 9-253—Relative Location Error field format 1028
Figure 9-254—Usage Rules/Policy subelement format 1028
Figure 9-255—Usage Rules/Policy Parameters field format 1028
Figure 9-256—Co-Located BSSID List subelement format 1029
Figure 9-257—Measurement Report field format for Transmit Stream/Category Measurement report 1030
Figure 9-258—Reporting Reason field format 1030
Figure 9-259—Measurement Report field format for a Multicast Diagnostics report 1033
Figure 9-260—Multicast Reporting Reason field format 1033
Figure 9-261—Location Civic report field format 1035
Figure 9-262—Location Civic subelement format 1036
Figure 9-263—Location Reference subelement format 1037
Figure 9-264—Location Shape subelement format 1037
Figure 9-265—2-Dimension Point Location Shape Value format 1038
Figure 9-266—3-Dimension Point Location Shape Value format 1038
Figure 9-267—Circle Location Shape Value format 1038
Figure 9-268—Sphere Location Shape Value format 1039
Figure 9-269—Polygon Location Shape Value format 1039
Figure 9-270—Prism Location Shape Value format 1039
Figure 9-271—Ellipse Location Shape Value format 1039
Figure 9-272—Ellipsoid Location Shape Value format 1040
Figure 9-273—Arcband Location Shape Value format 1040
Figure 9-274—Map Image subelement format 1041

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-275—Location Identifier report field format 1042
Figure 9-276—Public Identifier URI/FQDN subelement format 1042
Figure 9-277—Measurement report field format for Directional Channel Quality report 1044
Figure 9-278—Measurement Report field format for Directional Measurement report 1045
Figure 9-279—Measurement Results field format 1045
Figure 9-280—Measurement Report field format for Directional Statistics report 1046
Figure 9-281—Measurement Report field format for a Fine Timing Measurement Range report 1047
Figure 9-282—Range Entry field format 1048
Figure 9-283—Error Entry field format 1048
Figure 9-284—Quiet element format 1049
Figure 9-285—IBSS DFS element format 1050
Figure 9-286—Channel Map field format 1050
Figure 9-287—RSNE format 1051
Figure 9-288—Suite selector format 1053
Figure 9-289—RSN Capabilities field format 1058
Figure 9-290—Vendor Specific element format 1060
Figure 9-291—Extended Capabilities element format 1061
Figure 9-292—BSS Load element format 1067
Figure 9-293—EDCA Parameter Set element format 1068
Figure 9-294—Update EDCA Info field format 1068
Figure 9-295—AC_BE, AC_BK, AC_VI, and AC_VO Parameter Record field format 1069
Figure 9-296—ACI/AIFSN field format 1069
Figure 9-297—ECWmin/ECWmax field format 1069
Figure 9-298—TSPEC element format 1071
Figure 9-299—TS Info field format 1072
Figure 9-300—Nominal MSDU Size field format 1074
Figure 9-301—DMG Attributes field format 1077
Figure 9-302—TCLAS element format 1078
Figure 9-303—Frame Classifier field format 1079
Figure 9-304—Frame Classifier field format of Classifier Type 0 1083
Figure 9-305—Frame Classifier field format of Classifier Type 1 for traffic over IPv4 1083
Figure 9-306—Frame Classifier field format of Classifier Type 1 for traffic over IPv6 1083
Figure 9-307—Frame Classifier field format of Classifier Type 2 1083
Figure 9-308—Frame Classifier field format of Classifier Type 3 1084
Figure 9-309—Frame Classifier subfield format of Classifier Type 4 for traffic over IPv4 1085
Figure 9-310—Frame Classifier subfield format of Classifier Type 4 for traffic over IPv6 1085
Figure 9-311—Frame Classifier field format of Classifier Type 5 1086
Figure 9-312—Frame Classifier field format of Classifier Type 6 1086
Figure 9-313—Frame Control Match Specification subfield format of Classifier Type 6, 7, 8, 9 1087
Figure 9-314—Duration/ID Match Specification subfield format of Classifier Type 6 1087
Figure 9-315—Address 1 Match Specification subfield format of Classifier Type 6, 8, 9 1087
Figure 9-316—Address 2 Match Specification subfield format of Classifier Type 6, 7, 9 1087
Figure 9-317—Address 3 Match Specification subfield format of Classifier Type 6, 7, 8 1087
Figure 9-318—Sequence Control Match Specification subfield format of Classifier Type 6, 7, 8, 9 1087
Figure 9-319—Address 4 Match Specification subfield format of Classifier Type 6, 7, 8 1087
Figure 9-322—Frame Classifier field format of Classifier Type 7 1088
Figure 9-323—Address 1 (SID) Match Specification subfield format of Classifier Type 7 1088
Figure 9-320—QoS Control Match Specification subfield format of Classifier Type 6 1088
Figure 9-321—HT Control Match Specification subfield format of Classifier Type 6 1088
Figure 9-324—Frame Classifier field format of Classifier Type 8 1089
Figure 9-325—Address 2 (SID) Match Specification subfield format of Classifier Type 8 1089
Figure 9-326—Frame Classifier field format of Classifier Type 9 1089
Figure 9-327—Frame Classifier field format of Classifier Type 10 for packets using IPV4 or IPV6 1090

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-328—IPv4 packet example for Classifier Type 10 1091
Figure 9-329—IPv6 packet example for Classifier Type 10 1091
Figure 9-330—TS Delay element format 1092
Figure 9-331—TCLAS Processing element format 1092
Figure 9-332—Schedule element format 1093
Figure 9-333—Schedule Info field format 1093
Figure 9-334—QoS Capability element format 1094
Figure 9-335—AP Channel Report element format 1094
Figure 9-336—Neighbor Report element format 1094
Figure 9-337—BSSID Information field format 1095
Figure 9-338—Capabilities subfield format 1095
Figure 9-339—TSF subelement format 1097
Figure 9-340—BSS Transition Candidate Preference subelement format 1098
Figure 9-341—BSS Termination Duration subelement format 1099
Figure 9-342—Bearing subelement format 1099
Figure 9-343—Wide Bandwidth Channel subelement format 1100
Figure 9-344—RCPI element format 1101
Figure 9-345—BSS Average Access Delay element format 1101
Figure 9-346—Antenna element format 1102
Figure 9-347—RSNI element format 1103
Figure 9-348—Measurement Pilot Transmission element format 1103
Figure 9-349—BSS Available Admission Capacity element format 1104
Figure 9-350—BSS AC Access Delay element format 1105
Figure 9-351—Access Category Access Delay subfield format 1106
Figure 9-352—RM Enabled Capabilities element format 1107
Figure 9-353—Multiple BSSID element format 1110
Figure 9-354—Mobility Domain element format 1112
Figure 9-355—FT Capability and Policy field format 1112
Figure 9-356—FTE format 1112
Figure 9-357—MIC Control field format 1113
Figure 9-358—Optional Parameter(s) field format 1113
Figure 9-359—GTK subelement format 1114
Figure 9-360—GTK subelement's Key Info subfield format 1114
Figure 9-361—IGTK subelement format 1114
Figure 9-362—OCI subelement format 1115
Figure 9-363—BIGTK subelement format 1115
Figure 9-364—TIE format 1116
Figure 9-365—RDE format 1116
Figure 9-366—RIC Descriptor element format 1117
Figure 9-367—DSE Registered Location element format 1117
Figure 9-368—DSE Registered Location Information field format 1118
Figure 9-369—Extended Channel Switch Announcement element format 1119
Figure 9-370—Supported Operating Classes element format 1119
Figure 9-371—Current Operating Class Extension Sequence field format 1120
Figure 9-372—Operating Class Duple Sequence field format 1120
Figure 9-373—Management MIC element format 1121
Figure 9-374—HT Capabilities element format 1121
Figure 9-375—HT Capability Information field format 1122
Figure 9-376—A-MPDU Parameters field format 1124
Figure 9-377—Supported MCS Set field format 1124
Figure 9-378—HT Extended Capabilities field format 1125
Figure 9-379—Transmit Beamforming Capabilities field format 1126
Figure 9-380—ASEL Capability field format 1129

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-381—HT Operation element format 1129
Figure 9-382—HT Operation Information field format 1130
Figure 9-383—20/40 BSS Intolerant Channel Report element format 1133
Figure 9-384—Overlapping BSS Scan Parameters element format 1134
Figure 9-385—20/40 BSS Coexistence element format 1134
Figure 9-386—20/40 BSS Coexistence Information field format 1135
Figure 9-387—Time Advertisement element format 1135
Figure 9-388—Link Identifier element format 1137
Figure 9-389—Wakeup Schedule element format 1137
Figure 9-390—Channel Switch Timing element format 1138
Figure 9-391—PTI Control element format 1138
Figure 9-393—TPU Buffer Status Information field format 1139
Figure 9-394—Event Request element format 1139
Figure 9-392—TPU Buffer Status element format 1139
Figure 9-395—Transition Target BSSID subelement format 1141
Figure 9-396—Transition Source BSSID subelement format 1141
Figure 9-397—Transition Time Threshold subelement format 1141
Figure 9-398—Transition Result subelement format 1142
Figure 9-399—Match Value field definitions 1142
Figure 9-400—Frequent Transition subelement format 1142
Figure 9-401—RSNA Target BSSID subelement format 1143
Figure 9-402—Authentication Type subelement format 1143
Figure 9-403—EAP Method subelement format 1144
Figure 9-404—RSNA Result subelement format 1144
Figure 9-405—Match Value field definitions 1144
Figure 9-406—Peer Address subelement format 1145
Figure 9-407—Channel Number subelement format 1145
Figure 9-408—Event Report element format 1146
Figure 9-409—Event Report format for Transition event 1147
Figure 9-410—Event Report format for RSNA event 1149
Figure 9-411—Event Report format for peer-to-peer link event 1150
Figure 9-412—Event Report format for WNM log event 1151
Figure 9-413—Diagnostic Request element format 1151
Figure 9-414—Diagnostic subelement format 1153
Figure 9-415—Credential Type subelement format 1154
Figure 9-416—AKM Suite subelement format 1155
Figure 9-417—AP Descriptor subelement format 1155
Figure 9-418—Antenna Type subelement format 1155
Figure 9-419—Cipher Suite subelement format 1156
Figure 9-420—Collocated Radio Type subelement format 1156
Figure 9-421—Device Type subelement format 1157
Figure 9-422—EAP Method subelement format 1158
Figure 9-423—Firmware Version subelement format 1158
Figure 9-424—MAC Address subelement format 1158
Figure 9-425—Manufacturer ID String subelement format 1159
Figure 9-426—Manufacturer Model String subelement format 1159
Figure 9-427—Manufacturer OI subelement format 1159
Figure 9-428—Manufacturer Serial Number String subelement format 1159
Figure 9-429—Power Save Mode subelement format 1159
Figure 9-430—Profile ID subelement format 1160
Figure 9-431—Supported Operating Classes subelement format 1160
Figure 9-432—Status Code subelement format 1161
Figure 9-433—SSID subelement format 1161

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-434—Tx Power Capability subelement format 1161
Figure 9-435—Certificate ID subelement format 1162
Figure 9-436—Diagnostic Report element format 1162
Figure 9-437—Location Parameters element format 1164
Figure 9-438—Location Indication Parameters subelement format 1165
Figure 9-439—Location Indication Channels subelement format 1167
Figure 9-440—Location Status subelement format 1168
Figure 9-441—Radio subelement format 1168
Figure 9-442—Motion subelement format 1169
Figure 9-443—Location Indication Broadcast Data Rate subelement format 1170
Figure 9-444—Time of Departure subelement format 1171
Figure 9-445—Location Indication Options subelement format 1171
Figure 9-446—Options Used field format 1172
Figure 9-447—Nontransmitted BSSID Capability element format (non-DMG STA) 1172
Figure 9-448—Nontransmitted BSSID Capability element format (DMG STA) 1172
Figure 9-449—DMG BSS Control field format 1173
Figure 9-450—SSID List element format 1173
Figure 9-451—Multiple BSSID-Index element format 1173
Figure 9-452—FMS Descriptor element format 1174
Figure 9-453—FMS Counter field format 1174
Figure 9-454—FMS Request element format 1175
Figure 9-455—FMS subelement format 1175
Figure 9-456—FMS Response element format 1176
Figure 9-457—FMS Status subelement format 1177
Figure 9-458—TCLAS Status subelement format 1178
Figure 9-459—QoS Traffic Capability element format 1179
Figure 9-460—BSS Max Idle Period element format 1180
Figure 9-461—Idle Options field format 1180
Figure 9-462—TFS Request element format 1181
Figure 9-463—TFS subelement format 1182
Figure 9-464—TFS Request Vendor Specific subelement format 1182
Figure 9-465—TFS Response element format 1183
Figure 9-466—TFS Status subelement format 1183
Figure 9-467—TFS Response Vendor Specific subelement format 1184
Figure 9-468—WNM Sleep Mode element format 1184
Figure 9-469—TIM Broadcast Request element format 1185
Figure 9-470—TIM Broadcast Response element format 1186
Figure 9-471—Collocated Interference Report element format 1187
Figure 9-472—Interference Level Accuracy/Interference Index field format 1187
Figure 9-473—Channel Usage element format 1189
Figure 9-474—Time Zone element format 1189
Figure 9-475—DMS Request element format 1190
Figure 9-476—DMS Descriptor format 1190
Figure 9-477—GCR Request subelement format 1192
Figure 9-478—DMS Response element format 1193
Figure 9-479—DMS Status field format 1193
Figure 9-480—GCR Response subelement format 1195
Figure 9-481—Destination URI element format 1195
Figure 9-482—U-APSD Coexistence element format 1196
Figure 9-483—Interworking element format 1197
Figure 9-484—Access Network Options field format 1197
Figure 9-485—Advertisement Protocol element format 1199
Figure 9-486—Advertisement Protocol Tuple field format 1199

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-487—Query Response Info field format 1199
Figure 9-489—QoS Map element format 1201
Figure 9-488—Expedited Bandwidth Request element format 1201
Figure 9-490—DSCP Exception format 1202
Figure 9-491—DSCP Range description 1202
Figure 9-492—Roaming Consortium element format 1202
Figure 9-493—OI #1 and #2 Lengths field format 1203
Figure 9-494—Emergency Alert Identifier element format 1203
Figure 9-495—Mesh Configuration element format 1204
Figure 9-496—Mesh Formation Info field format 1207
Figure 9-497—Mesh Capability field format 1207
Figure 9-498—Mesh ID element format 1208
Figure 9-499—Mesh Link Metric Report element format 1208
Figure 9-500—Flags field format 1208
Figure 9-501—Congestion Notification element format 1209
Figure 9-502—Mesh Peering Management element format 1209
Figure 9-503—Mesh Channel Switch Parameters element format 1211
Figure 9-504—Flags field format 1211
Figure 9-505—Mesh Awake Window element format 1212
Figure 9-506—Beacon Timing element format 1212
Figure 9-507—Report Control field format 1212
Figure 9-508—Beacon Timing Information field format 1213
Figure 9-509—MCCAOP Setup Request element format 1213
Figure 9-510—MCCAOP Reservation field format 1214
Figure 9-511—MCCAOP Setup Reply element format 1214
Figure 9-512—MCCAOP Advertisement Overview element format 1215
Figure 9-513—Flags field format 1215
Figure 9-514—MCCAOP Advertisement element format 1216
Figure 9-515—MCCAOP Advertisement Element Information field format 1217
Figure 9-516—MCCAOP Reservation Report field format 1217
Figure 9-517—MCCAOP Teardown element format 1218
Figure 9-518—GANN element format 1218
Figure 9-519—RANN element format 1219
Figure 9-520—Flags field format 1219
Figure 9-521—PREQ element format 1220
Figure 9-522—Flags field format 1220
Figure 9-523—Target Tuple field format 1221
Figure 9-524—Per Target Flags field format 1221
Figure 9-525—PREP element format 1222
Figure 9-526—Flags field format 1222
Figure 9-527—PERR element format 1223
Figure 9-528—Destination Tuples field format 1224
Figure 9-529—Flags field format 1224
Figure 9-530—PXU element format 1225
Figure 9-531—Proxy Information field format 1225
Figure 9-532—Flags subfield format 1225
Figure 9-533—PXUC element format 1226
Figure 9-534—Authenticated Mesh Peering Exchange element format 1227
Figure 9-535—MIC element format 1227
Figure 9-536—QMF Policy element format 1228
Figure 9-537—QACM field format 1228
Figure 9-538—QACM Header subfield format 1228
Figure 9-539—Intra-Access Category Priority element format 1229

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-540—Intra-Access Priority field format 1229
Figure 9-541—SCS Descriptor element format 1230
Figure 9-542—QLoad Report element format 1231
Figure 9-543—QLoad field format 1233
Figure 9-544—HCCA TXOP Update Count element format 1233
Figure 9-545—Higher Layer Stream ID element format 1234
Figure 9-546—GCR Group Address element format 1234
Figure 9-547—DMG BSS Parameter Change element format 1235
Figure 9-548—Change Type Bitmap field format 1235
Figure 9-549—DMG Capabilities element format 1235
Figure 9-550—DMG STA Capability Information field format 1236
Figure 9-551—A-MPDU parameters subfield format 1237
Figure 9-552—Supported MCS Set subfield format 1238
Figure 9-553—DMG AP Or PCP Capability Information field format 1239
Figure 9-554—Extended SC MCS Capabilities field format 1240
Figure 9-555—DMG Operation element format 1242
Figure 9-557—DMG BSS Parameter Configuration field format 1243
Figure 9-556—DMG Operation Information field format 1243
Figure 9-558—DMG Beam Refinement element format 1244
Figure 9-559—FBCK-REQ field format 1244
Figure 9-560—FBCK-TYPE field format 1245
Figure 9-561—DMG Wakeup Schedule element format 1246
Figure 9-562—Extended Schedule element format 1247
Figure 9-563—Allocation field format 1247
Figure 9-564—Allocation Control subfield format (DMG) 1247
Figure 9-565—Allocation Control subfield format (CDMG) 1247
Figure 9-566—STA Availability element format 1250
Figure 9-567—STA Info field format 1250
Figure 9-568—DMG TSPEC element format 1251
Figure 9-569—DMG Allocation Info field format 1251
Figure 9-570—Traffic Scheduling Constraint Set field format 1253
Figure 9-571—Constraint subfield format 1253
Figure 9-572—Constraint subfield format for CMMG STAs 1254
Figure 9-573—Interferer Channel Bandwidth subfield format 1254
Figure 9-574—Next DMG ATI element format 1255
Figure 9-575—Awake Window element format 1258
Figure 9-576—Multi-band element format 1258
Figure 9-577—Multi-band Control field format 1258
Figure 9-578—Multi-band Connection Capability field format 1260
Figure 9-579—ADDBA Extension element format 1260
Figure 9-580—ADDBA Capabilities field format 1261
Figure 9-581—Next PCP List element format 1261
Figure 9-582—PCP Handover element format 1261
Figure 9-583—DMG Link Margin element format 1262
Figure 9-584—DMG Link Adaptation Acknowledgment element format 1263
Figure 9-586—Switching Parameters field format 1264
Figure 9-585—Switching Stream element format 1264
Figure 9-587—Session Transition element format 1265
Figure 9-588—Session Control field format 1265
Figure 9-589—Cluster Report element format 1266
Figure 9-590—Cluster Report Control field format 1267
Figure 9-591—Relay Capabilities element format 1268
Figure 9-592—Relay Capability Information field format 1268

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-593—Relay Transfer Parameter Set element format 1269
Figure 9-594—Relay Transfer Parameter field format 1269
Figure 9-595—Quiet Period Request element format 1270
Figure 9-596—Quiet Period Response element format 1271
Figure 9-597—BeamLink Maintenance element format 1271
Figure 9-598—MMS element format 1271
Figure 9-599—MMS Control field format 1272
Figure 9-600—U-PID element format 1273
Figure 9-601—ECAPC Policy element format 1274
Figure 9-602—ECAPC Policy Detail field format 1274
Figure 9-603—Cluster Time Offset element format 1275
Figure 9-604—Antenna Sector ID Pattern element format 1275
Figure 9-605—Sequence Generator 1 1276
Figure 9-606—Sequence Generator 2 1277
Figure 9-607—VHT Capabilities element format 1277
Figure 9-608—VHT Capabilities Information field format 1278
Figure 9-609—Supported Channel Width Set field format (TVHT) 1281
Figure 9-610—Supported VHT-MCS and NSS Set field format 1282
Figure 9-611—Rx VHT-MCS Map and Tx VHT-MCS Map subfields and Basic VHT-MCS And NSS Set field format 1284
Figure 9-612—VHT Operation element format 1284
Figure 9-613—VHT Operation Information field format 1284
Figure 9-614—Extended BSS Load element format 1286
Figure 9-616—Transmit Power Envelope element format 1288
Figure 9-617—Transmit Power Information field format 1288
Figure 9-615—Wide Bandwidth Channel Switch element format 1288
Figure 9-618—Channel Switch Wrapper element format 1290
Figure 9-619—AID element format 1291
Figure 9-620—Quiet Channel element format 1291
Figure 9-621—Operating Mode Notification element format 1292
Figure 9-622—UPSIM element format 1292
Figure 9-623—UPSIM Flags field format 1292
Figure 9-624—Fine Timing Measurement Parameters element format 1293
Figure 9-625—Fine Timing Measurement Parameters field format 1293
Figure 9-626—Calculation of the value of the Partial TSF Timer subfield 1296
Figure 9-627—Device Location element format 1297
Figure 9-628—WSM element format 1297
Figure 9-629—Reduced Neighbor Report element format 1298
Figure 9-630—Neighbor AP Information field format 1298
Figure 9-631—TBTT Information Header subfield format 1298
Figure 9-632—TBTT Information field (format 1299
Figure 9-633—TVHT Operation element format 1300
Figure 9-634—TVHT Operation Information field format 1300
Figure 9-635—FTM Synchronization Information element format 1301
Figure 9-636—Estimated Service Parameters Inbound element format 1302
Figure 9-637—ESP Information field format 1302
Figure 9-638—Future Channel Guidance element format 1304
Figure 9-639—Association Delay Info element format 1304
Figure 9-640—CAG Number element format 1305
Figure 9-641—CAG Tuple field 1305
Figure 9-642—FILS Request Parameters element format 1306
Figure 9-643—Parameter Control Bitmap field format 1306
Figure 9-644—FILS Criteria field format 1307

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-645—FILS Key Confirmation element format 1308
Figure 9-646—FILS Session element format 1309
Figure 9-647—FILS Public Key element format 1309
Figure 9-648—AP-CSN element format 1309
Figure 9-649—FILS Indication element format 1310
Figure 9-650—FILS Information field format 1310
Figure 9-651—Realm Identifier field format 1311
Figure 9-652—Public Key Identifier field format 1311
Figure 9-654—FILS IP Address Assignment element format 1312
Figure 9-655—IP Address Data field format for request 1312
Figure 9-653—FILS HLP Container element format 1312
Figure 9-656—IP Address Request Control subfield format 1313
Figure 9-657—IP Address Data field format for response 1314
Figure 9-658—DNS Info Control subfield format 1315
Figure 9-659—Key Delivery element format 1316
Figure 9-661—DILS Flags field format 1317
Figure 9-662—FILS User Priority field format 1317
Figure 9-663—MAC Address Filter field format 1317
Figure 9-660—DILS element format 1317
Figure 9-664—FILS Wrapped Data element format 1318
Figure 9-665—Fragment element format 1319
Figure 9-666—FILS Nonce element format 1319
Figure 9-667—S1G Open-Loop Link Margin Index element format 1319
Figure 9-668—RPS element format 1320
Figure 9-669—RAW Assignment subfield format 1320
Figure 9-670—RAW Control subfield format 1321
Figure 9-671—RAW Slot Definition subfield format 1323
Figure 9-672—RAW Group subfield format 1324
Figure 9-673—Channel Indication subfield format 1324
Figure 9-674—Periodic Operation Parameters subfield format 1325
Figure 9-675—Page Slice element format 1325
Figure 9-676—Page Slice Control field format 1325
Figure 9-677—AID Request element format 1327
Figure 9-678—AID Request Mode field format 1328
Figure 9-679—Service Characteristic field format 1329
Figure 9-680—AID Response element format 1329
Figure 9-681—S1G Sector Operation element format (sectorization type is group sectorization) 1330
Figure 9-682—S1G Sector Operation element format (sectorization type is TXOP-based sectorization operation) 1332
Figure 9-683—S1G Beacon Compatibility element format 1332
Figure 9-684—Short Beacon Interval element format 1333
Figure 9-685—Change Sequence element format 1333
Figure 9-686—TWT element format 1333
Figure 9-687—Control field format 1334
Figure 9-688—Request Type field format 1334
Figure 9-689—TWT Group Assignment field format 1336
Figure 9-690—NDP Paging field format 1338
Figure 9-691—S1G Capabilities element format 1339
Figure 9-692—S1G Capabilities Information field format 1340
Figure 9-693—Supported S1G-MCS and NSS Set field format 1347
Figure 9-694—Rx S1G-MCS Map and Tx S1G-MCS Map subfields and Basic S1G-MCS and NSS Set field format 1349
Figure 9-695—Subchannel Selective Transmission element format 1349

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-696—Channel Activity Schedule subfield format (Sounding Option = 0) 1349
Figure 9-697—Channel Activity Schedule subfield format (Sounding Option = 1) 1350
Figure 9-698—Authentication Control element format (Control subfield equal to 0) 1351
Figure 9-699—Centralized Authentication Control Parameters format 1352
Figure 9-700—Authentication Control element format (Control subfield equal to 1) 1352
Figure 9-701—Distributed Authentication Control Parameters format 1352
Figure 9-702—TSF Timer Accuracy element format 1353
Figure 9-703—S1G Relay element format 1353
Figure 9-704—Relay Control field format 1353
Figure 9-705—Reachable Address element format 1354
Figure 9-706—Reachable Address subfield format 1354
Figure 9-707—S1G Relay Activation element format 1355
Figure 9-708—Relay Function field format 1355
Figure 9-709—S1G Relay Discovery element format 1356
Figure 9-710—UL/DL Data Rate field format 1356
Figure 9-711—Relay Discovery Control field format 1357
Figure 9-712—AID Announcement element format 1358
Figure 9-713—AID Entry field format 1358
Figure 9-714—PV1 Probe Response Option element format 1358
Figure 9-715—EL Operation element format 1362
Figure 9-716—Sectorized Group ID List element format 1363
Figure 9-717—S1G Operation element format 1363
Figure 9-718—S1G Operation Information field format 1363
Figure 9-719—Basic S1G-MCS and NSS Set field format 1364
Figure 9-720—Header Compression element format 1365
Figure 9-721—Header Compression Control field format 1365
Figure 9-722—CCMP Update field format 1366
Figure 9-723—BPN subfield format 1366
Figure 9-724—SST Operation element format 1366
Figure 9-725—MAD element format 1367
Figure 9-726—Password Identifier element format 1367
Figure 9-728—Extended Request element format 1368
Figure 9-729—Request Tuple field format 1368
Figure 9-727—Max Channel Switch Time element format 1368
Figure 9-730—CDMG Capabilities element format 1369
Figure 9-731—CDMG STA Capability Information field format 1369
Figure 9-732—Supported MCS Set subfield format 1369
Figure 9-733—CDMG AP Or PCP Capability Information field format 1370
Figure 9-734—Dynamic Bandwidth Control element format 1371
Figure 9-735—DBC Control field format 1371
Figure 9-736—CDMG Extended Schedule element format 1372
Figure 9-737—Allocation field format 1372
Figure 9-738—BF Control field format when both IsInitiatorTXSS and IsResponderTXSS subfields are equal to 1 and the BF Control field is transmitted in Grant or Grant Ack frames 1373
Figure 9-739—BF Control field format in all other cases 1373
Figure 9-740—SSW Report element format 1374
Figure 9-741—Report Info field format when the SSW Report Control subfield is 1 1374
Figure 9-742—Report Info field format when the SSW Report Control subfield is 0 1374
Figure 9-743—Cluster Probe element format 1375
Figure 9-744—Extended Cluster Report element format 1376
Figure 9-745—Cluster Switch Announcement element format 1376
Figure 9-746—Enhanced Beam Tracking element format 1377
Figure 9-747—E-BT Control field format 1377

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-748—Peer TX Antenna Parameter field format ... 1378
Figure 9-750—SPSH List field format ... 1379
Figure 9-749—SPSH Report element format ... 1379
Figure 9-752—Clustering SPSH Control field format ... 1380
Figure 9-753—CMMG Capabilities element format ... 1380
Figure 9-751—Clustering Interference Assessment element format ... 1380
Figure 9-754—CMMG Capabilities Info field format ... 1381
Figure 9-755—A-MPDU Parameters field format ... 1385
Figure 9-756—Supported CMMG-MCS and NSS Set field format ... 1385
Figure 9-757—Rx CMMG-MCS Map and Tx CMMG-MCS Map subfields and Basic CMMG-MCS and NSS Set field format ... 1386
Figure 9-758—Transmit Beamforming Capabilities field format ... 1387
Figure 9-760—CMMG Operation element format ... 1389
Figure 9-759—CMMG AP Or PCP Capability Information field format ... 1389
Figure 9-761—CMMG Operation Information field format ... 1390
Figure 9-762—CMMG Operating Mode Notification element format ... 1390
Figure 9-763—CMMG Link Margin element format ... 1391
Figure 9-764—CMMG Link Adaptation Acknowledgment element format ... 1392
Figure 9-765—GLK-GCR Parameter Set element format ... 1392
Figure 9-766—GLK-GCR Parameters field format ... 1393
Figure 9-767—Estimated Service Parameters Outbound element format ... 1394
Figure 9-768—Outbound Air Time Bitmap field format ... 1394
Figure 9-769—Outbound Air Time Information field format ... 1394
Figure 9-770—OCI element format ... 1395
Figure 9-771—Service Hint element format ... 1395
Figure 9-772—Bloom Filter Information field format ... 1396
Figure 9-773—Service Hash element format ... 1397
Figure 9-774—GAS Extension element format ... 1397
Figure 9-775—GAS Flags field format ... 1397
Figure 9-776—Response Map Duple subfield format ... 1398
Figure 9-777—Non-Inheritance element format ... 1398
Figure 9-778—List Of Element IDs field format ... 1399
Figure 9-779—List Of Element ID Extensions field format ... 1399
Figure 9-780—RSNXE format ... 1399
Figure 9-781—TCLAS Mask element format ... 1400
Figure 9-782—MSCS Descriptor element format ... 1400
Figure 9-783—User Priority Control field format ... 1401
Figure 9-784—Supplemental Class 2 Capabilities element format ... 1402
Figure 9-785—Class 2 Supplemental Rates Set field format ... 1402
Figure 9-787—Rejected Groups element format ... 1403
Figure 9-788—Anti-Clogging Token Container element format ... 1403
Figure 9-786—OCT Source element format ... 1403
Figure 9-789—Subelement format ... 1404
Figure 9-790—ANQP-element format ... 1409
Figure 9-791—Query List ANQP-element format ... 1410
Figure 9-792—Capability List ANQP-element format ... 1411
Figure 9-793—Venue Name ANQP-element format ... 1411
Figure 9-794—Venue Name Tuple subfield ... 1412
Figure 9-795—Emergency Call Number ANQP-element format ... 1412
Figure 9-796—Emergency Call Number Duple subfield format ... 1412
Figure 9-797—Network Authentication Type ANQP-element format ... 1413
Figure 9-798—Network Authentication Type Tuple subfield format ... 1413
Figure 9-799—Roaming Consortium ANQP-element format ... 1414

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-800—OI Duple subfield format 1414
Figure 9-801—Vendor Specific ANQP-element format 1415
Figure 9-802—IP Address Type Availability ANQP-element 1415
Figure 9-803—IP Address field format 1415
Figure 9-804—NAI Realm ANQP-element format 1416
Figure 9-805—NAI Realm Tuple subfield format 1417
Figure 9-806—NAI Realm Encoding subfield format 1417
Figure 9-807—EAP Method Tuple subfield format 1417
Figure 9-808—Authentication Parameter subfield format 1418
Figure 9-809—3GPP Cellular Network ANQP-element format 1420
Figure 9-810—AP Geospatial Location ANQP-element format 1420
Figure 9-811—AP Civic Location ANQP-element format 1421
Figure 9-812—AP Location Public Identifier URI/FQDN ANQP-element format 1421
Figure 9-813—Domain Name ANQP-element format 1421
Figure 9-814—Domain Name Duple subfield format 1422
Figure 9-815—Emergency Alert URI ANQP-element format 1422
Figure 9-816—Emergency NAI ANQP-element format 1422
Figure 9-817—TDLS Capability ANQP-element format 1423
Figure 9-818—Neighbor Report ANQP-element format 1423
Figure 9-819—Venue URL ANQP-element format 1423
Figure 9-820—Venue URL Duple field 1424
Figure 9-821—Advice of Charge ANQP-element format 1424
Figure 9-822—Advice of Charge Duple field 1424
Figure 9-823—Plan Information Tuple field format 1425
Figure 9-824—Local Content ANQP-element format 1425
Figure 9-825—Local Content Duple field format 1426
Figure 9-826—Network Authentication Type with Timestamp ANQP-element format 1427
Figure 9-827—Network Authentication Timestamp Tuple subfield format 1427
Figure 9-828—Query AP List ANQP-element format 1427
Figure 9-829—AP List field format 1428
Figure 9-830—AP List Response ANQP-element format 1428
Figure 9-831—AP Response Tuple field format 1428
Figure 9-832—CAG ANQP-element format 1429
Figure 9-833—Service Information Request ANQP-element format 1429
Figure 9-834—Service Information Request Tuple subfield format 1429
Figure 9-835—Service Information Response ANQP-element format 1430
Figure 9-836—Service Information Response Tuple subfield format 1430
Figure 9-837—Local MAC Address Policy ANQP-element format 1431
Figure 9-838—Restricted Address Prefix subfield format 1432
Figure 9-839—Address Prefix Control subfield format 1432
Figure 9-840—RLQP-element format 1433
Figure 9-841—Channel Availability Query RLQP-element format 1434
Figure 9-842—Channel Query Info field format 1435
Figure 9-843—Channel Schedule Management RLQP-element format 1435
Figure 9-844—Network Channel Control RLQP-element format 1436
Figure 9-845—Vendor Specific RLQP-element format 1437
Figure 9-846—SSW field format 1437
Figure 9-847—Dynamic Allocation Info field format 1438
Figure 9-848—SSW Feedback field format when transmitted as part of an ISS 1439
Figure 9-849—SSW Feedback field format when not transmitted as part of an ISS 1439
Figure 9-850—BRP Request field format 1440
Figure 9-851—BF Control field format when both IsInitiatorTXSS and IsResponderTXSS subfields are equal to 1 and the BF Control field is transmitted in Grant or Grant Ack frames 1441

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-852—BF Control field format in all other cases 1441
Figure 9-853—Beamformed Link Maintenance field format 1442
Figure 9-854—Spectrum Measurement Request frame Action field format 1444
Figure 9-855—Spectrum Measurement Report frame Action field format 1444
Figure 9-856—TPC Request frame Action field format 1445
Figure 9-857—TPC Report frame Action field format 1445
Figure 9-858—Channel Switch Announcement frame Action field format 1446
Figure 9-859—Vendor Specific frame Action field format 1458
Figure 9-860—Radio Measurement Request frame Action field format 1459
Figure 9-861—Radio Measurement Report frame Action field format 1460
Figure 9-862—Link Measurement Request frame Action field format 1460
Figure 9-863—Link Measurement Report frame Action field format 1461
Figure 9-864—Neighbor Report Request frame Action field format 1462
Figure 9-865—Neighbor Report Response frame Action field format 1463
Figure 9-866—Measurement Pilot frame Action field format 1465
Figure 9-867—Condensed Capability Information field 1466
Figure 9-868—DSE Enablement frame Action field format 1467
Figure 9-869—DSE Deenablement frame Action field format 1468
Figure 9-870—DSE Registered Location Announcement frame Action field format 1468
Figure 9-871—Extended Channel Switch Announcement frame Action field format 1469
Figure 9-872—DSE Measurement Request frame Action field format 1470
Figure 9-873—DSE Measurement Report frame Action field format 1470
Figure 9-874—DSE LCI field format 1471
Figure 9-876—Vendor Specific Public Action frame Action field format 1472
Figure 9-875—DSE Power Constraint frame Action field format 1472
Figure 9-877—Query Request Length field 1473
Figure 9-878—Query Request field 1474
Figure 9-879—GAS Comeback Delay field format 1475
Figure 9-880—Query Response Length field format 1475
Figure 9-881—Query Response field format 1475
Figure 9-882—Location Track Notification frame Action field format 1479
Figure 9-883—QMF Policy frame Action field contents 1480
Figure 9-884—QMF Policy Change frame Action field contents 1480
Figure 9-885—HCCA TXOP Advertisement frame Action field format 1482
Figure 9-886—HCCA TXOP Response frame Action field format 1482
Figure 9-887—Public Key frame Action field format 1483
Figure 9-888—Channel Availability Query frame Action field format 1484
Figure 9-889—Channel Schedule Management frame Action field format 1485
Figure 9-890—Contact Verification Signal frame Action field format 1486
Figure 9-891—GDD Enablement Request frame Action field format 1487
Figure 9-892—GDD Enablement Response frame Action field format 1487
Figure 9-893—Network Channel Control frame Action field format 1488
Figure 9-894—White Space Map Announcement frame Action field format 1489
Figure 9-895—Fine Timing Measurement Request frame Action field format 1489
Figure 9-896—Fine Timing Measurement frame Action field format 1490
Figure 9-897—Format of the TOD Error field 1490
Figure 9-898—Format of the TOA Error field 1490
Figure 9-899—FILS Discovery Information field format 1494
Figure 9-900—FILS Discovery Frame Control subfield format 1495
Figure 9-901—FD Capability subfield format 1496
Figure 9-902—FD RSN Information subfield format 1498
Figure 9-903—Mobility Domain subfield format 1499
Figure 9-904—DCS Measurement Request frame Action field format 1500

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-905—DCS Channel Measurement Request subelement format 1501
Figure 9-906—DCS Measurement Response frame Action field format 1501
Figure 9-907—DCS Channel Measurement Report subelement format 1502
Figure 9-908—DCS Request frame Action field format 1503
Figure 9-909—DCS Response frame Action field format 1504
Figure 9-910—FT Request frame Action field format 1509
Figure 9-911—FT Response frame Action field format 1510
Figure 9-912—FT Confirm frame Action field format 1511
Figure 9-913—FT Ack frame Action field format 1511
Figure 9-914—SA Query Request frame Action field format 1513
Figure 9-915—SA Query Response frame Action field format 1513
Figure 9-916—Event Request frame Action field format 1529
Figure 9-917—Event Report frame Action field format 1530
Figure 9-918—Diagnostic Request frame Action field format 1530
Figure 9-919—Diagnostic Report frame Action field format 1531
Figure 9-920—Location Configuration Request frame Action field format 1531
Figure 9-921—Location Configuration Response frame Action field format 1532
Figure 9-922—BSS Transition Management Query frame Action field format 1533
Figure 9-923—BSS Transition Management Request frame Action field format 1534
Figure 9-924—Request Mode field format 1534
Figure 9-925—Disassociation Timer field format 1535
Figure 9-926—Session Information URL field format 1535
Figure 9-927—BSS Transition Management Response frame Action field format 1536
Figure 9-928—FMS Request frame Action field format 1537
Figure 9-929—FMS Response frame Action field format 1537
Figure 9-930—Collocated Interference Request frame Action field format 1538
Figure 9-931—Request Info field format 1538
Figure 9-932—Collocated Interference Report frame Action field format 1539
Figure 9-933—TFS Request frame Action field format 1539
Figure 9-934—TFS Response frame Action field format 1540
Figure 9-935—TFS Notify frame Action field format 1540
Figure 9-937—WNM Sleep Mode Request frame Action field format 1541
Figure 9-936—TFS Notify Response frame Action field format 1541
Figure 9-939—WNM Sleep Mode GTK subelement format 1542
Figure 9-938—WNM Sleep Mode Response frame Action field format 1542
Figure 9-940—WNM Sleep Mode IGTK subelement format 1543
Figure 9-941—WNM Sleep Mode BIGTK subelement format 1543
Figure 9-942—TIM Broadcast Request frame Action field format 1544
Figure 9-943—TIM Broadcast Response frame Action field format 1544
Figure 9-944—QoS Traffic Capability Update frame Action field format 1545
Figure 9-945—Channel Usage Request frame Action field format 1545
Figure 9-946—Channel Usage Response frame Action field format 1546
Figure 9-947—DMS Request frame Action field format 1547
Figure 9-948—DMS Response frame Action field format 1547
Figure 9-949—Timing Measurement Request frame Action field format 1548
Figure 9-950—WNM Notification Request frame Action field format 1548
Figure 9-951—WNM Notification Response frame Action field format 1549
Figure 9-952—TIM frame Action field format 1550
Figure 9-953—Timing Measurement frame Action field format 1551
Figure 9-954—SCS Request frame Action field format 1566
Figure 9-955—SCS Response frame Action field format 1566
Figure 9-956—SCS Status duple format 1566
Figure 9-957—Group Membership Request frame Action field format 1567

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 9-958—Group Membership Response frame Action field format ... 1567
Figure 9-959—MSCS Request frame Action field format ... 1568
Figure 9-960—MSCS Response frame Action field format ... 1568
Figure 9-961—Channel Measurement Info field format ... 1576
Figure 9-962—Relay Operation Type field format ... 1583
Figure 9-963—Definition of the OCT MMPDU Descriptor field ... 1588
Figure 9-964—FILS Container frame Action field format ... 1593
Figure 9-965—TWT Flow field format ... 1598
Figure 9-966—Sector ID Index format ... 1600
Figure 9-967—Receive Sector Bitmap format ... 1600
Figure 9-968—Notification Period Request frame Action field format ... 1607
Figure 9-969—Channel Splitting Request frame Action field format ... 1608
Figure 9-970—CDMG Allocation Request frame Action field format ... 1609
Figure 9-971—A-MPDU format ... 1612
Figure 9-972—EOF Padding field format ... 1612
Figure 9-973—A-MPDU subframe format ... 1613
Figure 9-974—MPDU delimiter (non-DMG) ... 1613
Figure 9-975—MPDU delimiter (DMG) ... 1613
Figure 9-976—MPDU Length field format (non-DMG) ... 1614
Figure 9-977—MPDU delimiter CRC calculation ... 1615
Figure 9-978—PV1 frame format) ... 1619
Figure 9-979—Frame Control field format ... 1619
Figure 9-980—SID field format ... 1622
Figure 9-981—Frame Control field subfield values within PV1 Control frames ... 1623
Figure 9-983—BAT frame format ... 1624
Figure 9-982—STACK frame format ... 1624
Figure 9-984—Starting Sequence Control field format ... 1625
Figure 9-985—PV1 Management frame format ... 1625
Figure 9-986—PV1 Probe Response frame format ... 1627
Figure 9-987—Frame Control field of PV1 Probe Response frame format ... 1628
Figure 9-988—Resource Allocation frame format when Slot Assignment Mode field is 0 ... 1628
Figure 9-989—Resource Allocation frame format when Slot Assignment Mode field is 1 ... 1628
Figure 9-990—Slot Assignment Indication field for MU group when Slot Assignment Mode field is 0 and the Group Indicator field is 1 ... 1629
Figure 9-991—Slot Assignment Indication field for a STA when Slot Assignment Mode is 0 and the Group Indicator field is 0 ... 1629
Figure 9-992—Slot Assignment Indication field when Slot Assignment Mode field is 1 ... 1629
Figure 9-993—Frame Control field format for Resource Allocation frame ... 1629
Figure 10-1—Non-DMG non-CMMG non-S1G STA MAC architecture ... 1631
Figure 10-2—S1G STA MAC architecture ... 1632
Figure 10-3—DMG STA and CMMG STA architecture ... 1633
Figure 10-4—Fragmentation ... 1639
Figure 10-5—Some IFS relationships ... 1644
Figure 10-6—RTS/CTS/data/Ack and NAV setting ... 1649
Figure 10-7—Data/Ack with RID setting ... 1652
Figure 10-8—RTS/CTS with fragmented MSDU ... 1653
Figure 10-9—RTS/CTS with transmitter priority and missed acknowledgment ... 1654
Figure 10-10—Example of dual CTS mechanism (STBC initiator) ... 1659
Figure 10-11—Example of dual CTS mechanism (non-STBC initiator) ... 1659
Figure 10-12—Individually addressed data/Ack/BlockAck frame ... 1660
Figure 10-13—Example of TXOP containing VHT MU PPDU transmission with immediate acknowledgment to VHT MU PPDU ... 1664

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 10-14—Example of TXOP containing VHT MU PPDU transmission with no immediate acknowledgment to VHT MU PPDU 1664
Figure 10-15—Example of exponential increase of CW 1673
Figure 10-16—Basic access method 1674
Figure 10-17—Backoff procedure 1675
Figure 10-18—Example topology of NAV setting in DMG STAs 1676
Figure 10-19—Backoff procedure for DMG STAs 1676
Figure 10-20—Transmission of a fragmented MSDU using SIFS 1678
Figure 10-21—DCF timing relationships 1681
Figure 10-22—Illustration of dynamic AID assignment 1731
Figure 10-23—Reference implementation model when dot11AlternateEDCAActivated is false or not present 1738
Figure 10-24—Reference implementation model when dot11AlternateEDCAActivated is true 1739
Figure 10-25—EDCA mechanism timing relationships 1743
Figure 10-26—Illustration of TXOP sharing and PPDU construction (DL MU-MIMO) 1747
Figure 10-27—Illustration of TXOP sharing and PPDU construction (non-A-MPDUs) 1748
Figure 10-28—Example of TXOP truncation 1752
Figure 10-29—CAP periods 1757
Figure 10-30—Polled TXOP 1760
Figure 10-31—Restricted Access Window (RAW) 1769
Figure 10-32—Illustration of the RAW slot assignment procedure (RAW not restricted to STAs whose AID bits in the TIM element are equal to 1) 1770
Figure 10-33—Illustration of the RAW slot assignment procedure (RAW restricted to STAs whose AID bits in the TIM element are equal to 1) 1771
Figure 10-34—Backoff procedure for restricted channel access control 1772
Figure 10-35—Example MCCAOP reservation with MCCAOP Periodicity equal to 2 1776
Figure 10-36—HT-immediate block ack architecture 1791
Figure 10-37—Example of frame exchange with GCR block ack retransmission policy 1803
Figure 10-38—DMG block ack architecture 1804
Figure 10-39—Flow control and its associated parameters as a function of receiver buffer size 1805
Figure 10-40—Example of the element fragmentation without Element ID Extension 1818
Figure 10-41—Example of the element fragmentation with Element ID Extension 1818
Figure 10-42—Illustration of PSMP sequence with and without PSMP recovery 1825
Figure 10-43—PSMP burst 1826
Figure 10-44—PSMP burst showing resource allocation 1827
Figure 10-45—PSMP burst showing retransmission and resource allocation 1827
Figure 10-46—Example PPDU exchange for unidirectional implicit transmit beamforming 1843
Figure 10-47—Example PPDU exchange for bidirectional implicit transmit beamforming 1844
Figure 10-48—Calibration procedure with sounding PPDU containing an MPDU 1846
Figure 10-49—Calibration procedure with NDP 1847
Figure 10-50—Calibration procedure with NDP when STA B supports transmitting sounding PPDUs for which only one channel dimension can be estimated (i.e., a single column of the MIMO channel matrix) 1848
Figure 10-51—Transmit ASEL 1858
Figure 10-52—Receive ASEL 1859
Figure 10-53—Example of the sounding protocol with a single VHT beamformee 1865
Figure 10-54—Example of the sounding protocol with more than one VHT beamformee 1866
Figure 10-55—Example of access periods within a beacon interval 1878
Figure 10-56—Example of access periods within a beacon interval for CMMG STAs 1879
Figure 10-57—Example of frame exchanges during the ATI 1880
Figure 10-58—The guard time 1888
Figure 10-59—An example of creating a CDMG protected period on two channels for CDMG STAs 1893
Figure 10-60—Example of dynamic allocation of service period mechanism 1897

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 10-61—Opportunistic transmission in alternative channels for CDMG STAs 1907
Figure 10-62—Decentralized AP or PCP clustering for 3 APs and PCPs 1910
Figure 10-63—Example of a decentralized AP or PCP cluster on a 1.08 GHz channel 1921
Figure 10-64—Example of decentralized clusters for two APs or PCPs of a synchronization pair 1921
Figure 10-65—Example of joining the CDMG AP or PCP cluster for a CDMG AP or PCP involved in a synchronization pair with another AP or PCP 1922
Figure 10-66—Example of spatial sharing with interference mitigation among multiple BSSs 1930
Figure 10-67—An example of beamforming training 1931
Figure 10-68—An example of SLS 1934
Figure 10-69—An example of SLS 1935
Figure 10-70—Initiator TXSS or initiator RXSS 1936
Figure 10-71—Responder TXSS or responder RXSS 1938
Figure 10-72—Example of beam refinement transaction 1942
Figure 10-73—Example of BRP setup subphase procedure (SLS in BTI and A-BFT) 1945
Figure 10-74—Example of skipping the BRP setup subphase (SLS in DTI) 1945
Figure 10-75—A-BFT structure 1948
Figure 10-76—SSW slot (aSSSlotTime) definition 1948
Figure 10-77—Example of time allocation for the MIDC subphase with MID and BC subphases 1953
Figure 10-78—Example of time allocation for the MIDC subphase with the MID subphase only 1954
Figure 10-79—Example of using BRP setup subphase to set up subsequent MIDC subphase in A-BFT and DTI 1954
Figure 10-80—Example of using BRP setup subphase to set up subsequent MIDC subphase in DTI 1955
Figure 10-81—Conceptual flow of sample MIDC subphase execution with MID and BC subphases for initiator link 1956
Figure 10-82—Examples of using MID Extension field during execution of MID subphase 1958
Figure 10-83—Beam combining 1959
Figure 10-84—Conceptual flow of sample MIDC subphase execution with only MID subphase for initiator link 1959
Figure 10-85—Example of using BRP setup subphase to set up subsequent R-MID subphase 1960
Figure 10-86—Example beam refinement transaction (receive training) 1962
Figure 10-87—Example beam refinement transaction (transmit training) 1962
Figure 10-88—Example beam refinement transaction (combination of receive and transmit training) 1963
Figure 10-89—Example of beam tracking procedure with initiator requesting TRN-R 1965
Figure 10-90—Example of beam tracking procedure with initiator requesting TRN-T 1965
Figure 10-91—SLS phase state machine (initiator) 1967
Figure 10-92—SLS phase state machine (responder) 1967
Figure 10-93—Example of an enhanced beam tracking procedure with the initiator requesting TRN-R 1969
Figure 10-94—Example of an enhanced beam tracking procedure with the initiator requesting TRN-T 1970
Figure 10-95—Example of fast link adaptation procedure 1972
Figure 10-96—Example of Normal mode operation with FD-AF relay 1977
Figure 10-97—Example of operation with HD-DF relay 1978
Figure 10-98—TPA mechanism 1979
Figure 10-99—Example of data transmission in SP with link cooperation relay 1981
Figure 10-100—Example of PRAW operation 1997
Figure 10-101—Example of uplink sync frame transmission procedure in RAW 2000
Figure 10-102—Example of BDT exchange 2002
Figure 10-103—Page slicing with Page Slice element with 4 TIMs 2003
Figure 10-104—Selective Subchannel Transmission channel transmission permission allocation for SST element 2006
Figure 10-105—Sectorized BSS operation 2011
Figure 10-106—SO frame exchange sequence 1 2013
Figure 10-107—SO frame exchange sequence 2 2014
Figure 10-108—SO frame exchange sequence 3 2015

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 10-109—SO frame exchange sequence 4 2016
Figure 10-110—CTS-to-self preceding SO frame exchange sequence 2016
Figure 10-111—Sector training 2018
Figure 10-112—S1G relay architecture 2020
Figure 10-113—EL STA operation 2034
Figure 10-114—Example of an AP or PCP that starts its infrastructure BSS or PBSS on channel 35 by transmitting DMG Beacon frames on both channel 2 and channel 35 2037
Figure 10-115—Example of a CDMG AP or PCP that starts its infrastructure BSS or PBSS on channel 35 by transmitting DMG Beacon frames on channel 2 only 2037
Figure 10-116—Two APs or PCPs with NPs arranged consecutively 2041
Figure 10-117—Two APs or PCPs with BHIs arranged apart from each other 2041
Figure 10-118—Service cessation for an AP or PCP on channel 35 2041
Figure 10-119—Moving TBTT by a neighboring AP or PCP on channel 2 2042
Figure 10-120—AP or PCP operating on channel 35 with independent beacon interval expanding the operating bandwidth to channel 2 2044
Figure 10-121—AP or PCP operating on channel 35 without independent beacon interval expanding the operating bandwidth to channel 2 2044
Figure 10-122—SPs or CBAPs allocated for DMG STAs on channel 2 with beacon intervals starting on channel 35 2045
Figure 10-123—SPs or CBAPs allocated for DMG STAs on channel 2 without starting a beacon interval on channel 35 2046
Figure 10-124—SPs or CBAPs allocated for DMG STAs on channel 2 with beacon intervals starting on channels 35 and 36 2046
Figure 10-125—SPs or CBAPs allocated for DMG STAs on channel 2 without starting a beacon interval on channels 35 and 36 2046
Figure 11-1—Beacon transmission on a busy network 2051
Figure 11-2—Example of DMG beacon transmission by an AP or PCP during the BTI 2053
Figure 11-3—Beacon transmission in an IBSS 2055
Figure 11-4—Active scanning by a non-DMG STA with a probe request addressed to a specific BSSID 2063
Figure 11-5—Active scanning by a non-DMG STA with a probe request addressed to wildcard BSSID 2063
Figure 11-6—Active scanning for DMG STAs 2065
Figure 11-7—NDP probing procedure 2069
Figure 11-8—Example of a probe request addressed to an individual address 2071
Figure 11-9—PCP factor for a DMG STA 2072
Figure 11-10—PCP factor for a CDMG STA operating on a 1.08 GHz channel 2072
Figure 11-11—Infrastructure power management operation 2083
Figure 11-12—Power management in an IBSS—basic operation 2110
Figure 11-13—State transition diagram of non-AP and non-PCP STA in active and PS modes 2116
Figure 11-14—State transition diagram of PCP power management mode 2120
Figure 11-15—Example operation of PPS mode 2122
Figure 11-16—Example of ATIM frame response behavior in PS mode 2123
Figure 11-17—Relationship between state and services between a given pair of nonmesh STAs 2127
Figure 11-18—TS life cycle 2151
Figure 11-19—TS setup 2152
Figure 11-20—TS setup when initiated by the AP 2153
Figure 11-21—Failed TS setup detected within non-AP STA's MLME 2158
Figure 11-22—TS deletion 2160
Figure 11-23—Deletion of a TS established using a PTP TSPEC 2161
Figure 11-24—Deletion of an allocation in which both Source AID and Destination AID are not the broadcast AID 2161
Figure 11-25—TS timeout 2164

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 11-26—Block ack setup 2167
Figure 11-27—Block ack deletion 2170
Figure 11-28—Error recovery by the receiver upon a peer failure 2171
Figure 11-29—Example of Measurement Pilot frame scheduling 2220
Figure 11-30—Dependent STA state machine 2227
Figure 11-31—Events occurring for a TDLS direct-link channel switch 2251
Figure 11-32—STA transmission on three channels, three frames per channel with Normal Report Interval 2265
Figure 11-33—Timing measurement procedure 2268
Figure 11-34—Concurrent FTM sessions 2270
Figure 11-35—Example negotiation and measurement exchange sequence, ASAP=0, and FTMs Per Burst = 2 2274
Figure 11-36—Example negotiation and measurement exchange sequence, ASAP=1, and FTMs Per Burst = 2 2275
Figure 11-37—Example negotiation and measurement exchange sequence for a single burst instance, ASAP=1, and FTMs Per Burst = 3 2276
Figure 11-38—GAS frame sequence with dot11GASPauseForServerResponse equal to true 2309
Figure 11-39—GAS frame sequence with GAS fragmentation and dot11GASPauseForServerResponse equal to true 2309
Figure 11-40—GAS frame sequence with GAS fragmentation and dot11GASPauseForServerResponse equal to false 2310
Figure 11-41—Group addressed GAS Query Request exchange sequence 2310
Figure 11-42—Group addressed GAS Query Response exchange sequence 2311
Figure 11-43—Group addressed GAS Query Request for a specific fragment exchange sequence 2312
Figure 11-44—GAS frame exchange sequence using CAG Version 2313
Figure 11-45—Example TDLS Capability discovery using ANQP 2324
Figure 11-46—Example of beamformed link maintenance 2357
Figure 11-47—Moving the TBTT position 2362
Figure 11-48—Changing beacon interval duration 2363
Figure 11-49—Example of spatial sharing assessment 2365
Figure 11-50—Example of spatial sharing between SP1 and SP2 2366
Figure 11-51—Procedure of the FST setup protocol 2369
Figure 11-52—States of the FST setup protocol 2370
Figure 11-53—On-channel tunneling procedure 2378
Figure 11-54—Forward path of OCT messages based on OCT parameters 2382
Figure 11-55—Return path of OCT messages based on OCT parameters 2382
Figure 11-56—Quieting adjacent BSS operation 2390
Figure 11-57—Beamforming training procedure in the DTI 2392
Figure 11-58—Beamforming training when joining an infrastructure BSS or PBSS 2392
Figure 11-59—GDD dependent STA state transition diagram 2408
Figure 11-60—Examples of using DCS procedure 2428
Figure 11-61—Procedure of dynamic channel selection 2429
Figure 12-1—Construction of expanded WEP MPDU 2446
Figure 12-2—WEP encapsulation block diagram 2448
Figure 12-3—WEP decapsulation block diagram 2448
Figure 12-4—SAE finite state machine 2469
Figure 12-5—TKIP encapsulation block diagram 2477
Figure 12-6—TKIP decapsulation block diagram 2478
Figure 12-7—Construction of expanded TKIP MPDU 2478
Figure 12-8—TKIP MIC relation to IEEE 802.11 processing 2480
Figure 12-9—TKIP MIC processing format 2480
Figure 12-10—Michael message processing 2481
Figure 12-11—Michael block function 2482

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 12-12—Authenticator MIC countermeasures 2484
Figure 12-13—Supplicant MIC countermeasures 2485
Figure 12-14—Phase 1 key mixing 2488
Figure 12-15—Phase 2 key mixing 2489
Figure 12-16—Expanded CCMP MPDU 2491
Figure 12-17—Expanded PV1 CCMP MPDU 2491
Figure 12-18—CCMP encapsulation block diagram 2493
Figure 12-19—AAD construction for PV0 MPDUs 2493
Figure 12-20—AAD construction for PV1 MPDUs 2494
Figure 12-21—Nonce field 2495
Figure 12-22—Nonce Flags subfield 2496
Figure 12-23—CCMP decapsulation block diagram 2498
Figure 12-24—BIP encapsulation 2501
Figure 12-25—BIP AAD construction 2501
Figure 12-26—Expanded GCMP MPDU 2504
Figure 12-27—GCMP encapsulation block diagram 2505
Figure 12-28—Nonce field format 2506
Figure 12-29—GCMP decapsulation block diagram 2507
Figure 12-30—Pairwise key hierarchy 2538
Figure 12-31—Group key hierarchy 2541
Figure 12-32—FT key hierarchy at an Authenticator 2542
Figure 12-33—EAPOL-Key frame format 2548
Figure 12-34—Key Information bit format 2548
Figure 12-35—KDE format 2551
Figure 12-36—GTK KDE format 2552
Figure 12-37—MAC address KDE format 2553
Figure 12-38—PMKID KDE format 2553
Figure 12-39—Nonce KDE format 2553
Figure 12-40—Lifetime KDE format 2553
Figure 12-41—Error KDE format 2553
Figure 12-42—IGTK KDE format 2553
Figure 12-43—Key ID KDE format 2555
Figure 12-44—Multi-band GTK KDE format 2555
Figure 12-45—Multi-band Key ID KDE format 2555
Figure 12-46—OCI KDE format 2555
Figure 12-47—BIGTK KDE format 2555
Figure 12-48—Sample 4-way handshake 2566
Figure 12-49—Sample group key handshake 2571
Figure 12-50—RSNA Supplicant key management state machine 2578
Figure 12-51—Authenticator state machines, part 1 2583
Figure 12-52—Authenticator state machines, part 2 2584
Figure 12-53—Authenticator state machines, part 3 2584
Figure 12-54—Authenticator state machines, part 4 2585
Figure 12-55—FILS Shared Key authentication 2595
Figure 13-1—FT key holder architecture 2609
Figure 13-2—FT initial mobility domain association in an RSN 2612
Figure 13-3—FT initial mobility domain association in a non-RSN 2614
Figure 13-4—FT initial mobility domain association using FILS authentication in an RSN 2615
Figure 13-5—Over-the-air FT protocol in an RSN 2617
Figure 13-6—Over-the-DS FT protocol in an RSN 2619
Figure 13-7—MLME interfaces for over-the-DS FT protocol messages 2620
Figure 13-8—Over-the-air FT protocol in a non-RSN 2621
Figure 13-9—Over-the-DS FT protocol in a non-RSN 2622

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 13-10—Over-the-air FT resource request protocol in an RSN 2623
Figure 13-11—Over-the-air FT resource request protocol in a non-RSN 2624
Figure 13-12—Over-the-DS FT resource request protocol in an RSN 2626
Figure 13-13—Over-the-DS FT resource request protocol in a non-RSN 2627
Figure 13-14—R0KH state machine 2637
Figure 13-15—R1KH state machine, including portions of the SME (part 1) 2639
Figure 13-16—R1KH state machine, including portions of the SME (part 2) 2640
Figure 13-17—S0KH state machine 2642
Figure 13-18—S1KH state machine, including portions of the SME (part 1) 2644
Figure 13-19—S1KH state machine, including portions of the SME (part 2) 2645
Figure 13-20—Sample message flow for over-the-DS resource request 2649
Figure 13-21—RIC-Request format 2650
Figure 13-22—Resource Request format 2650
Figure 13-23—Resource Request example #1 2651
Figure 13-24—Resource Request example #2 2651
Figure 13-25—RIC-Request example #1 2651
Figure 13-26—RIC-Request example #2 2651
Figure 13-27—RIC-Request example #3 2652
Figure 13-28—RIC-Response format 2652
Figure 13-29—Example QoS RIC-Response 2652
Figure 13-30—Overview of RIC processing at an AP 2654
Figure 14-1—Logical flowchart of protocol interaction in the mesh peering management framework 2660
Figure 14-2—Finite state machine of the MPM protocol 2669
Figure 14-3—Finite state machine of the AMPE protocol 2680
Figure 14-4—Illustration of definitions 2689
Figure 14-5—Example of mesh power management mode usage 2741
Figure 14-6—Mesh power management operation 2745
Figure 14-7—Mesh peer service period 2747
Figure 15-1—PPDU format 2753
Figure 15-2—CRC-16 implementation 2755
Figure 15-3—Example CRC calculation 2756
Figure 15-4—Data scrambler 2756
Figure 15-5—Data descrambler 2757
Figure 15-6—Transmit PHY 2757
Figure 15-7—PHY transmit state machine 2758
Figure 15-8—Receive PHY 2759
Figure 15-9—PHY receive state machine 2761
Figure 15-10—Transmit spectrum mask 2767
Figure 15-11—Transmit power-on ramp 2767
Figure 15-12—Transmit power-down ramp 2768
Figure 15-13—Modulation accuracy measurement example 2769
Figure 15-14—Chip clock alignment with baseband eye pattern 2769
Figure 16-1—Long PPDU format 2775
Figure 16-2—Short PPDU format 2775
Figure 16-3—CRC-16 implementation 2779
Figure 16-4—Example of CRC calculation 2780
Figure 16-5—Data scrambler 2781
Figure 16-6—Data descrambler 2782
Figure 16-7—Transmit PHY 2783
Figure 16-8—Receive PHY 2784
Figure 16-9—PHY receive state machine 2786
Figure 16-10—Transmit spectrum mask 2795
Figure 16-11—Transmit power-on ramp 2796

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 16-12—Transmit power-down ramp 2796
Figure 16-13—Modulation accuracy measurement example 2797
Figure 16-14—Chip clock alignment with baseband eye pattern 2798
Figure 17-1—PPDU format 2808
Figure 17-2—Illustration of OFDM frame with cyclic extension and windowing for (a) single reception or (b) two receptions of the FFT period 2813
Figure 17-3—Inputs and outputs of inverse Fourier transform 2814
Figure 17-4—OFDM training structure 2814
Figure 17-5—SIGNAL field bit assignment 2816
Figure 17-6—SERVICE field bit assignment 2817
Figure 17-7—Data scrambler 2818
Figure 17-8—Convolutional encoder (k = 7) 2821
Figure 17-9—Example of the bit-stealing and bit-insertion procedure (r = 3/4, 2/3) 2822
Figure 17-10—BPSK, QPSK, 16-QAM, and 64-QAM constellation bit encoding 2824
Figure 17-11—Subcarrier frequency allocation 2828
Figure 17-12—Transmitter and receiver block diagram for the OFDM PHY 2829
Figure 17-13—Transmit spectrum mask for 20 MHz transmission 2832
Figure 17-14—Transmit spectrum mask for 10 MHz transmission 2832
Figure 17-15—Transmit spectrum mask for 5 MHz transmission 2833
Figure 17-16—Constellation error 2835
Figure 17-17—Transmit PHY 2839
Figure 17-18—PHY transmit state machine 2841
Figure 17-19—Receive PHY 2842
Figure 17-20—PHY receive state machine 2844
Figure 19-1—PPDU format 2873
Figure 19-2—Transmitter block diagram 1 2876
Figure 19-3—Transmitter block diagram 2 2876
Figure 19-4—Timing boundaries for PPDU fields 2883
Figure 19-5—L-SIG structure 2888
Figure 19-6—Format of HT-SIG1 and HT-SIG2 2891
Figure 19-8—HT-SIG CRC calculation 2893
Figure 19-7—Data tone constellations in an HT-mixed format PPDU 2893
Figure 19-9—Generation of HT-DLTFs 2897
Figure 19-10—Generation of HT-ELTFs 2897
Figure 19-11—Puncturing at rate 5/6 2903
Figure 19-12—Examples of cyclic-permutation matrices with Z=8 2905
Figure 19-13—LDPC PPDU encoding padding and puncturing of a single codeword 2907
Figure 19-14—Beamforming MIMO channel model (3×2 example) 2919
Figure 19-15—Baseband-to-baseband channel 2920
Figure 19-16—Example of an NDP used for sounding 2927
Figure 19-17—Transmit spectral mask for 20 MHz transmission in the 2.4 GHz band 2930
Figure 19-18—Transmit spectral mask for a 40 MHz channel in the 2.4 GHz band 2931
Figure 19-19—Transmit spectral mask for 20 MHz transmission in the 5 GHz band 2931
Figure 19-20—Transmit spectral mask for a 40 MHz channel in the 5 GHz band 2932
Figure 19-21—PHY-TXEND.confirm alignment (HT-greenfield format with short GI) 2933
Figure 19-22—PHY transmit procedure (HT-mixed format PPDU) 2940
Figure 19-23—PHY transmit procedure (HT-greenfield format PPDU) 2940
Figure 19-24—PHY transmit state machine 2942
Figure 19-25—PHY receive procedure for HT-mixed format PPDU 2943
Figure 19-26—PHY receive procedure for HT-greenfield format PPDU 2943
Figure 19-27—PHY receive state machine 2944
Figure 20-1—Transmit mask 2966
Figure 20-2—PPDU structure 2970

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 20-3—SC preamble 2970
Figure 20-4—Channel Estimation field for SC PPDUs 2971
Figure 20-5—Data scrambler 2974
Figure 20-6—DMG control mode PPDU format 2975
Figure 20-7—DMG control mode preamble 2975
Figure 20-8—SC frame format 2979
Figure 20-9—BPSK constellation bit encoding 2988
Figure 20-10—QPSK constellation bit encoding 2989
Figure 20-11—8-PSK constellation bit encoding (before π/2 rotation) 2989
Figure 20-12—16-QAM constellation bit encoding 2990
Figure 20-13—64-QAM constellation bit encoding 2991
Figure 20-14—Block transmission 2992
Figure 20-15—Blocking for DMG low-power SC mode 2997
Figure 20-16—PHY transmit procedure 2998
Figure 20-17—Typical Tx state machine (Training Length = 0 is assumed; some optional features such as DMG SC low-power mode are not shown) 2999
Figure 20-18—PHY receive procedure 3000
Figure 20-19—Typical Rx state machine (some optional features such as DMG low-power SC mode are not shown) 3002
Figure 20-20—BRP PPDU structure 3003
Figure 20-21—TRN field definition 3005
Figure 21-1—PHY interaction on transmit for various PPDU formats 3024
Figure 21-2—PHY interaction on receive for various PPDU formats 3024
Figure 21-3—PHY-CONFIG and CCA interaction with Clause 17, Clause 19, and Clause 21 PHYs 3025
Figure 21-4—VHT PPDU format 3027
Figure 21-5—Transmitter block diagram for the L-SIG and VHT-SIG-A fields 3029
Figure 21-6—Transmitter block diagram for the VHT-SIG-B field of a 20 MHz, 40 MHz, and 80 MHz VHT SU PPDU 3029
Figure 21-7—Transmitter block diagram for the VHT-SIG-B field of a 20 MHz, 40 MHz, and 80 MHz VHT MU PPDU 3030
Figure 21-8—Transmitter block diagram for the VHT-SIG-B field of a 160 MHz VHT SU PPDU 3030
Figure 21-9—Transmitter block diagram for the VHT-SIG-B field of an 80+80 MHz VHT SU PPDU 3031
Figure 21-10—Transmitter block diagram for the Data field of a 20 MHz, 40 MHz, or 80 MHz VHT SU PPDU with BCC encoding 3031
Figure 21-11—Transmitter block diagram for the Data field of a 20 MHz, 40 MHz, or 80 MHz VHT SU PPDU with LDPC encoding 3032
Figure 21-12—Transmitter block diagram for the Data field of a 20 MHz, 40 MHz, or 80 MHz VHT MU PPDU 3033
Figure 21-13—Transmitter block diagram for the Data field of a 160 MHz VHT SU PPDU with BCC encoding 3034
Figure 21-14—Transmitter block diagram for the Data field of a 160 MHz VHT SU PPDU with LDPC encoding 3034
Figure 21-15—Transmitter block diagram for the Data field of an 80+80 MHz VHT SU PPDU with BCC encoding 3035
Figure 21-16—Transmitter block diagram for the Data field of an 80+80 MHz VHT SU PPDU with LDPC encoding 3036
Figure 21-17—Timing boundaries for VHT PPDU fields 3049
Figure 21-18—VHT-SIG-A1 structure 3057
Figure 21-19—VHT-SIG-A2 structure 3057
Figure 21-20—Data tone constellation in the VHT PPDU pre-VHT modulated fields 3060
Figure 21-21—Generation of VHT-LTF symbols per frequency segment 3063
Figure 21-22—VHT-SIG-B bits in 20 MHz, 40 MHz, 80 MHz, 160 MHz, and 80+80 MHz transmissions 3066

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 21-23—VHT-SIG-B and SERVICE field relationship 3071
Figure 21-24—Constellation bit encoding for 256-QAM (1st quadrant) 3080
Figure 21-25—Constellation bit encoding for 256-QAM (2nd quadrant) 3081
Figure 21-26—Constellation bit encoding for 256-QAM (3rd quadrant) 3082
Figure 21-27—Constellation bit encoding for 256-QAM (4th quadrant) 3083
Figure 21-28—VHT NDP format 3093
Figure 21-29—Example transmit spectral mask for 20 MHz mask PPDU 3095
Figure 21-30—Example transmit spectral mask for 40 MHz mask PPDU 3096
Figure 21-31—Example transmit spectral mask for 80 MHz mask PPDU 3097
Figure 21-32—Example transmit spectral mask for 160 MHz mask PPDU 3097
Figure 21-33—Example transmit spectral mask for 80+80 MHz mask PPDU 3098
Figure 21-34—PHY transmit procedure for SU transmission 3107
Figure 21-35—PHY transmit state machine for SU transmission 3109
Figure 21-36—PHY receive procedure for SU transmission 3110
Figure 21-37—PHY receive state machine 3111
Figure 22-1—VHT PPDU format in TVWS bands 3150
Figure 22-2—Transmitter block diagram for the Data field of a TVHT_MODE_2N or TVHT_MODE_4N SU PPDU with BCC encoding 3152
Figure 22-3—Transmitter block diagram for the Data field of a TVHT_MODE_2N or TVHT_MODE_4N SU PPDU with LDPC encoding 3153
Figure 22-4—Example transmit spectral mask for an 6+6 MHz mask PPDU 3172
Figure 23-1—S1G_SHORT format 3198
Figure 23-2—S1G_LONG format 3199
Figure 23-3—S1G_1M format 3199
Figure 23-4—Transmitter block diagram for the Data field of an S1G_1M PPDU with BCC or LDPC encoding and MCS 10 3201
Figure 23-5—Timing boundaries for S1G PPDU fields 3217
Figure 23-6—Generation of LTF symbols 3225
Figure 23-7—SIG-1 structure 3226
Figure 23-8—SIG-2 structure 3226
Figure 23-9—Data constellation in SIG field of S1G_SHORT 3228
Figure 23-10—4-bit CRC calculation 3230
Figure 23-11—SIG-A1 structure for SU PPDU 3233
Figure 23-12—SIG-A2 structure for SU PPDU 3233
Figure 23-13—SIG-A1 structure for MU PPDU 3233
Figure 23-14—SIG-A2 structure for MU PPDU 3233
Figure 23-15—Data constellation in SIG-A field of S1G_LONG 3237
Figure 23-16—Structure of the 6 symbol SIG field of S1G_1M PPDU 3247
Figure 23-17—S1G NDP for sounding format 3264
Figure 23-18—NDP CMAC PPDU for ≥ 2 MHz 3265
Figure 23-19—NDP CMAC PPDU for 1 MHz 3265
Figure 23-20—SIG field format for 1 MHz NDP CMAC PPDU 3265
Figure 23-21—SIG field format for ≥ 2 MHz NDP CMAC PPDU 3265
Figure 23-22—NDP CMAC PPDU body field of the NDP_1M CTS frame 3267
Figure 23-23—NDP CMAC PPDU body field of the NDP_2M CTS frame 3267
Figure 23-24—NDP CMAC PPDU body field of the NDP_1M CF-End frame 3268
Figure 23-25—NDP CMAC PPDU body field of the NDP_2M CF-End frame 3268
Figure 23-26—NDP CMAC PPDU body field of the NDP_1M PS-Poll frame 3269
Figure 23-27—NDP CMAC PPDU body field of the NDP_2M PS-Poll frame 3270
Figure 23-28—NDP CMAC PPDU body field of the NDP_1M Ack frame 3271
Figure 23-29—NDP CMAC PPDU body field of the NDP_2M Ack frame 3271
Figure 23-30—NDP CMAC PPDU body field of the NDP_1M PS-Poll-Ack frame 3272
Figure 23-31—NDP CMAC PPDU body field of the NDP_2M PS-Poll-Ack frame 3273

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 23-32—NDP CMAC PPDU body field of the NDP_1M BlockAck frame 3273
Figure 23-33—NDP CMAC PPDU body field of the NDP_2M BlockAck frame 3274
Figure 23-34—NDP CMAC PPDU body field of the NDP_2M Beamforming Report Poll frame 3275
Figure 23-35—NDP CMAC PPDU body field of the NDP_1M Paging frame 3275
Figure 23-36—NDP CMAC PPDU body field of the NDP_2M Paging frame 3276
Figure 23-37—NDP CMAC PPDU body field of the NDP_1M Probe Request frame 3277
Figure 23-38—NDP CMAC PPDU body field of the NDP_2M Probe Request frame 3277
Figure 23-39—Transmit spectral mask for 1 MHz channel 3279
Figure 23-40—Transmit spectral mask for 2 MHz channel 3280
Figure 23-41—Transmit spectral mask for 4 MHz channel 3280
Figure 23-42—Transmit spectral mask for 8 MHz channel 3281
Figure 23-43—Transmit spectral mask for 16 MHz channel 3281
Figure 23-44—PHY transmit procedure for an SU transmission using S1G_1M procedure 3295
Figure 23-45—PHY transmit procedure for an SU transmission using S1G_SHORT procedure 3295
Figure 23-46—PHY transmit procedure for an SU transmission using S1G_LONG procedure 3296
Figure 23-47—PHY transmit procedure for an NDP CMAC PPDU transmission using S1G_1M format 3297
Figure 23-48—PHY transmit procedure for an NDP CMAC PPDU transmission using S1G_SHORT format 3297
Figure 23-49—PHY transmit state machine for an S1G PPDU transmission 3298
Figure 23-50—PHY receive procedure for an SU transmission, S1G_1M procedure 3299
Figure 23-51—PHY receive procedure for an SU transmission, S1G_SHORT procedure 3300
Figure 23-52—PHY receive procedure for an SU transmission, S1G_LONG procedure 3300
Figure 23-53—PHY receive state machine 3301
Figure 24-1—Transmit mask 3323
Figure 24-2—CDMG SC mode preamble 3326
Figure 24-3—Channel Estimation field for SC packets 3327
Figure 24-4—CDMG control mode PPDU format 3328
Figure 24-5—CDMG control mode preamble 3328
Figure 24-6—SC frame format 3331
Figure 24-7—64-QAM constellation bit encoding 3335
Figure 24-8—Typical Tx state machine (Training Length=0 is assumed; some optional features such as CDMG SC low-power mode are not shown) 3340
Figure 24-9—BRP PPDU structure (CDMA STAs) 3342
Figure 25-1—Packet structure for the SC mode PPDU with CBW540 MHz 3354
Figure 25-2—Packet structure for the SC mode PPDU with CBW1080 MHz 3355
Figure 25-3—Packet structure for the OFDM mode PPDU 3355
Figure 25-4—Control mode preamble 3358
Figure 25-5—CMMG SC mode preamble for CBW540 MHz 3359
Figure 25-6—CMMG SC mode preamble for CBW1080 MHz 3359
Figure 25-7—CMMG OFDM mode preamble for CBW540 MHz 3360
Figure 25-8—CMMG OFDM mode preamble for CBW1080 MHz 3360
Figure 25-9—16-bit CRC calculation 3361
Figure 25-10—8-bit CRC calculation 3361
Figure 25-11—Scrambler 3361
Figure 25-12—CMMG SIG structure 3364
Figure 25-13—CMMG control mode PPDU format 3370
Figure 25-14—Constellation bit encoding for BPSK 3371
Figure 25-15—Transmitter block diagram for CMMG SC mode SIG field 3373
Figure 25-16—Transmitter block diagram for data fields of CMMG SC mode PPDUs 3374
Figure 25-17—Format of CMMG SC mode PPDU 3375
Figure 25-18—QPSK constellation bit encoding 3379
Figure 25-19—16-QAM constellation bit encoding 3379

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure 25-20—64-QAM constellation bit encoding 3380
Figure 25-21—Block transmission 3381
Figure 25-22—Format of the CMMG OFDM mode PPDU 3384
Figure 25-23—Transmitter block diagram for CMMG OFDM mode SIG fields 3385
Figure 25-24—Transmitter block diagram for the data field of CMMG OFDM mode 3385
Figure 25-25—Generation of OCEF symbols per frequency segment 3391
Figure 25-26—BPSK, QPSK, 16-QAM, and 64-QAM constellation bit encoding 3395
Figure 25-27—CMMG NDP format 3401
Figure 25-28—BRP PPDU structure 3405
Figure 25-29—TRN-R subfield definition 3406
Figure 25-30—TRN-T subfield definition 3406
Figure 25-31—Generation of ZCZ sequences set 3407
Figure 25-32—Channelization for CBW540 MHz 3412
Figure 25-33—Channelization for CBW1080 MHz 3412
Figure 25-34—Example transmit spectral mask for a PPDU 3413
Figure 25-35—PHY transmit procedure for a CMMG SC mode transmission 3414
Figure 25-36—PHY transmit procedure for a CMMG OFDM mode transmission 3415
Figure 25-37—Typical Tx state machine 3416
Figure 25-38—PHY receive procedure for a CMMG SC mode transmission 3417
Figure 25-39—Typical Rx state machine 3418
Figure D-1—Transmit spectrum mask and application 4108
Figure H-1—Ethertype 89-0d frame body 4148
Figure I-1—DMG control mode preamble expressed in Ga128 and Gb128 sequences 4205
Figure I-2—DMG control mode header coding and modulation 4206
Figure I-3—DMG control mode payload coding and modulation 4208
Figure I-4—DMG SC mode preamble expressed in Ga128 and Gb128 sequences 4209
Figure I-5—DMG SC mode header coding and modulation 4210
Figure I-6—DMG SC mode MCS 1 payload coding and modulation 4213
Figure I-7—DMG SC mode MCS 2—MCS 12 payload coding and modulation 4214
Figure I-8—DMG low-power SC mode payload coding and modulation 4218
Figure J-1—Randomness generating circuit 4245
Figure K-1—Schedule for stream from STA i 4283
Figure K-2—Schedule for streams from STAs i to k 4283
Figure K-3—Reallocation of TXOPs when a stream is dropped 4284
Figure L-1—Partial Virtual Bitmap example #1 4292
Figure L-2—Partial Virtual Bitmap example #2 4293
Figure L-3—Partial Virtual Bitmap example #3 4293
Figure L-4—Partial Virtual Bitmap example #4, Method A and Method B 4293
Figure L-5—Partial Virtual Bitmap example #5, Method A or Method B 4294
Figure L-6—Partial Virtual Bitmap example #6, Method A 4294
Figure L-7—Partial Virtual Bitmap example #6, Method B 4295
Figure L-8—Partial Virtual Bitmap example #7 for S1G STAs, Block Bitmap mode 4295
Figure L-9—Partial Virtual Bitmap example #8 for S1G STAs, Single AID mode 4296
Figure L-10—Partial Virtual Bitmap example #9 for S1G STAs, OLB mode 4297
Figure L-11—Partial Virtual Bitmap example #7 for S1G STAs, ADE mode 4297
Figure L-12—Partial Virtual Bitmap example #10 for S1G STAs, Inverse Bitmap + Block Bitmap mode 4298
Figure L-13—Partial Virtual Bitmap example #11 for S1G STAs, Inverse Bitmap + Single AID mode 4298
Figure L-14—Partial Virtual Bitmap example #12 for S1G STAs, Inverse Bitmap + OLB mode 4299
Figure L-15—Partial Virtual Bitmap example #10 for S1G STAs, Inverse Bitmap + ADE mode 4300

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Figure M-1—EPD BPDU subframe 4307
Figure M-2—EPD VLAN tagged IPv4 subframe 4307
Figure M-3—EPD VLAN tagged IS-IS subframe 4307
Figure N-1—Very high level UML use case diagram for the AP 4310
Figure N-2—Very high level UML use case diagram for the WLAN system 4310
Figure N-3—High-level UML use case diagram for the WLAN system 4311
Figure N-4—High-level UML entity diagram for the WLAN system 4312
Figure N-5—AP UML composition diagram (alternate syntax) 4313
Figure N-6—High-level UML use case diagram for the AP 4314
Figure O-1—A-MPDU parsing 4317
Figure O-2—Example of RD exchange sequence showing response burst 4318
Figure O-3—Determination of NDP source and destination for unidirectional NDP sequences 4319
Figure O-4—Determination of NDP source and destination for bidirectional NDP sequence 4320
Figure P-1—Parameters recorded by Observing STA when monitoring Fine Timing Measurement frames 4326
Figure R-1—Interworking IEEE 802.11 infrastructure supporting multiple SSPNs 4333
Figure R-2—Basic architecture of the interworking service 4335
Figure S-1—Format of a CCMP-128-encrypted mesh Data frame containing a single MSDU 4347
Figure V-1—Example of TSPEC aggregation (SPCA and EDCA access policies) 4368
Figure V-2—Example of TSPEC aggregation (SPCA, EDCA, and SEMM access policies) 4369
Figure W-1—An arrange mode of 1-D uniform linear antenna array 4371
Figure W-2—Beam patterns generated by the codebook 4371
Figure W-3—An arrange mode of 2-D uniform linear antenna array 4372
Figure Y-1—Example of a frame exchange for background search with Service Hint matching 4375
Figure Y-2—Example of frame exchange for background search with matching Service Hash element 4376
Figure Y-3—Example of frame exchange for immediate search 4377

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

IEEE Standard for Information Technology—Telecommunications and Information Exchange between Systems Local and Metropolitan Area Networks—Specific Requirements

Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications

1. Overview

1.1 Scope

The scope of this standard is to define one medium access control (MAC) and several physical layer (PHY) specifications for wireless connectivity for fixed, portable, and moving stations (STAs) within a local area.

1.2 Purpose

The purpose of this standard is to provide wireless connectivity for fixed, portable, and moving stations within a local area. This standard also offers regulatory bodies a means of standardizing access to one or more frequency bands for the purpose of local area communication.

1.3 Supplementary information on purpose

Specifically, in the context of IEEE 802.11™-compliant devices, this standard

- Describes the functions and services required by a device to operate within independent, personal, and infrastructure networks as well as the aspects of device mobility (transition) within those networks.
- Describes the functions and services that allow a device to communicate directly with another such device outside of an independent or infrastructure network.
- Defines the MAC procedures to support the MAC service data unit (MSDU) delivery services.
- Defines several PHY signaling techniques and interface functions that are controlled by the MAC.
- Permits the operation of a device within a wireless local area network (WLAN) that coexists with multiple overlapping IEEE 802.11 WLANs.
- Describes the requirements and procedures to provide data confidentiality of user information and MAC management information being transferred over the wireless medium (WM) and authentication of devices.
- Defines mechanisms for dynamic frequency selection (DFS) and transmit power control (TPC) that may be used to satisfy regulatory requirements for operation in any band.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

- Defines the MAC procedures to support local area network (LAN) applications with quality-of-service (QoS) requirements, including the transport of voice, audio, and video.
- Defines mechanisms and services for wireless network management of devices that include BSS transition management, channel usage and coexistence, collocated interference reporting, diagnostic, multicast diagnostic and event reporting, flexible multicast, efficient beacon mechanisms, proxy ARP advertisement, location, timing measurement, directed multicast, extended sleep modes, traffic filtering, and management notification.
- Defines functions and procedures aiding network discovery and selection by devices, information transfer from external networks using QoS mapping, and a general mechanism for the provision of emergency services.
- Defines the MAC procedures that are necessary for wireless multi-hop communication to support wireless LAN mesh topologies.
- Defines medium access control mechanisms to support the prioritization of Management frames.
- Defines mechanisms to improve audio video (AV) streaming QoS while maintaining data and voice performance.
- Defines the PHY signaling, MAC, and beamforming procedures required for operation with directional antenna patterns.
- Defines the PHY and MAC enhancements to enable operation in the Chinese millimeter wave frequency bands (60 GHz and 45 GHz).
- Defines the mechanisms for communications over the wireless medium used as a link in an IEEE 802.1Q™ bridged network.
- Defines mechanisms to enable delivery of preassociation service discovery information to IEEE 802.11 stations (STAs).

1.4 Word usage

In this document, the word *shall* is used to indicate a mandatory requirement. The word *should* is used to indicate a recommendation. The word *may* is used to indicate a permissible action. The word *can* is used for statements of possibility and capability.

The construction “between *x* and *y*”, “*x* to *y*” or “*x*-*y*” represents an inclusive range (i.e., the range includes both values *x* and *y*).

The construction “up to *y*” represents an inclusive upper bound (i.e., the range includes the value *y).*

Any action specified as relating to a SAP primitive is to be interpreted as an action on an invocation or instance of that primitive.

If <x> represents a scalar field, scalar subfield, scalar parameter or scalar MIB attribute:

- if “<x> is” is used in a context that relates to the testing or setting the value of “<x>” this usage is to be interpreted as though written “the value of <x> is”
- “<x> indicate(s)” is to be interpreted as though written “the value of <x> indicate(s)”
- “indicated by <x>” is to be interpreted as though written “indicated by the value of <x>”
- “<x> that indicate” is to be interpreted as though written “<x> whose value indicates”

If <x> represents a frame, element, subelement, structured field, structured subfield, structured parameter or structured MIB attribute:

- “<x> indicate(s)” is to be interpreted as though written “the contents of <x> indicate”
- “indicated by <x>” is to be interpreted as though written “indicated by the contents of <x>”
- “<x> that indicate” is to be interpreted as though written “<x> whose contents indicate”

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

If <x> represents a SAP primitive:

— "<x> indicate(s)" is to be interpreted as though written "the (or an) invocation of <x> indicates"

— "indicated by <x">" is to be interpreted as though written "indicated by the (or an) invocation of <x>"

The construction of descriptions for uses of the SHA family of hash algorithms [HMAC-]SHA-<1,256,384>[-*n*] is used to refer to hash algorithms/HMACs where square brackets indicate optional information, and *n* is an integer indicating the length, in bits, of the output when truncating.

A construction of the form "the x element can be included in a, b and c frames" or "the x element can be present in a, b and c frames" is not to be understood as being a complete list of frames in which the element might be present.

Constructions of the form that a frame, MPDU or A-MPDU is transmitted with a certain TXVECTOR parameter, or received with a certain RXVECTOR parameter, are to be understood as referring to the TXVECTOR or RXVECTOR parameter, respectively, corresponding to the PSDU containing the frame, MPDU or A-MPDU. Similarly, constructions of the form that a PPDU is transmitted with a certain TXVECTOR parameter, or received with a certain RXVECTOR parameter, are to be understood as referring to the TXVECTOR or RXVECTOR parameter, respectively, corresponding to the PSDU contained in the PPDU.

References in this standard to a "<name> frame", where <name> corresponds to one of the Management frame subtypes, are to be understood as being to a "<name> MMPDU, where the MMPDU is carried in the frame body of one or more Management frames with the Subtype field value corresponding to <name>, plus information from the MPDU headers (the Management frame subtype and the addresses)".

References in this standard to a "<name> request", where <name> corresponds to one of the Measurement Types in Table 9-98 is equivalent to (according to context) a) "a Spectrum Measurement Request frame or Radio Measurement Request frame carrying a Measurement Request element with the Measurement Type field equal to <name>" or b) "a Measurement Request element with the measurement type field equal to <name>".

An ASCII or UTF-8 string is a sequence of ASCII or UTF-8 encoded code points, respectively, without a terminating null.

References in this standard to "<adjective> STA" correspond to a specific instance of a STA implementation that will statically support and execute the <adjective> feature or role for the lifetime of the instance. Such a STA implementation may be capable of a different configuration where <adjective> is not supported (or even a mutually exclusive state is supported instead), but the switch from support to nonsupport of <adjective> is beyond the scope of this standard. The <adjective> support is to be understood as static for the lifetime of the instance, unless explicitly discussed otherwise.

References in this standard to "FILS authentication frame" or "SAE authentication frame" are to be understood as references to an Authentication frame that contains fields and elements for FILS or SAE (respectively) operation per Table 9-41.

1.5 Terminology for mathematical, logical, and bit operations

Floor (x), also written as $\lfloor x \rfloor$, is the largest integer smaller than or equal to x. For example, Floor (2.3) is 2 and Floor (–2.3) is –3. The two parameter form, Floor (x, y), is the largest multiple of y smaller than or equal to x; this operator is not used in this standard if y is negative. For example, Floor (3.3, 2) is 2 and Floor (–3.3, 2) is –4.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

Ceil (x), also written as $\lceil x \rceil$ is the smallest integer larger than or equal to x. For example, Ceil (2.3) is 3 and Ceil (–2.3) is –2. The two parameter form, Ceil (x, y), is the smallest multiple of y larger than or equal to x; this operator is not used in this standard if y is negative. For example, Ceil (2.3, 2) is 4 and Ceil (–2.3, 2) is –2.

Round (x) is the integer closest to x, rounding values with a fractional part of 0.5 away from zero. For example, Round (2.3) is 2, Round (2.5) is 3, Round (–2.3) is –2 and Round (–2.5) is –3.

x mod y is the remainder when x is divided by y; this operator is not used in this standard if y is negative; the result is positive even if x is negative. For example, 5 mod 3 is 2 and –5 mod 3 is 1.

The symbol ⊕ represents bitwise exclusive OR (XOR).

log2 (x) is the logarithm of x to the base 2. For example, log2 (32) is 5.

Re (z) is the real part of complex number z. Im (z) is the imaginary part of complex number z (not including the factor i). For example, Re ($1 – 2i$) is 1 and Im ($1 – 2i$) is –2.

x && y is the short-circuiting Boolean AND.

x || y is the concatenation of x and y, except in code, where it sometimes is the short-circuiting Boolean OR (as determined by the context).

!x is the Boolean NOT.

x >> y is x logically shifted right (i.e., zeros are inserted at the most significant end) by y; this operator is not used in this standard if y is negative.

x << y is x shifted left (i.e., zeros are inserted at the least significant end) by y; this operator is not used in this standard if y is negative.

x == y is Boolean equality.

x != y Boolean inequality.

x & y, where x and y are numbers, is the bitwise AND of x and y.

x | y, where x and y are numbers, is the bitwise OR of x and y.

0x introduces a hexadecimal number. For example, 0x12 is 18 decimal.

L(S, F, N) is bits F to F+N–1 of the bit string S starting from the left, using the IEEE 802.11 bit conventions from 9.2.2.

Truncate-N(S) is bits 0 to N–1 of the bit string S starting from the left, using the IEEE 802.11 bit conventions from 9.2.2). Other bits are irretrievably deleted.

exp(x) is e to the power x, where e is the base of natural logarithms.

A[b:c] is the bit string consisting of bits b to c of A, where bit 0 of the output is the value of bit b. This operator is not used in this standard with b larger than c.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

int(*S*) is the numeric value of bit string *S*, where bit 0 of S is the least significant bit, using the IEEE 802.11 bit conventions from 9.2.2.

NOTE—The *int* operator applied to a (portion of a) MAC address implies that octet 0 of the MAC address is the least significant octet under this operator.[1]

bin[*x*, *k*] is the operator that casts decimal value *x* into *k* bits binary vector, where *x* is less than 2^k.

[1] NOTEs in text, tables, and figures of a standard are given for information only and do not contain requirements needed to implement the standard. Lettered footnotes to tables and figures, however, are normative.

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

2. Normative references

The following referenced documents are indispensable for the application of this standard (i.e., they must be understood and used; therefore, each referenced document is cited in the text and its relationship to this document is explained). For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments or corrigenda) at the time of publication of this standard applies.

3GPP TS 24.302, Access to the 3GPP Evolved Packet Core (EPC) via non-3GPP access networks; Stage 3.[2]

ETSI EN 301 893, Broadband Radio Access Networks (BRAN); 5 GHz high performance RLAN (latest Official Journal of the European Union published version).[3]

FIPS 180-4, Secure Hash Standard.[4]

FIPS 186-4, Digital Signature Standard.

FIPS 197, Advanced Encryption Standard (AES).

IANA EAP Method Type Numbers, http://www.iana.org/assignments/eap-numbers.

IEEE Std 754™-2008, IEEE Standard for Binary Floating-Point Arithmetic.[5,6]

IEEE Std 802®, IEEE Standards for Local and Metropolitan Area Networks: Overview and Architecture.

IEEE Std 802c™-2017, IEEE Standard for Local and Metropolitan Area Networks: Overview and Architecture—Amendment 2: Local Medium Access Control (MAC) Address Usage.

IEEE Std 802.1AC™-2016, IEEE Standard for Local and Metropolitan Area Networks—Media Access Control (MAC) Service Definition.

IEEE Std 802.1AS™, IEEE Standard for Local and Metropolitan Area Networks—Timing and Synchronization for Time-Sensitive Applications in Bridged Local Area Networks.

IEEE Std 802.1Q™-2003, IEEE Standard for local and metropolitan area networks—Virtual Bridged Local Area Networks.

IEEE Std 802.1Q™, IEEE Standard for Local and Metropolitan Area Networks—Bridges and Bridged Networks.

IEEE Std 802.1X™-2010, IEEE Standard for Local and Metropolitan Area Networks—Port-Based Network Access Control.

IEEE Std 802.3™-2018, IEEE Standard for Ethernet.

IEEE Std 802.21™-2017, IEEE Standard for Local and metropolitan area networks—Part 21: Media Independent Services Framework.

[2] 3GPP™ documents are available from the 3rd Generation Partnership Project Web site (http://www.3gpp.org).
[3] ETSI documents are available from the European Telecommunications Standards Institute (http://www.etsi.org).
[4] FIPS publications are available from the National Technical Information Service (NTIS) (http://csrc.nist.gov).
[5] The IEEE standards or products referred to in this clause are trademarks owned by The Institute of Electrical and Electronics Engineers, Inc.
[6] IEEE publications are available from The Institute of Electrical and Electronics Engineers (http://standards.ieee.org/).

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

IEEE Std 802.21.1™-2017, IEEE Standard for Local and metropolitan area networks—Part 21.1: Media Independent Services.

IETF RFC 791, Internet Protocol, Sept. 1981.[7]

IETF RFC 826, An Ethernet Address Resolution Protocol, Plummer, D. C., Nov. 1982.

IETF RFC 1035, Domain Names — Implementation and Specification, Mockapetris, P., Nov. 1987.

IETF RFC 1042, A Standard for the Transmission of IP Datagrams over IEEE 802® Networks, Postel, J., and J. Reynolds, Feb. 1988.

IETF RFC 1321, The MD5 Message-Digest Algorithm, Apr. 1992 (status: informational).

IETF RFC 2104, HMAC: Keyed-Hashing for Message Authentication, Krawczyk, H., M. Bellare, and R. Canetti, Feb. 1997 (status: informational).

IETF RFC 2131, Dynamic Host Configuration Protocol, Mar. 1997.

IETF RFC 2409, The Internet Key Exchange (IKE), Harkins, D., and D. Carrel, Nov. 1998 (status: Standards Track).

IETF RFC 3279, Algorithms and Identifiers for the Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile, Apr. 2002.

IETF RFC 3315, Dynamic Host Configuration Protocol for IPv6 (DHCPv6), July 2003.

IETF RFC 3394, Advanced Encryption Standard (AES) Key Wrap Algorithm, Schaad, J., and R. Housley, Sept. 2002 (status: informational).

IETF RFC 3447, Public-Key Cryptography Standards (PKCS) #1: RSA Cryptography Specification Version 2.1, Feb. 2003.

IETF RFC 3490, Internationalizing Domain Names in Applications (IDNA), Mar. 2003.

IETF RFC 3610, Counter with CBC-MAC (CCM), Whiting, D., R. Housley, and N. Ferguson, Sept. 2003 (status: informational).

IETF RFC 3748, Extensible Authentication Protocol (EAP), Aboba, B., L. Blunk, J. Vollbrecht, J. Carlson, and H. Levkowetz, June 2004.

IETF RFC 3986, Uniform Resource Identifier (URI): Generic Syntax, Jan. 2005.

IETF RFC 4017, Extensible Authentication Protocol (EAP) Method Requirements for Wireless LANs, Stanley, D., J. Walker, and B. Aboba, Mar. 2005 (status: informational).

IETF RFC 4119, A Presence-based GEOPRIV Location Object Format, Peterson, J., Dec. 2005.

IETF RFC 4282, The Network Access Identifier, Dec. 2005.

IETF RFC 4776, Dynamic Host Configuration Protocol (DHCPv4 and DHCPv6) Option for Civic Addresses Configuration Information, Nov. 2006.

[7] IEFT documents (i.e., RFCs) are available from the Internet Engineering Task Force (http://tools.ieft.org/).

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

IETF RFC 4861, Neighbor Discovery for IP version 6 (IPv6), Narten, T., E. Nordmark, W. Simpson, and H. Soliman, Sept. 2007.

IETF RFC 4862, IPv6 Stateless Address Autoconfiguration, Sept. 2007.

IETF RFC 5116, An Interface and Algorithms for Authenticated Encryption, Jan. 2008.

IETF RFC 5216, The EAP-TLS Authentication Protocol, Simon, D., B. Aboba, and R. Hurst, Mar. 2008.

IETF RFC 5227, IPv4 Address Conflict Detection, Cheshire, S., July 2008.

IETF RFC 5280, Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile, May 2008.

IETF RFC 5295, Specification for the Derivation of Root Keys from an Extended Master Session Key (EMSK), Aug. 2008.

IETF RFC 5297, Synthetic Initialization Vector (SIV) Authenticated Encryption Using the Advanced Encryption Standard (AES), Harkins, D., Oct. 2008 (status: informational).

IETF RFC 5424, The Syslog Protocol, Gerhards, R., Mar. 2009.

IETF RFC 5480, Elliptic Curve Cryptography Subject Public Key Information, Mar. 2009.

IETF RFC 5869, HMAC-based Extract and Expand Key Derivation Function, Krawczyk, H., and P. Eronen, May 2010.

IETF RFC 5985, HTTP-Enabled Location Delivery (HELD), M. Barnes (Ed.), Sept. 2010.

IETF RFC 6225, Dynamic Host Configuration Protocol Options for Coordinate-Based Location Configuration Information, Polk, J., M. Linsner, M. Thomson, and B. Aboba, July 2011.

IETF RFC 6335, Internet Assigned Numbers Authority (IANA) Procedures for the Management of the Service Name and Transport Protocol Port Number Registry, Aug. 2011.

IETF RFC 6696, EAP Extensions for the EAP Re-authentication Protocol (ERP), July 2012.

IETF RFC 6942, Diameter Support for the EAP Re-authentication Protocol (ERP), May 2013.

IETF RFC 8200, Internet Protocol, Version 6 (IPv6) Specification, Deering, S., and R. Hinden, 2017.

IETF RFC 8265, Preparation, Enforcement, and Comparison of Internationalized Strings Representing Usernames and Passwords, Saint-Andre, P., and A. Melnikov, 2017.

ISO 639, Codes for the Representation of Names of Languages.[8]

ISO 3166-1, Codes for the representation of names of countries and their subdivisions — Part 1: Country codes.

ISO 3166-2, Codes for the representation of names of countries and their subdivisions — Part 2: Country subdivision code.

[8] ISO publications are available from the ISO Central Secretariat (http://www.iso.ch/).

Copyright © 2021 IEEE. All rights reserved.

This is a preview - click here to buy the full publication

ISO 4217, Currency codes.[9]

ISO/IEC 7498-1:1994, Information technology — Open Systems Interconnection — Basic Reference Model: The Basic Model.[10]

ISO/IEC 8802-2:1998, Information technology — Telecommunications and information exchange between systems—Local and metropolitan area networks — Specific requirements — Part 2: Logical link control.

ISO/IEC 8824-1:1995, Information technology — Abstract Syntax Notation One (ASN.1): Specification of basic notation.

ISO/IEC 8824-2:1995, Information technology — Abstract Syntax Notation One (ASN.1): Information object specification.

ISO/IEC 8824-3:1995, Information technology — Abstract Syntax Notation One (ASN.1): Constraint specification.

ISO/IEC 8824-4:1995, Information technology — Abstract Syntax Notation One (ASN.1): Parameterization of ASN.1 specifications.

ISO/IEC 11802-5:1997, Information technology — Telecommunications and information exchange between systems—Local and metropolitan area networks — Technical reports and guidelines — Part 5: Medium Access Control (MAC) Bridging of Ethernet V2.0 in Local Area Networks (previously known as IEEE Std 802.1H, 1997 Edition [B19]).[11]

ISO/IEC 14888-3:2006, Information technology — Security techniques — Digital signatures with appendix — Part 3: Discrete logarithm based mechanisms.

ITU-T Recommendation Z.120 (2004), Programming Languages—Formal Description Techniques (FDT)—Message Sequence Chart (MSC).[12]

NIST Special Publication 800-38B, Recommendation for Block Cipher Modes of Operation: The CMAC Mode for Authentication, Dworkin, M.[13]

NIST Special Publication 800-38D, Recommendation for Block Cipher Modes of Operation: Galois/ Counter Mode (GCM) and GMAC, Dworkin, M., Nov. 2007.

NIST Special Publication 800-56A R2, Recommendation for Pair-Wise Key Establishment Schemes Using Discrete Logarithm Cryptography, May 2013.

NIST Special Publication 800-57, Part 1 Rev 4, Recommendation for Key Management, Barker, E., Jan. 2016.

OASIS Standard EDXL-DE, “Emergency Data Exchange Language (EDXL) Distribution Element, v. 1.0.” OASIS Emergency Management Technical Committee, May 2006.

OMA-TS-ULP-V2_0_1, UserPlane Location Protocol, Dec. 2012.[14]

[9] See http://www.currency-iso.org/en/home/tables/table-a1.html

[10] ISO/IEC publications are available from the ISO Central Secretariat (http://www.iso.ch/). ISO/IEC publications are also available in the United States from the American National Standards Institute (http://www.ansi.org/).

[11] The numbers in brackets correspond to the numbers of the bibliography in Annex A.

[12] ITU publications are available from the International Telecommunications Union (http://www.itu.int/).

[13] NIST publications are available from the National Institute of Standards and Technology (http://csrc.nist.gov/).

Copyright © 2021 IEEE. All rights reserved.