

INTERNATIONAL STANDARD

IEC
62196-1

First edition
2003-04

**Plugs, socket-outlets, vehicle couplers
and vehicle inlets –
Conductive charging of electric vehicles –**

**Part 1:
Charging of electric vehicles up to 250 A a.c.
and 400 A d.c.**

*Fiches, socles de prise de courant, prises mobiles
et socles de connecteur pour véhicule –
Charge conductive des véhicules électriques –*

*Partie 1:
Charge des véhicules électriques jusqu'à 250 A c.a.
et 400 A c.c.*



Reference number
IEC 62196-1:2003(E)

Publication numbering

As from 1 January 1997 all IEC publications are issued with a designation in the 60000 series. For example, IEC 34-1 is now referred to as IEC 60034-1.

Consolidated editions

The IEC is now publishing consolidated versions of its publications. For example, edition numbers 1.0, 1.1 and 1.2 refer, respectively, to the base publication, the base publication incorporating amendment 1 and the base publication incorporating amendments 1 and 2.

Further information on IEC publications

The technical content of IEC publications is kept under constant review by the IEC, thus ensuring that the content reflects current technology. Information relating to this publication, including its validity, is available in the IEC Catalogue of publications (see below) in addition to new editions, amendments and corrigenda. Information on the subjects under consideration and work in progress undertaken by the technical committee which has prepared this publication, as well as the list of publications issued, is also available from the following:

- **IEC Web Site** (www.iec.ch)

- **Catalogue of IEC publications**

The on-line catalogue on the IEC web site (http://www.iec.ch/searchpub/cur_fut.htm) enables you to search by a variety of criteria including text searches, technical committees and date of publication. On-line information is also available on recently issued publications, withdrawn and replaced publications, as well as corrigenda.

- **IEC Just Published**

This summary of recently issued publications (http://www.iec.ch/online_news/justpub/jp_entry.htm) is also available by email. Please contact the Customer Service Centre (see below) for further information.

- **Customer Service Centre**

If you have any questions regarding this publication or need further assistance, please contact the Customer Service Centre:

Email: custserv@iec.ch
Tel: +41 22 919 02 11
Fax: +41 22 919 03 00

INTERNATIONAL STANDARD

IEC 62196-1

First edition
2003-04

Plugs, socket-outlets, vehicle couplers and vehicle inlets – Conductive charging of electric vehicles –

Part 1: Charging of electric vehicles up to 250 A a.c. and 400 A d.c.

*Fiches, socles de prise de courant, prises mobiles
et socles de connecteur pour véhicule –
Charge conductive des véhicules électriques –*

*Partie 1:
Charge des véhicules électriques jusqu'à 250 A c.a.
et 400 A c.c.*

© IEC 2003 — Copyright - all rights reserved

No part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from the publisher.

International Electrotechnical Commission, 3, rue de Varembé, PO Box 131, CH-1211 Geneva 20, Switzerland
Telephone: +41 22 919 02 11 Telefax: +41 22 919 03 00 E-mail: inmail@iec.ch Web: www.iec.ch



Commission Electrotechnique Internationale
International Electrotechnical Commission
Международная Электротехническая Комиссия

PRICE CODE **XB**

For price, see current catalogue

CONTENTS

FOREWORD	4
INTRODUCTION	5
1 Scope	6
2 Normative references.....	8
3 Definitions	9
4 General	13
5 Ratings	14
6 Connection between the power supply and the electric vehicle	14
7 Classification	17
8 Marking	18
9 Dimensions.....	20
10 Protection against electric shock.....	20
11 Size and colour of earthing conductors	21
12 Provision for earthing.....	21
13 Terminals.....	23
14 Interlocks.....	28
15 Resistance to ageing of rubber and thermoplastic material	28
16 General construction.....	28
17 Construction of socket-outlets.....	31
18 Construction of plugs and vehicle connectors	32
19 Construction of vehicle inlets.....	32
20 Degrees of protection	33
21 Insulation resistance and dielectric strength.....	34
22 Breaking capacity	36
23 Normal operation	37
24 Temperature rise	38
25 Flexible cables and their connection	39
26 Mechanical strength.....	41
27 Screws, current-carrying parts and connections	44
28 Creepage distances, clearances and distances.....	47
29 Resistance to heat, fire and tracking.....	48
30 Corrosion and resistance to rusting.....	50
31 Conditional short-circuit current withstand test.....	51
32 Electromagnetic compatibility.....	52
33 Vehicle driveover	53
Annex A (informative) EV charging.....	70
Bibliography.....	71

Figure 1 – Diagram showing the use of the accessories	54
Figure 2 – Standard test finger	55
Figure 3 – Circuit diagrams for breaking capacity and normal operation tests.....	56
Figure 4 – Apparatus for testing the cable anchorage.....	57
Figure 5 – Ball Impact test	58
Figure 6 – Arrangement for mechanical strength test for plugs and vehicle connectors	58
Figure 7 – Apparatus for flexing test.....	59
Figure 8 – Ball-pressure apparatus	59
Figure 9 – Test apparatus (example).....	60
Figure 10 – Glow-wire and position of the thermocouple	61
Figure 11 – Arrangement and dimensions of the electrodes for the tracking test	62
Figure 12 – Gauges for testing insertability of round unprepared conductors having the maximum specified cross-section	63
Figure 13 – Examples of terminals	64
Figure 14 – Equipment test arrangement.....	66
Figure 15 – Diagram of the test circuit for the verification of short-circuit current withstand of a two-pole equipment on a single-phase a.c. or d.c.....	67
Figure 16 – Diagram of the test circuit for the verification of short-circuit current withstand of a three-pole equipment.....	68
Figure 17 – Diagram of the test circuit for the verification of short-circuit current withstand of a four-pole equipment.....	69
Table 1 – Modes and permissible connections specified in IEC 61851-1	7
Table 2 – Intermateability of mating devices at vehicle	15
Table 3 – Overview of the universal vehicle interface	16
Table 4 – Overview of the basic vehicle interface	17
Table 5 – Short-time test currents	22
Table 6 – Size for power and signal conductors	24
Table 7 – Value for terminal pull test.....	25
Table 8 – Value for flexing under mechanical load test.....	26
Table 9 – Cable length used to determine pull force on latch assembly	30
Table 10 – Test voltage for dielectric strength test	35
Table 11 – Breaking capacity	37
Table 12 – Normal operation	38
Table 13 – Test current and nominal cross-sectional areas of copper conductors for temperature rise test	39
Table 14 – Pull force and torque test values for cable anchorages	41
Table 15 – Impact energy for ball impact test	42
Table 16 – Mechanical load flexing test.....	43
Table 17 – Torque test values for glands.....	44
Table 18 – Tightening torque for verification of mechanical strength of screw-type terminals	45

INTERNATIONAL ELECTROTECHNICAL COMMISSION

PLUGS, SOCKET-OUTLETS, VEHICLE COUPLERS AND VEHICLE INLETS – CONDUCTIVE CHARGING OF ELECTRIC VEHICLES –

Part 1: Charging of electric vehicles up to 250 A a.c. and 400 A d.c.

FOREWORD

- 1) The IEC (International Electrotechnical Commission) is a worldwide organisation for standardisation comprising all national electrotechnical committees (IEC National Committees). The object of the IEC is to promote international co-operation on all questions concerning standardisation in the electrical and electronic fields. To this end and in addition to other activities, the IEC publishes International Standards. Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and nongovernmental organisations liaising with the IEC also participate in this preparation. The IEC collaborates closely with the International Organisation for Standardisation (ISO) in accordance with conditions determined by agreement between the two organisations.
- 2) The formal decisions or agreements of the IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested National Committees.
- 3) The documents produced have the form of recommendations for international use and are published in the form of standards, technical specifications, technical reports or guides and they are accepted by the National Committees in that sense.
- 4) In order to promote international unification, IEC National Committees undertake to apply IEC International Standards transparently to the maximum extent possible in their national and regional standards. Any divergence between the IEC Standard and the corresponding national or regional standard shall be clearly indicated in the latter.
- 5) The IEC provides no marking procedure to indicate its approval and cannot be rendered responsible for any equipment declared to be in conformity with one of its standards.
- 6) Attention is drawn to the possibility that some of the elements of this International Standard may be the subject of patent rights. The IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62196-1 has been prepared by IEC subcommittee 23H: Industrial plugs and socket-outlets, of IEC technical committee 23: Electrical accessories.

The text of this standard is based on the following documents:

FDIS	Report on voting
23H/132/FDIS	23H/135/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

The committee has decided that the contents of this publication will remain unchanged until 2006. At this date, the publication will be

- reconfirmed;
- withdrawn;
- replaced by a revised edition, or
- amended.

A bilingual edition of this standard may be issued at a later date.

INTRODUCTION

IEC 61851-1 specifies electric vehicle conductive charging equipment. This International Standard, referred to as the IEC 60309 series in IEC 61851-1, specifies the requirements for plugs, socket-outlets, connectors, inlets and cable assemblies as described in IEC 61851-1. Some charging can be achieved by direct connection from an electric vehicle to common mains socket outlets. Some modes of charging require a dedicated supply and charging equipment incorporating control and communication circuits. This standard covers the mechanical, electrical and performance requirements for dedicated plugs, socket outlets, vehicle connectors and vehicle inlets for interfacing between such dedicated charging equipment and the electric vehicle.

This International Standard may be published in several parts, as necessary, including this Part 1, comprising clauses of a general character, and subsequent parts, presenting particular requirements for individual types.

Withdrawal

PLUGS, SOCKET-OUTLETS, VEHICLE COUPLERS AND VEHICLE INLETS – CONDUCTIVE CHARGING OF ELECTRIC VEHICLES –

Part 1: Charging of electric vehicles up to 250 A a.c. and 400 A d.c.

1 Scope

This part of IEC 62196 is applicable to plugs, socket-outlets, connectors, inlets and cable assemblies for electric vehicles, intended for use in conductive charging systems which incorporate control means, with a rated operating voltage not exceeding:

- 690 V a.c., 50 – 60 Hz, at a rated current not exceeding 250 A;
- 600 V d.c., at a rated current not exceeding 400 A.

These accessories and cable assemblies are intended to be used for circuits specified in IEC 61851-1 which operate at different voltages and frequencies and which may include ELV and communication signals.

These accessories and cable assemblies are to be used in an ambient temperature of between -30 °C and $+50\text{ °C}$. In some countries, other requirements may apply.

These accessories are intended to be connected only to cables with copper or copper-alloy conductors.

The accessories covered by this standard are for use in certain modes of charging EV's. These modes are defined in IEC 61851-1. These definitions and a description of the types of connection (cases A, B and C), also described in IEC 61851-1, are reproduced herein as Annex A.

Table 1 illustrates the types of accessories (B, U_{32} , U_A , U_D) permitted for each charging situation (mode and case) and identifies where it is mandatory to use the accessories covered by this standard. These are indicated by the entries in the columns headed "62196" in Table 1.

The table also describes situations in which either an accessory covered by this standard, or other standardized accessories, are permitted to be used. They are identified by an entry in the column headed "62196" and the word "Any" under the column headed "Type".

This standard does not apply to those standardised accessories used in charging systems where the use of such accessories constructed to the requirements of other standards is permitted (e.g. in mode 1 and mode 2). Such standardized accessories may be used for those situations (mode and case) identified in Table 1 by the word "Any" under the column headed "Type" and with no corresponding entry under the column headed "62196".

This standard can be used as a guide for accessories with a lesser number of contacts and lower ratings for use with light duty vehicles.

Table 1 – Modes and permissible connections specified in IEC 61851-1

Mode	Amps	Phases	Plug & socket					EV connector & inlet					Comments											
			Power pins used & prot. earth	Control pins incl. pilot	Type	62196	Case	In line control box	Power pins used & prot. earth	Control pins incl. pilot	Type	62196		Case										
1	16	1	1+N, or 2	None	Any	[shaded]	A	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	A	See Note 1										
					Any		B						B or U ₃₂		B									
		3	3 + N	None	Any	[shaded]	A	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	A											
					Any		B						B or U ₃₂		B									
2	32	1	1+N, or 2	None	Any	[shaded]	B	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	B or U ₃₂	Uses in-line control box										
					Any		B						B or U ₃₂	B										
		3	3 + N	None	Any	[shaded]	B	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	B or U ₃₂	Uses in-line control box									
					Any		B							B or U ₃₂	B									
3	32	1	1+N, or 2	4	[shaded]	[shaded]	A	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	B or U ₃₂	A										
							B						B											
		3	3 + N	4	[shaded]	[shaded]	[shaded]	A	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	B or U ₃₂	A									
								B						B										
	250	1	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	U _A	C									
														3	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]
		[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]											
														[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]
400	-	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	U _D											
													[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]
													[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]	[shaded]

NOTE 1 Restrictions regarding load less than 16 A should be recognized by the vehicle maker.

NOTE 2 In the column headed "62196", the items listed are defined as:
 B Basic
 U₃₂ Universal interface rated for 32 A a.c. only
 U_A Universal interface rated for 32/250 A a.c. only
 U_D Universal interface prepared for 32/400 A d.c. only

NOTE 3 In the column headed "Type", the word "Any" indicates that any IEC standard plug/socket-outlet interface can be used.

NOTE 4 Either "L₁ with N" or "L₁ with L₂" are used for single-phase to match the supply.

NOTE 5 Earth-contact is mandatory in all accessories, pilot contact is mandatory in accessories in modes 2, 3, and 4. The other contacts are provided as required by the user.

2 Normative references

The following referenced documents are indispensable for the application of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60112, *Method for the determination of the proof and the comparative tracking indices of solid insulating materials*

IEC 60227 (all parts): *Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V*

IEC 60228:1978, *Conductors of insulated cables*

IEC 60245-4:1994, *Rubber insulated cables – Rated voltages up to and including 450/750 V – Part 4: Cords and flexible cables*

IEC 60269-1:1998, *Low-voltage fuses – Part 1: General requirements*

IEC 60269-2:1986, *Low-voltage fuses – Part 2: Supplementary requirements for fuses for use by authorised persons (fuses mainly for industrial application)*

IEC 60529, *Degrees of protection provided by enclosures (IP code)*

IEC 60664-1:1992, *Insulation coordination for equipment within low-voltage systems – Part 1: Principles, requirements and tests¹*

IEC 60664-3:1992, *Insulation coordination for equipment within low-voltage systems – Part 3: Use of coatings to achieve insulation coordination of printed board assemblies*

IEC 60695-2-10, *Fire hazard testing – Part 2-10: Glowing/hot-wire based test methods – Glow-wire apparatus and common test procedure*

IEC 60999-1:1999, *Connecting devices – Electrical copper conductors – Safety requirements for screw-type and screwless-type clamping units – Part 1: General requirements and particular requirements for clamping units for conductors from 0,2 mm² up to 35 mm² (included)*

IEC 60999-2:1999, *Connecting devices – Safety requirements for screw-type and screwless-type clamping units for electrical copper conductors – Part 2: Particular requirements for conductors from 35 mm² up to 300 mm²*

IEC 61851-1:2001, *Electric vehicle conductive charging system – Part 1: General requirements*

¹ There exists a consolidated edition 1.2 (2002) including edition 1.0 and its Amendments 1 (2000) and 2 (2002).